

kilobaud

MICROCOMPUTING

for business . . . education . . . FUN!



26	"Monitor".....	Rod Hallen
32	TRS-80/Selectric Word Processor.....	Allan J. Domuret
36	Thoughts on the SWTP Computer System (2).....	Peter A. Stark
44	New Life for Our Altair.....	Harley Dyk
48	TVBUG.....	Tim Ahrens
54	Creative Tabulation.....	Marc I. Leavey, M.D.
58	A Handle on Programming.....	Allan S. Joffe
60	Keepbook.....	Robert L. Marx
64	Vector Graphing Techniques.....	Wendell Brown
68	Putting the 1802 on the S-100 Bus.....	Bob Petty
74	A Personal Finance System (Part 1).....	James McClure

80	Building a New Horizon.....	Michael D. O'Brien
84	Microcomputers and TVI.....	Frank J. Derfler, Jr.
88	Translating Between TTL and RS-232 Levels.....	F. R. Ruckdeschel
92	Data Files for Processor Tech 5K BASIC.....	John R. Stanton
96	Little Bits.....	Hallen, Walker, Van Dyke, McCormick, Wright
100	What's so Magic about the Sorcerer?.....	Ken Barbier
108	A Telephone Data Coupler for the TRS-80.....	Fred G. Smith
110	The Cromemco Z-2D.....	Steven K. Roberts
114	Personal Computing, Meet Photography.....	Michael P. Avery
120	Peripheral Interfacing.....	Rod Hallen



Someday all terminals will be smart.....

- ◆ 128 Functions—software controlled
- ◆ 7 x 12 matrix, upper/lower case letters
- ◆ 50 to 38,400 baud—selectable
- ◆ 82 x 16 or 92 x 22 format—plus graphics
- ◆ Printer output port
- ◆ "CHERRY" keyboard

CT-82 Intelligent Terminal, assembled and tested. \$795.00 ppd in Cont. U.S.



SOUTHWEST TECHNICAL PRODUCTS CORPORATION
219 W. RHAPSODY
SAN ANTONIO, TEXAS 78216

THE NEW COMPRINT PRINTER

copy was printed on the new COMPRINT model 912 computer printer. Designed to produce quality printed output suitable for business and professional applications, but with a price tag affordable for virtually everyone including the home/hobby user.

PRIMARY APPLICATIONS INCLUDE:

- * Micro and mini computer system printer
- * CRT hardcopy device
- * Message network printer
- * Distributed data processing (remote) printer
- * Industrial/scientific data logging
- * Backup printer for data processing center

The model 912 is \$560. In single quantities with parallel lines are printed on 8 1/2" wide paper normally associated with price range.

The COMPRINT top-of-form feature automatically or 11" long blocks with 8 1/2" space between for con output into 11" pages.

The COMPRINT printer runs at a fast 225 characters/second. It is virtually noiseless and ideal for small in size and lightweight of materials result in an extremely low cost of materials and labor with a 6 month warranty.

This exceptional print quality for \$560!

The new Comprint model 912 printer for computers and terminals:

- Fast—225 characters/second (170 lpm)
- 80 character lines on 8 1/2" wide paper
- Quiet, non-impact operation
- 6 month warranty

Available now at computer stores and industrial distributors.

comprint



Computer Printers International, Inc. 340 E. Middlefield Rd., Mt. View, CA 94043 • 415 969-6161

PUBLISHER'S REMARKS

Wayne Green

No Blues in St. Louis

The St. Louis hamfest/computerfest, which I wrote about in this magazine, came to pass and was a giant success for all involved. I believe that they had the largest microcomputer audience I've ever addressed—well over 1500 in the big auditorium at the St. Louis Cervantes Center.

The exhibitors, many talked into coming via my "Microcomputing Industry Newsletter," all expressed delight over the attendance and the amount of money these people brought with them . . . and didn't take home. Over 3000 were registered at the gate, so the exhibit area was packed most of the time. What sold? What didn't? I don't think anyone brought enough software to meet the demand. Every computer exhibit was packed, constantly, with people waving money.

After this display of interest you may be sure that the 1980 St. Louis hamfest/computerfest is going to be a corker. Remember that this one was planned right at the last minute, with little notice to anyone except in *Kilobaud MICROCOMPUTING* and *73 Magazine*.

The whole thing started when Bob Heil (K9EID) called one day to ask what he had to do to get me to come out to the Marissa (IL) radio club and talk. I said all he had to do was put on a major

hamfest and I'd be out. This was in December. A few weeks later he had all but one ham club in the area, plus all the computer clubs, lined up to cooperate; the rest is history. It doesn't take a lot of money or experience—all it takes is a lot of drive, which Bob Heil certainly has in spades.

Software Ideas

Since those interested in the stock market need timely information, this is a fertile market for the microcomputer.

There is a telephone-line service available from both the New York Stock Exchange and the American Exchange that will bring stock-market action to a home or business. The NYSE service is reported to cost under \$150, and Amex is around \$50 per month, including wire costs. All that is needed is a simple interface to your computer and the software to make it work.

You might want to have the immediate quotations running across the top of your screen and then be able to use the rest of the tube to look into memory for quotes on specific stocks. You might want the program to put aside quotations on stocks that are of interest for display on command. You might also want an automatic alert on certain price levels or changes in specific stocks.

Reader Responsibility

One of your responsibilities, as a reader of *Kilobaud MICROCOMPUTING*, is to aid and abet the increasing of circulation and advertising, both of which will bring you the same benefit: a larger and even better magazine. You can help by encouraging your friends to subscribe to *Kilobaud MICROCOMPUTING*. Remember: Subscriptions are guaranteed—money back if not delighted, so no one can lose. You can also help by tearing out one of the cards just inside the back cover and circling replies you'd like to see: catalogs, spec sheets, etc. Advertisers put a lot of trust in reader requests for information. To make it more worth your while to send in the card, a drawing will be held each month and the winner will get a lifetime subscription to *Kilobaud MICROCOMPUTING*!

This month's winner of a lifetime subscription to *Microcomputing* is Gary S. Fix of Alliance OH.



That's me on the right talking about the St. Louis computerfest on the Channel 2 news. An Apple is being demonstrated on the left by Dennis Jolly of a local computer store.

Other exchange data, such as market volume, warrant actions and various indices, can be saved and accessed on demand.

How much would such a program earn for a programmer? It's early to tell, but my guess is at least \$50,000 a year for two or three years in sales. It could well go to ten times that if a substantial percentage of the firms interested in the stock market went for it.

I suggest that only people familiar with the market get involved in a project such as this.

Other Market Data

A good program to help people interested in the commodity market would be another winner. This would want to access quotations as quickly as possible, chart the action, project probabilities and get input on as many significant factors as possible.

Warrant lovers might go for a special program to help them with their data and calculations . . . and so it goes. A lot of market-oriented programs that should sell well could be written.

Data Tapes

Eventually I think we'll be able to access the data we need, for a change, from what we might call data libraries or data banks. For instance, stockbrokers might want to get data on the minute-by-minute action in a stock over a period of years (who knows why?). Such data could then be accessed and paid for at a nominal fee. In the interim, as a way to lay the foundation for such a service, possibly over a cable TV line

or telephone line—maybe even by direct satellite access—the data banks could start on a paying basis via cassette storage.

How many investors might prefer to have a daily or even weekly cassette with the ticker data? It might be sorted out and made easier to find what you want, but with the daily action available for computer manipulation.

Once something like that starts there will be a market, I think, for indexes for businessmen. Dentists need indexes for their literature. So do doctors and lawyers. Every professional man depends on recent magazine articles, books and technical papers. The problem is finding what you want when you need it. A data-bank system could do it.

Such a service, I'm sure, would interest Instant Software in marketing the data.

Price Lists

In every field is a serious need for updated price lists of products. This is required by dealers, many of whom have to keep large books of price data and make daily changes in pricing sheets. If someone gets a few days behind it can raise hell with things. In *73 Magazine*, Tufts Electronics tried for a couple of years to publish a current catalog of ham-equipment prices. But no matter how hard they tried, by the time the catalog was in the hands of the customers, a fair number of the retail prices had changed—seldom going lower.

A firm could grow considerably just by providing a weekly list of the latest prices for ham equipment, plumbing, automotive

parts, etc. These could be stored on cassette for the time being—until some data-bank communications system develops. Yes, I know that there are services such as this in a few fields via microfiche. That's OK, except that you really need the information in a computer so you can access it in several ways and massage it however you want.

With a good program, you could follow the trends of any particular firm or product. It might even be able to tie in with an inventory program and update it for current prices by matching part numbers, thus giving you a more accurate current value for your inventory.

Telephone Program

A relatively simple sensor connected to your phone line could decipher the area code you are calling; have a lookup table for the phone rates to that area and a real-time clock to get the correct time-of-day rates; and then read out the dollars as they mount up for a phone call.

An extension of this program could keep track of the outgoing calls from all extensions of a business and print out a listing of the number called, extension used and cost of call.

If you design the hardware, we can have one of the *MICROCOMPUTING* advertisers put it into production to be marketed with the program as a package.

Phone List

There was a program in *Personal Computing*—a simple one—that allowed you to put in as data the name and phone number of people you would like to call. When you typed the name of the person, the program would print out the number.

I'd like to see a more sophisticated program that would go another step along that path. A hardware dialer or tone generator would be needed to interface the phone line. Then you could look up the phone number with the computer and give it the OK to call. On a busy signal it would report this and make the call for you later, with your OK.

I'd like to be able to call someone by company, by last name, perhaps have a cross-index of first names and even a listing by trade. Thus I might want to call the police, the doctor, Apple, Bill Godbout. . . .

Using up Your Tapes

I'm a registered skinflint. Even with thousands of perfectly good cassettes around me that I could use for program and data storage, I prefer to put as much as I can on a single cassette. Call me frugal.

This use of my cassettes has a drawback at first trial in that it can take a long time to find a particular program or data dump on a tape. There is a simple solution to this misery, if you think about it. Why not run the tape fast-forward to the segment you need? If you have a counter on your recorder you have no problem. For some reason all of our recorders with counters seem to end up in the Instant Software lab, and I'm usually stuck with an uncountered one. No big deal.

I made a quick chart of the rewind time vs the fast-forward time so I could tell how much time to run the tape at fast-forward to get to the place I needed. After each program or data dump on the tape, I keep the tape running for a few more seconds to leave a blank space that's easy to locate later. Then I rewind the tape to the beginning, watching the clock. By converting from rewind time to fast-forward time I can then determine just where to start my next dump. I mark most cassettes with the time in seconds of fast-forward for the start of each dump. It works every time and is simple.

With a little trick like this you can dump programs or data on the ends of most of your program cassettes. Why waste all that tape by just leaving it blank?

Yes, I know, when you change recorders, all those times go out the window.

Getting Rich

Would you truly like to be rich? Would you like to own your own plane, perhaps a yacht and

maybe an Arabian horse? How about being able to travel anywhere in the world you want . . . perhaps a 30-room home on 50 acres with a fantastic view, your own fish pond and even an outside sauna? Fantasy? Not one bit of it. There are fortunes to be made in microcomputing if you go about it the right way. No matter what your education or intelligence, you can become a millionaire . . . if you really want to.

While the talks at computer shows on computer history, on bus structures, etc., usually attract small groups of interested listeners, my talks on how to make money in microcomputing usually pack the house.

Apprenticeship

I can't give you a crash course in just one editorial on how to get rich—this would leave too many questions open. However, I'll try to cover various aspects of the process over a series of editorials, with the end result being your enrichment.

One of the basics of being successful is to learn as much as you can on someone else's money. The failure to do this has much to do with the high failure rate of new businesses, even in microcomputing, which has been particularly forgiving. But how do you go out and get your first job so you can start learning with someone else paying for it?

Many people fall into that old Catch-22 situation where they have to have experience before they can get a job . . . but how are they going to get experience if they don't have a job? In the microcomputing field there is a simple way around this problem: start by getting your experience on your own microcomputer . . . and then help others with theirs. Computer-club and user-group attendance can be very helpful in your obtaining the experience

(continued on page 24)

About the Cover

All retail outlets of the Computer Store feature the Data General microNOVA computer for the small-business market. The microNOVA line is sold with a wide range of options in both computer and peripheral devices. Small-business customers of the Computer Store have Data General full field service and post-sales support available as well as professional, fully proven hardware and software. The Computer Store is Data General's largest distributor of the microNOVA line and the leading retailer of computer systems for small businesses in the Northeast. (Photo courtesy of Alan Ross, Total Communications, Inc., Newton MA, for the Computer Store of Burlington MA.)

Kilobaud MICROCOMPUTING

Publisher/Editor
Wayne Green

Executive Vice President
Sherry Smythe

Assistant Publisher/Editor
Jeffrey D. DeTray

Managing Editor
John Barry

Editorial Assistants
Dennis Brisson
Susan Gross

Administrative Assistant
Dotty Gibson

Production Department Manager:
Lynn Panciera-Fraser

Staff:
Craig Brown
Gayle Cabana
Judith Dalby
Robert Drew
James H. Gray II
Bruce Hedin
Dion Owens
Noel R. Self
Robin M. Sloan
John W. White

Typesetting
Barbara J. Latti
Sara Bedell
Mary Kinzel
Holly Walsh

Photography
Bill Heydolph
Tedd Cluff

Projects Editor
Jim Perry

Associate Editors
John Arnold
Phil Feldman
Steve Fuller
Rod Hallen
Tom Rugg
Peter Stark
Sherm Wantz
Dick Whipple
Ken Widellitz

Bookkeeper
Knud E. M. Keller

Marketing/Circulation Mgr.
Robert LaPointe

Bulk Sales Mgr.
Judy Waterman

Asst. Circulation Mgr.
Mary Beth Stanek

Circulation
Pauline Johnstone

Computer Programming
Richard Dykema

Instant Software
Micro Lab
William F. Gollan
Alan Anderson
Scott Spangenberg
Cida Teixeira
Palmer T. Wolf
Stan Wszola

Advertising
Aline Coutu, Mgr.
Bill York
Marcia Stone
William Q. Hoyle
Nancy Ciampa
Gaye Halbig
Lori Mugford
Rita Rivard

European Marketing Dir.
Reinhard Nedela

Australian Distributor
Katherine Thirkell

Kilobaud MICROCOMPUTING (USPS 346-690) is published monthly by 1001001, Inc., Pine St., Peterborough NH 03458. Subscription rates in U.S. and Canada are \$18 for one year and \$45 for three years. In Europe: Kilobaud erscheint monatlich bei Fachschriftenvertrieb Monika Nedela, 7778 Markdorf, Markstr. 3, Australia: For subscriptions write—Katherine Thirkell, Sentron Instruments, 17 Arawatta St., Carnegie, Vic. 3163 Australia. Please write for other foreign rates. Second-class postage paid at Peterborough NH 03458 and at additional mailing offices. Phone: 603-924-3873. Entire contents copyright 1979 by 1001001, Inc. INCLUDE OLD ADDRESS AND ZIP CODE WITH ADDRESS CHANGE NOTIFICATION.

OUTPUT FROM ISI

Sherry Smythe

First Gets Most

Every now and then I get a letter from a programmer who wants to limit the time that Instant Software can sell his program . . . who wants a different deal on royalties . . . who wants a special contract. For the edification of programmers, I'd like to explain a simple fact of life.

With over 1000 programs backed up for evaluation and publication at Instant Software, the natural course of events is to follow the path of least resistance and process those that present no problems. When an author has trouble signing a contract for some reason, when he wants some individual attention—this brings things to a stop . . . for that program. One of these days there will be enough staff to handle special cases and to answer questions and maybe even make individual deals.

Oh, I understand the plight of the programmer quite well. With sharks on every side looking to take advantage of programmers,

they have to be very wary. I've seen case after case in which some outfit has conned a gullible programmer into giving up his work, only to get nothing for it. In this context, some of the user groups are real users.

But the programmer really has to put this into perspective. With relatively simple programs, ones that any good programmer could write in a couple of weeks or so, the odds are very high that dozens of these programs will be submitted to Instant Software. Only one of these will probably reach publication. This means that one programmer will hit the jackpot and the others will be holding a sack of nuts.

The jackpot programmer will not likely be one who has slowed or stopped work on his programs. The published programs will be from programmers who make our work the simplest by providing good documentation, flexible and easy-to-use programs, fast turnaround on communications and as few problems as possible.

The programmer has little to

go on but our reputation. I will guarantee that Instant Software will try to do everything possible to treat all programmers well and make them a maximum of royalties. This is a fundamental rule for the whole organization, and it is a constant guideline. The long-range position of the firm relies on the goodwill of programmers and customers.

All programs published by Instant Software must be good, must be a good value and should be as simple to use as possible.

Associate Editors

More and more of the people who have submitted applications for program reviewing as associate editors have been hearing from us. I mentioned that back in December we put all the associate editors on file along with their systems and fields of expertise, only to have the North Star Horizon, complete with both the program and the data disks, stolen from the Instant Software lab.

The man who had written that program for us was back in school, so we had to wait for a new super-programmer to sign on. The new associate-editor program is now going on line, and this will greatly speed up the fielding of programs for evaluation.

We have received over 750 applications from people to review

programs, so we'll be keeping a close eye out for outstanding work. The editor who takes too long with the evaluation, or who obviously hasn't put much serious thought into his work, gradually will be weeded out. I like to get a carefully considered review of a program, a suggestion on sales price and perhaps some ideas on improvement that can be discussed with the author. The editor who sits down and develops a program significantly will likely find himself sharing in the action to the extent of his contribution.

The speed of processing programs through Instant Software depends on the number of people on the staff. This, in turn, depends to some extent on the sales volume. We are now turning out well over one new package of programs per working day. This means that with an average of two programs per package and an acceptance of one in ten, we are able to process about 20 submitted programs per day. We're planning to expand that output to five packages per day, two programs per package on the average. We hope that one in three programs will be accepted as the quality of submitted programs increases . . . or a bit over 30 submissions per day processed.

The Instant Software staff is presently up to about 25 full-time employees and perhaps 20 part-timers. More help is needed for marketing, clerical work, package production, advertising, etc.

PET- POURRI

Len Lindsay

Hot News

Programmers and software companies: your worries about unauthorized copying of your programs are over. BC Computing (2124 Colorado Ave., Sun Prairie WI 53590) will protect your programs for you. I was fortunate to be able to spend an hour with the main PET programmer at BC Computing. Their system is impressive, and *it works!* Load a protected program by typing L-O-A-D [RETURN]. You will then be amazed to see the program

LOAD and immediately run. If for some reason you manage to break out of the program (the STOP key does not work), the program will not list correctly and you lose control of your PET and have to turn it off and on again. A SAVE will not work; neither will the SYS equivalent!

Adding this protection is complex, so BC Computing charges a nominal fee for the service of protecting your program. Anyone marketing good PET programs now would be foolish not to have BC protect them.

Tapes

I have gone through almost 1000 cassettes now, and tested almost all brands and types. I have found one tape that is far superior to all the others for use on the PET (and other personal computers as well). These cassettes come from Computer Way and are "Agfa Premium" tape. Be careful of other companies advertising Agfa tapes—they have several different grades. "Agfa Premium" is the best. Just as important as the tape is the cassette housing. Make sure that it is a top-quality, screw-type housing, steel pins, flanged rollers and a hard window.

Computer Way sells only one kind of tape: the best. Since it has all the quality features I mentioned, all my programs and data are now recorded on their tapes. Their prices on Agfa Premium C-10 cassettes are lower than others advertised. Prices are:

- 25 at \$1 each (total \$25)
- 50 at 96¢ each (total \$48)
- 100 at 85¢ each (total \$85)
- 200 at 80¢ each (total \$160)
- 400 at 75¢ each (total \$300)

Approved computer clubs receive a ten percent discount on orders of 200 or more. Shipping and quick delivery anywhere in the USA are included, but boxes are extra.

Contact Computer Way, PO Box 7006, Madison WI 53707.

News

I have the light pen being sold by 3G Company (Rte. 3, Box 28A, Gaston OR 97119) for \$29.95, and it does work. I had to turn up the brightness of my screen, though. The light pen plugs into your user port. With a small amount of software, the computer can "sense" where the pen is and react accordingly. I now will try to write some programs for

kids using a light pen. Please write with your applications or request information on what I have developed so far.

Commodore has now shipped PETs with expanded memory and hopes to have their peripherals out very soon. The ROM operating system in the new PETs is indeed different from that in the old PETs and is not compatible. Some programs written on older PETs may not function correctly on the new PETs.

The problems occur when PEEK, POKE, SYS or USR commands are used with locations that are different with the new ROMs, which supposedly correct all known flaws in the previous set. They are available only in the new PETs, but in the future they may be offered for sale separately.

Axiom (5932 San Fernando Rd., Glendale CA 91202) is now shipping electrostatic printers for \$535 that simply plug into the PET IEEE port. They print uppercase and lowercase as well as full PET graphics. There is about a 16 week backlog of orders already. Also available is their electrostatic plotter for \$895. It also simply plugs in and has the added feature of being able to print a graphic display from PET screen to paper. It doesn't leave a thin blank line between lines while in the plot mode. The plotter is available now; there are few back orders.

Recommendations

I want to put myself out on a limb and look at games commercially available for the PET. Many readers have written asking me to recommend games.

These serious, thinking games get my recommendation:

Microchess from Personal Software (PO Box 136-05, Cambridge MA 02138). Play a good game of chess against your PET for \$19.95. Reviewed in the *Best of the PET Gazette*, p. 40.

Mastermind from *PET Gazette* (1929 Northport Dr., Room 6, Madison WI 53704). This is the best implementation of the game of Mastermind. Your PET can be either code-breaker or code-maker. The PET will almost always break your code faster than you can break its code. Cost is only \$10 for Game Pak 1, which includes Mastermind and five other good games.

Maxit from Harry Saal (810 Garland Dr., Palo Alto CA 94303). This number-strategy game can be played either by two players or you vs the PET. Re-

viewed on p. 55 of the *Best of the PET Gazette*, Maxit costs only \$4.95.

Othello from CMS Software (5115 Menefee, Dallas TX 75227). Reviewed in issue #7 of the *PET Gazette*, this is a good version of Othello. Price is \$7.95.

Market from Dr. Daley (425 Grove Ave., Berrien Springs MI 49103). In this two-player game, each player manages his own company, including advertising budget, product prices and production. Your PET calculates how many units each person will sell for each quarter. Go broke and you lose. Invest \$7.95 in this program.

I also recommend these classic computer games:

Star Trek is the all-time classic. Almost everyone is selling a version of it. I recommend these three sources:

Dr. Daley has several versions, some with sound effects, real time and other added extras . . . \$7.95, or a super 16K version for \$19.95. See its review on p. 84 of the *Best of the PET Gazette*.

Warren Swan (15933 Grove Ave., Oak Forest IL 60452) has a good real-time version for \$20. It is reviewed on p. 28 of *PET Gazette*, issue #7.

Dad's Reliable Software (1614 Norman Way, Madison WI 53705) has a unique real-time version for \$12.95 that is very challenging. It is reviewed on p. 84 of the *Best of the PET Gazette* and p. 28 of *PET Gazette*, issue #7.

Breakout is a standard video game. A good PET version with sound effects is available from CAP Electronics (1884 Shulman Ave., San Jose CA 95124) for only \$4.95. It is reviewed on p. 26 of the *PET Gazette*, issue #7.

Kingdom is a simulation allowing you to attempt ruling a kingdom. Of the many versions available, my favorite is from Personal Software, Cambridge MA, for \$14.95 (with three other programs): reviewed on p. 47 of the *Best of the PET Gazette*.

Block is a classic video game also known as Blockade, Snake and Wraptrap. ZZYP (2313 Morningside, Bryan TX 77801) has a good version for \$9.95 (along with Football). It's reviewed on p. 87 of the *Best of the PET Gazette*.

Chase is a superb action game in which robots chase you around the screen. The best version I have seen is from *PET User Notes* (Box 371, Montgomeryville PA 18936).

There are a few unique games I can recommend.

Tanktics from Pleiades Game Co. (202 Faro Ave., Davis CA

95616) is a good tactical game that pits you against the PET. Fifteen dollars includes a game board, two-part program on cassette, game markers and manual. See pages 24 and 30 of *PET Gazette*, issue #7, for a review.

Two excellent fantasy games are *Swordquest* from Fantasy Games Software (PO Box 1683, Madison WI 53701), at \$12.95 for tape and manual, and *Devils Dungeon* from Engel Enterprises (PO Box 16612, Tampa FL 33687), with listing and manual only. They're available on cassette from Jon Staebell (5102 Arrowhead Dr., Monona WI 53716). See their review on pages 66 and 67 of the *Best of the PET Gazette* and in the *Kilobaud MICRO-COMPUTING* March 1979 *PET-pourri*.

MAX from Tycom (68 Velma Ave., Pittsfield MA 01201) is a great dice game for \$7.95. Also known as "lying dice," it is reviewed on pages 18 and 31 of *PET Gazette* issue #7.

Press-Up from Jamestown Small Computer Systems (2508 Valley Forge Dr., Madison WI 53719) is a fun, graphically illustrated game for kids as well as adults. Play against the PET or an opponent. Price is \$7.95.

Periodicals

Looking for information on the PET? Here are my recommendations:

PET User Notes is \$6 for 6 issues. Vol. 1, No. 7 was 16 pages; Vol. 2, No. 1 was 24 pages. Great for program listings and tidbits of information.

PET Gazette. The last two issues of this nonprofit magazine were each 36 pages. The *PET Gazette* has printed almost 200 PET product reviews already. Each issue also contains program listings, a complete list of PET companies and informative articles. Unbelievable as it may seem, the *PET Gazette* is a free publication. (Donations are gratefully accepted.)

Micro (PO Box 3, S. Chelmsford MA 01824) is a magazine for 6502-based computers, including the PET, Apple and KIM. It's \$12 for 12 issues. Each issue is about 50 pages, and contains at least one or two good articles on the PET.

Recreational Computing (1263 El Camino Real, Box E, Menlo Park CA 94025) is the new name for the oldest personal computing magazine (formerly *People's Computers*). Price is \$10 for one year of six issues. Besides the

good information on computing for fun, each issue has information on the PET.

Books

Programming the 6502 by Rodney Zaks from Sybex, \$9.95, over 300 pages. This is a good book for any PET programmer wishing to learn machine language.

Best of the PET Gazette (1929 Northport Dr., Room 6, Madison WI 53704) is 100 pages of articles, reviews, program listings, resources and more, specifically for PET users . . . only \$10 while they last.

PET User Manual from Commodore (901 California Ave., Palo Alto CA 94304) is \$9.95 at dealers. If you already own a PET, get a copy by sending a photocopy of your proof of purchase, serial number and \$3.50 to Commodore. Information from their previous tiny mini-manuals, plus some added information, is all contained in this one, bigger manual.

TIS Workbooks (PO Box 921, Los Alamos NM 87544) cost \$4-\$5 each. There are six different workbooks, each focusing on some specific area of PET programming.

Recommended PET Accessories

Keyboard—Skyles Electric Works (599 N. Mathilda Ave. #26, Sunnyvale CA 94086) has a full-size keyboard with numeric keypad that just plugs into the PET keyboard plug. Price is \$125. It is reviewed in the *PET Gazette*, issue #7.

Joysticks—Coyote Enterprises (Box 101, Coyote CA 95013) has a well-designed connector that plugs into the user port. With two Atari joysticks and sample game programs, test program and programming-instruction programs, the cost is \$50. Creative Software (PO Box 4030, Mountain View CA 94040) has a connector for the user port. With two joysticks and sample games the cost is \$60.

Printers—Connecticut Micro-computer (150 Pocono Rd., Brookfield CT 06804) has a printer adapter (output RS-232) for \$169. It should work with any RS-232 printer. I use it with a Teletype 43 and am pleased with it.

Sound—The best way to get sound output is to hook up your own speaker/amplifier using pins

(continued on page 12)

OHIO SCIENTIFIC'S SMALL SYSTEMS JOURNAL

Introduction to this month's journal

This month we will begin a multi-part series on Ohio Scientific's information management systems, OS-MDMS and OS-DMS. Ohio Scientific believes that data base managers and their subsequent information management systems are important keys to making microcomputers much more useful and generally accepted. They are also an important building block towards more sophisticated systems which demonstrate capabilities that we currently think of as being part of "artificial intelligence."

An Introduction to Microcomputer Information Management

Advanced applications of personal systems and small business computers utilize extensive data storage on disk. If one writes a few programs which utilize data storage, he quickly realizes that he is doing a lot of repetitive coding from program to program. Each program system which utilizes disk files must utilize routines that load the disk with information, routines that edit this information and routines that output the information. Commonly available DISK BASICS certainly provide the fundamental facilities for such operations, but in practice several lines of code are required for even the most rudimentary file handling routines. These routines expand greatly when sophisticated error checking and human engineering are incorporated into programs. Furthermore, in the process of developing programs the programmer may want to dump or list information in the files. As the programming system is refined over a period of months or years, it may be desirable to reorganize the information in the files. Therefore, the programmer typically develops file utilities. These may include a simple file dumper, some form of universal editor and file reorganizing facilities such as SORT, PACKER, etc.

Repetitive file handling and the need for utilities leads naturally to the concept of a data base management system. In its simplest form a data base management system is simply a convention or stand-

ardized format for disk usage. In conjunction with the standardized format several programs exist as part of the data base manager to support and maintain its format. These may include a standard editor, output routines, diagnostics such as file dumpers, utilities such as a SORT package and a library of standard subroutines which can be incorporated into user generated programs. Most, if not all, of these programs and subroutines will be typically generated in the standard upper level language of the operating system which on microcomputers would be BASIC and on large computers might be COBOL.


The immediate advantages of such an approach to file handling include the fundamental concept of standardized files which makes it possible for files generated and supported by one programming system to be used now and in the future by other programs. Standardization justifies the development of sophisticated diagnostics and utilities to aid further development of programs. Standardization along with the availability of sophisticated support programs make data base compatible software much easier to maintain than non-standardized programs. These concepts are all fundamentally part of the building block approach in which work is performed once and then used to build on as opposed to non-standardized approaches in which the same type of task is performed over and over. Thus, the data base approach inherently allows and justifies the development of more and more sophisticated software.

The disadvantage of the data base management system approach over conventional non-standardized file handling is primarily that the programmer must learn the syntax of the DMS convention. That is, one must overcome the natural resistance to new ways of doing things. Furthermore, the necessarily more general purpose code for the data base manager is not as compact or as fast as the best specialized code which can be generated for a specific file structure for a specific application. However, both of these disadvantages can be minor if the data base management system is properly designed and are certainly outweighed by the tremendous advantages of modern data base management systems.

Information Management Systems

The data base manager can be easily extended to include a stand alone package. If this package is carefully designed, it should be capable of handling a broad range of data file intensive applications without user programming. Instead of requiring programming, the information management system is to a simple degree adaptive, that is, the various modules of the information management system present the user with options which he selects. The system typically also accepts user defined syntax and incorporates it into data files and support programs. So in effect, traditional programming is replaced with a simple question and answer dialogue which specializes a generalized information system.

**Evolution of Software Sophistication
for Information Intensive Applications**



Application's of Information Management on Microcomputer Systems

Home and Personal Computers

Floppy disk based personal computer systems are well suited to the storage of personal data in conjunction with a small concise information management system. Under a general purpose information manager telephone numbers, addresses, appointments, checking account transactions, savings account records, personal financial transactions and other data bases such as recipes can be directly "computerized" without any programming.


Many personal hobbies lend themselves to the information management approach including collections of information concerning the stock market, the value of coins and stamps and even sports records. These are all naturals for a well designed information management system approach without any user programming.

Small Business Applications

Information management systems have even a more profound impact in small business applications. The data base approach can be applied to traditional small computer business applications such as accounts receivable, accounts payable, cash receipts, disbursements and general ledger. The use of standardized formats and the general report writing and inquiry capability of information management systems allows this collective data base to be used for many managerial applications besides their primary application. However, the real impact on small business is in the application of an information management system on the primary information which concerns that business. For example, in a retailing/wholesaling operation inventory on hand, vendor lists and principal customers are all vitally important to the operation of the business. The storage and manipulation of these three data bases is a trivial matter for a well designed information system. Likewise, in real estate the home listings are crucial, in manufacturing, raw parts finished goods, vendors and customers are crucial. An auto dealer may require an inventory of new cars, used cars, parts, etc. Other applications include mailing lists, estimation packages and general client information for doctors, lawyers and service companies. In each case, the

business relies on collections of information which are easily computerized by information management systems effectively without any programming.

The Hierarchy of Microcomputer Information Management



With a well designed system the transition from a general information system to what "seems" to be a highly customized applications package requires only a short question answering session at the computer terminal.

Ohio Scientific Information Management Products

Ohio Scientific offers two information management systems — OS-MDMS and OS-DMS. These two sys-

tems have similarities but are designed for different applications as outlined below.

OS-MDMS

OS-MDMS is designed to run on mini-floppy base personal computers, specifically the C2-4P series and the C1P series mini-floppy computer system. The system operates under OS-65D V3.0 disk operating system and runs in a minimum configuration of 24K RAM in one 5¼" mini-floppy disk. The system is designed primarily for personal use in such areas as checking and savings account maintenance, personal calendar, etc. It has features comparable to competitive microcomputer data base management systems. The system features very high speed and very low system overhead. Although this system is designed primarily for mini-floppy, it can be utilized on 8" floppy disk systems running OS-65D.

OS-DMS

OS-DMS is a highly sophisticated information management system that is designed specifically for Winchester disk based microcomputers. The system is based on OS-65U and readily extendable to multi-user and network systems under OS-65U Level II and Level III. The system directly supports single file up to 74 million bytes long. The system features advanced data structures and access routines which minimize access time and maximally utilize available disk storage for high levels of sophistication and "apparent intelligence." The system is also usable on 8" floppy based Ohio Scientific systems which have 48K user partitions when running OS-65U.

The system is designed to be extendable to support areas that we commonly consider to be in the realm of "artificial intelligence." It can handle general question and answering under a Query facility and has provisions for extensions to include voice I/O capabilities as well as more elaborate English language parsing. In every way, OS-DMS is the information management system of the future. It can be installed on relatively small 48K 8" floppy base computers and directly expanded to a 74 million byte Winchester disk system with multiple-users. In the future, the same fundamental system will be extended to much more elaborate language parsing and human-like I/O. Thus, OS-DMS is already prepared for the future when a typical \$1000 computer will have a 20 megabyte storage capacity. The following section is a quick summary of the capabilities of OS-DMS and OS-MDMS.

	OS-MDMS	OS-DMS
Base System	OS-65D V3.0	OS-65U Level 1, 2 or 3
Base Configuration	24K mini or 8" floppy	48K 8" floppy
Max. Configuration	48K 4-floppy system	Multi-user Winchester hard disk system with network communication
Data Structures	Entries Fields Records Files — (with key labels)	Entries Fields Records Master Files (with key labels) Key Files (Key, index pairs)
Access Types	Numeric by record and field Append Associative by specified field or general contents Conditional (< , = , > , < = , > =) to constant	Numeric by record and field Append Associative field or general contents Conditional (< , = , > , < = , > =) to constant Associative conditional as above to another field's contents ISAM by one of up to 8 key files per master file
Associative Access Technique	BASIC code Few hundred compares/sec	OS-65U "Find" command 250 Kbits/sec at 1 MHz 500 Kbits/sec at 2 MHz
Statistics Pack (All Access Types Apply)	Sum of a field Average of a field Sum of the products of two fields	Sum of N fields Average of N fields Min/max determination number of occurrences Sum of the products of N fields Standard deviation Variance
Data Base Programs	Create File Edit File File Dumper MDMS Directory Record Delete/Repack Repack SORT	Create File Edit File File Dumper DMS Directory Record Delete/Repack Record Inserter File Merge and Load SORT Optional ISAM Facility Key File Create Key File Edit Key File Load from Master Key File Sort
Information Management Programs	Statistical Analyzer Report Writer Single File Horizontal or Vertical Conditional Access Mailing Label Generator	Statistical Analyzer Single File Report Writer Horizontal or vertical Full Stat Pack Conditional and Associative Conditional Multi-File Report Writer Cross links up to 3 files by Associative Access and generates user specified report Mailing Label Generator Query System (Answers "general" questions)
Data Base Compatible Applications Systems	Checking Account Savings Account Personal Calendar Address/phone book Educational Testing System Mini A/R Mini Mailing List Mini Payroll Mini Inventory Mini A/P	Cash Receipts Cash Disbursements A/R A/P General Ledger Inventory/order entry Personnel/Payroll Estimation System Educational Testing System

In the next issue of the journal we will demonstrate many of the features of OS-DMS and OS-MDMS by typical application examples.

(from page 7)

M and N of the user port. This was explained in the February 1979 *Kilobaud MICROCOMPUTING* PET-pourri and in the *Best of the PET Gazette*.

Floppy Disks—I can't recommend any because I haven't yet seen any in operation with the PET.

List Protection

In the April 1979 PET-pourri I described a method of protecting lines in any BASIC program from being listed. Now I will explain another method, equally simple and easy to use, but which has different effects. As before, the best way to explain it is with some quick examples that you can type

```
10 PRINT"CLRLJ TRACE BY BUTLER
11 PRINT"MAY RUN SIMULTANEOUSLY WITH
12 PRINT"A BASIC PROGRAM"
13 PRINT"SYS(7868) TURNS TRACE ON"
14 PRINT"SYS(7853) DISABLES TRACE"
15 PRINT"HOLD SHIFT KEY DOWN TO SPEED IT UP
16 PRINT"CHANGE TRACE SPEED WITH POKE 7972.X
20 FOR I= 7853 TO 8192 :READDC:POKEI,DC:NEXT I
22 DATA162,5,189,181,224,149,194,202
24 DATA16,248,169,239,133,210,96,169
26 DATA172,133,134,169,30,133,135,169
28 DATA255,133,124,160,0,162,3,134,125
30 DATA162,3,32,239,30,208,249,202,208
32 DATA248,32,239,30,32,239,30,162,5
34 DATA189,249,31,149,194,202,16,248
36 DATA169,242,133,210,76,106,197,230
38 DATA124,208,2,230,125,177,124,96
40 DATA230,201,208,2,230,202,96,32,197
42 DATA0,8,72,133,79,138,72,152,72,166
44 DATA137,165,136,197,77,208,4,228
46 DATA78,240,107,133,77,133,82,134
48 DATA78,134,83,173,4,2,208,14,169
50 DATA3,133,74,202,208,253,136,208
52 DATA250,198,74,16,246,32,201,31,169
54 DATA160,160,80,153,255,127,136,208
56 DATA250,132,76,132,84,132,85,132
58 DATA86,120,248,160,15,6,82,38,83
60 DATA162,253,181,87,117,87,149,87
62 DATA232,48,247,136,16,238,216,88
64 DATA162,2,169,48,133,89,134,88,181
66 DATA84,72,74,74,74,32,211,31,104
68 DATA41,15,32,211,31,166,88,202,16
70 DATA233,32,217,31,32,217,31,165,75
72 DATA197,201,240,55,165,79,208,4,133
74 DATA77,240,47,16,42,201,255,208,8
76 DATA169,94,32,225,31,24,144,33,41
78 DATA127,170,160,0,185,145,192,48
80 DATA3,200,208,248,200,202,16,244
82 DATA185,145,192,48,6,32,223,31,200
84 DATA208,245,41,127,32,223,31,165
86 DATA201,133,75,104,168,104,170,104
88 DATA40,96,168,173,64,232,41,32,208
90 DATA249,152,96,9,48,197,89,208,4
92 DATA169,32,208,2,198,89,41,63,9,128
94 DATA132,81,32,201,31,164,76,153,0
96 DATA128,192,79,208,2,160,7,200,132
98 DATA76,164,81,96,76,255,30,32,248
100 DATA30,55,32
READY.
```

BASIC program to POKE in correct values of Trace program.

```
READY.
0 REM PI FIND REPLACE WITH 19 / 20
1 NL=19:A=1999:REM NL=VALUE TO BE POKED=A=LAST MEMORY LOCATION TO SEARCH
2 FOR X=1024 TO A:IF PEEK(X)=255 THEN POKE X,NL
3 NEXT X
4 POKE 525,5:PRINT "CLRLJ 2 DOWN":FOR X=1 TO 4:POKE 526+X,13:PRINT X:NEXT X:PRINT "HOME":END
```

READY.

Program A.

```
READY.
10 FOR L=832 TO 878:READX:POKE L,X:NEXT L
20 REM SYS832 STOP DISABLE
30 REM SYS845 STOP FUNCTIONAL AGAIN
100 DATA120,169,99,141,25,2,169,3,141,26,2,88,96,120,169,133,141,25,2,169,230
110 DATA141,26,2,88,96,169,0,72,72,72,72,76,133,230,32,90,3,234,169,255,141,9
120 DATA2,76,126,230
READY.
```

Program B.

cial function you wish to be executed. Since a DELETE will erase the previous character in the listing, 20 DELETES at the end of the line will erase the last 20 characters listed. Including the HOME function at the end of a line will cause the next line listed to start at the top of the screen.

As a quick example type in:

```
5 REM π
```

Now a normal LIST will list line 5 with a REM followed by a pi symbol. The value of that pi is stored in memory location 1030. Change it to a DELETE by entering:

```
POKE 1030,20
```

Now do a LIST and notice the line lists as:

```
5 RE
```

The M was deleted. Now add line 10 as follows:

```
10 REM THIS IS LISTED ON
TOP
```

Now change the DELETE at 1030 to a HOME by:

```
POKE 1030,19
```

Now when you do a LIST, line 5 will list fine; then line 10 will list on the top of your screen. For fun you could put the HOME function at the end of every line. Your entire program will list on the second line of the screen. Here Program A will search for a pi symbol (value of 255) and change it to whatever you wish.

This program looks for a pi symbol and changes any it finds into whatever value you specify in line 1. When it is done it erases itself. Line 4 is the line that performs the self-erasing. Please write to me and let me know of any applications of this technique you may devise.

Trace

Trace is a machine-language

program that is designed to run at the same time as your BASIC program. Trace uses the top two lines of the PET video display. It continually lists the line number and command that the PET currently is executing. Your BASIC program continues to function normally.

In Trace's normal mode, your BASIC program is slowed down enough so that you can read each line as it is executed. Thus you can see when your program branches and gets caught in a loop.

Trace also has a FAST mode. Simply press the shift key. This allows you to quickly skip through sections of the program you know are functioning correctly. Trace is excellent for debugging your own programs. It also is very useful to help you understand someone else's program. You can watch the PET screen and see how the program is functioning at the same time.

Bret Butler did a superb job with this program. He has graciously placed it in the public domain. For your convenience, we have listed a BASIC program that POKES in the correct values of the Trace machine-language program. It is well worth taking the time to type it into your PET. Hope you enjoy watching the PET execute two programs at once (Trace and your BASIC program).

STOP-Key Disable

Add the six lines in Program B to the beginning of your program. Then anytime in your program you wish to disable the STOP key, simply add the line:

(continued on page 25)

BOOKS BOOKS BOOKS

Personal Information Management Systems (PIMS)
Madan L. Gupta
Scelbi Pub., PO Box 133
Milford CT 06460, 87 pp., \$9.95

If you have been in need of a good, versatile information-management system capable of sorting and listing and that will handle the addition, deletion and change of records consisting of a variable number of variable-length fields, you should seriously consider this package. It is a well-conceived, relatively efficient method of keeping track of myriad types of information. Its applications are limited only by the user's imagination.

As written, the program permits in-memory manipulation of up to 99 records, each consisting of up to ten fields of data. Records can be formatted any way you wish, limited only by Microsoft's BASIC maximum string length of 255 characters. The program requires about 8K of user memory; at least 16K is required for this package to be of any real use.

Unlike many application packages available these days, PIMS comes without a cassette tape of the program. A BASIC listing is given in the 87-page manual, and you must do the initial keyboarding of the program into your computer. Although the manual suggests that this process will require from two to three hours, it took me about an hour.

Since the package is written in BASIC, changes are more easily achieved than they would be if the program were provided in machine code. Customizing is thus within the reach of any computer owner with a working familiarity of the BASIC language.

When the program is first run, two operating modes are available: new-file creation and file load from cassette. Creation of a new file requires the definition of field names and type of data in each (whether alphanumeric or numeric) that is to make up each record of the new file. Up to ten

fields, each with a four-character name, may be defined for each file.

Specifying a field name of more than four characters is OK, but the program truncates the name so that on subsequent display you see only the first four. For this reason, avoid field names that contain differences only beyond the fourth character (such as NAME1 and NAME2).

These field names and their type codes form the first record in your file; this record is used when the file later loads from tape to display the field names and types.

When field definition is complete, the program promptly displays (COMMAND)? and waits for your next operation. Replying with HELP results in a display of all the available commands: ADD, LIST, CHANGE, LABELS, HELP, END, SEARCH, SUM, SAVE, RUBOUT and SORT. To create a file initially, ADD puts you into the data-entry mode beginning with record 1, and displays, sequentially, each of the field names you originally specified. You simply respond to the prompting and enter data for your file.

When data entry is complete, entering STOP for the first field content places you back into the COMMAND mode from which you gain access to other features of the package.

The commands LIST, CHANGE, LABELS and RUBOUT each invoke a sub-mode that permits specifying whether you are processing *all* records, *one* record or a *range* of records (like the fifth through the tenth). LIST produces a screen list of all the specified records, including the name of the field and the data contained within. CHANGE permits the content of any field to be altered. RUBOUT deletes the record(s) from the file.

LABELS prints, without the field name, data from the first five fields of selected records. Thus, it is possible to carry data in addition to name, address, etc., in your records and still pro-

duce mailing labels with only data required for mailing.

SEARCH asks for a field number and the literal data to be used in comparison. Each record that satisfies the search constant is displayed, along with its record number. SUM permits the accumulation of a total from data within either all records or, in combination with the SEARCH function, in only those records that contain the specified data.

SORT permits the file to be sequenced according to information in any of the active fields. Sorting programs written in BASIC tend to be slow, and you notice it because nothing else is going on at the time. This sort is no exception. If you lean toward impatience, simply consider how long it would take you to do the equivalent job manually.

When you are finished with the file you are working, the SAVE command records it on tape for later use. When you are finished with the program, the END command takes you back to the BASIC interpreter, but not before reminding you to SAVE your data. This nice feature prevents inadvertent erasing of data accumulated during your session.

The first 67 pages of the PIMS manual are exhaustively complete. The first three chapters present a pleasant discussion of data management and possible uses of your home computer in a chatty, non-tutorial style . . . easy reading.

Chapter 4 discusses in detail each of the PIMS commands with examples and mentions a few tricks associated with their use.

In chapter 5, the author describes in detail 15 typical PIMS applications from building a mailing list to methods by which PIMS can be forced into being a tutor and giving tests. These last two applications, although workable, are a little difficult to manipulate; however, a few program modifications would make them excellent application areas for PIMS.

Chapter 6 contains the program listing in BASIC. The version presented will run "as is" (after you eliminate a few bugs discussed later) on Radio Shack's TRS-80. However, the author includes replacement code required for Commodore's PET and also discusses in general terms changes that may be required for support by other computers.

It is indeed unfortunate that a package as well conceived as this has to suffer from errors in the printed program listing—but it does, and seriously. A couple of the errors are sufficient to make the program useless as it is printed. But if you make the following changes to the program contained in the PIMS manual, your program will resemble the one that I have now been using for several weeks without problems.

1. Delete line 1900. This statement is apparently residue from a disk version . . . causes immediate problems in Level II TRS-80.

2. Line 990: change to: $T\$ = N\$ + T\$ + CHR\(126) . As written, the statement causes each displayed field to be shifted one field number toward higher numbers; thus, whatever you enter against field 1 is located in field 2, and so on.

3. Line 1918: change to: IF $T\$ = F\$$ THEN GOTO 1950. As written, this statement will result in an empty file after reading from tape.

4. Line 2260: the 0 in this statement is not a zero; it is an alpha O.

5. Line 2450: change to GOTO 540. The program, as published, won't exit from the mode-solicit unless a valid input is received, so you have to rub out at least one record, even if you change your mind. This change returns control to the command solicit.

6. Line 3430: change to:
 PRINT "ERROR";ERR/2+1;"IN LINE"
 :ERL

Error codes must be manipulated arithmetically to agree with their definitions in Radio Shack's *Level II BASIC Reference Manual*.

7. Line 1260: change to GOTO 540—otherwise, an attempt to SUM a file that contains only alphanumeric field types won't let you back into the command-solicit mode.

In addition to the above changes, two statements must be added in order to prevent residue from prior variable use from appearing in your data:

1675 T1\$=""
 This statement will prevent data from a field change from appearing in a following field delete operation.

2065 FOR Z=1 TO 5:B\$(Z)="":NEXT
 This statement clears out the content of array B\$ following a file load from tape; otherwise, producing labels from a file of rec-

```
2160 INPUT"FIELDS IN USE";Z$:IF LEFT$(Z$,1)="Y" THEN 440 ELSE RETURN
```

Fig. 1. Statement added to HELP routine.

ords that contains fewer than five fields results in residue from the file's description record being printed in the unused field positions.

I added an additional, helpful statement within the HELP routine that displays the field names currently in use (see Fig. 1).

Except for the bugs in the printed listing, which the above information should solve, this is a fine package, certainly worth \$9.95. Contrary to the cover's claim, it hasn't done a thing for my "life-style," but it sure helps in information management.

Curtner B. Akin, Jr.
New London CT

Countdown
Robert Eisberg and Wendell Hyde
dillithium Press
Forest Grove OR
Softcover, \$6.95, 1979

The cover of *Countdown* states that the book is concerned with skydiver, rocket and satellite motion on programmable calculators. My first reaction upon reading this was one of astonishment! How could anyone write more than half a dozen pages about simulating rocket and satellite motion on hand-held programmable calculators?

After reading more than 100 pages of text, my question was answered. When you cover everything from parachute drag to Kepler's laws, with a good introduction to conditional logic as well, it becomes difficult to write less than 100 pages!

Step-by-step instructions and, more important, step-by-step explanations are given for all the program examples. Full details are given for both Texas Instruments TI57 and Hewlett-Packard HP33E calculators, with the information needed to convert to the HP25 in a short appendix. With a bit of thought, you can modify all the programs to run on any programmable calculator that has similar functions to either the TI57 or HP33E. With a little more thought, you can use the flowcharts and program listings to develop programs in whatever brand of computerese you prefer—BASIC being an obvious candidate.

With all the Lunar Lander games being played on personal (and not so personal) systems, this book is a valuable source of both reference data and ideas. If Klingon battle cruisers obey the laws of physics from now on—in computer simulations—then this book may well be the reason!

All in all, if you ever get the urge to provide more realism in your simulations, this book is well worth investigating. The text is both clear and precise, with a sprinkling of humor. Both authors deserve a round of applause for an excellent book.

Jim Perry
MICROCOMPUTING staff

The Little Book of BASIC Style
John M. Nevison
Addison-Wesley Publishing Co.
Reading MA 01867
Softcover, 151 pages, \$5.95

Have you ever attempted to modify a computer program you wrote and had trouble recapturing the program's logic sequence or recognizing its array of variables? If so, you need the help this book provides.

A computer program is composed of code and comment, the author observes. Without code, the program cannot be read by the computer; without comment, the program cannot be read by a person. A programmer's comment clothes his program's code.

The book's subtitle, "How to Write a Program You Can Read," hints at the reward that awaits if you follow author Nevison's 19 simple rules of style. Most of the rules tell you how to indent program code and how to use blank lines to enhance program readability.

The Little Book of BASIC Style is, unquestionably, a "how to" manual, devoid of theoretical trappings. It should appeal to the computer hobbyist as well as to those who want to write good program documentation for small-business users.

Nevison's first rule, "Space symbols so that a line may be easily read," might strike you as self-evident. If the rule seems superfluous to you, compare examples of programs you are used to seeing printed in computer magazines with the well-spaced program lines that appear in the author's examples. Only then will you appreciate the need for reiterating the obvious.

Rule 10 states: "Tag variables and constants for quick reference." Few of us identify program variables (letter abbreviations whose values change) and are, therefore, doomed to reread our "cold" programs in their entirety before we are able to recapture the meanings we assigned to such symbols.

As Example 1 shows, using Nevison's rule 10 is simple.

160 REM
170 REM
190 REM

I.....THE HISTOGRAM INTERVAL
J,K.....INDEX VARIABLES
X.....A RANDOM NUMBER

Example 1.

Rule 18, "Exit carefully," contains a significant bit of advice: "When a GOTO statement exists, it should say precisely where it is going with an on-line comment." In other words, rather than using

180 GOTO 270, Nevison recommends using:

180 GOTO 270: REM PRINT OUT

Hints on selecting variables suggested by the author include using the letters I, J and K as index-counting variables (a convention carried over from algebra), using the letters L, M and N for endpoints or loops and using letters that have meaning and, thereby, enhance recognition (for example, R for radius or C for circumference).

As a computer hobbyist, you might have a legitimate excuse for not adhering to all of Nevison's rules. Each blank line and space character used in a program to improve readability consumes memory that you might require to run your program.

But even if your computer has insufficient core memory to accommodate the comment you need to chart the program's direction, there is no reason why your hand-written draft of the program should not contain a full explanation and be retained for later review should you need it.

Nevison wisely ends his list of rules with these two unwritten rules: (1) follow the rules before you break them; (2) when there are good reasons, break the rules.

The Little Book is not merely easy to read; it is easy to reread. It presents programming hints simply and punctuates them amply with examples.

If you are looking for an inexpensive reference book to guide you in writing clear, concise computer programs, Nevison's style book is certain to fulfill your needs.

Sherman Wantz
Sebring FL

Computer Capers
Thomas Whiteside
T. Y. Crowell Co.
New York NY 10022
Hardcover, 164 pp., \$7.95

On the subject of computer crime, two distinct categories of

exposition have emerged: first, the technical studies directed at data-processing professionals, and second, the tabloid stories directed at computerphobics. *Computer Capers* is a thoughtfully written compromise. Although it is not the work of an industry insider (Whiteside is a staff writer for *The New Yorker*), it demonstrates a reasonable grasp of the new computer-crime phenomenon.

Most of the text is devoted to the presentation and analysis of factual but disguised case histories. Within the constraints of general-interest, nontechnical writing, Whiteside describes the techniques used in each case to penetrate the computer. His emphasis, however, is on the human side of the crime.

What motivates someone to steal through a computer? The most obvious reason is greed. Whiteside reports that a take of \$1 million is considered "respectable but not extraordinary." But there are more subtle reasons: resentment against an underpaying, overworking position is by far the most common.

Appendix 2, "Computer-Related Crimes in Federal Programs," should be read and thoroughly digested by anyone involved in the implementation of business computers. A condensed version of a General Accounting Office report, it details the precautions that management should take to reduce the risk of a computer-abetted theft or embezzlement.

Computer Capers is a bit superficial at times. It has to be. No one could cover this topic adequately in 164 pages. The book is intended primarily for the interested layman rather than the sophisticated professional; it serves this purpose very well.

Numerous individuals, myself included, have written with consternation on the sloppy security practices common to most microcomputer systems. Perhaps this book will help enlighten those designers and businessmen who should know better.

David Price
Midlothian VA

(continued on page 25)

AMERICAN DATA INTRODUCES **OHIO SCIENTIFIC** PRODUCTS TO EUROPE.

CONTACT YOUR NEAREST DEALER.

BELGIUM

International Electronic Center
Avenue Charles Plisnier 37
B 1070 Brussels
Telephone: 521-1620
Telex 85055

UNITED KINGDOM

Abacus Computers, Ltd.
62 New Cavendish Street
London W.1
Telephone: 01-580-8841
Telex 8813085

Calderbrook Technical Services
1 Higher Calderbrook
Littleborough, Lancs.
Telephone: 0706-79332

COMP Computer Components
14 Station Road
New Barnet
Herts. EN5 1QW
Telephone: 01-441-2922
Telex: 25769

Linn Products
235 Drakemire Drive
Castelmilk, Glasgow
G45 95Z Scotland
Telephone: 041-634-3860
Telex: 77301

Mutek
Quarry Hill
Box, Corsham
Wiltshire SN14 9HT
Telephone: 0225-743289

Thames Personal Computers
13 Wilmot Way
Camberley, Surrey
Telephone: 0276-27860
Telex: 847851

U Microcomputers
PO Box 24
Northwich, Cheshire CW8 IRS
Telephone: 0606-75627

FRANCE

Computer Shop Janal
12 Rue Pasquier
75008 Paris
Telephone: 329-6237
Telex: 203919

Electronic JL
97 Rue de Chantiers
78000 Versailles
Telephone: 950-2820
Telex: 260717

GERMANY

Balu Electronics
Burchardsplatz 1
2000 Hamburg 1
Telephone: 330935
Telex: 2161373

BISY
Rheinstrasse 2
4040 Neuss 1
Telephone: 02101-28124
Telex: 8517931

LC-Rechenzentrum
Bernhardstrasse 71-73
D 55 Trier
Telephone: 0651-31026
Telex: 472621

GREECE

Compumak, Ltd.
117 Solonas Street
Athens 142
Telephone: 363-2952

ITALY

Edi Consult SRL
Via Caccini 12
20052 Monza
Telephone: 039-38-9850

Skylab
Via M. Gioia 66
20125 Milano
Telephone: 688-38-06
Telex: 32271

NETHERLANDS

Ingenieursbureau Koopmans
Joh. Vermeerstraat 7
3351 BN Papendrecht
Telephone: 078-56033

AMERICAN DATA-HOME AND OFFICE COMPUTER

1030 — 15TH STREET, N.W., SUITE 300
WASHINGTON, D.C. 20005
(202) 466-6612
CABLE ADDRESS — "AD HOC"
TELEX: 64405

150 REGENT STREET, SUITE 500
CHESHAM HOUSE
LONDON W1R 5FA
TELEPHONE: 01/439-6288
TELEX: 261426

✓ A74

NEW PRODUCTS

Edited by Dennis Brisson

Bulls and Hits

Although it's called Bulls and Hits, this game cassette from the Computer Bus, PO Box 397B, Grand River OH 44045, is really Mastermind, using numbers instead of colors. It takes a bit of work to cope with the ten different numbers that can be used for each of the four spots instead of the five used by Mastermind. The action is the same and so is the logic.

Since I'm a Mastermind fan, I enjoyed this game. It didn't take long before I could guess the numbers in five or six tries.

For like-minded people there is a paperback book out that is packed with Mastermind games. I work a few every night to help put me to sleep . . . some of these games are easy, with my record being 8 seconds . . . some are a pain and kept me gnashing my teeth for 15 minutes.

Bulls and Hits is fun, but at \$14.95 . . . whew! I checked with Instant Software as to how much they were going to charge for this type of game and found that there will be one very much like this coming out soon which

will be about one-third of a \$7.95 package of games. That seems more reasonable to me. I can see educational simulation games perhaps costing more than \$8, but the run-of-the-mill games, particularly older ones, just don't seem right at the higher prices. This sort of pricing will get newcomers in the habit of stealing software by friendly exchanges, something we really want to get away from so we can get some good software written. It will only get written if there is a way to get paid for it. Reader Service number is C127.—Wayne.

CP/M-Compatible Micral C

Micral C is now compatible with the CP/M operating system, offering double-density mini-floppy drives and an optional 10/80 megabyte disk system with removable media. The CP/M-compatible Micral C offers dynamic allocation of disk storage on floppies or hard disk, plus all the standard features of CP/M—the Save, Rename, Erase and Display Directories of Files commands, as well as editor, assem-



The Micral C system.



The AQ8080Z.

bler and dynamic debugging programs. Also available are Microsoft Extended Disk BASIC, FORTRAN IV and COBOL.

With this system, you can effectively utilize 320K bytes of floppy-disk storage (standard) and up to 80 megabytes of optional hard-disk storage (up to four disk drives, each with a 10 megabyte fixed and/or 10 megabyte removable disk). Other software available includes an advanced business applications BASIC language (BAL) with a sequential and random access file management system.

The Micral C system with dual double-density floppies, 32K of RAM, a 1920 character upper-case/lowercase CRT display, keyboard and CP/M is \$8995. The same system with a 10 megabyte disk is \$15,950. Microsoft Extended Disk BASIC is \$350; FORTRAN IV is \$450; and COBOL is \$675.

R2E of America, 47 Bedford St., SE, Minneapolis MN 55414. Reader Service number R30.

Z-80 Circuit Tester

The AQ8080Z Microprocessor Analyzer can now handle in-circuit testing of Z-80 systems, as well as 8080 and 8085 systems. Using three separate probes, the AQ8080Z now offers the safety and convenience of clip-on probe connections, direct user interaction with all memory locations and internal microprocessor registers and compatibility with all 8080, 8085 and Z-80 system configurations. As a cost-effective alternate to in-circuit emulators and CRT analyzers, the AQ8080Z needs no separate terminal, no memory allocation and no address or I/O port assignment.

The fully buffered probe clips directly to the microprocessor chip in the system being tested. The chip remains in its socket or can be soldered in. Since the microprocessor chip is never removed, the possibility of damage to the chip or socket is eliminated, and the microprocessor chip is tested along with other system components.

The interactive register access functions of the AQ8080Z include the Z-80's background (alternate) register set and index registers IX and IY. The user may examine or modify all memory locations and I/O ports and all internal 8080, 8085 and Z-80 registers, including the program counter and the stack pointer. The initial memory address may be specified by the front panel switch register or by the contents of any 16-bit internal register. Sequential access to the next memory location forward or backward is provided. Data may be transferred to or from any I/O port to help isolate faults in peripheral devices. The AQ8080Z is \$2795.

AQ Systems, Inc., 1736 Front Street, Yorktown Heights NY 10598. Reader Service number A87.

Microcomputer Analyzer

The M68UCANA1 (110 V, 60 Hz) Microcomputer Analyzer (μ CA) is a portable stand-alone test instrument for locating faults at the system, module and component level in 6800 microprocessor-based products. The lightweight attache-style case measures 19 inches wide by 10½ inches high, with a depth of 7½ inches. Weight is 21 pounds.

The microcomputer analyzer



Motorola's μ CA.

uses a microprocessor within the analyzer as the data generator, and the microprocessor socket of the system under test as the standard common test point for system analysis. The μ CA is capable of fault diagnosis at all levels because it combines the power of two diagnostic techniques—in-circuit emulation (emulating microprocessor functions with an external device) and signature analysis (locating faults by probing test modes).

Several additional built-in features include: software control of both the alphanumeric display and the keyboard, which can be modified through program instructions, rather than hardware changes, and a multiple position card cage with space for additional modules such as memory, communications interface or other microprocessor emulators. Price is \$3750.

Motorola Semiconductor Products, Inc., PO Box 20912, Phoenix AZ 85036. Reader Service number M20.

Production Duplicator

Oliver Advanced Engineering, Inc., 676 W. Wilson Ave., Glendale CA 91203, has a new production duplicator that combines both EPROM testing and programming in one unit. The UPP-2700 incorporates a unique circuit that evaluates all EPROMs both before and after programming. This circuit is designed to detect poorly erased or static-damaged EPROMs that might otherwise pass a verify test.

Simply press a single key, and the 8048 processor will test and duplicate sixteen 2708s in less than 200 seconds. A solid-state

audio "beeper" will inform you of any incorrectly inserted devices or test failures. A 40-pin personality module contains the programming and test algorithms for a complete generic EPROM family. A complete system, including UPP-2700 duplicator, personality module and power supply, costs \$2450. For medium or high production, a second duplicator (\$1995) may be connected to the power supply to program 32 EPROMs simultaneously.

Five modules are currently available to program the following EPROMs: 2704, 2708, 27L08, TMS2716, I2758, I2716, TMS2516 and TMS 2532. Reader Service number O7.

Micropolis Software

Business and personal software packages for the Micropolis Mod II Disk System (48K RAM, 8080 and Z-80 CPU and Centronics 779 printer) are available from Small Business Computer Services, 813 MacArthur Dr., Urbana IL 61801.

The consumer software includes the investment pack, which includes options analysis, bond analysis, intrinsic value of stock (Molodovsky method) and a complete portfolio management system, and the family pack, which includes family/home budget analysis, mail and phone lists and tutorials in math and spelling. The packages are \$35 each or \$60 for both.

Business software includes: Accounts Receivable System—complete cash receipts journal, aged accounts receivable report, total sales report, sales and commissions—and the Accounts



The UPP-2700.

Payable System, which allows 20 invoices per vendor and features random access files; it prints a complete status of accounts, has satellite reports that document the accounts paid and directs the totals to the appropriate General Ledger Account. The price is \$250 for both the accounts receivable and payable packages; if purchased separately, the cost is \$150. Reader Service number S95.

Bubble-Memory Computers

The Findex line of microcomputers, combining the power of a central computer with the small size and portability of a terminal, features a sophisticated BASIC-language operating system; bubble-memory mass storage; uppercase and lowercase, alphanumeric plasma display; and integral printer.

The major model in the Findex line, System 128, incorporates 128K bytes magnetic bubble

memory for mass storage. The bubble memory can be expanded in increments of 128K. This state-of-the-art data-storage technique offers high capacity in a small, stationary, lightweight package.

System 100 offers 90K bytes of mass storage in a mini-floppy disk housed inside the computer. The floppy storage can be expanded to 400K. Built-in memory in this system is the same as in System 128 and includes 48K bytes of dynamic RAM and 1K bytes of static RAM, expandable to over 2 megabytes, plus 8K bytes of ROM, expandable to 32K. External disk drives can be interfaced with the Findex to provide additional megabytes of mass storage.

Findex also contains serial, parallel I/O and S-100 capability for interfacing with a wide range of peripheral units. Findex uses a flat, gas plasma, display panel instead of the usual CRT. The scrolling display provides six rows of 40 dot-matrix uppercase and lowercase characters. The field of view can be scanned over any data base, making a large



Findex computer.



Super Grip II.

screen unnecessary for most applications. The Findex is programmed in Business BASIC but also supports a FORTRAN and COBOL compiler. Systems are priced from less than \$5000.

Findex, Inc., 1625 West Olympic Boulevard, Suite 707, Los Angeles CA 90015. Reader Service number F16.

Test Clip/IC Puller

Now you can readily test ICs with as little as 0.040 inch between opposing legs with the Super Grip II, a new test clip that features a narrower nose clearance, which easily attaches to high-density boards. The new "duck bill" contour of the contact tips provides more secure contact with DIP ICs. Super Grip II provides positive, reliable, no-shorting connections every time.

A new pin design keeps test probes where they belong: Offset pin rows make it easier to attach test probes. "Button heads" on the ends of the pins prevent probes from sliding off once they're in place.

Heavy-duty springs apply firm contact pressure for testing, hefty grip when pulling ICs. Industrial-grade nylon forms the test clip body and is integrally molded around contact pins and the steel pivot pin in the unit's hinge. Test clips are available in 8, 14, 16, 16 LSI, 18, 20, 22, 24, 28, 36 and 40 pin configurations.

A P Products, Inc., Painesville OH. Reader Service number A22.



The Tone/80.

TRS-80 Tone Generator

TRS-80 owners can now create sound effects for games, compose musical tunes or add sound to a burglar alarm with the Telesis Tone/80 Programmable Tone Generator. Designed for the Level II system, the Tone/80 responds to output commands from the TRS-80 and can produce 128 different tones.

No additional interfacing with the TRS-80 is required (it can be used with the TRS-80 expansion interface). Tone/80 is equipped with approximately 2 inches of ribbon cable with mating connector and can be plugged into either the TRS-80 keyboard module or the screen printer port on the expansion interface.

Completely assembled and tested, Tone/80 comes with a data and applications package that includes software for producing whistles, sirens, phasor sounds and even a few tunes and also includes notes on how to add various sounds to your favorite computer games. Cost is \$89.95.

Telesis Laboratory, Peripherals Division, PO Box 1843, Chillicothe OH 45601. Reader Service number T51.

Digital Multimeter

The LX 303 is a 3½-digit pocket-sized digital multimeter for electrical/electronic test, calibration and field service applications. The LX 303 features auto-polarity, auto-zero and automat-

also excellent due to the use of sockets for the major components, including the display, and the extensive use of standard components. The unit is covered by a 1 year warranty. Price is \$74.95.

The Hickok Electrical Instrument Company, 10514 Dupont Ave., Cleveland OH 44108. Reader Service number H35.

Studio II Converter


The information you've been waiting for on how to convert the RCA Studio II video game into a simple microcomputer (see New Products, *Microcomputing*, February 1979, p. 12) is now available from ARESO, PO Box 43, Audubon PA 19407. The information package describes how to construct a new cartridge for the Studio II and includes schematics, ROM monitor listing, operating instructions and program listings. ARESO also offers a printed circuit board and pre-programmed PROM containing the conversion program, as well as a fully assembled and tested cartridge.

No modifications to the Studio II are required. With the new cartridge, you simply enter machine-language programs through the keypads, and the programs can be controlled from the keypads and generate TV displays on a standard TV attached to the Studio II. The converted Studio II contains 512 bytes of RAM, 256 bytes of ROM, an RCA COSMAC 1802 microprocessor, a video graphics interface, an FCC-approved rf modulator, two 10-key keypads and a processor-controlled beeper.

The information package costs \$5. Reader Service number A86.



The LX 303.



Flashwriter II.

Double-Density Floppies

A new double-density floppy disk drive by Micro-Peripherals, Inc. (MPI), 21201 Oxnard St., Woodland Hills CA 91367, comes in two versions: Model B51 is single-sided, storing up to 250K bytes of data on one side of a 5.25-inch diskette. Model B52 reads/writes on both sides of the diskette, giving direct access to 500K bytes.

An automatic diskette positioning and ejector mechanism in the models pre-positions the diskette over the spindle hub before the clutch-centering device is engaged. This facilitates precise alignment of the diskette for operation. The mechanism also partially ejects the diskette when the door is opened, making diskette removal quick and easy.

A band head-positioning device reduces track-to-track access time to 5 milliseconds. In this development the stepper motor turns a precision pulley, built to tolerances of .0001 inch, which moves the recording head forward or backward to a track. A proprietary metal band assures years of trouble-free operation without


loss of positioning accuracy.

Both models of floppy disk drives will accommodate FM, MFM, M²FM or GCR encoding techniques. Reader Service number M14.

High Density/Reverse Video Board

The Flashwriter II video board displays 80 characters \times 24 lines and uses an 8×10 dot matrix to produce sharp resolution for 1920 character positions in a 2048 byte memory block. In addition to normal video, reverse video is optionally controlled by the higher-order bit of the character code. As many as 256 characters can be generated by 2708/2716 EPROMs, which may be user-programmed for special symbols or graphic displays.

The Flashwriter II allows rapid updating of the screen via memory-mapped I/O. Special circuitry prevents flashes on the screen when updating memory, and a keyboard port with latched data provides easy interface to other parallel keyboards. Price is \$320,



INMOD-885.

assembled.

Vector Graphic, Inc., 31364 Via Colinas, Westlake Village CA 91361. Reader Service number V10.

S-100 Processor/Console

The INMOD-885 is an S-100 processor/console board with integral CPU and console functions. It features a 3 MHz 8085A CPU, versatile EPROM monitor, 20-digit keyboard and 8-digit prompting hex display.

The 8085A CPU executes all 8080 programs at 50 percent faster speed than other S-100 CPU boards even though the system chip count and power supply requirements are reduced. The hex keyboard/displays increase speed and versatility in programming and debugging. The prompting hex displays reduce the chance of error in reading or entering data, and the clear hex console keyboard reduces the chance of conversion error in program entry.

The conversational monitor provides usual I/O functions plus memory protect/unprotect and two powerful debugging aids. The unit, assembled and tested, costs \$399.

Industrial Modules, Inc., PO Box 2985, Santa Clara CA 95051. Reader Service number I37.

Flat Cable Guide

Bonded and laminated flat cable, bulk and prestripped flat jumper cable and custom cable assemblies are described in a new 8-page guide published by Belden Corp.'s Electronic Division. The publication, No. ED79-1, describes the space-, weight- and cost-saving benefits of Belden's UL-recognized flat cable for multi-point interconnection applications. Specifications and technical data are presented for 26 bonded constructions, rated at 80° C/300 V, with 10 to 30 round conductors.



Belden's cable guide.

The illustrated booklet also describes new bulk and stripped-to-length flat jumper cable with 3 to 36 conductors at 0.100 inch spacing and Belden's custom cable-conductor assembly and harness capabilities. Ordering information keyed to Uniform Product Code designations is included for standard constructions, along with a special chart that aids specification of custom jumper cable designs.

Belden Corp., Marketing Communications, 2000 S. Batavia Ave., Geneva IL 60134. Reader Service number B41.


S-100 Serial Port

ESP+ is an eight, full-duplex serial board for the S-100 bus. It is the first of three boards and associated license software to comprise a data communications subsystem available from Trace Electronics, Inc., 570 West DeKalb Pike, King of Prussia PA 19406.

The ESP+ provides memory-bank switching, two (or one, if bank switching is used) 8-bit bidirectional parallel ports, an 8-bit sense switch and three 16-bit counters, which may be used independently or in tandem for interval interrupt and nonstandard baud rate generation. Each port may run at any of nine baud rates from 110 to 9600. All lines present one LS load to the bus. Inter-



MPI flexible disk drive.



The CI-S100.

rupt modes are provided for each counter, serial port and parallel port.

Three additional cost options are available:

- a six-digit time of day clock accessible through the ESP+.
- a modem controller to handle incoming lines from up to eight modems.
- a software baud rate controller to select the baud rate for each serial port independently.

The ESP+ is \$895, assembled and tested. Reader Service number T60.

64K Byte Memory

The CI-S100 is designed to plug directly into the memory slots of most S-100 microcomputers. The dynamic RAM memory module requires no wait states at 2 or 4 MHz and is compatible with most S-100 bus microcomputers, including the Z-80 at 4 MHz.

The CI-S100 includes expandability to a half megabyte with a bank-select feature, which allows you to select up to eight 64K byte memory cards. On-board hidden refresh requires no outside intervention, making the CI-S100 look like a static RAM to the outside world, even during block DMA write applications.

The 5×10 inches memory


module is addressable in 4K increments up to 512 bytes of memory. It is available with battery backup capability. Price is \$695.

Chrislin Industries, Inc., 31312 Via Colinas #102, Westlake Village CA 91361. Reader Service number C125.


Universal Card Cages

The CCM 13 (5.25×9 inches) and the CCM 14 (3.5, 5.25, 7 or 8.75×9 or 12 inches) series cages give designers a choice of compatible 19-inch rack-mounted enclosures with four heights and two depths. Thirty-two individual aluminum L-shaped cardmount modules of various heights, widths and lengths accommodate virtually all standard and many special card sizes.

The universal card-cage system features heavy-duty aluminum side walls joined by rigid extruded channels and slots in the side walls and mounting brackets that permit four-way connector adjustment—up, down, forward and backward. The cages' cardguides, on one-inch centers, permit installation of up to 16, one-inch cardmounts or any similar combination utilizing one-inch, two-inch, three-inch or four-inch wide modules. Captive nuts in the rear extrusions allow receptacle



The CCM 14.



The PE-24T.

mounting with any spacing. The cages also accept motherboards for rear-panel interconnections.

In under ten quantities the CCM 13 card cages range from \$54.22 to \$135.03, and the CCM 14 card cages range from \$50.04 to \$75.00, depending on size. Cardmount modules must be ordered separately, except for the CCM 13 series, and range from \$5.01 to \$8.50 (1-49), depending upon the size.

Vector Electronic Company, 12460 Galdstone Ave., Sylmar CA 91342. Reader Service number V8.

EPROM Eraser

The PE-24T is a new EPROM erase lamp that includes a pair of ultraviolet-emitting glass tubes. Weighing only 3 lbs., it is intended for the bench or engineering lab and gives big-lamp results at a much lower cost. A conductive-foam pad holds up to nine EPROMs at the correct distance and exposure angle to assure fast and complete erasure of today's largest EPROMs.

Operator safety and convenience are provided by a slide-out tray that has a blue viewport and automatically shuts the lamp off if opened during operation. The built-in timer can be preset for automatic shutoff times of up to one hour. Price is \$114.50.

Adco Electronics, 2182 DuPont, Suite 222, Irvine CA 92715. Reader Service number A85.

Compose II

Compose II, a new report generation software package designed for Data General end users, is written in Business BASIC and is designed to operate under DG's RDOS operating system. Based upon the original Compose package, the enhanced software pro-

vides even greater value to users, who can now benefit from advanced refinements.

Reports can be custom-designed, formatted and produced by answering a set of video-displayed questions and require no programming knowledge or previous computer experience to generate. Secondary files can be accessed to retrieve related data for inclusion, and an existing index permits definition of the selection and sort in order to speed processing.

Compose II allows 16 columns, up from nine previously provided, and incorporates a test for any column to determine whether a specific print line should be included. Price is \$3000.

Compusource Corp., 21735 S. Western Ave., Torrance CA 90501. Reader Service number C126.

Zilog Data Book

Zilog, Inc., announces the *Zilog Data Book*, the first compilation of detailed specifications for the firm's components, boards and development systems. The 132-page book is aimed at design engineers who will use Zilog products in constructing their own microcomputer systems. It includes sections on the Z-80 family of MOS LSI microcomputer components, Zilog memory components, the MCB series of microcomputer board products and the ZDS-1 series of microcomputer development systems.

Each of the *Data Book's* three major sections begins with an introductory description of that category's significant features. The catalog also contains a list of Zilog's regional offices and an order form for additional Zilog literature. Cost is \$5.

Zilog Literature Dept., 10340 Bubb Rd., Cupertino CA 95014. Reader Service number Z3.

THE \$798 INTERTUBE II®



It's already a big success!

The party's over for all dumb terminals and a lot of smart ones too. But, at \$798 (quantity 25), the party's just beginning for Intertec's InterTube II.

Standard features to celebrate include a full 24 line by 80 character display, 128 upper and lower case ASCII characters, reverse video, complete cursor addressing and control, an 18 key numeric keypad, special function keys, blinking, protected fields, character and line insert/delete, editing, eleven special graphics symbols, a 25th status line which displays the terminal operating mode and an RS-232 printer port.

You'll discover even more reasons to celebrate when you sit down in front of an InterTube II. Our wide bandwidth monitor produces crisp, sharp characters everywhere on the screen. InterTube's Z-80 processor enables a host of operator oriented features to boost the efficiency of both software and programmers. And, InterTube's rugged modular design combined with its built-in self-test mode insures quick and reliable servicing.

InterTube's price/performance ratio can satisfy your requirements whether they be a sophisticated data entry application or a simple

inquiry/response environment. So, there's really no reason to think "dumb" when you can afford to be so smart!

Join the thousands of InterTube celebrations going on around the country at this very moment. Call us at the number below and start your own celebration (BYOB—we'll bring the InterTube).



2300 Broad River Road, Columbia, S. C. 29210
(803) 798-9100 TWX: 810-666-2115

* \$995 Quantity One

COMPUTER CLINIC

I am using the "(Con)text Editor" program described in the September 1978 issue of *Kilobaud* with my Level II TRS-80 and an elderly Model 15 TTY. I am pleased with the program, except for one thing: no commas or colons allowed. The author cures this problem for Mits 8K BASIC 4.0 by poking a 34 into locations 2507 and 2509 early in the program, and then restoring a 58 and 44 to those locations before the user leaves the editor. Does anyone know the secret locations for the same things in TRS-80 Level II BASIC? If so, I would appreciate their getting in touch with me.

Louise H. Frankenberg
1289 Magothy Rd.
Pasadena MD 21122


I have just received a "Nibbler I" microcomputer (SC/MP II with 4K NIBL BASIC in ROM and 2K RAM), to which I intend

adding 6K more RAM. I would be pleased to communicate with anyone who is using this unit with a view to exchanging information on the expansion, use and programming of this tiny system. I request that any *direct* postal communication to Australia be via *air mail*, as the 3-month-plus delay of surface mail makes for v-e-r-y extended communications.

Graham Gaiger
50, Armour Way
Lesmurdie 6076
Western Australia

Some have encountered forced-air cooling problems with Imsai's I-8080 series of microcomputers. The problem stems from improperly designed air-inlet slots. Cooling efficiency is compromised by excess slots on the cover and a poorly placed power transformer.

Cooling can be considerably improved by blocking certain



cooling slots, thus balancing the air flow through the chassis. Just match the power-supply combination installed in your computer with the descriptions above and cover the slots accordingly. Duct tape may be used to effect these alterations. All panel views are from the inside of the cover.

Michael J. Fries
PO Box 17296
Irvine CA 92713

Our Washington office needs help in locating teachers for computer science and electronics.

The Department of Defense Dependents Schools, serving the children of US military and civilian support personnel throughout much of the world, are in need of computer-science teach-

ers and electronic-training instructors. Thirty-eight computer systems are available to the instructional program, with BASIC being the most commonly used language.

Qualification requirements: A minimum of nine semester hours in computer science plus sufficient additional course work to qualify as a teacher in another subject.

For full information, call Mr. Francisco or Ms. Wycoff at (202) 325-0690 or write to the address below for an employment application.

Samuel W. Calvin
Coordinator,
Computer Education
DOD Dependents Schools
2461 Eisenhower Ave.
Alexandria VA 22331

LETTERS

Hail Heath

Ron Rocheleau's fine article on the Heath Disk System (April 1979, p. 30) covered the main points of this first-rate disk operating system, but Ron omitted some of the more subtle features. For instance, the controller-board ROM contains a memory-test routine called up from the H8's front panel that tests both its own and the H8's RAM. Another useful technique is the use of the Peripheral Interchange Program (PIP) to concatenate files or programs, usable with one disk drive or two.

Ron mentioned the SET feature, which allows, among other things, the setting of drive seek time. The manuals indicate that

seek times down to eight msec. can be set, but I have found that five out of six drives I've seen will in fact go to six msec. The drives are extremely reliable; in nine months of nearly full-time use, neither has shown a hint of a problem.

One of the greatest advantages of a disk system comes from the ease of creating assembly-language programs. Always a tedious process with the standard two-pass tape assemblers, the disk makes this chore fun. Heath's editor is optimized for this function, not for word processing (but the Heath Users' Group has a disk-based character-oriented editor available for \$16.50). Until you've used a disk to create an assembly-language program, you won't appreciate the true value of

the system.

Also worth noting: Heath has just released a version of Microsoft's BASIC with formatted print statement and double precision (\$100) and Microsoft's disk FORTRAN (\$150), both real bargains, with business-oriented software packages available in June. Furthermore, Lifeboat Associates' Tony Gold has announced the impending release of CP/M for the H8, which will allow use of all sorts of specialized ready-to-run software.

Happy with Heath? I should say so. They've been around for a great many years, and their support is the industry's standard. I can only echo Ron: Compare system-for-system, and you'll go with Heath, too.

D. C. Shoemaker
Leavenworth KS

Dot Dot Dot

The first (and only) response to my challenge ("The 1802 is the most powerful 8-bit micro") ar-

rived in my mailbox before the February issue of *Kilobaud MICROCOMPUTING*, in which the challenge was printed. You can imagine, then, my astonishment to find that Mike Amling had beaten my code not by 10 percent but by over 30 percent! Aside from a few inconsequential bugs in his code, he did meet the requirements. Therefore, I did award him his \$50 (ouch!) prize, though rather reluctantly. I say reluctantly, because he used another way of organizing his tables than I did. As soon as I saw what he had done, I revised my program along the same lines and beat his code by another 0.2 percent.

What Mike proved, then, was not the superiority of the Z-80 over the 1802, but the superiority of his cleverness over mine. I will have to concede, however, that the Z-80 fared no worse in the contest. I have to infer from the lack of large numbers of entries that none of the other micros came anywhere near.

Let me suggest an alternative version of my claim: All the 65K-8-bit microprocessors have about

the same power (measured in bytes-memcycles), so you might as well pick yours for other reasons, such as available software (Z-80/8080) or buy-in price (6502 or 1802) or low power (1802) or the phase of the moon. I still think the 1802 has a cleaner architecture. It is a great pity that the folks at RCA who make it (and even the guy who designed it!) do not understand its fine qualities well enough to promote the 1802 adequately against the 8080 family.

Tom Pittman
San Jose CA

Purrs over PET-pourri

Just a note to let you know how much I appreciate Len Lindsay's "PET-pourri" column in your magazine. As an owner of the notoriously undocumented PET machine (which I think is a wonderful piece of hardware), I have found the column to be almost invaluable. I sincerely hope you encourage Mr. Lindsay to keep it up, and that you continue to publish it, notwithstanding grumblings from TRS-80 owners, etc. I entirely agree with your editorial comment in the March 1979 issue that the column is justified by the lack of information from Commodore. Of course I am prejudiced.

In any event, I think the column has a good balance between software and hardware content, sources of software and hardware, and comments on some of the PET-related products available.

E. T. Greeley
Rome NY

Every Key

I was looking through my Radio Shack Level II's memory map the other day and poking and peeking around, when I ran across some interesting information that might be of interest to your readers.

Every key on the keyboard is available for direct access by the user. That means every key, including the four arrows and clear key. By typing in the program below, some programmers can get some ideas on how to put this to use. Probably the first and foremost use would be in games, where instead of using INKEY\$ and U or D for up and down the programmer might directly use the arrows. The interactive clear key could be used the same way

Level I uses it by clearing the screen while the program is executing if there is a need to do so.

```

10 CLS
20 IF PEEK(14400)=8 THEN PRINT
  "UP";
30 IF PEEK(14400)=16 THEN PRINT
  "DOWN";
40 IF PEEK(14400)=32 THEN PRINT
  "LEFT";
50 IF PEEK(14400)=64 THEN PRINT
  "RIGHT";
60 GOTO 10

```

After running this program, start depressing the four arrow keys, and see how smoothly the operation runs.

Greg Perry
Tulsa OK

Curious Catasquian

In his attempt to compare algorithms ("Testing PET Search Algorithms," April 1979, p. 112), Mr. Morse discovered that a FOR loop is faster than a routine containing a GOTO, and that a GOTO that goes to its own line number

is faster than one that goes somewhere else... and someone has labeled all this as "curious idiosyncrasies."

Isn't it obvious that a routine that does not require a line-number search is faster than one that does? Also, PET (Microsoft) BASIC has a somewhat optimized GOTO. A few tests are made before a line-number search is begun. I have seen BASICs that ran at half the speed of PET BASIC. Those are the ones I would call "curious."

Earl Wuchter
Catasqua PA

Simplifying "Depreciation"

Joe Ligori's program for the comparison of methods of depreciation

Polishing "Diamonds"

I enjoyed the "Two Diamonds" game by Bill Colsher in the April

The COMPUTER FACTORY

TO ORDER CALL TOLL FREE 800-223-7318

COMMODORE "PET"

only \$795 USED \$549

- 14K ROM Operating system
- 8K RAM Memory
- 9" Video Monitor
- Built in Keyboard
- Digitally controlled tape

Today's best value in personal computers, along with the latest in peripherals, are always in stock at the COMPUTER FACTORY.

NEW! PET BUSINESS SYSTEM

The PET is now a truly sophisticated Business System with the Floppy Disk and Printer which makes an ideal cost efficient business system for most professional and specialized fields: medicine, law, research, engineering, education, etc.

PET 2001-16K \$995 32K \$1195

- 16 or 32K Bytes Dynamic RAM
- 14K ROM Operating System
- 9" CRT
- Upper/Lower Case and Graphics
- Full Speed Business Keyboard
- Full Screen Editing
- Operating system will support multiple Languages (BASIC resident)
- Machine Language Monitor
- 8K ROM Expansion Sockets

\$549

ELECTROSTATIC PRINTER 2021

- 80 column dot matrix
- Full PET graphics
- 8 1/2 inch paper

PET MUSIC BOX
Add music and sound effects to your programs. Compose, play, and hear music on your pet. Completely self-contained (no wiring). Free 3 programs including Star Wars theme, sound effects, etc. \$35.

DUAL DRIVE FLOPPY DISK 2040 \$1095

- 360 K Bytes Storage
- High Speed Data Transfer
- Plugs into IEEE Port
- 8084 Microprocessor
- 8K ROM Operating System
- 8K ROM Encoding and Decoding
- 4K RAM
- Use Single or Dual sided Disks

SINGLE DRIVE FLOPPY UNIT 2041 \$595

- Intelligent mini floppy
- 171.5K net user storage

PERIPHERALS FOR PET

- 4K Memory Expansion \$499
- 8K Memory Expansion \$599
- 16K Memory Expansion \$899
- 16K RAM (up to 32K)
- Serial and Parallel I/O
- Real Cassettes I/O
- 2K 8K Emulator
- 5 1/8" Disks
- 8K User Defined Characters
- 256 x 128 Resolution Graphics

Modular design allows use of both systems for program and data. Real RAM controller for instant language connections (Ada, APL, Pascal, PL/I, FORTRAN, etc.) Add more and more to disk for computer expansion.

Word Processing For PET

With this program to hand, you can create text and add, delete, center, recall lines and more text stored on page or between pages. Use either PET or terminal keyboard. \$49.95

FREE \$25 of Software with purchase of any computer in this ad.

NEW! BILLINGS MICROSYSTEM

EXPANDABLE TO 2 MEGABYTES

features:

- 12" CRT
- 64K RAM
- Z-80
- Dual mini floppy
- 320 K Storage
- Graphics
- 34 Keys
- 2 RS-232 ports
- 1 parallel port

only **\$3645**

BUSINESS SOFTWARE AVAILABLE!

Compucolor II

COMPUCOLOR II Disk-Based Model I

Advanced hardware and software technology gives you:

- 12" Color Display
- Advanced Color Graphics
- 51K Disk Built-In
- 16K ROM Operating System
- 8K RAM User Memory
- 8K RAM Refresh
- 8084 Microcomputer
- RS-232 I/O

Every unit comes with an extended DISA BASIC that has full file management capability resident in the COMPUCOLOR II on 16K of ROM. Color is fantastic, but COMPUCOLOR II has the power to handle complex tasks and small business applications. An impressive software library supplements your own creativity.

\$1495 Complete! 16K Model add \$200 32K Model add \$500

SALE!

Come In Or Call For Special Low Prices

WE'RE MOVING TO LARGER QUARTERS AND MUST SELL EVERYTHING IN OUR INVENTORY

SORCERER

SPECIAL 12" Video Monitor for SORCERER (\$299 value)

ONLY \$125 with 8K unit 95 with 16K unit 65 with 32K unit

RADIO SHACK • PET • SORCERER • APPLE • COMPUCOLOR • ETC.

PRINTERS • PRINTERS • PRINTERS

The COMPUTER FACTORY's extensive CENTRONICS 779 \$1045 inventory and wide selection of computer AXIOM (Parallel) 395 printers assures you of finding the printer AXIOM (Serial) 485 best suited for your needs and EXPANDOR (Tractors) 425 specifications. The following printers work INTEGRAL DATA 795 well with all known personal computers. QUME or DIABLO 3400

APPLE II from \$970

Western Digital's new 16-bit Pascal Computer System

- 64K bytes (32K words) of RAM
- 2 RS-232 ports
- 2 8-bit parallel ports
- Floppy disk controller
- Floating point hardware
- Memory Mapped I/O
- Enclosed power supply

\$2995

Open Mon.-Fri. 10-6 Sat. 10-4

SPECIAL SALE
Buy any computer and take 10% off price of printer of your choice

TO ORDER CALL TOLL FREE 800-223-7318

The COMPUTER FACTORY

485 Lexington Avenue 750 Third Avenue New York, N.Y. 10017
(212) 687-5001 (212) 212-2121 Foreign order desk - Telex 640055


```

0473 IF ABS(X1-X)=1 IF ABS(Y1-Y)<>1 F=1:RET.
0474 IF ABS(X1-X)=2 IF ABS(Y1-Y)<>2 F=1:RET.
0475 IF ABS(X1-X)=0 IF ABS(Y1-Y)>4 F=1:RET.
0476 IF AB(X1-X)>2 F=1:RET.

```

```

0703 IF B(3,5)<>0 T.750

```

Additions to "Two Diamonds" program.

1979 issue (p. 115); however, I would like to make the following correction and suggestions. Line 90 has a typographical error in running J from 0 to 5—it should run from 0 to 9. Second, the program only checks for attempts to use "unusable" spaces. I have reworked the program, adding lines 473, 474, 475 and 476, which check for moves from permissible locations and only permit those in accordance with the rules. Line 703 adds the restriction that the 0 must be returned to the center of the board before the game is over.

I enjoy your magazine. Please try to keep up the number of 6800 articles. The renumbering editor in the January 1979 issue was absolutely outstanding!

C. H. Looney
Hyattsville MD

Mr. Looney is right. Sorry about the typo in line 90 (though they let me know people like my programs!).

Bill Colsher
Lisle IL

Long Live Lexicography!

I, too, was thrown by Ancelme's reference to ASCII being people who cast no shadow (see "Letters," March 1979, p. 22). Having no *Webster's Unabridged*, I turned to my 1911 copy of Laird & Lee's *Webster's New Standard Dictionary* and found this: ASCIANS (as'si-anz), n. pl. Inhabitants of the torrid zone who at midday of one or two days in the year cast no shadow, the sun being directly overhead. (L. *ascii*; from Gr. *askioi*, pl. of *askios*, without shadow; from a priv. and *skia*, shadow.)

Leaving all that aside, have you tried to pronounce USASCII?

Dr. X
The Chroma-Zone
San Francisco CA

Ascii have been discovered only betwixt the Tropics of Cancer and Capricorn, never in the higher latitudes. Apart from this, detection is not facile owing to the paucity of their penumbral solar eclipse. Please also bear in mind,

if intending to mount a hunting expedition, that there will more than likely be Englishmen and mad dogs in their immediate vicinity.

M. Parris
Victoria BC
Canada

Mr. Roichel must have been exposed to the classics or a classicist. The prefix A- means devoid of. SCI- is defined by *Webster's* as being a prefix referring to shadows. Finally, the terminal I is constructed to be the masculine plural suffix. Put them all together; they spell ASCII—men without shadows. I hesitate to spoil Ancelme's fun by suggesting that the proper form might be ai askioi. I suppose next he will be complaining you should say omnibus instead of bus.

David Block
Gainesville FL

Ancelme Roichel's "transcendentally cryptic statement" needs no translation, but could bear a close look at pronunciation. My *Webster's* lists ascian as "a person who casts no shadow at noon; said of the inhabitants of the torrid zone where the sun is vertical for a few days each year." Unfortunately, the word is pronounced "ash yan."

Serendipitously, the word ascii also appears! This is shown as the plural of ascus. An ascus, it turns out, is a "spore sac in an ascomycetous fungus." I think this word fits the mold a lot better.

Warren S. Kirkland
Security CO

Also contributing to this etymological elucidation were Warrick M. Locke of Milpitas CA and Gary Harris of Panorama City CA. Thanks, one and all.—Editors.

EPROM Follow-up

Two of your readers wrote me to tell me that my "El Cheapo EPROM Programmer" (*Kilobaud MICROCOMPUTING*, March 1979, p. 46) would work on the

Intel 2716 16K EPROM as well as the 2758 by one's merely rewiring pin 19 to the A10 address line. As far as I can discover, only the Intel version allows the 5 volt programming pulse to be used as required with the programmer I described.

Dr. Ward J. McFarland, Jr.
New Haven CT

Editorial Review

Thank you for publishing the excellent guest editorial, "Review That Book!" by Rod Hallen (March 1979, p. 7).

All any book publisher wants is a fair appraisal. Some reviewers are going to like the book and some aren't, but as long as the reviewer is fair, I'm happy.

Keep up the good work!

Merl K. Miller
Publisher, dilithium Press
Portland OR

PUBLISHER'S REMARKS

(from page 5)

you need, and you'll be helping others as you learn.

Once you know your way around a half dozen different microcomputer systems, both the hardware and software, you will be ready for your next big step: experience in the industry. I suggest starting with a computer store since you'll get invaluable experience there for anything you may want to do later on. You'll be able to learn about servicing, selling, purchasing, advertising, bookkeeping, printing, shipping, accounting, contracts, taxes, governmental problems, licenses, financing. If you work for a store and don't learn about all those things (and a lot more), it means that you have not been taking advantage of your job.

Getting the Job

It's awfully easy to get work if you go about it the right way. Will it surprise you that about 99.9 percent of the people looking for work go about it all wrong? We have whole industries, such as job-placement outfits and resumé-writing firms,

built up around the wrong way to get a job. You don't want to waste the time and expense of preparing a resumé. What you really should do is sit down and think about selling yourself . . . and getting the best price you can for the package.

If you think about a resume for a moment, you'll recognize that it is mostly self-satisfying. Few resumé's are written with the view of selling your experience and talents. The key to all selling can be boiled down to two simple words: *user benefits*. So, taking these two words in hand, how can you apply them to getting that job you want?

First, you have to be aware of the vast difference between looking for a job and looking for a career. You're looking for a career, not a job. This means that you are in no way looking for a firm that has a job opening. You will never ask if the firm needs someone or has an opening because that is irrelevant. The talents and experience you have to offer are such that the firm you choose *has to hire you*.

You can sell yourself to any firm if you keep in mind the user benefits. What are the benefits to the firm of having you work for them? If you are talking to the president, and you should be, since you'll be able to learn far more with a small firm than with a large one—be sure to make the benefits that you will bring to the president abundantly clear. You'll be able to help make more money for the firm and you can then explain exactly why. Bring out everything you can think of that will benefit the firm and your interviewer.

For several years I've been writing in my editorials that I am looking for people to join the staff. In all of that time I don't think anyone has ever tried to sell me on what he or she could do for me. I get resumé's by the gross, and they tell me very little.

If someone walked into my office and said to me that he had been looking over *Kilobaud MICROCOMPUTING* and he could put together a book of programs we had already published which would sell at least 5000 copies for a gross profit of at least \$15,000, I would start listening closely. If he went on to say that this would take him no more than a week or two and that then he'd like to start writing to every known programmer to get us more programs for both *MICROCOMPUTING* and *Instant Software*, I'd be real anxious not to let this ball of fire get away.

You can get into just about any

firm you want if you put a little work into it. First, pick out a likely business and then start checking it out for its needs. It doesn't hurt to visit the place and talk to the people working there. This can give you invaluable leads toward things that they need to have done.

Put yourself in the seat of your prospective employer and see what might be attractive to him. Would the certainty of increased income be a selling point? How much do you think I would pay for someone who could get a dozen books produced for us during a year? How much would an advertising salesman who could sell \$250,000 worth of advertising a year be worth?

What have you to offer a computer-store owner? This is a great way to gain your experience, but you have to be worth at least the minimum wage to start getting this experience.

Let's say you have a good background in hardware service, so you'll be able to step right in and produce a faster turnaround on servicing for the owner. This could save a lot of money and time on equipment that otherwise might have to be returned to the factory.

You can also help keep the book section and magazines straight for him, help sell systems to customers—perhaps do some simpler custom programming for business customers—see that his inventories are kept up to snuff, do a lot of the paperwork that has gotten behind, and maybe even bring in a lot of the friends you've made through the computer club and users groups as customers.

If you can't get into the place this way, you might try a left-handed approach by providing some free-lance service for him for starters, charging per job instead of by the hour. The main thing is to get your foot in the door and then work hard, always doing much more than you're paid to do.

No matter what work you are doing, make it your business to know more about it than anyone else. If you are involved with bookkeeping, start reading books on the subject and maybe even take a night course. Read every magazine even remotely involved with your work. (I read over 150 magazines a month, plus several books and a lot of spec sheets and instruction books, to keep up with my work.)

It's good to make letter writing simple for yourself. Always have typewriter, paper, envelopes, stamps at hand so you can quickly dash off a letter asking for in-

formation, order parts, confirm telephone orders.

Point out how you can benefit the owner of a business, and you will usually have a place to work. From then on it is up to you to spend every possible minute getting things done and learning more. I'll write more in the future about how to parlay this into a fortune.

I practice what I preach, and I have the results to prove it. Everything I mentioned in the first paragraph I pulled from my own experience. Twenty years ago I had a yacht, two Porsches, my own plane, an Arabian horse and had already been around the world once. I'm having so much fun now with my magazines and Instant Software that I don't

have time to horse around. I still travel around the world a bit, despite the horrendous cost of travel these days.

Now that I know exactly how to start a new magazine, it isn't very difficult—and a new magazine adds another million dollars or so to the yearly gross. Once you understand the fundamentals of success and how to work toward it, there is almost no way you can fail. Anyone who really wants to can become a millionaire within five to seven years—and in the microcomputing field I'd shorten that to a maximum of five years, just starting from scratch.

About 15 years ago, I started thinking seriously about the basic

difference between people who were making it and those who were aiming at mediocrity and poverty for life. Once I began thinking about it and doing a bit of research, I found that there were some secrets that hardly anyone had recognized.

Unfortunately, these secrets are very difficult for those inculcated by the establishment to accept, no matter how obvious they are. Having facts and reason on my side helps some in arguments, but not a lot. Many people wasted a lot of their lives because they didn't take the time to sit down and figure out the ramifications of what they were doing. If you're really interested I'll continue this exposé into the secrets of success. Let me know.

BOOKS BOOKS

(from page 14)

**The Datasearch Guide to
Low Capital, Startup
Computer Businesses
Datasearch Incorporated
Memphis TN, 1977
156 pages, Softbound, \$20**

When I saw the ad for this book in *Kilobaud MICROCOMPUTING*, I thought that this was just what I was looking for. I wanted a home computer that would pay for itself, and this book would apparently provide the answers I needed. This turned out not to be the case.

This book is not aimed at the computer hobbyist, but rather at the computer professional who is looking for extra income.

There are, in fact, 22 ideas for businesses, as advertised, but they deal mainly with the sales area. Unless you have a knowledge of the major computer industry, and this does not include micros, the ideas will not be of much use to you.

Micros are covered briefly in two small sections. One section deals with home computers coming of age, and the other section covers program and peripheral development needed for this industry, but does not give any real information or ideas on how to tap this area. It does mention Instant Software, but any regular reader of *Kilobaud MICROCOMPUTING* will get more information on this from the editorials than is provided in this guide.

The copyright statement states that no specific guidance for a business is intended, and I was not looking for specifics, anyway, but ideas. This book has them, but not in the areas I expected.

There are sections dealing with image building and personal evaluation. These are a must if you plan to start your own business, and I think they are well covered.

Is this book worthwhile? If you are a computer professional and thinking of venturing off on your own—yes. In addition to giving you some ideas, it will help you to evaluate yourself and your prospects for success. It also offers some good image-building advice. If you are a hobbyist looking for a way to make your system pay for itself, the ideas in this book will not be very helpful to you.

**Thomas Laich
Charleston SC**

PET- POURRI

(from page 12)

**550 SYS(832) : REM STOP
DISABLED**

You should disable the STOP key while you are playing music or producing sound effects via user-port pins M and N. If a user stops your program while in the sound mode, his/her tape units will not function correctly. You can enable the STOP key again with this line:

**650 SYS(845) : REM ENABLE
STOP**

Be careful about adding this to your program while you're still testing it. You won't be able to stop your program unless you include a way out. This could be a simple GET command that monitors your keyboard. For example:

```
1200 part of program is here
1210 GET AS : IF AS = "Q"
      THEN END
```

1220 program continues here

Next month I will tell you about Axiom's graphic plotter for the PET with some sample output. Also, I'll relate more general, helpful tips and sources for materials.

Please write with your comments and suggestions to Len Lindsay, 1929 Northport Drive, Room 6, Madison WI 53704.

Contest!

March's "best article" winner is Gregory Yob, author of "PET User Port Cookbook."

In the Book Nook drawing, Rudolf Lehn of Ertingen West Germany is the recipient of a book choice.

Winner of a lifetime subscription to *Microcomputing* is listed on page 4.

Congratulations, everyone.

"Monitor"

"Monitor" is a Level II TRS-80 assembly-language operating system with many capabilities.

Rod Hallen
Road Runner Ranch
PO Box 73
Tombstone AZ 85638

recently purchased a 16K Level II TRS-80 from Radio Shack. I write and sell magazine articles and programs, and since the TRS-80 is fast becoming one of the more popular of the personal computers, I decided that I had to have one to keep abreast

of the latest trends in the industry.

One distinct advantage of the TRS-80 and other personal computers of a similar nature is that the BASIC interpreter is stored in ROM. Every time you turn the machine on you have

immediate access to BASIC. This is in contrast to computers, such as my SOL, that contain assembly-language operating systems in ROM. This gives you direct control of the inner workings of the CPU but requires loading BASIC from

Although I have owned a SOL for almost two years, I

Program A. A listing of "Monitor—A TRS-80 Assembly-Language Operating System," written in Radio Shack's Level II BASIC. It occupies about 2K of RAM. Delete the REMarks and line 310 to run in a 4K system.

```

100 REM-TRS-80 ALOS
110 REM-BY ROD HALLEN TOMBSTONE, AZ 85638 20 NOV 78
120 REM-TAPE 15 SIDE 2 --> 185
130 DIM A$(16), S(16): A$="0123456789ABCDEF"
140 CLS:PRINT
150 PRINT TAB(25)"MONITOR":PRINT
160 INPUT"SELECT: DUMP, ENTER, EXECUTE, SAVE, LOAD, OR BASIC. ";C$
180 IF LEFT$(C$,2)="DU" THEN 310
190 IF LEFT$(C$,2)="EN" THEN 610
200 IF LEFT$(C$,2)="EX" THEN 910
210 IF LEFT$(C$,2)="SA" THEN 1110
220 IF LEFT$(C$,2)="LO" THEN 1310
230 IF LEFT$(C$,2)="BA" THEN END
240 GOTO 160
300 REM-DUMP SUBROUTINE
310 PRINT:PRINT"ENTER START AND END ADDRESSES IN HEX."
320 PRINT:INPUT"START ADDRESS ";H$(1)
330 PRINT:INPUT"END ADDRESS ";H$(2)
340 FOR I = 1 TO 2
350 H$=H$(I)
360 GOSUB 1510
370 D(I)=D
380 NEXT I
390 FOR I = D(1) TO D(2) STEP 16
392 D=I
396 GOSUB 1710
400 PRINT MID$(A$,H4+1,1);MID$(A$,H3+1,1);
405 PRINT MID$(A$,H2+1,1);MID$(A$,H1+1,1); " "
410 FOR J = 0 TO 15
420 D = PEEK(I+J)
430 GOSUB 1710
440 PRINT MID$(A$,H2+1,1);MID$(A$,H1+1,1); " "
450 NEXT J
460 PRINT
470 NEXT I
480 GOTO 160
600 REM-ENTER SUBROUTINE
610 PRINT:INPUT"START ADDRESS OF ENTER IN HEX ";H$
620 GOSUB 1510
630 D1 = D
640 FOR I = 0 TO 8191
650 INPUT H$
660 IF H$="/" THEN 160
670 GOSUB 1510
680 POKE D1+I,D
690 NEXT I
700 GOTO 160
900 REM-EXECUTE SUBROUTINE
910 PRINT:INPUT"EXECUTE ADDRESS IN HEX ";H1$

```

```

920 FOR I = 2T04 STEP 2
930 H$=MID$(H1$,I-1,2)
940 GOSUB 1510
950 POKE 16328-I/2,D
960 NEXT I
970 PRINT USR(0)
980 GOTO 160
1100 REM-SAVE SUBROUTINE
1110 PRINT:INPUT"ADDRESS OF SAVE START IN HEX ";H$
1120 GOSUB 1510
1130 D1=D
1140 PRINT:INPUT"ADDRESS OF SAVE END IN HEX ";H$
1150 GOSUB 1510
1160 D2=D
1170 FOR I = D1 TO D2 STEP 16
1180 FOR J = 0 TO 15
1190 S(J+1) = PEEK(I+J)
1200 NEXT J
1210 PRINT#-1,S(1),S(2),S(3),S(4),S(5),S(6),S(7),S(8),S(9),
S(10),S(11),S(12),S(13),S(14),S(15),S(16)
1220 NEXT I
1230 PRINT#-1,999,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0
1240 GOTO 160
1300 REM-LOAD SUBROUTINE
1310 PRINT:INPUT"ADDRESS OF LOAD START IN HEX ";H$
1320 GOSUB 1510
1330 FOR I = D TO 32767 STEP 16
1340 INPUT#-1,S(1),S(2),S(3),S(4),S(5),S(6),S(7),S(8),S(9),
S(10),S(11),S(12),S(13),S(14),S(15),S(16)
1345 IF S(1)=999 THEN 160
1350 FOR J = 0 TO 15
1360 POKE I+J,S(J+1)
1370 NEXT J
1380 NEXT I
1390 GOTO 160
1500 REM-HEX TO DECIMAL SUBROUTINE
1510 D=0:RESTORE
1520 Z=LEN(H$)
1530 FOR K = Z TO 1 STEP -1
1540 READ M
1550 FOR J = 1 TO 16
1560 IF MID$(H$,K,1) = MID$(A$,J,1) THEN X = J-1: J=16
1570 NEXT J
1580 D = D+X*M
1590 NEXT K
1600 RETURN
1700 REM-DECIMAL TO HEX SUBROUTINE
1710 H4 = INT(D/4096)
1720 H3 = INT((D-H4*4096)/256)
1730 H2 = INT((D-(H4*4096)+(H3*256))/16)
1740 H1 = D-(H4*4096)-(H3*256)-(H2*16)
1750 RETURN
1800 REM-2 DIGIT DEC TO HEX SUBROUTINE
1810 H2=INT(D/16)
1820 H1=D-H2*16
1830 RETURN
2000 DATA 1,16,256,4096

```


ADDRESS	MACHINE	LABEL	MNEMONICS	COMMENTS
	CODE			
7000	21 00 3C		LXI H,3C00H	SCREEN ADDRESS
7003	1E 04		MVI E,04	REPEAT 4 TIMES
7005	AF	REPEAT	XRA A	CLEAR A REGISTER
7006	77	LOOP	MOV M,A	MOVE TO SCREEN
7007	23		INX H	INCREMENT SCREEN
7008	3C		INR A	INCREMENT CHARACTER
7009	FE FF		CPI 255	COUNT CHARACTERS
700B	C2 06 70		JNZ LOOP	GO BACK FOR MORE
700E	1D		DCR E	COUNT REPEATS
700F	C2 05 70		JNZ REPEAT	GO AROUND AGAIN
7012	C9		RET	RETURN TO CALLER

Program B. A simple 8080 assembly-language program designed to display the contents of the TRS-80 character set. When entering it into memory, only the machine code is actually entered. Change 70 at 000D and 0011 to 4C for the 4K version.

cassette.

However, if you like to work with assembly-language programming as much as I do, then the advantage and the disadvantage trade places. I had almost made up my mind to buy Radio Shack's T-BUG assembly-language monitor when the idea occurred to me that I ought to write my own version. My first intention was to write it in Z-80 machine code, but at the time I was looking for a project that would enable me to get to know Level II BASIC better, so I decided on a BASIC ALOS (assembly-language operating system).

By writing ALOS in BASIC I also increased its portability, which is the ability to move programs from one machine to another. While you can easily rewrite this program to fit almost any computer that supports BASIC, it is designed for the Level II Radio Shack machine. It occupies about 2K bytes of RAM, and with a little squeezing (see Program A) it will fit and run inside of 4K, but it really shines if you have more memory than that.

I patterned my TRS-80 version after Processor Technology's SOLOS monitor, with which I am quite familiar. That is, some of the functions are the same, but otherwise there is no

similarity since SOLOS is written in assembly language and ALOS is written in BASIC.

Here are the ALOS commands that I felt were necessary:

DUMP: select and print any desired block of memory.

ENTER: put machine code into selected memory.

EXECUTE: run an assembly-language program that has been loaded from the keyboard or cassette tape.

SAVE: save on tape an assembly-language program that now resides in memory.

LOAD: load a program from tape into memory.

With these commands I have complete control of the TRS-80 and can now enter and run 8080 or Z-80 assembly-language programs. A command that combines LOAD and EXECUTE might also be desirable, but I found that I don't really need it because it would enlarge an already memory-hungry program, which is especially undesirable if you only have 4K to work with.

Implementation

Let's consider how to use ALOS before we go into a step-by-step explanation of how it works. I'll use Program B as an example of an assembly-language program that we've written and now want to try out

This simple program will fill the video screen with the entire TRS-80 character set four times. Unfortunately, the lower-case characters will be shown as uppercase, but I have recently come across both software and hardware methods of remedying this problem, which I consider Radio Shack's one major oversight as far as the TRS-80 is concerned.

We will enter the program from the keyboard, dump it to the screen to be sure we didn't mistype anything, execute it to verify that it does what we want it to do, save it on cassette tape for future use and load it from tape to make sure that we got a good save.

As you can see the machine code of Program B is written in hexadecimal notation. I use hex because that is what the SOL taught me and because most of the assembly-language programs that you encounter in the magazines are in hex. However, since BASIC handles its numerical values in decimal notation, you will note when we get to a discussion of the inner workings of Program A that it is necessary for the software to constantly convert between the hex and decimal forms.

Turn off your TRS-80 and then turn it on again. This will display MEMORY SIZE? Answer 28672 if you have a 16K machine, and 19456 for the 4K version. The former will reserve 4K for machine code and the latter 1K. For longer assembly-language programs on the 16K TRS-80, you can reserve 12K by answering 20480.

When you use the memory-reservation feature of the TRS-80, remember that you are

affecting the MEM command. If you type ?MEM, you will still get the number of unused bytes available to the BASIC interpreter. This will not include the memory that you reserved for machine code. However, if you normally type ?15572-MEM to find the length of a program, you will have to change it to ?15572-4096-MEM, with 4096 being the number of bytes reserved.

Enter Program A from your keyboard just as you would any other BASIC program and CSAVE a copy on tape. Type RUN and you will be presented with the Command Table. Type ENTER (or EN) and you will be asked for a start address: 7000 on the 16K machine and 4C00 on the 4K. 7000 hex equals 28672 decimal and 4C00 equals 19456, which is the beginning of our reserved memory.

After the ALOS has digested that information, it will print a question mark (?). Enter the first byte of Program B and hit the enter key; when the ? appears again, type the second byte and enter. Continue until the entire program has been typed and entered one byte at a time. After the last byte has been typed and entered, type / and hit enter to return to the Command Table.

Now we want to see if everything went into memory OK. Type DUMP (or DU) and give a start address of 7000 and an end address of 7012 (4C00 and 4C12 on the 4K machine). You should receive a printout similar to Fig. 1. We are not concerned with the data after the C9 in the second line since the program ends there.

The completion of each com-

```

SELECT: DUMP, ENTER, EXECUTE, SAVE, LOAD, OR BASIC. ? DU
ENTER START AND END ADDRESSES OF DUMP IN HEX.

START ADDRESS ? 7000

END ADDRESS ? 7012

7000  21 00 3C 1E 04 AF 77 23 3C FE FF C2 06 70 1D C2
7010  05 70 C9 FF FF FF FF FF FF FF FF FF FF FF FF

```

Fig. 1. The result of a DUMP command. Here we've asked for a DUMP of 7000 to 7012 hex. The data after 7012 is not part of Program B and is read from memory to fill out the line to 16 bytes.




Fig. 2. The flowchart for Program A. It follows the flow of Program A and should be self-explanatory.

mand always takes you back to the Command Table for a new choice. If you detect a typing error, use the ENTER command to reenter the correct data. It is not necessary to type the entire program again in order to correct one byte. Give the address of the incorrect byte and then the correct information.

When the program looks correct, type EXECUTE (or EX) and give 7000 as the EXECUTE address (4C00 in 4K). After a moment's hesitation, the screen should fill with alphanumeric and graphic characters. The Command Table inquiry will also be printed somewhere on the screen.

Our next step is to save a tape copy of Program B. Position the tape to a blank spot and press the recorder's PLAY and RECORD buttons. Type SAVE, give a start address of 7000 and an end address of 7012 (4C00 and 4C12 for 4K). The recorder should run for a short while and then turn off.

Release the RECORD button and return the tape to the program's starting point. You do keep a written log of your taped programs, don't you? Press the PLAY button and type LOAD. Give a start address of 7000 (4C00 for 4K); the recorder should run three short spurts, and then the Command Table should return.

Try the EXECUTE command again to be sure that you got a good save and load. If anything fails to work properly, Level II BASIC should give you some clues as to the problem area. If not, compare your listing of

Program A in memory with the listing in this article.

The supreme test is to turn your TRS-80 off and then on again. CLOAD Program A, load Program B from tape using the Command Table and execute. Remember that you will have to enter your reserved memory address (28672 or 19456) each time you turn the machine on.

I've performed some simple modifications to my Radio Shack CTR-41 tape recorder that make loading and saving programs much easier. These modifications allow you to hear the data on the tape and give you complete control of the recorder without constantly plugging and unplugging the cords. The total cost is one quarter-Watt resistor and fifteen minutes' work. The resistor feeds some audio to the speaker on playback, and the tone-control switch becomes a motor-control switch.

A detailed description of these modifications and a lot of other good information are in the initial issue of "TRS-80 Computing," available from Computer Information Exchange, Inc., PO Box 158, San Luis Rey CA 92068, for \$1.50. I believe that the same modification information is available from Radio Shack Computer Corp., Hugh Mathias, Customer Service, PO Box 185, Ft. Worth TX 76101. I have seen gadgets (costing up to \$40) to accomplish the same functions.

The Program

Program A is a listing of my BASIC ALOS. I don't have a

printer interfaced to the TRS-80 yet, so I had to transfer the program to the SOL and then print it. This is a difficult and error-prone method of doing things, and it strengthened my resolve to hook up some type of printer interface for the TRS-80 so that I could use the Malibu 160 line printer that the SOL drives.

As I've said, the program occupies about 2K, which leaves 1K for machine-language programs if you have 4K and 12K in the 16K machine. In order to reduce the size of Program A for the 4K TRS-80, you can:

Remove all REMark statements.

Remove line 310, and in line 180 change 310 to 320.

Use multi-statement lines.

When I write a program for publication I use remarks and place each statement on a separate line because it is easier to read that way. However, for my own use, I prefer programs that are as compact as possible. This not only conserves memory space, but it makes for a faster-running program. Speed is an important consideration here because a BASIC program runs much slower than one written in assembly language.

Fig. 2 is the flowchart for Program A. The program and the flowchart should follow each other exactly. Fig. 3 is a list of the variables used in Program A.

Lines 100 to 120 are intended for my information, but they can be eliminated if you like. Line 130 dimensions a couple of variables and establishes the hexadecimal character set. After clearing the screen and printing a title, lines 140 to 160

ask for the command that you want to use, and lines 180 to 230 call the subroutine associated with each command. Line 240 gives you another chance if you enter something that the computer doesn't understand. Note that either the entire command or just the first two letters can be entered and that the choice of BASIC as a command provides an exit function.

Number-Base Converters

Before I detail the command subroutines, let's look at the two number-base converters, since they play such an important part in the operation of the ALOS. In Program A and the following discussion, any variable that starts with H (H\$, H1\$, etc.) contains a hexadecimal value, and those that start with a D (D, D1, etc.) contain decimal values.

The hex-to-decimal subroutine starting at line 1510 is always entered with a hex value in H\$ and returns with the decimal equivalent in the variable D. Line 1510 clears D and restores the data pointer, and line 1520 determines how many digits are contained in H\$. The loop between lines 1530 and 1590 assigns a weight to each hex digit position, and line 1580 multiplies each digit times its weight. The result, which is stored in D, is the decimal equivalent of the hex value.

The decimal-to-hex converter starts at line 1710. Each of the four hex digits is determined by dividing the decimal number by the hex-digit weights. These weights are shown in Fig. 4. The result is stored in H4, H3, H2 and H1. These are actually deci-

```
A$ = Hexadecimal character set
C$ = Command choice
H$,H1$,H$(1),H$(2) = Hexadecimal inputs
D,D1,D2,D(1),D(2) = Decimal inputs and results
H1,H2,H3,H4 = Hexadecimal digits
I,J,K, = Loop variables
H = Hexadecimal digit weight storage
S = Storage of tape input and print files
Z = H$ length
```

Fig. 3. A list of the variables of Program A and an explanation of their use.

mal digits ranging from 0 to 15, and these digits (+ 1) are compared in lines 400, 405, 440 to their position in A\$ to recover the hex equivalent.

DUMP

If you want to look at a specific block of memory, you would enter DUMP (or DU) in response to the question in line 160, and line 180 would jump to line 310, which is the beginning of the DUMP subroutine. Line 310 reminds you that all entries are in hex (as are all printouts). Line 320 is looking for the start address of the DUMP, and 330 is looking for the end address. If you answered 0 and 3F, the result should be similar to that shown in Fig. 5. This is the first 64 bytes of the Level II BASIC interpreter.

Fig. 5 came about as follows: Lines 320 and 330 stored the starting and ending addresses in two variables, H\$(1) and H\$(2). The loop in lines 340 to 380 calls the hex-to-decimal converter starting at line 1500 and creates two new variables, D(1) and D(2). These are identical to H\$(1) and H\$(2), except that they contain the decimal equivalent of the DUMP start and end addresses.

The loop between lines 390 and 470 calls the decimal-to-hex converter (at line 396), prints the memory address (lines 400 and 405) and prints 16 bytes of data (lines 410 to 450). Line 460 starts a new line, and line 470 sends us back for the next address and another 16 bytes. This continues until you encounter the end address that you originally entered. The pro-

gram completes the line that it is working in and then goes back to line 160 for a new command.

ENTER

The ENTER subroutine asks for the address at which you want to start entering data (line 610) and sends that address to the hex-to-decimal converter (line 620). On return we have a decimal variable (D) containing the start address. We're going to need D for another conversion in a moment, so we move its contents to D1 (line 630).

The loop from lines 640 to 690 will allow up to 8K (8192 bytes) to be entered. This can be easily changed in line 640 to suit your requirements. Line 650 asks for a byte, line 660 checks to see if it is /, which we use to exit the ENTER command, line 670 converts it to decimal, line 680 pokes it into memory and line 690 goes back for another byte. This continues until line 660 or a fallout to line 700 returns us to the Command Table.

EXECUTE

In order to execute an assembly-language program in the TRS-80, you must poke the execute address into memory at 16526 and 16527 and then call that address by using the Level II USR(0) command. You can approximate the same function by using the following assembly-language segment:

```
LXI    H,EXECUTE ADDRESS
PUSH   H
RET
```

When the CPU encounters the return (RET) it will take the

top two bytes—your execute address—off the stack, place them in the program counter and proceed from there. This latter procedure, of course, assumes that you are already in the assembly-language mode.

Line 910 asks for the execute address, and the loop from lines 920 and 960 splits it in half (half for 16526 and half for 16527—least significant byte first). Line 930 executes the actual splitting, line 940 calls our hex-to-decimal converter and line 950 pokes 16526 and 16527. Line 970 is a call to 16526 and 16527. Your machine-language program should end with some variation of the RETURN instruction (RET, RZ, RNZ, RC, RNC, etc.), and control will be returned to line 980 when it is done.

SAVE

It is, of course, desirable to be able to store programs on cassette tape after they have been entered and tested so that you don't have to reenter them from the keyboard each time you want to run them. Level II BASIC makes this easy to do.

Line 1110 asks for the start address of the program you want to save, line 1120 calls the hex-to-decimal converter and line 1130 assigns this value to D1. Line 1140 is looking for the last address you want to SAVE, line 1150 converts it to decimal and line 1160 assigns this value to D2.

The loops between lines 1170 and 1220 do the actual SAVING. Machine code is recorded on tape as 16 byte files. Lines 1180 to 1200 store 16 bytes in

the S array, and line 1210 puts them on tape as a file. If we're not done yet, line 1220 goes back for another 16 bytes. If the program that you are SAVING does not contain an exact multiple of 16 bytes, the last file will be filled out with whatever follows the program in memory. Line 1230 records "999" as an identifier on tape so that the LOAD routine will know when it has reached the end of a taped program.

LOAD

Line 1310 is looking for the address at which you want the program loaded, and line 1320 is our old friend, the hex-to-decimal converter. Line 1330 starts a loop that will LOAD until it runs out of memory unless something stops it. Line 1340 will load 16 bytes at a time. Lines 1350 to 1370 will poke those 16 bytes into memory, and line 1380 will keep going back for more until line 1345 discovers "999," which indicates we're done.

As I mentioned earlier, LOAD and EXECUTE could be combined by calling the EXECUTE subroutine when the load is done. It would also be quite easy to put the LOAD start address at the beginning of the program on tape. Then all you'd have to do is type LO for the program to load at the proper address and execute.

I haven't implemented either of these functions because most of the time I'm experimenting, and I often load a program and make changes before I run it. If you'd like an automatic load and execute, the follow-

Digit Position	4	3	2	1
Decimal weight	1000	100	10	1
Hex weight	4096	256	16	1

Hex Digit	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
A\$ Position	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16

Fig. 4. The comparative weights of hex and decimal digit positions. The hex positions are in multiples of 16, and the decimal positions are in multiples of ten. For instance, 1234 decimal equals one thousand, two hundred thirty-four ($1 \cdot 1000 + 2 \cdot 100 + 3 \cdot 10 + 4 \cdot 1 = 1234$). 1234 hex equals four thousand, six hundred fifty decimal ($1 \cdot 4096 + 2 \cdot 256 + 3 \cdot 16 + 4 \cdot 1 = 4650$). Also shown are the contents of A\$ and how the results of the decimal-to-hex converter are used to identify the correct hex digits.

```
SELECT: DUMP, ENTER, EXECUTE, SAVE, LOAD, OR BASIC. ? DU
ENTER START AND END ADDRESSES OF DUMP IN HEX.

START ADDRESS ? 0
END ADDRESS ? 3F

0000  F3 AF C3 74 06 C3 00 40 C3 00 40 E1 E9 C3 9F 06
0010  C3 03 40 C5 06 01 18 2E C3 06 40 C5 06 02 18 26
0020  C3 09 40 C5 06 04 18 1E C3 0C 40 11 15 40 18 E3
0030  C3 0F 40 11 1D 40 18 E3 C3 12 40 11 25 40 18 DB
```

Fig. 5. A DUMP of the first 64 bytes of the Level II BASIC ROM. The addresses requested were 0 to 3F hex (0 to 63 decimal).

ing suggestions should help.

Add lines 1115 H1\$=H\$ and 1165 PRINT#-1,H1\$. This will make the first file on tape the SAVE start address. Change line 1310 to INPUT#-1,H\$ and delete line 1320. In line 1345 change 160 to 920. With these changes, you will still be able to use the EXECUTE command by itself when desired.

Note that the above procedure assumes that the first address of a program and the EXECUTE address are the same. I always write my assembly-language programs that way. If for some reason you want to start executing in the middle, then make the first as-

sembly-language program instruction a jump to the start location.

Conclusion

BASIC certainly has its advantages. Foremost is its ease of constructing complicated programs. However, it does have two distinct disadvantages: the large amount of memory required to store these programs and the slowness of their operation. Add to this the memory required to hold the BASIC interpreter, and there are many times when assembly-language programs are desirable or even necessary.

Assembly-language program-

ming is more difficult to learn and use than BASIC, but it does have the virtue of compactness and speed. I read somewhere recently that a well-written assembly-language program will run at least 100 times faster than its BASIC equivalent. For those of you who are familiar with 8080 machine code, the TRS-80 will accept and run it as well as it does Z-80 code. I haven't attempted to provide any instruction on the subject of assembly-language programming because that would consume quite a few articles all by itself.

Since speed and compactness are factors to consider in

BASIC programs, you might want to go through my ALOS and clean it up a little. The statements within loops are especially profitable candidates for cleanup since they are executed so many times. The hex-to-decimal converter is another area to look at.

One interesting possibility is to use my ALOS to construct and experiment with an ALOS written in assembly language. You could then discard the BASIC version. In any case, using the information that I've provided here, you can now go into the inner regions of your TRS-80 and speak to it in its own language. ■

Dr. Daley presents The finest in software for **PET**

PILOT—A second high level language for the PET. With sample program and documentation.

\$12.95 ppd.

✓ D43

Dr. Daley
425 Grove Ave.
Berrien Springs, MI
Ph. (616) 471-5514
Sun. thru Thurs.
noon to 9:00 p.m.
eastern time.

save more than 20%!

NORTH STAR—XITAN

The smartest computers at the smartest price.

DOUBLE DENSITY

HORIZON-1-16K kit,	list \$1599	\$1279
Assembled & tested,	list \$1899	\$1519
HORIZON-2-16K kit,	list \$1999	\$1599
Assembled & tested,	list \$2349	\$1879
PASCAL for NORTH STAR on Disk.....		\$49
Powerful NORTH STAR BASIC.....		FREE
XITAN Computers—Now—With QUAD DENSITY DISKI		
Famous XITAN Software & BASIC.....		FREE
HORIZON & XITAN are S-100, Z-80—THE BEST		
INTERTUBE II Terminal,	list \$995	\$795
NEW: Our VIDEO BOARD CODE on Disk! Now you can run our computers on a TV! SAVE HUNDREDS \$555		
TV Code on DISK . . . \$10	LISTING . . .	FREE
Business Software, Terminals, Printers, Computers in stock & special-ordered Other brands at good discounts. Ask!		
Which Computers are best? BROCHURE		FREE

**AMERICAN
SQUARE
COMPUTERS**

✓ A66


KIVETT DR. • JAMESTOWN NC 27282
(919) 883-1105

R.E. Purser's Reference List of TRS-80, APPLE II, & PET Computer Cassettes



Quarterly.
Subscription Price
\$12.00 Year.

P.O. Box 466
El Dorado
Ca. 95623



6800 OWNERS

At last a real world fully addressable SS-50 control interface. Control robots, appliances, organs, solar devices, etc. Applications limited only by your imagination. Easy to use with machine language as well as basic. Fully buffered board plugs directly onto motherboard and responds to any address defined by user. 2 fast relays latch data while 8 optoisolators allow handshaking capacity. Kit comes with 2 relays while other 6 I/O lines are left at TTL levels. Circuit board allows addition of 6 relays available from us at nominal cost.

Kit \$74.95

Assembled and tested \$99.95
Additional Relays \$3.98 ea

EXTENDER BOARDS

Extend both the 30 and 50 pin buses in SWTP 6800.

Both for \$19.95

No COD on Canadian orders
Visa & Master Charge • Ariz Res add 4% Sales Tax


WRITE FOR DETAILS

✓ T46

TRANSITION ENTERPRISES INC.

Star Route, Box 241, Buckeye, AZ 85326

SHORT CASSETTES



List \$1.00 10 for \$7.50 50 for \$32.50

MICROSETTE CO.

777 Palomar Ave. • Sunnyvale, CA 94086

Duplication Services


Microsette also offers professional duplication services for Commodore PET and Radio Shack TRS-80 Level I and Level II cassettes. Our service provides mastering, quality control, all material including two-piece box, affixing of your labels or supplying our blank labels and shipping. Prices start at \$2.00 each in 100 quantity.

MICROSETTE CO. ✓ M67
777 Palomar Ave. • Sunnyvale, CA 94086

TRS-80

Micro-Mega CASSETTE CONTROL UNIT

• Speed up your cassette tape handling • Pinpoint program locations on tape with an audible auxiliary monitor • Get protection from recording and playback glitches resulting from ground loops • Eliminate the tedious plugging and unplugging of recorder cables.



The Micro-Mega Cassette Control Unit does all this and more. You get instant manual control of the recorder at the flick of a switch. Want to find the beginning or end of a program? Flick another switch, and you'll hear it. All cables remain plugged in all the time.

The Micro-Mega Cassette Control Unit does a lot to clean up and neaten up your whole TRS-80 installation, too. As shown at the left, it's in a 2½" x 5" box which snugles between the keyboard and your recorder. There is no need to move the recorder, and there no longer are any 90 degree cable bends whipping around. It's fast, neat and convenient—and it's a bargain!

CASSETTE CONTROL UNIT—\$37.50

Micro-Mega ✓ M54

P.O. BOX 6265 • ARLINGTON VA 22206
(Virginia residents add 4% sales tax)

Starving for business software for your TRS-80?

Here's food for thought!

Graham-Dorian now has a special department to serve the special needs of TRS-80 owners. And we have four comprehensive business software packages available on disk for any TRS-80 system with 32K or more of memory, 2 to 4 disk drives, and a line printer. They operate with the CP/M[™] disk operating system and CBASIC-2.

Each package includes source code on disk and hardcopy source listings in the comprehensive user's manual.

Use your TRS-80 system to its fullest with these sophisticated programs:

- **Inventory Package** — Can be connected with cash register for point of sale inventory control. Number of on-line items limited only by disk space available.
- **Cash Register Package** — Creates daily sales reports containing information on gift certificates, payouts, overrings, refunds, and how much in each category a salesperson sold.
- **Payroll Package** — Handles 100% of all necessary payroll functions including state income tax tables for your state. Ideally suited for both large and small companies.
- **Apartment Package** — Said one user, "Obviously, this was developed by apartment owners." The package fills virtually all the needs of apartment owners and managers. Ideal for projects with 75 units or more.

\$695.00 for any package listed above. Any single package order includes free CBASIC-2.

CBASIC-2 sold separately - \$89.95.
CP/M Disk Operating System - \$150.00.

Send for detailed packet of information explaining capabilities of each program and sample runs. Or, phone our software technicians.

Attractive dealerships available.

Graham-Dorian Software Systems programs are copyrighted and require licensing agreement.



Visa and
MasterCharge accepted.

Graham-Dorian Software Systems
A Division of Graham-Dorian Enterprises
211 N. Broadway / Wichita, KS 67202
(316) 265-8633



STRONG.

**Your A P Jumper
isn't just crimped,
it's fused together
for keeps.**

You can't pull one of our assemblies apart on purpose, much less by accident. Not without tools.

It's because we don't just crimp them together like other jumper makers, we mold our connectors to the flat ribbon cable. And after they're fused together, we test each assembly to make sure it's in perfect working order.

All of this means you're not going

to be bugged by gaps or shorts. Not with A P Jumpers. Not even after repeated use. They're the world's most dependable way to jumper within PC boards and interconnect between PC boards, backplanes and motherboards.

If your application involves sockets, card edge or DIP connectors, you'll find your A P dealer has the contacts and lengths you need.

Who's your dealer? Phone (toll-free) 800-321-9668. And ask for the complete A P catalog, The Faster and Easier Book.

✓ A22



**AP PRODUCTS
INCORPORATED**

Box 110E • 72 Corwin Drive
Painesville, Ohio 44077
Tel. 216/354-2101
TWX: 810-425-2250

Faster and Easier is what we're all about.

TRS-80/Selectric Word Processor

This word-processing system has many genuinely useful applications. Read and see.

Allan J. Domuret
7825 Willowcrest Way
Fair Oaks CA 95628

As the hobby computer market continues to grow, increasingly more attention is given to questions about the actual or potential utility of the personal computer. In spite of claims that the microcomputer will revolutionize the home, skeptics are demanding answers as to how and in what ways this so-called revolution will occur. After all, playing blackjack or balancing a checkbook with a microcomputer is hardly revolutionary.

As a partial answer to the skeptics, let me suggest the usefulness and affordability of a personal word-processing system. Here, finally, is something practical and simple enough for most of the family to enjoy. And, more important, the cost is gradually becoming somewhat reasonable. My TRS-80/Selectric word-processing system cost about \$2000, including the price of the TRS-80. You can do the same with off-the-shelf products and with very little technical hassle.

But first you may reasonably ask what you or your family can do with a personal word processor. At the very least, it makes any typing chore a piece of cake. For example, as a pseudotypist I can sometimes manage up to 30 words per minute, but my problem is that erasures and corrections slow me down

considerably. And when my letter or term paper, or whatever, is finally finished, the "final" copy is usually unsatisfactory, and typically I wind up cutting out paragraphs, rearranging the text and retyping.

Needless to say, this traditional method is tedious and slow. But no more. Now I can erase faster than 100 words per minute. Term papers for college courses are much less tedious, and my final copy for the professor is always typed error-free on standard-size white bond paper.

In addition to high school or college term papers and theses, routine letter writing or typing becomes much simpler and faster. In fact, just about any kind of correspondence generated in the home for friends, business associates, consumer complaints, etc., is just the thing for a home word processor. Typed consumer complaints are much more effective than the typical handwritten variety.

Consider, too, the preparation of job resumés. When the young college graduate, or the recently laid-off breadwinner for that matter, goes job-hunting, he should tailor each resumé for each different employer. For example, he may choose to emphasize his computer background to IBM or his stock market winnings and skills to Merrill Lynch.

Additionally, an original typed copy is much more impressive to the potential employer than a standardized ma-

chine copy. You can be certain that a "personally typed" resume will stand out in a pile of machine copies.

As one more example of what my word processor can do, I would like to pay tribute to my daughter Kelli and her ingenuity. She wanted to know if the system would automatically type out 100 times: "I will not chew gum in school." The answer is, "Of course." Simply type out the sentence once on the monitor and give it a print command for, say, 50 times per page. The TRS-80 word processor makes duck soup out of these previously time-consuming chores.

The Basic System and Cost

When bragging about the super capabilities of my TRS-80 word processor to other computer owners, I am frequently asked: "What can your word processor do that the built-in TRS-80 editor can't do?" The answer is, a lot. Let me defend this claim by starting with a description of the system components and approximate costs.

The printer I use with my Level II TRS-80 is an Anderson-Jacobson 841 IBM selectric terminal with built-in ASCII logic circuitry, and the software is Michael Shryer's versatile Electric Pencil, a machine-language word-processing program. My TRS-80 system has 48K, but 16K is adequate, thus keeping down the initial cost of the basic system. The Pencil will also run on a Level I system.

The Level II, 16K TRS-80 currently retails for \$988; the AJ-841 is currently advertised at \$1095 (in a different computer mag); and the Electric Pencil is advertised at \$99.95 (see *Kilobaud*, December 1978, p. 35).

For some additional money-saving possibilities, Tandy shareholders qualify for a ten percent discount on Radio Shack products, including the TRS-80, and at least one retail outlet is advertising ten percent or more off on Radio Shack computer products (see the V. R. Data Corp. ad in *Kilobaud*, December 1978, p. 110).

This hardware-software combination compares favorably with commercial word processors retailing for many more kilobucks. With some arithmetic computations on your pocket calculator (assuming you don't yet have a microcomputer), you can add up the prices I gave you (minus the possible ten percent or more savings on a Radio Shack TRS-80) and arrive at a total system cost of around \$2000, less sales tax. Of course, if you already have a TRS-80, you are halfway there.

The Electric Pencil

The Electric Pencil has far more flexibility and capability than can be described in the limited space of this article. (See *Kilobaud MICROCOMPUTING*, March, 1979, p. 114.) The Electric Pencil operator's manual contains 24 pages of clear, well-written instructions.

In addition to mere insertion, deletion or addition of charac-

ters or words, the Pencil supports block moves as well. Paragraphs, sentences or any group of characters can be relocated from one area in the text to another. The block move operation automatically adjusts to close up the text previously occupied by the block, and the newly assigned area is automatically opened up to provide space for the relocated text.

Forward and reverse scrolling (moving the text up or down on the monitor screen) permit easy viewing of all parts of the text, both before and after block move(s). String search also facilitates text review and analysis.

String search allows the user to locate any desired string of characters with reference to a name, social security number, age, address or whatever. Not only does this search capability facilitate block moves, but also mailing or address lists can be constructed without a need to alphabetize. Simply tell the computer to display the file on John Doe, and there it is.

Typing speed is enhanced by the automatic carriage-return feature at the end of each line of text and by eliminating the requirement for hyphenation. Simply keep right on typing, and any text word that does not completely fit at the end of the current line is automatically reconstructed as a whole text word at the start of the next line. Of course, a carriage return can be inserted anywhere by the user for shorter lines or for column construction.

Other features of the Electric Pencil include automatic pagination and titling, right-hand justification, an assortment of print commands and so on. If you choose to have the printer type out 80 characters per line (or up to 125 characters per line), as opposed to the 65 characters per line displayed on your monitor, simply select the appropriate command for the number of characters per line desired and give the print command. All line and word spacing is adjusted automatically.

If your computer memory becomes filled with text, "FILE AREA FULL" will be displayed



Photo 1. TRS-80 and printer.

on the monitor. You can then dump the text from memory onto cassette tape. A "Tape Verify" feature assures a good tape load. Of course, a tape dump can be performed at any time.

The Electric Pencil has many more versatile features—I counted 52 different controls and commands—but the preceding paragraphs should give the reader a good idea of the program's capabilities.

The AJ-841 I/O Terminal

The TRS-80, the Electric Pencil and the AJ-841 terminal form a natural trio, almost as if they were designed to function together. The TRS-80, however, is deficient because of its uppercase-only capability, whereas the IBM-based AJ-841 supports both uppercase and lowercase.

Not to worry... the Pencil documentation provides complete instructions to easily convert your TRS-80 into an uppercase and lowercase system. Total cost of the lowercase mod is less than \$5 for parts. Installation of the mod was my first experience in hard-wiring a microcomputer, and it was quite simple—it took less than an hour.

Be aware that this lowercase conversion will void your TRS-80 warranty, so you may want to

allow the computer to age for the 90-day life of its warranty before installing the mod. In this way, any bugs that happen to develop in a new TRS-80 can be repaired under the warranty at no cost to the owner.

After expiration of the 90-day warranty, however, you will have to pay for repairs anyway, so go ahead and modify it... it's easy. (One more caution: Radio Shack repairs on modified computers are billed at a higher hourly rate than on unmodified computers.)

The lowercase mod requires the installation of a 2102A memory chip (\$2.49 at Radio Shack) plus two simple switches. One switch is an SPDT, which allows for upper only or upper-lower selection; the second is a push-button normally open switch that accesses the Electric Pencil's control functions such as cursor movement, printer activate and so on.

The Electric Pencil will support a stock uppercase-only TRS-80, and with this unmodified setup no wiring of any kind to the computer is required. Thus, the integrity of your TRS-80 and its warranty are preserved. This is explained very clearly in the Pencil operator's manual. Whether or not you modify, you can still utilize the

Radio Shack or Centronics line printer in lieu of the AJ-841 terminal.

Back to printout capability: the Pencil allows selectable printout options of any or all parts of the text. One line or several lines can be identified for printout, and the AJ-841 supports the Pencil printout commands beautifully.

The AJ-841 terminal connects to the 34-pin printer port of the TRS-80 expansion interface. Alternatively, an RS-232 option is available from Small Systems Software, a firm that retails the Electric Pencil, if you don't use the Radio Shack expansion interface. If you go this route, you will need another RS-232 interface on the AJ-841, which is also available.

No wiring modifications to either the TRS-80 or the AJ-841 are required, but the connector cable that interfaces the two systems must be wired as described in Fig. 1. The only exception to this claim for non-wiring involves the AJ-841's logic board, which utilizes a Z-80 MPU plus a Z-80 PIO for proper handshaking with a variety of computer systems. On the logic board are two jumpers marked "P R" and "S T." See Photo 2 for jumper locations.

Instructions for setting up these jumpers are provided in

the AJ-841 documentation, and the TRS-80 requires them to be set at P and T. The jumpers do not have to be unsoldered and resoldered to be moved. They are friction-fitted on mounting posts that are mounted on the logic board.

Carefully pull the jumpers off the mounting posts with long-nose pliers and reposition them as required. (On my AJ-841, the jumpers were already properly positioned, so they did not have to be moved.) Proper positioning of the jumpers provides high and low logic handshaking signals that are compatible with the TRS-80.

The TRS-80 end of the cable can easily be constructed or purchased already wired with a 34-pin, .01 inch center edge connector. My cable is four feet long. The AJ-841 end of the cable uses a standard DB 25-pin female connector.

I used a 25-pin connector with solder-type leads because the connections do not form a one-to-one correspondence between it and the TRS-80 edge connector. Solder the leads according to the instructions in

Fig. 1, being careful to make neat solder connections. Also be careful of solder splashes or tiny stranded wire shorts across the 25-pin connector terminals.

The AJ-841 has a self-test function that automatically runs itself through a printer output of all uppercase and lowercase characters. A power supply and all necessary electronics are inside the AJ-841, and no software overhead is required. This system is therefore much simpler than the one put together by Emerson Brooks (see *Kilobaud*, June and July 1978). Once the cable is assembled, simply plug the AJ-841 and TRS-80 together and go.

It is important to note that the AJ-841 accepts all of the BASIC line printer commands from the TRS-80, such as LLIST or LPRINT. It does not, therefore, limit the user to only Electric Pencil usage. The AJ-841 supports all the functions of the standard TRS-80 line printer except for the speed. The AJ-841 advertises a printout of 14.9 characters per second, which is, of course, slower than the line printer output of about

90-100 lines per minute.

The folks at Microtronix have developed a graphics ball for the AJ-841, so you can also have the option of a graphics printout capability (see their ad in *Kilobaud*, November 1978, p. 80). And, of course, you can use any of the available IBM character print balls for different type fonts.

I might add that Microtronix retails the AJ-841 complete with cable, ready for TRS-80 operation. Their advertised price should save you the expense of purchasing the connector cable separately, but don't forget to figure in shipping costs when applicable.

Alternative Printers

Before closing, I might add why I went the AJ-841 route instead of some other IBM Selectric printer alternative. First, converting a standard IBM Selectric would probably have been a headache, and in the end it probably would not have saved much money. If a used Selectric could be found, I would have had to pay about \$500 or \$600, minimum. Add to

this the solenoid kits available from various sources for about \$250 and up; plus the ASCII, solenoid driver and power supply electronics; plus the software overhead required to make such a home-brew system work (either in PROM or resident software).

The end result would have been a printer that was not as simple, compatible or capable as the heavy-duty mechanism of the AJ-841. And the total cost of a home-converted IBM can easily approach the retail cost of the AJ-841.

As for buying inexpensive solenoids to save money as suggested by Don Lancaster (see his *TV Typewriter Cookbook*), I suggest, first, looking at the guts of an IBM Selectric. Also, consider the bewildering variety of available solenoids, plus the problem of how to mount and interface them. I wouldn't touch the project with a ten-foot pole.

If you need additional discouragement in putting together a home-brew IBM-based printer, I suggest you read Sheila Clarke's article, "What's Happening with the IBM Selectric?" in *Kilobaud*, May 1978. If you are like me, you don't have a corps of engineers available for technical consultation. And, finally, I didn't have the time to either tackle the modification or to iron out the bugs, which would, no doubt, breed at an exponential rate.

Other IBM-based used or rebuilt Selectrics with ASCII boards are available from other retailers, and some of them are slightly less expensive than the reconditioned AJ-841, but the ads on these alternative systems are not clear as to what is required in terms of hard-wiring to the TRS-80 or in terms of software requirements as in Emerson Brooks' system. Even additional brochures and other printed materials from some advertisers were not clear in telling me what would be involved in adapting their printers to the TRS-80.

As for the AJ-841, I knew the system was compatible with the TRS-80 because the folks at Microtronix had already made

LOGIC BOARD JUMPERS SET AT "P" & "T" POWER SUPPLY BOARD SOLENOID DRIVER BOARD




Photo 2. Back view of the AJ-841 PC board and mechanics.

In summary, I knew that the AJ-841 was compatible with the TRS-80, but I was less certain

My next project is to learn how to utilize the input capability of the AJ-841 with my TRS-80. This input capability is another feature that is not available on several of the other IBM typewriter systems. I hope to make this project the subject for future discussion. ■

**AJ-841 Pin Number
and Label**

9	(DXSTRB)
1	(D0)
2	(D1)
3	(D2)
4	(D3)
5	(D4)
6	(D5)
7	(D6)
21	(Ground)
10	(DXACK)

1. Leave D7 from the TRS-80 disconnected.
2. On the cable coming from the TRS-80, tie line 22 to 23 and tie lines 25, 26 and 28 together. (Don't connect them to anything—just tie them as stated.)
3. On the AJ-841 logic board (see Photo 1), put the jumpers at P and T.

Fig. 1. Connecting-cable connections.

IMPLEMENTED BY

jim tamburo

✓ T59 **graphics**

1920 N. 34th AVE. · HOLLYWOOD, FL. 33021



A → **D** **D** → **A**

FAST: 1us; Bi-Polar or Uni-Polar; 8 Bits;
Precision Adjust; Only 4 I.C.S.! With
Sockets; Programs. **SYNTHESIZE!**
CONTROL! SENSE! CREATE!
Temperature, Speed, Light, Sound(s),
Humidity, Power, Processes, Voltage,
Current, Resistance, Pressure. **THE**
LIMIT? YOUR CREATIVITY!!!

KIT: \$32.50 — ASSEMBLED: \$39.50
Florida Residents add 4% Sales Tax

S **S** → **5**

'68' MICRO JOURNAL™

★ The only ALL 6800 Computer Magazine.

CHARTER
SUBSCRIPTION SPECIAL

1-Year \$10.50 2 Years \$18.50
3 Years \$26.50

OK, PLEASE ENTER MY
SUBSCRIPTION

Bill my: M/C ☐ — VISA ☐

Card # _____

Expiration Date _____

For ☐ 1-Yr. ☐ 2 Yrs. ☐ 3 Yrs.

Enclosed: \$ _____

Name _____

Street _____

City _____

State _____ Zip _____

'68' MICRO JOURNAL™

3018 Hamill Road
HIXSON, TN 37343 ✓ S74

**12" BLACK & WHITE
LOW COST VIDEO
TERMINAL**

Easily interfaced with Radio Shack TRS 80

\$139.00 LIST

Will sell 6 feet coaxial cable \$5.00

Texas residents add 5% sales tax.
Add \$5 for shipping and handling



One year
limited warranty

- Ideal for home, personal and business computer systems; surveillance monitors • 12" diagonal video monitor • Composite video input • Compatible with many computer systems • Solid-state circuitry for a stable & sharp picture • Video bandwidth—12 MHz \pm 3 dB • Input impedance—75 Ohms • Resolution—650 lines Minimum 1H Central 80% of CRT; 550 Lines Minimum beyond central 80% of CRT ref EIA RS-375 • Dimensions—11.375" high; 16.250" wide; 11.250" deep (exclude video input connector) • Weight—6.5 KG (14.3 lbs) net

Use Master Charge/Visa or send money order.

Micro Products Unlimited

P.O. Box 1525, Arlington, TX 76010  M81
817/461-8043

Dealer Inquiries welcome

**RECYCLE(D)
COMPUTERS**

BUY ☆ SELL ☆ SWAP

Hardware & Software

NEW PRODUCT ANNOUNCEMENTS

22 pages

Mailed 1st Class every 3 Weeks

1 yr. (18 issues) ☆ \$3.75

ON _ LINE


✓ O2

Dobr. Dvete. Publisher **Established 1973**

24695 Santa Cruz Hwy. • Los Gatos, CA 95030

THE BEST WAY TO DETERMINE IF ON LINE CAN BE OF VALUE TO YOU IS TO TRY A ...

FREE SAMPLE ISSUE

? ? ? ? # # # ! ! ! ? ? ? # # # ? ? ? ! ! ! # # # ? ? ?
 ? DISK DRIVE WOES? MEMORY LOSS?
 !
 ? ERRATIC OPERATION?
 !
 ? DON'T BLAME THE SOFTWARE!
 !
 *Power Line Surges & Hash could be the culprit!
 Floppies, memory & processor often interact!
 # *Curb damaging Surges & Hash with our ISOLA-
 # TORS and Suppressor/Filters. Eliminate Equip-
 # ment Interaction with our unique ISOLATORS.
 ? *ISOLATOR (ISO-1A) 3 filter isolated 3-prong
 ? sockets; integral surge suppression; 1875 W total
 ? load, 1 KW any socket. \$49.95
 ? *ISOLATOR (ISO-2) 2 filter isolated 3-prong socket
 ? banks (6 sockets total); integral surge suppres-
 # sion; 1875 watt total load, 1 KW load either
 # bank. \$49.95
 # *Suppressor/Filter (SFK-31) 3-prong socket; 1 KW
 # load. \$24.50
 # *Suppressor/Filter (SFK-33) Three 3- prong sock-
 # ets; 1250 watt load. \$32.50
 !
 ! PHONE ORDERS 1-617-655-1532
 !
 ! **ESP Electronic Specialists, Inc.**
 ! 171 South Main Street, Natick, Mass. 01760
 ?  Dept. KB
 ?  
 ? ? ? ? # # # ! ! ! ? ? ? # # # ? ? ? ! ! ! # # # ? ? ?

SURPLUS ELECTRONICS

ASCII  **ASCII**

**IBM SELECTRIC
BASED I/O TERMINAL
WITH ASCII CONVERSION
INSTALLED \$695.00**

- Tape Drives
- Cable
- Cassette Drives
- Wire
- Power Supplies 12V15A, 12V25A, 5V35A Others,
- Displays
- Cabinets
- XFMRs
- Heat Sinks
- Printers
- Components

Many other items
Write for free catalog
WORLDWIDE ELECT. INC. ✓ W16
130 Northeastern Blvd.
Nashua, NH 03060
Phone orders accepted using VISA
or MC. Toll Free 1-800-258-1036
In N.H. 603-889-7661

Some Thoughts on the SWTP Computer System

The first installment of this ongoing series appeared back in March. Here's number 2.

Peter A. Stark
PO Box 209
Mt. Kisco NY 10549

This is the second in a series of articles on the SWTP 6800 computer system. I trust you are finding them as interesting to read as I am finding them interesting to write.

A Strange Bug in the Heath H9

If you are using the Heath H9 CRT terminal with your SWTP 6800 computer, you may already have run across this strange problem, but then again, perhaps you haven't... yet.

Sometimes, just after the H9 executes a carriage return or prints a character, it outputs a short, unexpected 0 pulse on its keyboard output. Although short, it is of long enough duration so that it is interpreted by an MP-C interface as a character start pulse. Hence the MP-C starts to receive a character, which is not really there, from the H9. This character contains all ones and is a hex \$7F, a rubout.

Some of the standard SWTP software includes a test for rubout and ignores it. For instance, in SWTP 8K BASIC version 2.0, the test is at 03C8 and looks like this:

```
03C8 81 7F CMP A #$7F
03CA 27 F1 BEQ AGAIN
```

That there is an extra rubout doesn't bother it at all.

But other SWTP programs may not check; for instance, the CORES editor/assembler does not. Sometimes it does

strange things when it is used with an H9, that is, when extra rubout characters get mixed into your text. Program 1 is a patch for CORES to delete rubouts in the input in case you need it. In machine-language programs you write, make sure you include such a rubout test if at all possible.

Actually, in some programs this may pose quite a problem. I recently ran across a program that contained the following steps:

```
LDX #TEXT
JSR PDATA
JSR BADDR
```

The first two lines print a message, and the third goes to the BADDR routine in the monitor to get a four-digit hex number from the keyboard.

BADDR accepts only hex digits as input; if a non-hex character is entered, it returns to the monitor. What was happening in our case was that every single time we performed this segment, the program would bomb and return to the monitor. It

turned out that the H9 output a rubout after the carriage return in the message, and so BADDR was receiving a non-hex character.

To save the program, we have only a few choices: We can include a time delay before the JSR BADDR to allow the extra start bit to go by, or we can write our own BADDR routine to include a rubout test.

This is definitely a bug, albeit an interesting one, in the H9. Although the start pulse comes out of the H9, it can be set off by external events.

For instance, I found that several H9 terminals output this false start pulse while the computer was outputting to them. This is not usually a problem, unless you have the H9 paralleled with another terminal, since the H9 will then insert rubouts into the text coming into the computer from the other terminal's keyboard. So if you are getting strange results when you use the H9 on your SWTP system, you may want to look into this problem.

Program 2 may be of some

help. It accepts five characters input from the keyboard and then prints out the five hex ASCII codes for those characters. In normal operation you hit five keys on the keyboard, after which the computer sends back the five characters and their ASCII codes. If your H9 has this same problem, then the ASCII data will start coming out after only three or four keys are pressed and will contain extra \$7F codes. This program is also useful if you have unlabeled keys on the keyboard and want to know what codes they produce.

Paralleling Terminals

If you have two terminals—a CRT terminal and a teleprinter, for instance—that you would like to connect to the same port at the same time, here is how to do it.

If both are current loop interfaced, simply connect the two keyboards in series and the two printers in series. You may have to reduce the value of R10 in the interface to maintain a printer current of 20 mA and get reliable output.

If both terminals use an EIA RS-232C interface, the two printers can be connected in parallel to the same port output. But the two keyboards should not be paralleled since they will load each other down. Instead, use isolation diodes as shown in Fig. 1.

If you have one current loop and one EIA terminal, you can connect them to an MP-S or MP-C in the normal way. Just omit




Fig. 1. Connecting two terminals to one computer.




Fig. 2. CT-1024/CT-64 modification. (Diagram courtesy of Bobby E. Dunsmore, Oklahoma City OK)


```

00010      NAM      PATCH
00020      OPT      0,NOP
00080      *****
00090      *CORES PATCH TO DELETE RUBOUTS ON INPUT
00095      * PETER A. STARK 12/08/ 8
00100      *****
00110      *FIRST MAKE ROOM FOR THE PATCH BY MOVING
00120      *START OF SOURCE PROGRAM
00130 00FE      ORG      $00FE
00140 00FE 1B90      FDB      $1B90
00150      *
00160      *ACTUAL PATCH
00170 1B80      ORG      $1B80
00180 1B80 BD E1AC RUBPAT      JSR      $E1AC      GO TO INEE
00190 1B83 81 7F      CMP A      #$7F      IS IT RUBOUT?
00200 1B85 27 F9      BEQ      RUBPAT      GET ANOTHER CHARACTER IF YES
00210 1B87 39      RTS      RETURN IF NOT
00220      *
00230      *JUMPS TO PATCH
00240 1620      ORG      $1620
00250 1620 BD 1B80      JSR      RUBPAT
00260 19BE      ORG      $19BE
00270 19BE BD 1B80      JSR      RUBPAT
00280 19C5      ORG      $19C5
00290 19C5 BD 1B80      JSR      RUBPAT
00300      END

```

Program 1. Patch for CORES to eliminate rubouts on input.

the TI-TC and RI-ground jumpers you would use with just one terminal.

Bugs in the SWTP CT-1024 and CT-64 Terminals

The Heath H9 isn't the only unit with bugs; the CT-1024 and CT-64 have some too. My CT-64 has three of them:

1. When the letters pr appear together in certain spots on the screen, the p prints perfectly, but I get two r's, one on top of and slightly below the other. This is caused by the circuit that extends that lower end of the p below the line; it tries to do the same to the r right after it.

2. Occasionally control characters print on the screen, although the Control Character Print switch is off.

3. Often a line is not completely erased when being scrolled off the top of the screen and reappears instead at the bottom, either along with or instead of the new line being added.

The first problem appears unique to my own terminal, and I will have to go after it... someday. But the scrolling and erasing problem is more common, especially at 1200 baud. The problem is essentially due to the terminal's needing more time than it has at 1200 baud to erase the screen. The solution is to give it more time by delaying the computer output slight-

ly. This can be done either with hardware or software.

The hardware solution has been suggested by Bobby E. Dunsmore of Oklahoma City OK. It consists of the following changes:

1. Remove the wire from point C on the serial interface board and connect it to pin 3 of IC28.
2. Run a wire from point C on

the serial board to pin 2 of IC28.

3. Run another wire from pin 1 of IC28 to pin 6 of IC2.

4. Feed the terminal's clock from IC28, pin 3 to the computer and cassette interface and use it instead of the computer's baud rate clock.

Fig. 2 shows the circuit in which the baud rate clock inside the CT-64 or CT-1024 is gated in an unused AND gate in IC28 with a negative-going pulse from pin 6 of IC2. Whenever the terminal performs a "clear to end of frame" operation, this pulse turns off the clock to both the terminal and computer until the clearing is done. This gives the right time delay.

Another way to provide the delay is with a software fix. Program 3 shows OUTDEL, a short routine to provide the required delay. Instead of going directly to OUTEEE, redirect all of your programs to OUTDEL; this version is shown assembled at \$B000, but you can place it anywhere in memory. This version simply puts a short time delay after every line feed (\$0A) and home/erase (\$10) character. This does slow down the output to below 1200 baud, but the re-

sult is not adversely affected. One bad side effect, however, is that if the computer is in the wait loop at the exact instant you hit a control-C to get out of BASIC, it may not stop. You may have to hit control-C several times.

Back Space on the CT-64

On the right side of the CT-64 keyboard are two keys that are not connected; one of these is labeled Back Space and the other is blank. They can be hooked up for special functions without too much effort.

The keyboard encoder chip is an AY-5-2376, which can handle up to 88 keys. A good description of this IC and its uses is contained in Don Lancaster's *TV Typewriter Cookbook*, available through many electronics stores. Page 36 of the book shows the diagram.

If you remove the keyboard from the terminal and connect the Back Space switch to pins 26 and 36 of the 2376, it will generate a back space (control-H or \$08) code. While you are at it, you may want to modify your SWTP BASIC to accept control-H as back space instead of con-

```

      NAM      H9-TEST
      *PROGRAM TO CHECK OUTPUT OF HEATH H-9
      *P. STARK, 10/6/78
      OPT      PAG
      ORG      $1000
1000 CE 10 3B START LDX      $BUFF      GET BUFFER ADDRESS
1003 BE A0 42      LDS      $A042      INITIALIZE STACK POINTER
1006 C6 05      LDA B      $5      INITIALIZE COUNTER
1008 BD 23      BSR      PCRLF      PRINT CR/LF
100A BD E1 AC LOOPS JSR      $E1AC      GO TO INEE
100D A7 00      STA A      0,X      STORE CHARACTER
100F 81 03      CMP A      $03      IS IT CONTROL-C?
1011 27 25      BEQ      GOSWAT      YES, RETURN TO SWATBUG
1013 08      INX      INCR INDEX
1014 5A      DEC B      DECR COUNTER
1015 26 F3      BNE      LOOPS      REPEAT IF NOT DONE
1017 CE 10 3B PRINT LDX      $BUFF      PRINT RESULTS: GET BUFF ADDRESS
101A C6 05      LDA B      $5      INITIALIZE COUNTER
101C BD 0F      BSR      PCRLF      PRINT CR/LF
101E A6 00      LDA A      0,X      GET CHARACTER
1020 36      PSH A      SAVE IT
1021 BD E0 CA      JSR      $E0CA      GO TO OUT2HS TO PRINT HEX CODE
1024 32      PUL A      GET CHARACTER
1025 BD E1 D1      JSR      $E1D1      GO TO OUTEEE TO PRINT IT
1028 5A      DEC B      DECR COUNTER
1029 26 F1      BNE      LOOPP      REPEAT UNTIL DONE
102B 20 D3      BRA      START      OTHERWISE DO OVER
102D 86 0D      PCRLF      LDA A      $0D      PRINT CR
102F BD E1 D1      JSR      $E1D1
1032 86 0A      LDA A      $0A      PRINT LF
1034 BD E1 D1      JSR      $E1D1
1037 39      RTS      RETURN
1038 7E E0 D0      GOSWAT JMP      $E0D0      RETURN TO SWATBUG
103B      BUFF      RMB      5
A048      ORG      $A048      SET PC ADDRESS
A04B      FDB      START
A048 10 00      END
      NO ERROR(S) DETECTED

```

Program 2. Checks the output of a terminal.

trol-O. To do this in 8K BASIC version 2.0, change location 0154 to 08 and location 0155 to 00. (If you have a different version, consult your manual for the appropriate addresses.)

The unmarked key in the lower right corner of the keyboard can be wired to generate several missing characters. For instance, connected between pins 27 and 36, it will provide the at sign (@) and a backward slash (\). Between pins 31 and 38, it will generate a control-P for erasing the screen. Hooked up to pins 21 and 36, the key will provide the rubout. Various other combinations are possible; get the 2376 spec sheet from General Instruments or Don Lancaster's book.

Capsule Review of the H9 and CT-64

Heath's H9 and SWTP's CT-64 terminals are both about the same price and clearly compete with each other. Having used them both, I can comment and compare these two inexpensive terminals.

The Heath terminal is a single unit containing all the circuitry and a 12-inch monitor as well; it costs \$530, mail order. The SWTP CT-64 contains no monitor, but SWTP sells a CT-VM monitor in a matching case, which sits on top of the CT-64 in normal use. The two together cost \$500. They are not attached, but are connected with

a single cable and are easily separated.

The CT-64 can be purchased separately for \$325 and used with a standard monitor, modified TV set or a standard set with an rf modulator. (At the time of this writing, SWTP has introduced a new \$800 terminal, the CT-82, and it is possible that the CT-64 will be discontinued and/or sold at large discounts.)

In terms of professional looks, the Heath H9 is a clear winner. By contrast, the SWTP CT-64 looks somewhat clumsy and homemade. As with many SWTP products, the screw holes in the case do not line up well with the chassis, and the assembly is a bit flimsy. But it does look better in the flesh than it does in SWTP photos.

The CT-64 is also much smaller and lighter; with its separate video monitor, you can carry each piece separately. The single-case H9 is big and bulky.

Though the CT-64 screen is smaller than the H9's, it is much sharper. The CT-64 display is crystal clear; the H9 is fuzzy and dark. Moreover, H9 characters occupy less screen space, so that overall they are about the same size as those of the CT-64. The CT-64 is easier and more pleasant to read. If you get a different monitor, you can get a larger screen and possibly save some money as well.

But I really like the CT-VM monitor that SWTP sells for the CT-64.

The H9 display is 12 lines of 80 characters; the CT-64 has 16 lines of 64 characters. Although there have been some modifications published for adding another 12 lines to the H9, I suspect that the screen will then be too crowded vertically. It's a toss-up as to which is better—I prefer having more lines even if they are shorter. Twelve lines are definitely not enough.

The H9 also has a short-line mode that breaks up the screen into four columns of 20-character lines. This can be very useful for scanning the contents of memory locations. I have found, though, that this mode is only useful if all computer output fits these short lines. If there is an occasional long line, then the H9 display will be quite confusing.

The H9 also has a graphics mode. But it is only good for plotting graphs, such as those of voltage waveforms. It cannot be used for plotting several curves or any curve that has to bend back over itself. The resolution is extremely poor, and the graph consists of underlines rather than points. My own feeling is that it is of very limited use.

The CT-64 has full uppercase and lowercase, while the H9 is uppercase only. The H9 display can be modified to include low-

ercase, but I believe that it is quite difficult to modify the keyboard. On the other hand, the CT-64 keyboard is missing a few characters, such as the at sign or backward slash. But these can be added, as I mentioned above.

The H9 has a row of control keys, including screen and line erase, selectable scrolling, selectable automatic carriage return at the end of a line, choice of line length or graphics and several others. These are handy, but I have found that strangers tend to play with them, and I always find the keys in the wrong positions when I need them. The CT-64 has a much more limited range of controls.

One big complaint is that the H9 carriage return key is a small one, buried in the midst of a batch of other keys. I always have trouble finding it and keep hitting other keys instead. The CT-64 return key is larger and well placed.

The CT-64 can operate at a maximum of 1200 baud and, even at that speed, tends to sometimes miss characters. The H9 can operate up to 9600 baud. Moreover, the CT-64 does not have an external baud rate switch, while the H9 does. There is room to add a switch on the CT-64, but it is not supplied. In many applications, the CT-64 upper speed of 1200 baud is a definite disadvantage.

The CT-64 has a very handy switch that enables the display of control characters. Each control character is shown as a two-letter code, such as LF, CR NU or BS. This is very handy for debugging purposes or to see what your software is doing.

The CT-64 has an internal decoder that decodes all control codes. Of these, some, such as control-G or control-H, are dedicated for special functions, and some are decoded but not used. They can be used to control external functions. For instance, SWTP uses these control signals to control cassette recorder motors used with the AC-30 cassette interface. This can not be done with the H9.

Both terminals hide the on-off switch on the back. Both terminals provide EIA RS-232C

```

                                NAM    OUTDEL
                                OPT     0
*DELAY PROGRAM TO GIVE CT-64 OR CT-1024
*TIME TO ERASE, RETURN, ETC.
*P. STARK, 11/8/78
                                ORG     $B000
B000                                OUTDEL PSH B      SAVE ACC B
B001 37                                LDA B      GET PREVIOUS CHAR
B001 F6 A04C                                CMP B      IS IT LF?
B004 C1 0A                                BEQ DELAY   DELAY IF SO
B006 27 04                                CMP B      IS IT SCREEN ERASE?
B008 C1 10                                BNE PRINT  NO, SO GO TO PRINT
B00A 26 0C                                BNE PRINT  YES, SO SAVE INDEX AND DELAY
B00C FF A04A DELAY STX SAVEX
B00F CE 1000 LDX #$1000 SET UP DELAY LOOP
B012 09 WAIT DEX
B013 26 FD BNE WAIT LOOP UNTIL DONE
B015 FE A04A LDX SAVEX RESTORE INDEX
B018 B7 A04C PRINT STA A PREV SAVE CHARACTER
B01B 33 PUL B RESTORE ACC B
B01C 7E E1D1 JMP OUTEEE
                                *DATA IN SWTBUG RAM
                                ORG     $A04A
A04A 0002 SAVEX RMB 2
A04C 0001 PREV RMB 1
                                EQU     $E1D1
                                END

```

Program 3. OUTDEL program to give the CT-64 or CT-1024 time to erase.

connections, but neither provides the standard 25-pin connector. Heath uses their own nonstandard connector, which matches their H8 computer; SWTP provides a cutout on the back for the standard 25-pin EIA connector (not supplied).

The design of the CT-64 is fairly clear-cut, while the design of the H9 is quite sophisticated. The CT-64 is a basic, simple terminal; the H9 has a number of features, such as graphics. But the relative simplicity of the CT-64 is preferable, in my mind. It should be easily serviceable, while the H9 has complex circuitry that is not always easy to understand. It depends on several ROMs for its control functions and requires a different level of competence to do a good service job.

I also suspect that SWTP screens their incoming components better. We've built six H9s where I work and had multiple troubles with each one. There were numerous defective components, mislabeled parts and breaks on the printed circuit boards. The CT-64 does not seem to be nearly as plagued by poor quality control.

In terms of construction, the CT-64 is also simpler. Most of its guts are on one large printed circuit board, with several smaller boards that plug into it; there are relatively few wires strung between them. The H9, on the other hand, has a large cable harness connecting several smaller boards scattered throughout the chassis. There is a lot of chassis wiring to do.

Another consideration is that the CT-64's video monitor comes assembled; the video portion of the H9 takes up a considerable amount of time to mount and wire.

The H9 construction manual is a typical Heath masterpiece. By comparison, SWTP's CT-64 construction manual is deficient. It's badly organized and actually consists of several smaller manuals; it's hard to tell just how they fit together.

Put another way, you can work on the Heathkit at 2 o'clock in the morning with one eye closed, but you have to be wide awake to follow the SWTP

		NAM	FASTYP	
		*FASTYP OUTPUT FOR SWTP BASIC V2.0		
		*OPERATES THROUGH PORT 7		
		*P. STARK 10/19/78		
E1D1		OUTEEE	EQU	\$E1D1
7FD4		ORG	\$7FD4	
7FD4 81 0D	FASTYP	CMP	A	\$0D
7FD6 27 08		BEQ	PRINT	CR IS OK TO PRINT
7FD8 81 20		CMP	A	\$20
7FDA 25 21		BCS	DONE	SKIP OTHER CONTROL CHAR
7FDC 81 60		CMP	A	\$60
7FDE 24 1D		BCC	DONE	SKIP LOWER CASE CHAR
7FE0 FF 7F FE	PRINT	STX	SAVEX	PRINT SLOW: SAVE INDEX
7FE3 CE 10 00		LDX	\$1000	
7FE6 09	DELAY	DEX		DELAY A MOMENT
7FE7 26 FD		BNE	DELAY	
7FE9 36		PSH	A	
7FEA 8D E1 D1		JSR	OUTEEE	PRINT CHAR
7FED 32		PUL	A	
7FEE 81 0D		CMP	A	\$0D
7FF0 26 08		BNE	GETX	WAS IT A CR?
7FF2 86 05		LDA	A	\$05
7FF4 09	DELAY2	DEX		NO, SO RESTORE INDEX & EXIT
7FF5 26 FD		BNE	DELAY2	WAIT SOME MORE AFTER CR
7FF7 4A		DEC	A	
7FF8 26 FA		BNE	DELAY2	
7FFA FE 7F FE	GETX	LDX	SAVEX	GET INDEX
7FFD 39	DONE	RTS		RETURN
7FFE	SAVEX	RMB	2	INDEX STORAGE
	*SET UP JUMP FROM PORT 7 TO FASTYPE			
0145		ORG	\$0145	
0145 7E 7F D4		JMP	FASTYP	
	*REMOVE TEST FOR PLUGGED-IN INTERFACE			
121B		ORG	\$121B	
121B 20		FCB	\$20	
	*MAKE ROOM FOR FASTYPE AT TOP OF MEMORY			
0C41		ORG	\$0C41	
0C41 7F D4		FDB	FASTYP	
0044		ORG	\$0044	
0044 7F D3		FDB	FASTYP-1	
		END		
	NO ERROR(S) DETECTED			

Program 4. FASTYP patch for SWTP 8K BASIC version 2.0.

manual. Heath shows every board and its parts in several views and tells you about every view and tells you about every parts placement diagram for each board and requires that you look up the value of each part on the parts list to mount it. Moreover, SWTP instructions essentially say, "Mount all the resistors. . . . Mount all the capacitors. . . ."

But you can overlook this when you consider that the SWTP unit is simpler and hence requires less intricate work than the Heath requires. And I suspect the SWTP is more likely to work without extensive troubleshooting when you're finished.

The SWTP unit is less expensive than the Heath—even if you pay someone to build it for you, it may not be much more expensive. In particular, many computer stores have either personnel who build kits or bulletin boards listing people willing to do it. My unit was purchased wired from Lehigh Computer Works, 1132-2 Tilghman

St., Allentown PA 18102, which built it for a very reasonable additional amount.

PR-40 Ribbons, Etc.

PR-40 ribbons can be ordered from Addressograph-Multigraph Corp., part number 116-2395-326. If your PR-40 makes strange sounds and produces letters that are sometimes narrow and sometimes wide, perhaps it needs some grease on the cam. Mine did. See the power supply fix for C1 in Part 1 (March 1979, p. 58).

Compatibility of Cassette Tapes

Now that new software for the SWTP system is being produced by numerous companies, there is a problem of incompatible tapes. For instance, CORES source tapes cannot be read by the TSC Editor and Assembler used on cassette systems or on the SWTP disk system under FLEX, and vice versa. It's not just a matter of the language being a little different—the control characters and tape for-

mat are different.

But there is one format that all of these systems accept—that used when you sit at the keyboard and type in . . . fairly slow, no control characters and carriage returns, not line feeds, separating lines. Since the cassette interface of the SWTP comes in through the same port as the keyboard, all we have to do is reformat tapes to look like human input, although possibly somewhat faster, to the computer.

The result is what some people call the "fastypist" format . . . faster than a human, but still slow enough so that the computer can insert whatever control characters it needs. This format has no line feeds or other control characters other than carriage returns. It also has a lengthy delay after the carriage return to allow the computer to echo a line feed and a few nulls, and perhaps place the line in line-number order.

There are several ways to format your tapes this way. One is


```

NAM FASTYP-2
*FASTYP - CONVERTS ANY FORMAT TAPE INTO
*FASTYP-FASTYP TAPE
*P. STARK 10/19/78
E1AC INEEE EQU $E1AC
E1D1 OUTEEE EQU $E1D1
E0D0 SWATBG EQU $E0D0
0100 ORG $0100

*
*THE FOLLOWING PART READS THE TAPE
*
0100 CE 01 54 FASTYP LDX #TEXT
0103 BD E1 AC READ JSR INEEE
0106 81 0D CMP A #$0D
0108 27 0B BEQ STORE CR IS OK TO STORE
010A 81 20 CMP A #$20
010C 25 F5 BCS READ SKIP OTHER CONTROL CHAR
010E 81 60 CMP A #$60
0110 24 F1 BCC READ SKIP LOWER CASE CHAR
0112 A7 00 STORE STA A 0,X STORE IN MEMORY
0114 08 INX
0115 FF 01 4E STX LAST STORE NEXT EMPTY ADDRESS
0118 BC 01 52 CPX MLIMIT MEMORY FULL?
011B 26 E6 BNE READ NO, SO RETURN
011D 7E E0 D0 JMP SWATBG YES, SO EXIT

*
*THE FOLLOWING PART OUTPUTS THE TEXT
*
0120 CE 01 54 OUTPUT LDX #TEXT GET ADDRESS OF TEXT START
0123 FF 01 50 OLOOP STX NEXT SAVE ADDR OF NEXT CHAR
0126 CE 10 00 LDX #$1000
0129 09 DELAY DEX DELAY A MOMENT
012A 26 FD BNE DELAY
012C FE 01 50 LDX NEXT
012F A6 00 LDA A 0,X
0131 BD E1 D1 JSR OUTEEE PRINT CHAR
0134 A6 00 LDA A 0,X
0136 81 0D CMP A #$0D WAS IT A CR?
0138 26 0B BNE INCRX NO, SO INCREMENT X AND CONTINUE
013A 86 05 LDA A #$05 WAIT SOME MORE AFTER CR
013C 09 DELAY2 DEX
013D 26 FD BNE DELAY2
013F 4A DEC A
0140 26 FA BNE DELAY2
0142 FE 01 50 INCRX LDX NEXT GET POINTER TO NEXT CHAR
0145 08 INX INCREMENT
0146 BC 01 4E CPX LAST ALL DONE?
0149 26 D8 BNE OLOOP NO, SO CONTINUE
014B 7E E0 D0 JMP SWATBG YES, SO EXIT
014E LAST RMB 2 ADDR OF NEXT EMPTY MEM LOCATION
0150 NEXT RMB 2 ADDRESS OF NEXT CHARACTER
0152 80 00 MLIMIT FDB $8000 LIMIT OF MEMORY SIZE
0154 TEXT RMB 1
A048 *SET PROGRAM COUNTER
A048 ORG $A048
A048 01 00 FDB FASTYP
END
NO ERROR(S) DETECTED

```

Program 5. Tape-to-tape FASTYP.

to patch your program to produce this output directly; another is to write a program that will re-format an existing tape. Programs 4 and 5 show the two approaches.

Program 4 is a patch for SWTP 8K BASIC version 2.0, which substitutes a fastypist routine for the printer routines on port 7. This version is assembled to lie at the very top of memory for a 32K system, from 7FD4 to 7FFF; it can be loaded after BASIC and its source program are in memory. It is easily moved down for smaller memories, or up if you have a larger system.

To use the patch, simply tell BASIC to LIST#7, start the tape and then hit return. It will be re-

coded in the fastypist format. The patch makes three changes to BASIC to set up the jump and make sure that BASIC does not erase it.

The jump at location 0145 sets up the jump from BASIC into the fastypist routine after an output to port 7. The BRA or 20 inserted at 121B defeats a test in which BASIC checks to make sure that an interface is really plugged into port 7 before accepting the LIST#7 command. If you really have an MP-L plugged into port 7, you will not need this step.

When BASIC first starts up, it stores \$55 into each memory location above itself and then reads it back to see if it went in properly. This is how it finds out

how much memory your system has. Normally, location 0C41 has the address 8000, and BASIC stops checking when it gets there. If you ran this, BASIC would erase the fastypist patch. By placing the starting address of the fastypist routine into 0C41, we stop the memory-checking routine there. We then store one less than that into location 0044, which tells

03A3	B6	8004	LDA A	\$8004	DOES ACIA HAVE ANYTHING?
03A6	47		ASR A		
03A7	24	11	BCC	NO	IF NO CHARACTER
03A9	DF	8A	STX	\$008A	YES, SAVE INDEX REGISTER
03AB	DE	90	LDX	\$0090	GET CURRENT PORT ADDRESS
03AD	BD	E1AC	JSR	\$E1AC	GET THE CHARACTER

Program 6.

BASIC the last available address.

Program 5 shows a complete program that reformats almost any format tape into a fastypist tape. It starts at 0100 and goes up to 0153. The first part of the program reads the tape, strips off all lowercase letters and control characters other than the carriage return and stores the rest in memory. Before running it, set MLIMIT to one more than the last address you have; it is now set to \$8000 for a 32K system.

When the tape is done, reset the computer and start the second part of the program at OUTPUT. Fastypist will now output the text at the slower speed required. To read fastypist tapes back in, just make believe you are typing but turn on the cassette interface instead. Your program will never know the difference.

One last comment: Because of a hardware conflict, fastypist tapes will not read on the otherwise excellent Percom CIS-30+ interface. I will explain why later in this series of articles, when I review four cassette interfaces for the SWTP system.

More BASIC Patches

There are numerous patches you might make to BASIC for various other functions, and some have been published in *Kilobaud*. For instance, the idea used in Program 3 above of limiting the size of the memory BASIC uses was written in a recent issue by Dexter French of Longwood FL (see "Letters," October 1978 *Kilobaud*, p. 21).

Dale Puckett ("String Expansion for SWTP's BASIC," July 1978 *Kilobaud*, p. 68) recently wrote another patch for SWTP 8K BASIC version 2.0, which allowed changing the string length by changing the hex

number in location \$003E. It is currently at \$20 for 32 characters but can be changed to anything from 7 to 72. Dale's suggestion was that it can easily be changed with a POKE(62,) statement. But be sure to do it only once in a program, that is, at the very beginning.

Despite what SWTP says in their SWTBUG manual, 8K BASIC version 2.0 can be changed to run with the MP-S serial terminal. The patch you need to make is shown in Program 6. This is part of the routine that looks for a control-C character for a break. Once you make this change, BASIC will not work with the MP-C interface. My thanks to Tom Quay of the above-mentioned Lehigh Computer Works for this patch.

Another patch you may not have seen yet is for SWTP 8K BASIC version 3.0 (the FLEX disk version), which fixes the problem with the RESTORE command:

```
13DD 92
205C 09
2060 05
```

If you are using Cassette Super BASIC from Computerware Software Services, 830 First Street, Encinitas CA, and have 32K of memory, you may have noticed that this BASIC only uses 26K or 28K of it to leave room at the top for a disk operating system if you have one. If you don't, then you may want to patch the BASIC so it uses the space up to \$7FFF. In version 1.0 change location 010C from 70 to 80; in later versions the address is 010D and should be changed from 68 to 80.

Another function is to renumber BASIC lines. Island Computers, St. James City FL, offers a BASIC line renumberer program, which is actually written in BASIC itself, using line numbers 9900 through 9988. It is intended for SWTP 8K BASIC version 2.0. But note: It only renumbers the lines themselves; it does not update line numbers in GOTO or GOSUB statements. A more complete renumberer, called RENBAS, is available from Computerware Software Services.

The January 1979 Issue of

Kilobaud MICROCOMPUTING ("An Editor for 6800 BASIC Programs," p. 22) describes my own version of a renumberer/editor called BASEDIT. Editing allows global replacement of strings and searching for certain strings. Renumbering a program changes each line number and also updates all references inside GOTO, GOSUB, IF and ON . . . GOTO statements.

BASEDIT does not work on a BASIC source program while it is in memory with the interpreter. It is designed to read a BASIC source tape, edit it and then write out a new tape. You can probably think of many changes you'd like to make to BASIC, but the problem is finding out enough about the BASIC to know how to do it. Although you can get a fairly good idea of how BASIC works if you disassemble it and spend a few weeks studying the resulting 72 or so pages, it is certainly not easy.

But now somebody has finally done something about it. SSI, 4327 Easy Grove Street, Phoenix AZ 85040, publishes *A Companion to Robert Uiterwyk's BASIC Interpreters* by Dave Gardner. It outlines the major memory locations used in the various MSI and SWTP BASICs Robert Uiterwyk has authored, explaining what they do. Dave also presents 34 additions or patches you can make.

The BASICs covered are MSI version 1.2, SWTP 4K version 2.0, 8K version 2.3 and disk version 3.0. The book lists 72 locations and entry points in the BASICs and explains what they do.

Among the modifications and additions, one simple change makes BASIC print out the number of the line it was doing before it was stopped with a control-C. Another added command causes printout of how much memory is taken up by the BASIC program, its variables and string and stack buffers. Another implements an ON ERROR GOTO statement, which allows programs to recover from errors without stopping.

All in all, it's a very useful



Punching a diskette for double-sided use.

book; I'm waiting for Dave Gardner's next offering.

A 6800 Newsletter

'68' *Micro Magazine*, a monthly newsletter for 6800 users (actually, it will also be for users of the 6802, 6809 and other Motorola 6800-family processors) started publication early this year. Mickey Ferguson, a *Kilobaud* regular and 6800 expert, and Dennis Womack, another 6800 expert, are working on it, so it's definitely worth reading.

They plan articles on how to adapt the MF-68 disk and FLEX to the Sphere computer, how to modify BASIC to allow longer variable names, modifying the A/BASIC compiler to work with the SWTP MP-N calculator interface and various reviews of new and old equipment. They also plan to print a number of application programs. For further information, write to '68' *Micro* at 3018 Hamill Rd., Hixson TN 37343.

Selectric Parts and Golf Balls

One thing I love about my SWTP system is the ease with which I can interface other hardware to it. I am using a Dura 1041 Selectric typewriter terminal, interfaced to an MP-L card, to prepare this article. I wouldn't be surprised if some readers had a similar setup. If you need Selectric parts or interfacing information, I have found Kelly Data, 20589 S.W. Rosa Dr., Aloha OR 97005, very helpful. They also sell mainte-

nance manuals and all sorts of tools.

Broken golf balls? I'm referring to the little bouncing balls that the Selectric typewriter uses as typing elements. If you have one with cracked teeth, a broken stem or a broken top, you can get it repaired by DSG, Inc., 1737 Chestnut Street, Philadelphia PA 19103. They also sell new ones and provide quick service.

Two-sided Disks

SWTP has just lowered the price of their MF-68 mini-floppy dual disk system. You've probably noticed that. But a less known change is that they are now supplying it with Wangco model 82 disk drives instead of the Shugart SA400 drives they used before. Aside from the fact that it looks different, the Wangco drive has two mechanical changes. First, instead of 35 disk tracks, it allows the use of 40; this means that with a slight change in programming the Wangco drive has a seventh more storage than the older drives. (More on this in a future article.)

The second interesting change is that the Wangco drive has two optical hole sensors and two file-protect sensors instead of one. Now you can put the diskette in upside down and write on the back of the disk as well as the front. This gives you twice the storage on every disk. It's not quite as good as a double-sided drive, which would let you write on

the back without pulling the diskette out and flipping it, but it's better than a single-sided one.

If you are careful and do not have slippery fingers, you can do the same with older drives too. The trick is to punch holes in the diskette cover so that it can be put in upside down. Three holes are required—two in the spot where the sector holes have to be read and a third where the write-protect switch touches the edge.

Several people have apparently had the same idea at the same time. One technique was described by Morris J. Miller in the December 1978 issue of *Kilobaud* ("Scratched Disk-

ette?" p. 106). My technique is a little different, but the end result is the same.

I use a hand punch to punch a round hole in the diskette cover. I start by carefully marking on the black diskette cover the location of the hole, one on each side, symmetric with the sector-sensing hole it already has. To avoid scratching the disk beneath, I cut a narrow piece of slick paper into a strip, which I carefully slide into the diskette cover through the center hole, under where I want the new hole. Then I insert the hole punch and carefully punch the hole. See the photo for details.

Your hole punch must be absolutely new and sharp. The in-

side of the black cover is coated with a fabric layer that decreases the friction as the disk turns. If the hole punch is not sharp, tiny strands of thread will hang out and mess up the job. They are hard to remove and can become wedged between the disk and head.

You can use the same hole punch to cut a slot along the edge for the write-protect switch. But I prefer to use a tool designed to cut metal electronic chassis; it is called an Adel Nibbling Tool and makes a much more even slot.

Practice makes perfect. Be very careful, because if you ruin a few disks you will lose more than you will gain. I have

punched all of my disks this way and have had no problems.

What do you do with the new disk sides? Well, how about using them for backups? A good idea is to back up disk 1 on the back of 2, and back up disk 2 on the back of 1, and so on. In this way, you will quickly remember which disk has the backup of which other disk.

Conclusion

That's all for this installment. I'll include more ideas next time, along with some more capsule reviews. If you have any suggestions or would like something included, please let me know. (Do not write c/o *Kilobaud MICROCOMPUTING*.)■

SPECIAL SALE ON OSI

LIMITED QUANTITIES:

CHALLENGER II—4P with fast 6502 Microsoft BASIC, cassette interface; high resolution 32 x 64 video board with excellent graphics; rugged steel cabinet; 4 slot motherboard with 2 slots free; extensive documentation; **TESTED, BURNED-IN, WARRANTED**—4K \$525.00 (reg. \$598.00) additional 4K RAM (total 8K) add \$60.00; video monitor with video AND audio inputs! \$115.00.

MINIFLOPPY version of C2-4P with 20K RAM, DOS, 9 digit Microsoft BASIC, ASSEMBLER and EDITOR, Extended monitor, cassette functions retained; 5 free diskettes—a total of 25 programs in games, business, education, and personal applications. Single drive system—\$1475 (reg. \$1725) additional 4K—\$60.00; video monitor as above—\$115.00

Call Toll FREE (continental U.S. except Alabama) 1-800-633-8724 (Alabama number is 745-7735)

Plainsman Micro Systems

P.O. Box 1712

Auburn, Alabama 36830

ALL GOODS TESTED AND GUARANTEED



WEB ASSOCIATES



BREAK THE SILENCE!

Let TBEEP™ signal you for INPUT PROMPT and/or ENTRY ERROR.

- Software controlled
- Clear distinctive tone
- Requires two word instruction
- Plug in line with cassette AUX cable
- Doesn't interfere with cassette
- Long life battery included
- Disk compatible.

\$27.95



Dealer inquiries invited —

Club discounts available.

For more information circle #W20

Send check or money order to:

WEB ASSOCIATES

P.O. Box 60-KW, Monrovia, CA 91016

(California Residents add 6% tax)

PET 2001 • PET 2001 • PET 2001 • PET 2001 • PET 2001 • PET 2001 • PET 2001

Programmer's Guides for the PET™

TIS

WORKBOOKS FOR THE COMMODORE PET 2001

Getting Started with Your PET WB-1 \$4.00

Covers the fundamentals of PET BASIC, calculator and program mode, data input and output, data representation, program storage on the cassette.

PET String and Array Handling WB-2 \$3.95

Covers string and array handling, concatenation, replacement and manipulation.

PET Graphics WB-3 \$4.95

Covers use of cursor control and special graphics symbols to draw plots, histograms, and sketches.

PET Cassette I/O WB-4 \$4.95

Covers OPEN, CLOSE, string and numeric data files.

Miscellaneous PET Features WB-5 \$3.95

Covers the clock, random number generator, upper and lowercase alphabetic characters, saving memory space, etc.

PET Control and Logic WB-6 \$3.95

Covers IF, GOSUB, logical operations, and ON X.

Add \$1.50 for shipping and handling.

Dealer inquiries invited.

TIS P.O. Box 921

Los Angeles, NM 91544

Money back guarantee.

We also sell PET Software. Write for details. #T41

PET is a trademark of Commodore Business Machines

PET 2001 • PET 2001 • PET 2001 • PET 2001 • PET 2001 • PET 2001 • PET 2001

FRUGAL FRONT PANEL SERIES

S-100 DISPLAY-SENSE BOARD

Board and Manual \$34.95 Kit \$89.95

REMOTE HEX PANEL

Board and Manual \$27.50 Kit \$74.95

REMOTE BINARY PANEL

Board and Manual \$27.50 Kit \$69.95

* Assembled Versions Available *

HEAVY DUTY UPHOLSTERY VINYL COMPUTER CANOPY DUSTCOVERS

APPLE II \$13.95

H-8, H-11, HORIZON, INTEGRAND 800D \$15.95

HAZELTINE 1500/1510/1520, ADM-3, H-9 \$17.95

PET, SWTPC CT-82, ACT IVB \$19.95


SAVE ON 3-PIECE SETS:

TRS-80 — \$29.95; HEATH — \$39.95

* Write For Other Models *

Add \$2 per item for shipping & handling; \$1 extra for COD

Texas residents add 5% tax. M/C & VISA accepted.



Digital Dynamics, Incorporated
Dept K, 310C Breesport
San Antonio, TX 78216
(512) 341-8782 #D37

μ COMPUTER BOARDS

NEW! CPU WITH SERIAL PORT 8080A *** S-100 SINGLE BOARD

Now it's easy — with a CPU Board which includes an on-board serial port. This 2 MHz CPU Board talks directly to your terminal by 20 ma current loop or RS-232. Baud rate selectable from 110 to 9600.

ASSEMBLED AND TESTED... ONLY — \$195

NEW! AUDIO CASSETTE INTERFACE WITH 3 PARALLEL I/O PORTS S-100 *** SINGLE BOARD

Your best choice for mass storage. This board includes 3 parallel 8 bit ports, a tape motor control (on-off) and a driver for external data I/O monitor lamp. The 3 PIO port common handshake signal lines are independent of data lines.

ASSEMBLED AND TESTED... ONLY — \$195

OUR 20th YEAR OF ELECTRONIC EXCELLENCE

the Nucleus

#N13



INC. 461 Laboratory Road
Oak Ridge, TN 37830
615-482-4041

Visi Calc™

How did you ever do without it?

© 1979 PS Inc. #P39

5 reasons why you should not buy the electric pencil II™

© 1978 Michael Shrayner



Check the appropriate box(es):

- ☐ You love typing the same copy 20 thousand times a day.
- ☐ Your secretary can type 250 words per minute.
- ☐ You're dying to spend \$15,000 on a word processing system, just for the tax investment credit.
- ☐ All your capital assets are tied up in a 10-year supply of correction fluid.
- ☐ You never commit a single thought to paper.

If you have checked one or more boxes, you do not need The Electric Pencil. On the other hand, you may want to join the thousands of people who haven't checked a single box.

The Electric Pencil II is a *Character Oriented Word Processing System*.

This means that text is entered as a string of continuous characters and is manipulated as such. This allows the user enormous freedom and ease in the movement and handling of text. Since line endings are never delineated, any number of characters, words, lines or paragraphs may be inserted or deleted anywhere in the text. The entirety of the text shifts and opens up or closes as needed in full view of the user. The typing of carriage returns or word hyphenations is not required since lines of text are formatted automatically.

As text is typed and the end of a line is reached, a partially completed word is shifted to the beginning of the following line. Whenever text is inserted or deleted, existing text is pushed down or pulled up in a wrap around fashion. Everything appears on the video display as it occurs, which eliminates guesswork. Text may be reviewed at will by variable speed scrolling both in the forward and reverse directions. By using the search or search and replace functions, any string of characters may be located and/or replaced with any other string of characters as desired.

Numerous combinations of line length, page length, line spacing and page spacing permit automatic formatting of any form. Character spacing, bold face, multicolumn and bidirectional printing are included in the Diablo versions. Multiple columns with right and left justified margins may be printed in a single pass.

Wide screen video

Versions are available for Imsai VIO video users with the huge 80x24 character screen. These versions put almost twice as many characters on the screen!!!

CP/M versions

Digital Research's CP/M, as well as its derivatives, including IMDOS and CDOS, and Helios PTDOS versions are also available. There are several NEC Spinwriter print packages. A utility program that converts The Electric Pencil to CP/M to Pencil files, called **CONVERT**, is only \$35.

Features

- CP/M, IMDOS and HELIOS compatible
- Supports four disk drives
- Dynamic print formatting
- DIABLO and NEC printer packages
- Multi-column formatting in one pass
- Print value chaining
- Page-at-a-time scrolling
- Bidirectional multispeed scrolling controls
- Subsystem with print value scoreboard
- Automatic word and record number tally
- Cassette backup for additional storage
- Full margin control
- End-of-page control
- Non-printing text commenting
- Line and paragraph indentation
- Centering
- Underlining
- Bold face

Upgrading policy

Any version of The Electric Pencil

m
ss

MICHAEL SHRAYNER SOFTWARE, INC.

1253 Vista Superba Drive
Glendale, CA. 91205

(213) 956-1593

may be upgraded at any time by simply returning the *original* disk or cassette and the price difference between versions, plus \$15 to Michael Shrayner Software. Only the originally purchased cassette or diskette will be accepted for upgrading under this policy.

Have we got a version for you?

The Electric Pencil II operates with any 8080/Z80 based microcomputer that supports a CP/M disk system and uses an Imsai VIO, Processor Tech. VDM-1, Polymorphic VTI, Solid State Music VB-1B or Vector Graphic video interface. REX versions also available. Specify when using CP/M that has been modified for Micropolis or North Star disk systems as follows: for North star add suffix A to version number; for Micropolis add suffix B, e.g., SS-IIA, DV-IIB.

Vers.	Video	Printer	Price
SS-II	SOL	TTY or similar	\$225.
SP-II	VTI	TTY or similar	225.
SV-II	VDM	TTY or similar	225.
SR-II	REX	TTY or similar	250.
SI-II	VIO	TTY or similar	250.
DS-II	SOL	Diablo 1610/20	275.
DP-II	VTI	Diablo 1610/20	275.
DV-II	VDM	Diablo 1610/20	275.
DR-II	REX	Diablo 1610/20	300.
DI-II	VIO	Diablo 1610/20	300.
NS-II	SOL	NEC Spinwriter	275.
NP-II	VTI	NEC Spinwriter	275.
NV-II	VDM	NEC Spinwriter	275.
NR-II	REX	NEC Spinwriter	300.
NI-II	VIO	NEC Spinwriter	300.
SSH	SOL	Helios/TTY	250.
DSH	SOL	Helios/Diablo	300.

Attention: TRS-80 Users!

The Electric Pencil has been designed to work with both *Level I* (16K system) and *Level II* models of the TRS-80, and with virtually any printer you choose. Two versions, one for use with cassette, and one for use with disk, are available on cassette. The TRS-80 disk version is easily transferred to disk and is fully interactive with the READ, WRITE, DIR, and KILL routines of TRSDOS 2.1.

Version	Storage	Price
TRC	Cassette	\$100.
TRD	Disk	\$150.

Demand a demo from your dealer!

New Life for Our Altair

It's two years later. Whatever happened to those Altairs?

Harley Dyk
Computer Math Instructor
Mona Shores High School
Muskegon MI 49441

This article is a follow-up to my June 1977 *Kilobaud* article ("Put a Micro in Your School," p. 38), which outlined the acquisition of two Altair 8800A computers (bought in the summer of 1976) to use in my computer math classes. The purchase consisted of the two computers, a CRT, a Teletype and two cassette recorders.

I should first report that the computers have done everything I anticipated. The only downtime we experienced was when BASIC would die, or a power failure would wipe it out, and loading (toggling the bootstrap loader, etc.) would take about 10 minutes. Even both of the infamous Mits ACR boards (the reportedly undependable, obsolete design) have worked flawlessly for two school years as a cassette interface. We did use premium audio tape, and each student had his own tape,

which was kept in the classroom to avoid significant temperature changes and possible damage from being dropped in the sand or dirt.

The only hardware problem we encountered in two years was during the operation of a computer dating program when occasionally someone's name would lose a character. A memory test revealed that memory location 13038 on the 16K static memory board had some bad bits. Our decision to try time and materials on our system has worked out well.

The equipment was picked to accommodate an average of 25 students who had been taking the class each year. The equipment (with two on-line users) proved to be adequate the first year. However, the second year began with 47 students, and the only improvement in equipment was a Lear Siegler ADM-3A to use in place of the Teletype (ASR-33) terminal.

With this configuration, the CRTs were used most of the time and the Teletype was used only when hard copy was desired. It was also used (off line) so students could put their first

version of a program on paper tape for later loading into the computer. However, we still had only two on-line terminals for 47 students. We managed only because we were fortunate that half of the students had a free hour when the computers were available, and these students were willing to work on the computer then.

Where Do We Go from Here?

The fall of 1977 found me researching what we needed to get at least two more terminals on-line. The PET and TRS-80 were available, but not enough was known about them yet and the peripheral situation was very gray at that time.

I wanted to accomplish three goals with new equipment: (1) provide two or three more on-line terminals; (2) increase the speed of program storage and retrieval; (3) increase hard-copy speed. The equipment had to be compatible with what we had. Buying two or three PETs or TRS-80s would have taken care of the first goal but left us with incompatible cassette-tape formats. It would have given us two unidentical BA-

SICs, and the hard-copy situation was not totally clear for these systems at that time.

Time-sharing seemed a real possibility since it was available for the Altair. If you have watched the blinking lights on an Altair in a single-user system while students are entering, debugging and running programs, the computer is loafing 80-90 percent of the time. Why not run several users off the same mainframe and utilize its power?

With the equipment we had, time-sharing, a floppy disk, two more CRTs and a printer was the best way to proceed. Of course, the time-sharing system involved more I/O boards, more memory, etc. In fact, it meant an Altair with 13 full slots rather than the four we had full.

Ask and You Shall Receive

Spring 1978 found me asking for an additional \$8600 worth of equipment at a school board meeting. The meeting went as well as could be expected. The purchase of the additional equipment was approved with hardly a question.



L-R: Students Tim Fullmer, Scott Fisher, Jeff Cramer, Judy Stuhan and Jeannine Vandonkelaar working on our system.

(Photo by Gary Reed)

I guess the success of the program and an almost 100 percent increase in enrollment for the class helped convince the board that we needed more equipment. Another selling point was that another user could be added to the system with only the additional cost of a terminal.

The Equipment

The printer we chose was the Texas Instruments 810. The basic model (uppercase only) sold for \$1895 and handled paper up to 132 char. (tractor feed) and printed at 150 cps. This seemed the best buy in printers. It is an excellent value, if your application can tolerate the dot matrix quality. I have seen the printer advertised recently for \$1695.

The disk was the new Mits 3202 dual floppy. This is their first dual floppy and, at 80 lbs, it is a sturdy piece of equipment. It seems better built than their older single drives.

After talking to several people (including people at three other installations in Michigan that were using Mits Time-sharing) and after considering the good advice of Peter Blond

(owner of the Computer Store of Ann Arbor), we decided to get the dual floppy rather than a single. The ability to copy diskettes is a valuable feature, and with several users depending on the system, one drive out of alignment would leave half of the disk usable until the other half could be repaired.

I chose the Microterm ACT-IVB for the CRTs. For the same cost as the ADM-3A, the Microterm has the same features plus better cursor control, a local mode, printer port, number pad and lowercase.

Ordering and Delivery

We ordered the equipment about June 1, and I lovingly put one of our faithful 8800As in the mail to Ann Arbor for rebuilding. Peter Blond had strongly suggested that the power supply of our "A" be replaced with the "B" power supply. I guess the main reason we did not want to skimp on the power supply or disk was to forestall the 2 1/2 hours drive (by car) to Ann Arbor. (It is nice to have a reliable system . . . particularly when 45 students cry when it is not working.)

The system came about two weeks after school started, about the time the students were sick of flowcharting and watching demonstrations on our single-user system. Mits Time-sharing 1.1 (without files) had been out over a year, and was what we had ordered, but we were asked to be an Alpha test site for a preliminary version of Time-sharing 2.0 with files. Of course we agreed. The T/S 2.0 went on the market in early 1979.

Using the System

After five months of using the system, we loved it. We used to load 10.2K of BASIC in seven minutes from cassette after toggling in the bootstrap loader. The T/S BASIC 2.0 loads in about 5 seconds from the disk. An Autostart board holds the bootstrap in ROM. The T/S BASIC 2.0 occupies over 28K and is the full Extended Mits Disk BASIC complete with sequential and random files.

After the bootstrap load, the system must be initialized. At this point, the available RAM is divided among the users, the number of users (up to eight) is

picked, the users are placed at priority levels, and the number of sequential and random files per user is picked.

Our system with the full 64K leaves about 36K available for the four users. After memory for buffers, string space, swap areas, etc., we are left with an average of 7.7K for each of our four users. We are presently running three users at 6.6K each and one user at 11K. You could increase the memory by using T/S 1.1, and, of course, the memory can be divided as desired at initialization time.

The T/S BASIC with the dual floppy makes a beautiful system for the students saving and loading programs. I am using two diskettes for 45 students, which allows storage of a maximum of 560 programs for a total of over 570K bytes. Obviously this averages out to a little over 1K per program, and certainly some programs will be over that, so I recommend that each student keep a maximum of seven or eight programs on the disk.

Using the same two diskettes all day allows a student to work on the system during any free




Fig. 1. System configuration.

hour or after school and have his programs available instantly. It also means the students do not have to handle the diskettes, which I believe will help in maintaining a reliable disk system. I am all for hands-on experience, but when one student can mess up a disk by improper handling of a diskette with filthy hands, thereby inconveniencing 44 other students, I draw the line.

With all students able to access the disk, some sort of protection is needed. This is provided by the T/S software, and each student must use a password to save, load and kill programs. Degrees of protection are provided so that the instructor can put programs on the system, programs that are usable by the students but cannot be killed or altered by the students.

Our system is also versatile. Besides the obvious advantages of disk, we can use cassette in the single-user mode to take old cassette programs and store them on disk in the single-user mode. Then the disk can be read in the T/S mode. The Teletype with paper tape can be switched into the T/S system (see Fig. 1) so software available on paper tape can be read in and placed on disk.

I plan to require each student to do at least one program using paper tape and one program using cassette on the single-user system with the Teletype. I think the more exposure I can give them to different storage and retrieval methods, the

more valuable the class will be to them. They will truly appreciate the disk and CRTs after working on the Teletype with paper tape or cassette.

Conclusion

Is a T/S system a viable alternative or even competitive with several single-user TRS-80s or PETs? I guess that depends on the individual situation. We began choosing equipment and made our first purchase in the spring of 1976 when Mits was clearly the leader. That we had some of their equipment clearly influenced us when we were looking for more equipment.

Now that Mits has moved on to the small-business market (and does not even make kits anymore), there are many other companies and configurations to choose from. Yet an Altair 8800B with eight users, dual disk, 150 cps printer and eight

CRTs can be purchased for under \$2000 per user. This cost increases to about \$2850 per user for four users, which is a better situation with respect to memory and response time. This can be compared to a TRS-80 4K Level II with quick printer and cassette for about \$1500, or the TRS-80 16K Level II with quick printer and mini-disk for about \$2300. So at the four-user level the prices are in the same ball park, and four mini-disks would not give the same storage as a full-size dual unit.

Obviously response time would be slower with the T/S system compared to the single-user configuration, but in our four-user situation, response time has been no problem. All jobs are worked on "simultaneously" (the computer works on the user's jobs in .1 second slices), and it is seldom that all four users are crunching numbers at the same time.

A typical situation finds one user entering a program from the keyboard, one user listing his program, one user running his program, and one user staring at the CRT trying to figure out what he did wrong. I can see that eight users could degrade response time, especially if two or three users were crunching numbers. Table 1 shows exactly what to expect when two, three or four users do time-consuming jobs.

The argument that all users are down when a T/S system crashes is an important consideration and applies here. I can

only respond to that after we have used our system for some time and see how reliable it is. Had we purchased several single-user micros, we probably would have had better graphics, but I am not convinced that I need graphics to teach the logic of programming.


I think response time will improve in T/S systems as the newer, faster chips come out and the CPU frequencies rise ... and possibly as the 8-bit machine becomes rare. I can envision a 16-bit machine (if the people in the TI organization ever get one on the market) as fast in a T/S mode with eight users as a single-user 8080 machine now.

I believe there is a market for the T/S configuration. It may not be for the mass market or average consumer, at least not yet. I heard of a family (who owned an Altair, disk, etc.) that bought time-sharing. It was one way the father could get back on his machine without having to ask his children and wife to get lost. Who knows—in five years micros may come standard with the possibility of three or four simultaneous users.

We like our T/S system—we now have accessibility to the high-speed disk, we can print most programs in a matter of seconds, our Altair has been saved from obsolescence, and where else can you play Battleship, Star Trek, Hangman and monopoly simultaneously against an 8080 chip? ■

Program:		
10 FOR X=1 TO 10000		
20 NEXT		
Time to run program in single-user BASIC: 14.5 seconds		
Mits 8K Ver. 4.0		
Time to run same program in Time-share system: Mits T/S Ver. 2.0		
# of users running program	Time taken for each user to complete job	Average time to complete job once
1	16.6 sec.	
2	38.4 sec.	16.6 sec.
3	57.5 sec.	19.2 sec.
4	76.8 sec.	19.2 sec.

Table 1.



WE'VE GOT THE BUG,

(THE NEW MOTOROLA TV BUG, THAT IS!)

By now you've probably read the article in this issue of Kilobaud about Motorola's new fantastic Miro Chroma 68.

It is the latest in TV Bugs which enables you to hook up directly to your own standard color TV with the fewest of parts

Micro Chroma 68 kit includes:

MC1372—Color TV video modulator.

MC6821—Peripheral interface adapter.

MC6808—Microprocessor with clock.

MC6846—Rom—I/O—Timer.

MC6847—Video display generator.

MC6850—Asynchronous communications interface adapter.


Also includes printed circuit board and data sheets on all above mentioned LSI.



\$129.⁹⁵

IN STOCK AND NOW AVAILABLE THROUGH AUSTIN ELECTRONICS.

AND WE'VE GOT THE PARTS KIT!



We at Austin Electronics went one step further and put together a parts kit of all support devices. These parts for the average enthusiast would be very difficult to find and expensive. We've made it easy and substantially less expensive.

Bug kit II comes complete with all components necessary for on board operation. Including (6) 2114 rams.

BUG KIT II.....\$149.95

MICRO CHROMA 68 KIT.....\$129.95


PC BOARD SEPERATE.....\$45.00

ADDITIONAL 2114 RAMS.....\$8.50

BUY THE MICRO CHROMA 68 AND THE BUG KIT II NOW SAVE \$15.00.

SEND FOR OUR NEW CATALOG WHICH INCLUDES GREAT BARGAINS ON ASCII KEYBOARDS, MODEMS, COMPUTER POWER SUPPLIES, ETC.

AUSTIN ELECTRONICS



1536 EAST ANDERSON LN.
SUITE E
AUSTIN, TEXAS 78752



1-512-836-9677

TERMS: Check or money order, NO COD's. Texas residents add 5% sales tax. Overseas countries add \$5.00 for surface rates.

TVBUG

Motorola has borne another in a long line of BUGS.

Tim Ahrens
7405 Ladybug St.
Austin TX 78744

Motorola has given birth to a new bug: TVBUG. From the very beginning, the easiest way to use the MC6800 series microprocessors and peripherals was through the different "BUGs," or developmental firmware provided from Motorola. These ranged from the original MIKBUG to MINIBUG II to MIKBUG 2.0 to the new TVBUG. This latest bug enables you to hook up to a standard color TV with a minimal number of parts.

Traditionally, Motorola's microcomponent division has not been overly active in the hobby market, mainly because of the difficulties in marketing small quantities. Since the MEK6800-D2 kit sold well in both the OEM and hobbyist market, other systems that the hobbyist can find useful are underway in Austin. One of these projects is TVBUG. The following pages describe how to build and use this system. This kit has great potential for both software generation and general games-type usage.

One of the main advantages of the TVBUG system is simplicity. One small printed circuit card can contain an entire microprocessor system with color-graphics display capabilities, 8K of user RAM, 6K of display RAM and a complete Kansas City (KC) Standard audio-cassette-tape interface. By connecting a standard ASCII keyboard and standard televi-

sion set to the board, a complete system is born.

The system is composed of the following major pieces of hardware:

- MC6808 MPU with clock
- MC6847 Color Video Display Generator
- MC6846P3 TVBUG with I/O and Timer
- MC6821 Peripheral Interface Adapter
- MC6850 Asynchronous Communication Interface Adapter
- MC1372 Color RF (Radio Frequency) Video Modulator

Of course, external "glue" or hardware such as buffers and gates is required, but the above-mentioned parts represent the major portion of the chips.

This system can be wire-wrapped or built on a printed circuit board. Either is satisfactory and will provide a nice home-computer system. If you have been waiting for the easiest and least expensive hobby system, this is it!

Before describing how to hook it up, let's first go into TVBUG's insides to see how it works.

System Hardware

The TVBUG system as shown in Fig. 1 is configured for a minimum hardware application. This system includes the MC6808 Microprocessor, ROM with TVBUG 1.2, I/O, the MC6846 Timer, MC6821 PIA, MC6850 ACIA for serial I/O, the MC6847 Video Display Generator and an MC1372 Video RF Modulator. In addition to this, the schematic shows 1K byte of RAM for display, the stack RAM area and

the user RAM. A KC Standard 300 baud cassette tape interface for ease of program storage is also shown.

Basic Operation

The new MC6808 (microprocessor with clock) is used as the microprocessor and is coupled with the MC6846P3 (ROM, I/O and timer) for a permanent monitor system. The MC6846P3 (TVBUG) has been programmed to "talk" to the MC6847 VDG display RAM as an output port, and a standard ASCII keyboard is connected to the MC6821 for data input. The actual hookup of the MPU is standard to almost any dedicated system with a few exceptions. The MCM2114s cannot have the R/\bar{W} pulse applied to them during the normal MC680X cycle, as any data on the bus will be written to the RAM. To solve this problem, the combination of $\phi 2$ with R/\bar{W} will provide a delayed R/\bar{W} pulse to be within the MCM2114 specifications.

All address decoding for 8K bytes of RAM has been done on board by use of the 74LS138 three-to-eight line decoder. With the decoding scheme shown, you can place up to 8K bytes of user RAM on the bus without further decoding, and decoding for every 1K block of memory from \$D000 to \$FFFF has also been provided. This latter decoding will provide you with an option of including up to an additional 5K bytes of display RAM to utilize the full 256 x 192 element graphic mode of the MC6847.

One note of caution though: No additional decoding (i.e.,

74LS138s) can be supported by the higher-order address bus lines without using the traditional bus extenders. An alternative to this problem is to perform a different decode with the present 138s and use MCM-6641's (4K x 1) RAM chips. This would mean that additional RAM could be added, but only in 4K blocks. MCM2114s were used in this project because of their ability to be added in 1K block increments, thereby reducing the initial cost of the project.

The Break key on the board, through the use of cross-coupled NAND gates, provides an NMI (non-maskable interrupt) input with a debounced key closure. This switch will cause the current contents of the registers within the MPU to be displayed on the TV screen.

The RESET is a normally open switch that does not need to be debounced due to the RC time constant of the 3.3k Ohms and 100 uF capacitor and the Schmitt trigger input on the MC6808.

The MC6821 PIA is configured to receive key closures from a standard ASCII keyboard. The negative-going strobe must be at least 100 ms due to the type of polling used to scan for a keyboard input. Perhaps a more conventional way to poll the keyboard would have been through the use of the PIA's IRQ line; but by dedicating the IRQ vector to a keyboard input routine, the capability of using this line for a user function would have been lost.

Although the ACIA in this system is dedicated to a KC

Standard tape interface unit, you can switch the inputs and outputs to provide a different use for the serial I/O port.

In the transmit mode, the clock for the ACIA, and tone for the KC Standard, is provided by an MC1455. This 4800 Hz is fed into the transmit circuitry and, when combined with the TX (transmit) data, provides the traditional 2400 Hz for a Mark (1) and 1200 Hz for Space (0) required by the KC Standard. This output data is not the S1-S9 data format used by some other systems, but is a binary format that is compatible with the many Motorola MEK6800D2 kits now in use. The speaker audio is brought onto the board and fed into the input of an MC14584. This hex Schmitt trigger provides approximately 0.5 volts of hysteresis when operated at 5 volts, and it does an excellent job of squaring up the incoming audio tones.

Following this squaring of the tones, the data is processed and fed into the RX (receive) data pin of the ACIA. Connected to this is a leading edge detector which is used to reset the binary counter that feeds the RX clock signal. By doing the clock recovery in this manner, the binary counter is assured to be in synchronization with the data and to provide the proper clock pulse to the ACIA at the correct time.

The cassette interface provided in this documentation has proven to be an effective and reliable method for generating and recovering data from audio tapes, while using only six CMOS packages.

The VDG and Associated Circuitry

The MC6847 VDG operates like a microprocessor. It accesses its own RAM by putting out the specific addresses on the bus. Because of this, the VDG address bus must be separate from the MPU's address bus, but both must have the ability to address the common display RAM. By using the 8T97 Tri-state buffers on the address lines—wherever the "A" signal goes low, signifying that the MPU is talking to the display

RAM—the VDG is turned off. In addition, the bidirectional data-bus buffers must have the same type of control. The other inverters and NAND gates (U19-A, B and U16-A, B, C) provide the display MCM2114s with the correct R/W signal. The VDG directly generates the chrominance and luminance analog (R-Y, B-Y, Y) output levels to be fed to the MC1372 rf modulator.

The new MC1372 modulator contains a chroma subcarrier oscillator (3.579 MHz to be used as a system clock) and all other circuitry necessary to support direct rf modulation to any standard color-television set. As shown in Fig. 1, the MC1372 clock is buffered and fed directly to the MC6847 and MC6808 EXTAL inputs where it is used as a system clock. This provides an internal system clock of approximately 895 kHz (02).

The Tank L-C values shown (56 pF and .1 uH) will provide a center frequency of 67.25 MHz (channel 4). The component values required for channel 3 operation are 75 pF and .1 uH. This provides a center frequency of 63 MHz. The 75 Ohm output may be fed directly to the set or through a 75 to 300 Ohm matching transformer available wherever televisions or electronic components are sold. Either method *must* include a 60 db switch to minimize rf radiation problems (TVI). This assures that the antenna is disconnected while you use TVBUG.

Construction Hints

Several devices in Fig. 1 require adjustment; these include L1, R10, C4 and R6. The following is a tune-up procedure for these.

The value of L1 determines the frequency of operation—in other words, which channel you are on. This coil can be bought as a .1 uH tuneable coil or fabricated on almost any type of coil form that uses a ferrite slug for tuning. The prototypes were made on forms 1/8 inch in diameter with 3 1/2 turns of #30 gauge wire-wrap.

After you have placed the coil in the circuit, turn the television on to the desired channel (3 or 4) and turn the slug until a

picture is presented on the screen. If confetti appears on the set, the coil could possibly be resonating at the wrong frequency. Change the channels until you see a clear picture. Turning the slug down into the coil lowers the frequency (and channel), and unscrewing it produces the opposite effect. If the picture is on an undesired channel, lower the frequency by adding one or two more turns.

The duty cycle adjustment varies the actual duty cycle of the 3.58 MHz clock. This is an optional part, since the MC1372 is internally set for a 50 percent duty cycle. Adjustment should be made while observing a picture and tuning the pot until you find the best picture.

Y1's frequency adjustment trimmer, C4, should be set for 3.57954 MHz with a frequency counter or adjusted until the television set responds with

Integrated Circuits: LSI, MSI, SSI				
Qty	Part#	Function	Manufacturer	Designation
1	MC6847P	VDG	Motorola	U3
1	MC6808P	MPU		U1
1	MC6821P	PIA		U2
1	MC6846P3	TV BUG-RI/OT		U4
1	MC6850P	ACIA		U15
6	MCM2114	RAM		U9-U14
1	MC1372P	RF Modulator		U20
2	MC6887P	8T97		U5,U6
2	MC6889P	8T28		U7,U8
3	MC74LS138P	3 to 8 Decoder		U28,U29,U30
3	MC74LS00P	QUAD NAND		U17,U18,U19
1	MC74LS04P	Hex Inverter		U16
1	MC1455P	Oscillator		U27
Integrated Circuits: CMOS				
2	MC14013BP	Dual D F-F	Motorola	U25,U26
1	MC14040BP	12 Bit Counter		U24
1	MC14584BP	Hex Schmitt Inv.		U22
1	MC14070BP	EXOR		U21
1	MC14001BP	NOR		U23
Resistors (1/4 W, ± 5% composition):				
Qty	Value: (Ω)	Designation		
1	33k	R27		
1	13k	R11		
4	240	R1,R2,R3,R28		
2	5.6k	R7,R14		
1	75	R4		
1	22k	R9		
1	370	R15		
1	750	R5		
2	10k	R8,R13		
1	2k	R19,R26		
1	20k	R12		
6	3.3k	R18,R21,R22, R20,R23,R24		
1	1k	R17		
1	100k	R16		
1	510	R25		
Adjustable Resistors (1 turn, carbon film, 110%)				
1	10k	R6		
1	5k	R10		
Capacitors (In microfarads, 25 WV dc ± 10%, ceramic):				
Qty	Value	Designation		
12	0.01	C1,C2,C12,C13,C14,C15, C16,C17,C18,C19,C20,C25		
2	100 (electrolytic) 16 V	C15,C21		
1	50 pF	C5		
5	0.1	C6,C8,C11,C22,C23		
2	.001	C7,C24		
1	.002	C14		
1	2700 pF	C10		
1	1500 pF	C13		
1	56 pF	C3		
1	.02	C9		
Misc. Components				
Qty	Component	Designation		
1	Variable Capacitor 9 to 35 pF	C4		
1	Crystal 3.57954 MHz	Y1		
1	Transistor 2N2222	Q1		
1	Keyboard-Cherry B70-05AB			
2	Switch Momentary B8600	S1,S2		
1	Switch, DPDT, 60 dB separation @ rf	S3		
1	Transformer, 75 to 300	T1		
2	Diodes, 1N 914	D1,D2		
Parts list.				

the correct colors.

The audio cassette standard has an adjustment, R10, which should be tuned for best data at pin 2 of the ACIA. This adjusts a time constant, and you will notice some chopping of the waveform until this adjustment has been made.

Care should be taken in parts placement, as there are several areas where there are low-level analog signals present. Fast digital signals do a good job of interfering with these, so keep as much space as possible between them. Also be sure to adequately bypass as shown in Fig. 1.

This minimum configuration provides a software and low-density (64 x 32 element) color-graphics development system. By expanding this system with a minimum number of components and enough support RAM (both display and user RAM), you can implement a full color-graphics system for any type of home computer, game or low-cost color-graphics system.

Firmware

The MC6846P3's ROM has been programmed with TVBUG—a system monitor that uses the MC6847 Video Display Generator as an output device into a standard color-TV set. The total package as shown in Fig. 1 provides you with a complete debug/operating system, input interface to a standard parallel ASCII keyboard and a KC Standard audio-cassette interface. The memory map of the TVBUG ROM and recommended RAM follows:

\$FFFF	TVBUG ROM
\$F800	6846 I/O
\$F3FF	STACK AREA (2K FREE)
\$F000	FREE
\$E400	6K DISPLAY RAM
\$CFFF	USER RAM AREA
	53K

\$2000

PROVIDED
DECODING

8K

\$0000

As you can see in the memory map, there is ample "free" space to execute even large user programs. Since the area from \$E800 to \$EFFF is also free, it can be used to put additional programs, such as disk operating system boots or standard graphics display packages, in EPROMs.

Operation of TVBUG

The following paragraphs delineate the use of, and some important features of, TVBUG.


Upon providing the system with 5 volts, the system executes a POWER-ON RESET, which initializes the entire system and prints the TV Bug-Debug system message at the top of the television screen. The cursor flashes through all of the eight available colors providing a blinking effect on the

screen. The RESET button should be depressed anytime the program "blows away" or you wish to regain program control without displaying the internal CPU registers.

The Break key is really a debounced switch that is connected to the NMI pin on the MC6808. Depressing this key will display the current contents of the registers in the CPU:

CC	B	A	X	P	S
XX	XX	XX	XXXX	XXXX	XXXX

Fig. 1. MicroChroma 68 (TVBUG 1.2).



data. A line feed will return data to memory and open the next location. To return to TVBUG, press the return key.

Memory Examine Function—

This function allows you to display a block of memory on the screen. To use this function:

1. Type E.
2. TVBUG will respond by asking for the beginning address.
3. Type the beginning address and a space, and TVBUG will respond by asking for an ending address.
4. Type the ending address and a space.
5. TVBUG will print the beginning address and contents of the first eight memory locations. Underneath the contents of each location is a period; if the data at that location is an ASCII character, it will replace the period. Each time a space is entered, the next eight locations will be printed until it reaches the ending address, at which time TVBUG will regain control.

Quick Load Function—This function allows you to enter blocks of hex data using the Memory Examine Function. To use this function:

1. Type Q. TVBUG will ask for a beginning address.
2. Type the beginning address and a space. TVBUG will ask for an ending address.
3. Type the ending address and a return. TVBUG will print the beginning address and wait for data.
4. Type the 8-bit hex data and follow with a space. The space will write the previously entered data into memory and open the next location. Following the eighth space, TVBUG will go to the next line and print the address of the ninth location and wait for data. When the ending address has been entered, TVBUG will regain program control.

Memory Fill Function—This function allows you to fill a blocked memory with any specified hexadecimal character. To use this function:

1. Type F. TVBUG will ask for a beginning address.
2. Type the beginning address and a space. TVBUG will ask for

L—Load KC Tape
P—Punch KC Tape
V—Verify KC Tape with Existing Memory
M—Memory Change
E—Examine Block of Memory
Q—Quick Load of Hex Data
F—Fill Memory Block
O—Calculate Offset
R—Display Contents of Target Stack
Z—Clear Screen
S—Set a Breakpoint with Address "N"
U—Unset a Breakpoint with Address "N"
D—Delete all Breakpoints
B—Display all Breakpoints
N—Next Instructions
C—Continue Execution from Current Location
T—Trace "N" Instructions
!—User Defined Function #1
"—User Defined Function #2
#—User Defined Function #3

TVBUG commands.

an ending address.

3. Type the ending address and a space. TVBUG will ask for a character.
4. Type the character and a space. TVBUG will write the character into each of the defined memory addresses, then return to TVBUG.

Offset Calculation Function

—This function allows you to calculate up to 16-bit offsets. Offsets outside two's complement limits will be printed followed by the message TOO FAR. This applies only to branch instructions. For calculations of KC tapes, add two to the resultant, which includes the beginning and ending address in a branch instruction. To use this function:

1. Type O. TVBUG will ask for the beginning address.
2. Type the beginning address and a space. TVBUG will ask for the ending address.
3. Type the ending address and a return. TVBUG will print the offset and return to program control. Negative offsets will be printed as a 16-bit word. The least significant eight bits will be the offset.

Print Contents of Stack—This function allows you to examine the MPU registers by reading them from the stack. To use the function:

1. Type R.
2. TVBUG will place the contents of the MPU register onto the stack RAM and then place them on the screen.

3. The display will be:

```
CC B A X P S
XX XX XX XXXX XXXX XXXX
```

Clear Screen Function—To use this function:

1. Type Z.
2. TVBUG will clear the screen and return to the top left-hand corner with the TVBUG response.

Seven of the eighteen commands of TVBUG deal specifically with the uses of breakpoints. They are as follows:

Set a Breakpoint with an Address—To use this function:

1. Type S followed by the address and a return.
2. TVBUG will print the breakpoint address along with up to eight other breakpoints, then return to TVBUG. Breakpoints must be set in order, as the monitor will not rearrange them.

Unset a Breakpoint with an Address—To use this function:

1. Type U followed by the address.
2. Firmware will remove the breakpoint and return to TVBUG.

Remove All Breakpoints—To use this function:

1. Type D and return.
2. TVBUG will remove all breakpoints and return to TVBUG program control.

Print Out All Breakpoints—To use this function:

1. Type B.
2. Firmware will print out all breakpoints and return to TVBUG.

Next Instruction—This command allows you to single-step through a series of instructions. To use this function:

1. Type N.
2. TVBUG will execute the next instruction and print the contents of the stack.

Continue—The Continue command is used to stop the program from breakpoint to breakpoint. To use this function:

1. Type C.
2. Firmware will execute program from current location to the next breakpoint and print out contents of stack.

Trace "N" Instructions—This command works exactly like Next Instruction, except after entering T:

1. Enter the number of instructions to be traced and a return.
2. TVBUG will print out the contents of the target stack after each instruction, then return to program control.

User Function !, " and #—These functions are used for one key call-up of specific routines. To use these functions:

1. For user number one function, enter the starting locations, first high then low byte, of the routine into memory locations \$F397 and \$F398.
2. For number two function, use locations \$F39A and \$F39B.
3. For number three function, use locations \$F39D and \$F39E.

By doing this, the call-up of specific programs can be accomplished by merely pressing one key.

Some Other Functions of Interest

SWI, IRQ, NMI—The same way the user 1, 2 and 3 functions are utilized, the SWI, IRQ and NMI vectors can be utilized. By supplying addresses in the following locations, programs can be executed by vectoring to any of the interrupt pointers:

1. IRQ—\$F37A, \$F37B
2. SWI—\$F384, \$F385
3. NMI—\$F380, \$F381

Note: All of the user functions must be loaded with the appropriate data following RESET. A RESET condition will re-

initialize this area in the stack.

User Functions Input and Output—The purpose of these functions will allow additional input and output ports attached to a TVBUG system for a hard copy or additional CRTs.

Input Routine. Each time the input routine goes around in a loop looking for an input from the keyboard, a subroutine located at locations \$F390, \$F391 and \$F392 is called. Since these all contain 39s (return from subroutines), the program will jump back out and continue looking for a keyboard input.

Suppose you have an external RS-232 device that is to be connected as an input. After performing the necessary hardware additions, you must change the software to allow this to happen. Placing 7E, XX,XX (where XX,XX is the location of the input subroutine) into locations \$F390, \$F391 and \$F392, respectively, allows the input loop to look at the alternate input routine.

There are several constraints in using this. Be sure to load the subroutine program before loading in the jump vectors, since the keyboard routine will go to this location. If nothing is there, the whole program will be destroyed. Place the vectors and JSR in the order \$F392, \$F391, \$F390, because after the 39 in location 90 is replaced with a 7E, the program will au-

tomatically start executing. Be sure to end your subroutine with an RTS (39) and don't trap the routine; otherwise you can't use the keyboard until you have had an input from the peripheral and it falls back through the loop. By the way, put the input character in the A accumulator. For further understanding of the routine, look at the flowchart in Fig. 2.

Output Routine. The user routine is convenient for interfacing a hard-copy printer or extra peripheral. The jump vectors work the same and should be handled accordingly. These reside at \$F393, \$F394 and \$F395, where \$F393 is the instruction

(7E) and \$F394 and \$F395 are the high and low byte, respectively, of the subroutine address. Once again, end the routine with an RTS, and if interfacing to a printer, be sure to put in enough nulls for a CR, as TVBUG will output no nulls. See Fig. 3 for the flowchart.

Conclusion

Well, there you have it. Up until now, to own a computer you had to have lots of money, a Teletype/terminal or another TV set in the house to use as a monitor. This kit guarantees to have no blinking lights, multitudes of switches or any complicated methods of usage. A




Fig. 2. Flowchart for User Input Function.




Fig. 3. Flowchart for User Output Function.

single 5 volt supply and your TV set is all you need. Maybe this should be part of the TVBUG challenge! Can you pull your family away from the tube to play with TVBUG? Of course, TVBUG works fine with that extra black and white set, but the colors are weak! Plug it in, turn it on and watch TVBUG come alive in color before your eyes.

It's easy to build, whether wire-wrapped or with the printed circuit board. The kit is called MicroChroma 68 or SCPRMO2 and is available from any Motorola distributor. Oh, by the way, the price for the board and LSI devices is around \$129.

Other applications of TVBUG include bus expansion, printer drivers, adaptation of common BASICs for TVBUG (SWTP, Tiny BASIC, MITS, Microsoft), easy expansion of TVBUG and even a version of a Morse code receiver/transmitter terminal for ham operators. How many more can you think of? ■

RAID...gets the bugs out!

Southern Systems of Birmingham's Real-time Assembler Interactive Debugger is the most sophisticated program development tool available for 8080 assembler programmers. Proven through use in over two years of commercial program development, RAID provides a powerful arsenal of over 70 unique commands.

In addition to the usual debug capabilities of examining or altering memory and registers, setting breakpoints, and tracing program execution, RAID allows the user to select octal, decimal, hexadecimal, ASCII-character, ASCII-string, symbolic, or instruction-mnemonic format for all RAID input and output. Simulation mode of program execution virtually eliminates the possibility of lethal system crashes.

RAID is available on 8" floppy disk for CP/M¹, ISIS-II², or ISIS-II² operating systems.

Manual only \$15.00
Manual and 8" diskette \$99.95

Order now or write for more information.

SOUTHERN SYSTEMS of Birmingham
Post Office Box 3373A
Birmingham, Alabama 35205

✓ S87

1 Trademark of Digital Research 2 Trademark of Intel Corp

TRS-80 LEVEL II AND DOS

GENERAL SUBROUTINE FACILITIES 'GSF'

Collection of fast easy-to-use machine language routines.
IN-MEMORY SORT with multiple variables and keys.
ARRAY read/write to tape, compress/uncompress/move data.
SCREEN scrolling, save screen displays, and more.

DISK SORT PROGRAM 'DSP'

SORT/MERGE multi-diskette files. Fast and easy to use.
MULTIPLE variables and keys. User input/output sort exists.
Includes GSF machine language in-memory sort, etc. 32 or 48K.

RENUMBER WITH 'REMOOEL' - MERGE WITH 'PROLOAO'

Renumber any section or an entire program.
Move program segments. DELETE program lines.
All line references readjusted as required.
COMBINE programs with renumber and merge.

LOAD OR SAVE any portion of program from tape.

COPY SYSTEM TAPES WITH 'COPYSYS'

COPY and VERIFY machine language object tapes.
MERGE object tapes to form single load module.

Dealer Inquiries Invited

REMOOEL	Order TS21	at \$24.95
REMOOEL + PROLOAO	Order TS22	at \$34.95
GENERAL SUBROUTINE FACILITIES	Order TS25	at \$24.95
DISK SORT PROGRAM	Order TS26	at \$34.95
Must specify 16, 32 or 48K on above.	Order TS24	at \$14.95
COPYSYS (Not DOS)	Order 10 ea	at \$14.95
For TAPES that TEST best		

User Manuals \$3.00 refundable on program purchase.

RACET COMPUTES R24
702 Palmdale, Orange CA 92665
Check, VISA, M/C, C.O.D.
Calif. residents add 6%
(714) 637-5016

Scotch[®] Diskettes

Order Direct:

2 for \$11.75
5 for \$26.45
10 for \$49.75 (Hard Box)

Price Includes Shipping

(Hawaii, Alaska & Canada add \$1.00 shipping)
VISA, Master Charge, Check, Money Order

740-0 - 8" Soft Sector
740-32 - 8" Hard (32) Sector
744-0 - 5" Soft Sector
744-10 - 5" Hard (10) Sector
744-16 - 5" Hard (16) Sector

Mass. residents add 5% sales tax.

cpu COMPUTER PACKAGES UNLIMITED

99 Reservoir St. Holden, MA 01520
(617) 829-2570 Div. of SCB Inc.

Creative Tabulation

This programming technique allows you to create right-justified columns (certainly a convenient feature to have) and also gives your computer the capabilities of a larger system.

```
0010 REM *****
0020 REM *      PROGRAM 1      *
0030 REM * CREATIVE TABULATION *
0040 REM *
0050 REM * MARC I. LEAVEY, M.D. *
0060 REM *****
0070 DIGITS= 2:LINE=0
0100 PRINT TAB(5);"A";TAB(25);"B";TAB(45);"C";TAB(65);"D"
0110 PRINT
0120 READ N
0130 IF N=0 GOTO 9999
0140 REM
0150 REM FIRST PRINT IT PLAIN
0160 REM
0170 PRINT TAB(2);N;
0180 REM
0190 REM NOW RIGHT JUSTIFY
0200 REM
0210 PRINT TAB(30-LEN(STR$(N)));N;
0220 REM
0230 REM ADD A COLUMNED DOLLAR
0240 REM
0250 PRINT TAB(40);"$";
0260 PRINT TAB(50-LEN(STR$(N)));N;
0270 REM
0280 REM OR A TIGHT ONE...
0290 REM
0300 PRINT TAB(70-LEN(STR$(N)));"$";N
0310 GOTO 120
0320 REM
0330 REM DATA STATEMENTS WITH
0340 REM THE NUMEERS TO PRINT
0350 REM
0360 DATA 10,12,3,2,.8,200.54,56.1
0370 DATA 5,32,5673,99.3,0
0400 REM
9999 END
```

Program 1.

The utility of BASIC as a programming language these days is beyond question. Many programs being written involve money or other similar columned data. Unfortunately, most BASICs have only a TAB command to format columns of figures. This results in columns with the left margin justified

and the right margin ragged (see Fig. 1a). A PRINT USING command, found in some interpreters, can be used to put the numbers where you want them and even to append dollar signs, but this is not available in most small-system BASICs.

By a creative use of the TAB command, coupled with the

```
0010 REM *****
0020 REM * PROGRAM 2 -- MAKE AN *
0030 REM * ACCOUNTING TYPE LIST *
0040 REM *
0050 REM * MARC I. LEAVEY, M.D. *
0060 REM *****
0070 DIGITS= 2:LINE=0
0080 PRINT TAB(10);"LIST"
0090 PRINT TAB(10);"----";PRINT
0100 READ N
0110 IF N=0 GOTO 999
0120 PRINT TAB(7);"$";
0140 LET N1=ABS(N)
0150 PRINT TAB(14-LEN(STR$(N1)));N1;
0160 IF N<0 THEN PRINT "-";
0170 PRINT
0180 GOTO 100
0200 DATA 1,22,43.5,-55.1,899.77,-.99,23.4,-33,-.1,0
0999 END
```

Program 2.

READY #RUN	A	B	C	D
10.00		10.00	\$ 10.00	\$10.00
12.30		12.30	\$ 12.30	\$12.30
2.00		2.00	\$ 2.00	\$2.00
0.80		0.80	\$ 0.80	\$0.80
200.54		200.54	\$ 200.54	\$200.54
56.10		56.10	\$ 56.10	\$56.10
5.00		5.00	\$ 5.00	\$5.00
32.56		32.56	\$ 32.56	\$32.56
99.30		99.30	\$ 99.30	\$99.30

READY
#

Fig. 1.

READY #RUN	LIST ----
	\$ 1.00
	\$ 22.00
	\$ 43.50
	\$ 55.10 -
	\$899.77
	\$ 0.99 -
	\$ 23.40
	\$ 33.00 -
	\$ 0.10 -

READY

Program 2 sample run.


```

0010 REM *****
0020 REM * PROGRAM 3 - SIMULATE *
0030 REM * THE "DIGITS" COMMAND *
0040 REM * OF SWTPC BASIC *
0050 REM *
0060 REM * MARC I. LEAVEY, M.D. *
0070 REM *****
0100 INPUT "NUMBER, PLEASE", A
0110 LET A1=-(INT(A)-A)
0120 LET A$=STR$(A1)
0130 IF A1<.01 THEN A$="0.00"
0140 IF LEN(A$)=4 GOTO 170
0150 IF LEN(A$)>4 THEN A$=LEFT$(A$,4)
0160 IF LEN(A$)<4 THEN A$=A$+"0"
0170 LET A$=RIGHT$(A$,3)
0180 LET A$=STR$(INT(A)+A$)
0190 PRINT "DIGITIZED VERSION = ";A$
0200 GOTO 100
0299 END

```

Program 3.

```

READY
#RUN
NUMBER, PLEASE? 1
DIGITIZED VERSION = 1.00
NUMBER, PLEASE? 2.3
DIGITIZED VERSION = 2.30
NUMBER, PLEASE? .34
DIGITIZED VERSION = 0.34
NUMBER, PLEASE? .01
DIGITIZED VERSION = 0.01
NUMBER, PLEASE? 678.992
DIGITIZED VERSION = 678.99
NUMBER, PLEASE? 10.228
DIGITIZED VERSION = 10.22
NUMBER, PLEASE? .005
DIGITIZED VERSION = 0.00
NUMBER, PLEASE?
READY

```

Program 3 sample run.

ability to determine the length of a string, a standard, right-justified display is easy. One condition is the use of the DIGITS command, as found in SWTPC BASIC, to truncate or fill the right of the decimal point to two places. I'll show a way to get around that later, but for now, bear with me.

How TAB Works

The TAB command operates

by referencing the column to a set left margin, the argument of the TAB command. Thus if you say, "TAB(20)," the first character to be printed is at the 20th print position. What we will do is reference the *last* position, having ensured that all data has two decimal places, and subtract back to find where to start.

Fig. 1b shows the result of this technique. See how nice

the columns look! By a little more manipulation, nicely columned dollar signs can be added, as in Fig. 1c, or "tight" dollar signs (Fig. 1d). A little more manipulation can produce trailing minus signs, as used in accounting (see Program 2 sample run).

Program 1 produced all of the columns in Fig. 1. The REM statements tell you which is which. Similarly, the account-

ing form in the Program 2 sample run was produced by Program 2.

The DIGITS Command

I did promise to show you how to fake the DIGITS command: Follow Program 3 for the steps. We first will extract the fractional part of the number by negating the subtraction of the integer from the number. This is converted into a string, and a series of string manipulations truncate or fill to two decimal places.


The product of these manipulations is concatenated to the original integer and converted to a string; the result is printed. To merge these two programs, substitute the "A\$" here for the "STR\$(N)" in the previous programs and perform the manipulations prior to tabbing.

This is a rather nice technique to apply to programs that produce data for others to use, and it gives your computer the capabilities of much larger systems. ■

THE PERFECT COMBINATION

\$139.00


VIDEO 100 MONITOR



The Video 100 is designed to meet your monitor needs for both personal and business use. It is compatible with a wide range of computer systems, and with a bandwidth of 12 MHz it is capable of displaying up to 80 characters per line on this 12" B/W CRT. The solid state circuitry assures a stable & sharp display. The front panel controls include power, contrast, horizontal and vertical holds. Adjustments for height, vertical linearity, and width control are located on a rear panel. All the above features for only \$139.00.

OE 1000 VIDEO TERMINAL

\$275.00



The OE 1000 Video Terminal provides you with a low cost means to communicate with your computer. The OE 1000 will display 16 lines of 64 characters on a monitor or modified TV. The terminal will generate and display the full 96 ASCII character set (upper and lower case) plus 32 special characters (Greek letters and math symbols). The terminal will also erase to end of line, erase to end of screen, scroll, and it has full X-Y cursor movement. Interfacing to your computer requires a full duplex, serial, RS232 or 20 mA loop I/O port at the rate of 110 or 300 baud. The OE 1000 sells for \$350 assembled or \$275 in kit form.

Master Charge, Visa, accepted. COD Extra. Add \$5 per unit, \$10 both units, shipping handling insurance.

The perfect low cost combination of the OE 1000 and Video 100 are available from

OTTO ELECTRONICS

PO BOX 3066, PRINCETON, NJ. 08540 or call (609) 448-9165

CIRCLE 185 ON READER SERVICE CARD






ANNOUNCES
THE

MINI-8100

AN S-100 BUS
ADAPTER/MOTHERBOARD
FOR THE TRS-80*

MINI-SIZE!

MINI-PRICE!



but **MAXI-PERFORMANCE!**

HUH Electronics' 8100 is the established leader in S-100/TRS-80 interfaces, running reliably since November 1978 and giving you the most features for your dollar. But some folks don't need all the 8100's versatility or want something more compact.

So we created the **MINI-8100**. The **MINI-8100** has the same proven reliable S-100 Bus interface circuitry as it's big brother coupled with a 4 slot shielded motherboard. It connects to the TRS-80 or to the expansion inter-

face and opens up the vast world of S-100 Bus products to the TRS-80 owner.

For those of you who already own an S-100 mainframe or motherboard, the **MINI-8100** may be purchased without the built-in motherboard, (**MINI-8100S**). Just plug it in and go!

The **MINI-8100** has the same high quality as all HUH Electronics products—easy assembly, fully socketed, solder mask and silk screen component legend, comprehensive manual and design excellence that speaks for itself.

PRICES

MINI-8100 KIT	- includes all parts and one S-100 connector	- \$115
MINI-8100 ASM	- assembled and tested, includes four S-100 connectors	- \$155
MINI-8100S KIT	- S-100 sized board, plugs into mainframe	- \$ 95
MINI-8100S ASM	- same as above, but assembled and tested	- \$125



1429 Maple St.
San Mateo, CA
94402
(415) 573-7359

ORDERING INFO: The **MINI-8100** is available from leading computer dealers or factory direct. Please include \$4 for shipping and handling. CA residents include 6% sales tax. We accept VISA or Mastercharge or we can ship COD.


USA DOMESTIC PRICES ONLY.

DEALER INQUIRIES INVITED

*TRS-80 is a Radio Shack® product.

The 8100 by HUH ELECTRONICS

**An S-100 Bus Adapter/Motherboard
for the TRS-80
plus a whole lot more!!!**



- S-100 BUS INTERFACE
- 6 SLOT MOTHERBOARD

The 8100 allows a Radio Shack TRS-80 computer to be interfaced to the popular S-100 Bus for memory expansion and extended I/O capabilities. For example, you can now easily add more memory, floppy disc systems, PROM boards, printer interfaces, multi-purpose I/O boards, AC device controllers, and a whole host of other varied peripherals.

The 8100 has its own built-in 6 slot motherboard which includes our unique card guide system which keeps the boards in their places.

The 8100 has support circuitry and sockets for eight 16K dynamic RAM chips allowing you to expand the memory of your TRS-80 by 16K without having to buy any S-100 RAM boards.



- SERIAL RS232/20ma I/O
- PARALLEL INPUT AND OUTPUT
- SPACE FOR 16K DYNAMIC RAM
- CAN USE LEFT OVER 4K CHIPS
- LOW COST—PRICES START AT \$185*
- AVAILABLE IMMEDIATELY

If you purchased an expansion memory kit for TRS-80 you could be left with eight 4K RAM chips and nowhere to put them! Well, they can go in the RAM sockets instead! That's right, you can use either 4K or 16K chips and address them anywhere you like.

The 8100 has a full RS232/20 ma serial interface who's features include: RS232 and 20 ma current loop interface, software programmable baud rate from DC to 56K baud, software programmable modem control lines, on board DB-25 connector and much more.

The 8100 also has an 8 bit parallel input port and an 8 bit parallel output port. Both are latched, have both positive and negative strobe inputs and outputs and have plenty of drive capability.

PRICES START AS LOW AS \$185* (S-100 BUS INTERFACE ONLY)



**1429 Maple St.
San Mateo, CA
94402
(415) 573-7359**

✓ H29

CALL OR WRITE FOR COMPLETE PRICING
INFORMATION AND MORE DETAILS

THE 8100 IS AVAILABLE FROM LEADING
COMPUTER DEALERS OR FACTORY DIRECT

DEALER INQUIRIES INVITED

*Extra S-100 connectors, RAM support,
I/O circuitry optional.
USA DOMESTIC PRICE ONLY.

A Handle on Programming

Allan has several handles on programming. This one grasps arrays and gamesmanship.

Although the TRS-80 Level II book is complete (factually speaking), it is not exactly the same gold mine of exposition that the Level I book is. Certain things are left to your intuition, and if you are like me, that spells problems with programming. The simple "game" in the program listing is offered as a programming playground to examine some of the puzzlements that may have allowed you to snatch programming defeat from the jaws of victory.

The "game" asks you to input a guess of a boy's name. If the name selected is contained within the memory bank of the program, you are awarded a correct guess; if not, you are awarded an incorrect guess. Scoring keeps track of right and wrong guesses and prints the running results on the screen. Scoring also limits the total number of tries to 10, after which your final score of right and wrong answers is flashed on the screen. Sure, it is not Star Trek or Wumpus, but it has been effective in grabbing the attention of the young visitors to my house. It is one answer to "What can your computer do?"

The main interest here is just how some of the routines work and how to implement them into a program without the annoyance of getting rid of a series of error messages during the programming process. One of the nice things about a computer program is that it is not a gigantic monolith. The biggest program is merely the sum of many small steps and routines. What this really means is that either you commit many of the

"standard" routines to memory or, better still, inscribe them in what I choose to call a style-book.

The Program

From the simple game description, it is obvious that a part of this program has to create a memory bank of boys' names. Then you have to program a way to input your guess. When this is done, the program must provide for a mechanism to search its memory for a match or lack of match of the input guess. Then it has to indicate the condition it found and implement the scoring.

We can create the memory bank by using an array, but since we are dealing with names to be stored and not numbers, we must amplify that to the use of a string array. Refer to the program listing . . . you will find that lines 1 through 22 are used

for the creation of the memory bank. You can check this out by temporarily inserting a line 25 END.

If you then input Print A\$(4) (in the calculator mode), for example, it would print out the fourth data item, namely Ted. Notice that A\$ has been dimensioned at 20. The data lines carry a total of 18 items, so that A\$ has to be dimensioned at least as high as 18 but can be set a bit higher to allow for some expansion of the data file.

If the maximum value for J in line 7 is set less than the total data items, you will have an incomplete data set in the data file. If it is set higher than the total data items, then your program will deliver an OD error message, indicating that an out of data condition has been programmed.

Line 100 provides the screen

message and allows the name guess to be input. The next four lines (310 to 380) provide the search through the data file. You should notice that in line 325 if the maximum value assigned to I does not equal the data element total, then the entire array will not be searched, resulting in lost data. If I is made larger than the total number of data elements, then the search will merely be running through blank spaces, which is a waste of motion.

Notice the position of the DIM statement in the program. It is not included accidentally in any of the loops. The good book usually says, "Put the DIM statement early in the program," but if you don't put it in properly, you will get the delightful DD error message, with the resultant hunt for the DEBUG.

The Restore statement is needed because in a program of this type you can't throw away entries in the array. Without the restore statement, you would be served up another OD error message with resultant problems.

There is an interesting way of losing a piece of data when typing in the data lines. Suppose in line 20 you accidentally or unwittingly typed a comma after the last name on the line. The computer would interpret this as, "There is a piece of data after Wayne, but since the operator didn't type in any letters I will fill that array cell with nothing." And that is exactly what it would do. You would wind up with one more piece of data in the data file than you

```

1 DIM A$(20)
2 CLS
3 RESTORE
4 FOR J = 1 TO 18
5 READ A$(J)
6 NEXT J
7 DATA TOM, JERRY, BILL, TED, FRANK, JACK, ARNOLD, DAN, WAYNE
8 DATA HARRY, CARL, TED, JIM, MARK, RAYMOND, CLARK, PHILLIP, IRA
9 INPUT "GUESS A BOY'S NAME "; B$
10 I = 0
11 I = I + 1
12 IF I > 18 PRINT "NAME NOT ON LIST" : GOTO 420
13 IF A$(I) = B$ GOTO 410
14 GOTO 320
15 PRINT "NAME IS ON THE LIST"
16 N = N + 1: PRINT @ 198, "CORRECT GUESS #" N: GOTO 438
17 D = D + 1
18 PRINT @ 326, "WRONG GUESS #" D
19 PRINT @ 837, "TOTAL GUESSES" N + D
20 IF N + D = 10 PRINT "YOUR GUESS IS " N "RIGHT" D "WRONG": END
21 FOR T = 1 TO 1000: NEXT T
22 GOTO 2

```

Program listing.

thought you had. In this program the search is through 18 array cells and you have filled 19 array cells, which means that the last name shown in the data file (in this case, Ira) could not be reached.

You know that you put this name in the data file, yet if you input this name the program would count you as having made an incorrect guess. This is a charming little item that you do not want to leave to your intuition. As the man says, "It's fun to be fooled, but it's more fun to know," and that goes triple when you are programming a computer.

The scoring portion of the program should be easy to follow. The general scheme comes in handy in any program that has to keep score on the screen. Lines 415, 430 and 438 show one good method of making everything come out properly on the screen. Just pay close attention to the use of the quote signs and everything will fall into place. Line 440 is merely a timing loop to hold the scoring in-

formation and titling information on the screen long enough for you to visually digest.

You may be wondering why line 310 $I=0$ is needed. This line, in conjunction with $I=I+1$, is part of the search mechanism. If I were not set back to 0 after each guess, the value of the counter I would continue to be incremented from the value it had assumed from the last pass through the program. You can demonstrate this for yourself by deleting line 310 and adding a temporary line 322 PRINT I. Then run two consecutive guesses through the program, and the screen printout will make very clear that you need line 310 to initialize the value of the counter.

You have undoubtedly come across the phrase "BASIC is an easy language," and the statement is probably true compared to, say, APL. But I prefer the original quote from Murphy himself, who said, "Where programmers work, there I lurk!" And you had just better believe he was basically on the level! ■



the ULTIMATE in CHEAP VIDEO

BOOK & KIT
ONLY \$42.95

Don Lancaster's "Cheap Video" concept allows almost unlimited options, including:

- * Scrolling - Full performance cursor.
- * Line/Character formats of 16/32, 24/80, 32/64 or almost anything.
- * Graphics - up to 256 X 256 B&W; 96 X 128 COLOR (requires low-cost option modules)
- * Works with 6502, 6800 and other micros.

SPECIAL OFFER: Buy the Kit (upper case alphanumeric option included) & get the Book at 1/2 price.

✓ P9 **PAIA** ELECTRONICS, DEPT. K, 1020 W. WILSHIRE BLVD., OKLAHOMA CITY, OK 73116

I'm Sold, PLEASE RUSH..... () SEND FREE CATALOG

() TVT-658 Kit & Cheap Video Cookbook - \$42.95

() TVT-658 Kit only (book required for assembly) - \$39.95

name: _____

address: _____

city: _____ state: _____ zip: _____


PAIA ELECTRONICS, DEPT. 6K, 1020 W. WILSHIRE BLVD., OKLAHOMA CITY, OK 73116

It's in the bag.

What is?

The biggest and best selection of microcomputer software anywhere. And the list grows bigger every day. CP/M configured for the most popular 8080/Z-80 microcomputer systems and other terrific software, now available. Call or write for our latest literature.

Lifeboat Associates, Suite 505, 2248 Broadway
New York, N.Y. 10024/(212) 580-0082



22 START-AT-HOME COMPUTER BUSINESSES


In "The Datasearch Guide to Low Capital, Startup Computer Businesses"

CONSULTING • PROGRAMMING • SOFTWARE PACKAGES • COM • FREELANCE WRITING • SEMINARS • TAPE/DISC CLEANING • FIELD SERVICE • SYSTEMS HOUSES • LEASING • SUPPLIES • PUBLISHING • TIME BROKERS • HARDWARE DISTRIBUTORS • SALES AGENCIES • HEADHUNTING • TEMPORARY SERVICES • USED COMPUTERS • FINDER'S FEES • SCRAP COMPONENTS • COMPUTER PRODUCTS AND SERVICES FOR THE HOME.

Plus -- Loads of ideas on moonlighting, going full-time, image building, revenue building, bidding, contracts, marketing, professionalism, and more. No career planning tool like it. Order now. If not completely satisfied, return within 30 days for full immediate refund.

• 8½ x 11 ringbound • 156 pp. • \$20.00

Phone Orders **901-382-0172**



DATASEARCH ✓ D40
Incorporated

5694 Shelby Oaks Dr., Suite 105, Dept. A, Memphis, TN 38134

Rush _____ copies of "Low Capital Startup Computer Businesses" at \$20 per copy to me right away.

NAME/COMPANY _____

ADDRESS _____

CITY/STATE/ZIP _____

☐ Check Enclosed ☐ BankAmericard ☐ Master Charge

Keepbook

This NS BASIC bookkeeping program is manageable—and adaptable to other BASICs.

Robert L. Marx
1077 Ticonderoga Dr.
Sunnyvale CA 94087

Everyone knows by now that the home computer is ideal for simple bookkeeping systems. Every catalog tells us that we can easily program our computers to keep track of household expenses, or even use its capabilities for our

small-business needs. Somehow, in over three years as a computer owner, however, I had never gotten around to this application, even though I run a small business from my home and went through the monthly drudgery of "doing the books" with pencil, paper and a pocket calculator.

All that is changed now. After checking out several com-

mercially available accounting packages, I discovered that all of them were too expensive or tailored to the needs of a professional accountant rather than to my needs, or both. So finally I wrote my own system, which I call Keepbook. It meets my needs, and I use it every month not only for my business, but also to keep track of normal household expenses.

System Requirements

In building Keepbook, I first had to decide just what my needs were. This took a few weeks of thinking about and studying the problem. I decided that the following factors were most important.

First, the system had to be simple. I only use the program once a month, so I don't want to have to review a complicated set of rules and procedures every time. This requirement resulted in a HELP command within the program, extensive editing of all input data and clear diagnostic messages when a mistake is encountered.

Second, I decided that the system should be simple in concept. My accounting problems are not involved with return on investment or other sophisticated accounting principles. I just want to know if there is more money coming in than going out, how much more, and where the money is going.

This requirement led to a design that allows me to set up accounts and to post expenses and income to those accounts and have the computer keep track of current balances and year-to-date balances for each account. Of course, I wanted a general picture of how I am doing, so the program had to provide sums for total expenses and total income and the difference between them, both on a current basis and on a year-to-date basis.

Third, I wanted the system to be reasonably foolproof. In particular, I wanted some backup capability in case my floppy diskette got scratched, or the power failed while I was updat-

ITEM	AMOUNT	ACCT	DESCRIPTION	DATE	REMARKS
1					
2					
3					
4					
5					
6					
7					
8					
9					
10					
11					
12					
13					
14					
15					
16					
17					
18					
19					
20					
21					
22					
23					
24					
25					
26					
27					
28					
29					
30					
31					
32					
33					
34					
35					
36					
37					
38					
39					
40					
41					
42					
43					
44					
45					
46					
47					
48					
49					
50					

Fig. 1. Entry source document.

Summary Report for March 1979		
Account Number and Name	Current \$ Year-to-date	
1 Food expenses	\$401.55	\$1,233.67
2 Clothing expenses	\$81.00	\$473.50
3 Rent and house upkeep expenses	\$201.44	\$912.44
4 Transportation expenses	\$88.50	\$276.85
5 Recreation expenses	\$0.00	\$135.67
6 Entertainment expenses	\$11.75	\$97.80
7 Utilities expenses	\$40.96	\$127.23
8 Home furnishings expenses	\$0.00	\$77.99
9 Medical & Dental expenses	\$33.50	\$75.50
10 Insurance premiums	\$79.00	\$238.50
11 Savings	\$0.00	\$42.50
12 Employment Income	\$1,500.00	\$4,500.00
13 Dividend/Interest Income	\$23.60	\$68.38
14 Other Income	\$125.00	\$125.00
GROSS INCOME	\$1,648.60	\$4,693.38
TOTAL EXPENSES	\$937.70	\$3,691.65
NET INCOME	\$710.90	\$1,001.73
Current expenses from line items 22 to 32		

Fig. 2. Financial summary output.

ing the files.

This resulted in the choice of writing to disk files after every transaction, rather than holding data in RAM until the end of a data-entry session. It also convinced me to use a paper source document for data entry, so that in the worst of all possible cases I could at least recreate the files from paper. (It also allowed me to simplify the computer files and provide readable documentation for auditors, if necessary.)

Finally, I wanted the system to be flexible enough to serve several purposes. I wanted to have one set of files for my primary business, another for my home accounts and perhaps still others to track specific investments that I wanted to isolate for maximum financial visibility.

Output

The requirements analysis led directly to the only two outputs produced by Keepbook: the entry source document and the financial summary report.

The entry source document is shown in Fig. 1. It consists of individual line items pre-numbered by the computer. A line item is either an expense item or an income item (determined by the account number, which is described later).

For each line item, the user fills in the amount, the account number, a description of the item, the date and remarks (which I use to record check numbers). Each numbered line

item is filled in, mixing expense and income items in any order. As we shall see later, only the amount and the account number are entered into the computer, keeping the boring task of keying data to a minimum.

The financial summary output is shown in Fig. 2. For each account, the account number, account title, current balance and year-to-date balance are shown. At the end of the output, a total for expenses, total for incomes and net income are presented.

The line items used to make up the current balances are also shown, directly tying the summary back to the paper source document. The source

document, as we have already seen, provides a direct tieback to individual receipts, check stubs, etc., so the whole package hangs together.

Options

The program provides eight separate routines, which are displayed on the screen in a menu, as can be seen from the first block of instructions of the program listing, called the initialization block. The routines, or options, are:

1. Construct a new file
2. Start a new year
3. Start a new month
4. Add data
5. Print monthly summary
6. Help

7. Print source document
8. Quit the program

The user selects an option from this menu, and program control shifts to the appropriate routine. At the completion of the option, control returns to the initialization block of the program, and the menu is again presented.

Construct a new file. Option 1 sets up a new file. Before running this option the user should spend some time thinking about the output he/she wants. He/she is permitted to specify as many different accounts as desired. Accounts are numbered by the computer in the order entered and are printed in that order, so some forethought will result in a more attractive printout.

Each account is referred to by number and also by the user-specified name, which may be up to 40 characters long. Each account must also be specified by the user as an expense (E) or income (I) account, which is used by the program in the totaling calculations. All this is coached on the screen during input.

Although the user never has to worry about it, the file structure created during this option is interesting to study. Each account record is 62 bytes long, which includes the account ti-

Program listing.

```

100 REM SIMPLE BOOK KEEPER
200 REM INITIALIZATION
300 LINE#1,132;B9$=CHR$(26);REM BLANK SCREEN
400 DIM T$(40),F$(8),O$(1),T2$(50),L9$(62),L8$(62)
500 DO=0;D1=1;REM DEVICE NRS
600 PRINT#D0,"Options are:"
700 PRINT#D0,"1=Construct new file"
800 PRINT#D0,"2=Start new year      3=Start new month"
900 PRINT#D0,"4=Add expense entries  5=Print monthly summary"
1000 PRINT#D0,"6=H E L P             7=Print source sheet"
1100 PRINT#D0,"8=Quit"
1200 INPUT#D0,"OPTION = ",O
1300 IF O=INT(O) THEN 1400;PRINT"ERROR:MUST BE INTEGER";GOTO 600
1400 IF O>0 AND O<9 THEN 1500;PRINT#D0,"ERROR";GOTO 600
1500 ON O GOTO 1700,4000,5000,5700,7200,9900,11800,11500
1600 REM *****
1700 REM OPTION = CONSTRUCT FILE
1800 INPUT#D0,"How many accounts are there ",A1;A1=INT(A1)
1900 IF A1>0 THEN 2000;PRINT"Minimum 1";GOTO 1800
2000 INPUT#D0,"Name of your data file ",F$
2100 CREATE F$(A1+1)*62/256+1;REM SIZE FOR (A1+1) RECORDS,EACH 62 BYTES
2200 OPEN#0,F$
2300 FOR I=1 TO A1
2400 PRINT#D0,"Title for acct. nr. ",I;INPUT#D0,T$
2500 INPUT#D0,"Is this an expense(E) or income(I) acct.",O$
2600 IF O$="I" THEN S1=1 ELSE IF O$="E" THEN S1=-1 ELSE 2500
2700 WRITE#0;62*I,T$
2800 WRITE#0;62*I+42,I
2900 WRITE#0;62*I+47,S1
3000 WRITE#0;62*I+52,0
3100 WRITE#0;62*I+57,0
3200 NEXT
3300 WRITE#0;0,A1,1,1

```




```

3400 REM FILE STRUCTURE&NR ACCTS,HIGHEST ENTRY LINE,LOWEST E.L.
3500 REM TITLE/ACCTNR/EXPTYPE/CURRENT$/YTD$
3600 INPUT#D0,"File is built. Hit 'return' to continue",0$
3700 CLOSE#0
3800 PRINT#D0,B9$&GOTO 600
3900 REM *****
4000 REM OPTION=START NEW YEAR
4100 GOSUB 13300
4200 FOR I=1 TO A1&WRITE#0%62*I+52,0,0,NOENDMARK&NEXT
4300 WRITE#0%5,1,1
4400 PRINT#D0,"File is set for new year"
4500 PRINT#D0,"Be sure to start a new sequence of line items at one."
4600 CLOSE#0
4700 PRINT#D0,"File set for new year"
4800 INPUT#D0,"HIT 'RETURN'",0$&PRINT#D0,B9$&GOTO 600
4900 REM *****
5000 REM OPTION = NEW MONTH
5100 GOSUB 13300
5200 FOR I=1 TO A1&WRITE#0%62*I+52,0,NOENDMARK&NEXT
5300 WRITE#0%10,L1,NOENDMARK
5400 PRINT#D0,"File set for new month"&CLOSE#0
5500 INPUT#D0,"HIT 'RETURN'",0$&PRINT#D0,B9$&GOTO 600
5600 REM *****
5700 REM OPTION = ADD ENTRIES
5800 GOSUB 13300
5900 PRINT#D0,"Enter amount 0,account 0 to quit"
6000 PRINT#D0,"line ",L1," Amount$",&INPUT#D0,A&INPUT#D0," AcctNr",A2
6100 IF A2>0 THEN 6400
6200 PRINT#D0,"Data entry completed"
6300 INPUT#D0,"hit 'return',0$:PRINT#D0,B9$&CLOSE#0:GOTO 700
6400 IF A2=INT(A2) THEN 6500&PRINT"ERROR"&GOTO 6000
6500 IF A2>0 AND A2<A1+1 THEN 6700
6600 PRINT"Accounts in range 1 - ",A1&GOTO 6000
6700 READ#0%A2*62+47,S1,C1,Y1
6800 A=A+S1&C1=C1+A&Y1=Y1+A&WRITE#0%A2*62+52,C1,Y1,NOENDMARK
6900 L1=L1+1&WRITE#0%5,L1,NOENDMARK
7000 GOTO 6000
7100 REM *****
7200 REM OPTION=PRINT SUMMARY
7300 GOSUB 13300&I1=0&I2=0&E1=0&E2=0
7400 INPUT#D0,"Month and year for title ",T2$
7500 INPUT#D0,"Printer on, paper in, hit 'return'",0$&PRINT#D0,B9$
7600 PRINT#D1
7700 PRINT#D1,TAB(15),"Summary Report for ",T2$
7800 PRINT#D1,"Account Number and Name",TAB(50),"Current $",
7900 PRINT#D1,TAB(60),"Year-to-date"&PRINT#D1
8000 FOR I=1 TO A1
8100 READ#0%62*I,T$&READ#0%62*I+47,S1,C1,Y1
8200 IF S1=1 THEN 8300&E1=E1+C1&E2=E2+Y1&GOTO 8400
8300 I1=I1+C1&I2=I2+Y1
8400 PRINT#D1,%4I,I,
8500 PRINT#D1,TAB(5),T$,
8600 PRINT#D1,TAB(50),%C$10F2,ABS(C1),ABS(Y1)
8700 NEXT
8800 PRINT#D1,TAB(5),"GROSS INCOME",TAB(50),
8900 PRINT#D1,%C$10F2,ABS(I1),ABS(I2)
9000 PRINT#D1,TAB(5),"TOTAL EXPENSES",TAB(50),
9100 PRINT#D1,%C$10F2,ABS(E1),ABS(E2)
9200 PRINT#D1,TAB(5),"NET INCOME",TAB(50),
9300 PRINT#D1,%C$10F2,I1+E1,I2+E2
9400 IF L1<=L0 THEN 9600
9500 PRINT#D1,"Current expenses from line items ",L0," to ",L1-1
9600 INPUT#D0,"Please turn off printer and hit 'return'",0$
9700 PRINT#D0,B9$&CLOSE#0&GOTO 600
9800 REM *****
9900 REM OPTION = HELP
10000 PRINT#D0,"Bookkeep is a simple bookkeeping system"
10100 PRINT#D0,"based on the idea that you have line item"
10200 PRINT#D0,"expenses and incomes which fit into account"
10300 PRINT#D0,"categories. Current period (month) and year-"
10400 PRINT#D0,"to-date totals are maintained. When you construct"
10500 PRINT#D0,"a new file all accumulators are set to zero, as"
10600 PRINT#D0,"they are with the new-year option, whereas"
10700 PRINT#D0,"the new-month option only sets the current"
10800 PRINT#D0,"accumulators to zero. To assure that you are"
10900 PRINT#D0,"recording all expenses, the system coaches"
11000 PRINT#D0,"for line items, so use the option to print"
11100 PRINT#D0,"data collection sheets as needed."
11200 INPUT#D0,"Hit 'return' to continue",0$&PRINT#D0,B9$
11300 GOTO 600
11400 REM *****
11500 REM OPTION = END
11600 PRINT#D0,B9$&PRINT#D0,"GOODBYE"&END
11700 REM *****
11800 REM OPTION=PRINT SOURCE SHEET
11900 INPUT#D0,"Lowest sequence number desired ",L0
12000 L0=INT(L0)&IF L0>0 THEN 12200
12100 PRINT#D0,"Lowest number allowed is one"&GOTO 11900
12200 INPUT#D0,"Printer on, paper in, hit 'return'",0$
12300 PRINT #D1," ITEM AMOUNT ACCT DESCRIPTION
12400 PRINT #D1," DATE REMARKS"
12500 L9$=""&FOR I=1 TO 30&L9$=L9$+CHR$(95)&NEXT
12600 L8$=L9$(1,1)+""&L9$(1,8)+""&L9$(1,4)+""&I"
12700 L8$=L8$+L9$(1,30)+""&L9$(1,6)+""&L9$(1,10)
12800 FOR I=L0 TO L0+49
12900 PRINT#D1,%4I,I,L8$
13000 NEXT
13100 INPUT#D0"Turn printer off and hit 'return'",0$&PRINT#D0,B9$&GOTO600
13200 REM *****
13300 REM OPEN FILE ETC
13400 INPUT#D0,"Name of your data file ",F$
13500 OPEN#D0,F$
13600 READ#0%0,A1,L1,L0
13700 RETURN

```

tle (40 characters plus two bytes of overhead), five characters for a real-number representation of the current balance and a final five bytes for the year-to-date balance.

The account number is represented by the position in the file (i.e., the *i*th account is stored starting at 62 times *i* bytes into the file). Since the lowest account number is one, this leaves the first 62 bytes of the file available, and some of this room is used to store three real numbers, representing the number of account numbers specified by the user, the next line item number to be coached for data entry and the lowest line item number used in the current balance period.

Notice that the program is written in North Star BASIC, release 4, and uses the capabilities of that language to read and write to this file structure as a random file. It also uses the CREATE command to establish and size the file properly without operator intervention. If you must adapt the program to a different dialect of BASIC, you may have to rearrange the file structure.

You can make as many files using this option as you desire, one for each set of books you want to keep. Just be sure to give each file a different name so you don't accidentally update the wrong files.

Start a new year. Option 2 resets balances and pointers within the file. For each account, the current balance and the year-to-date balance are set to zero. The program also assumes that you will want to begin with a fresh source document for the coming year, so it sets the next line item number to one. Obviously, before you exercise this option you should be sure that you have recently produced a summary report, since the data will no longer be available on disk after this option.

Start a new month. Option 3 sets only the current balance figures to zero. It assumes that you will wish to continue following months with the same source document, so does not set the next line item number to

zero. Again, be sure you have already produced a summary report for the current period; if not, though, the current expenses will be properly reflected in the year-to-date figures anyway.

Add data. Option 4 provides the data-entry capability for the system. For each entry, you must key in the amount and account number when coached on the screen. To finish the process simply enter zero for the account number, and you will be returned to the option menu.

If you make a mistake in data entry, simply enter an offsetting entry (i.e., same account number and a negative number). By the way, you don't have to wor-

ry about negative numbers to distinguish expenses from income entries; all entries are positive numbers and are distinguished within the program by the account descriptions you provided when constructing the file initially.

Print monthly summary. Option 5 provides the printed monthly summary, as shown in Fig. 2. You are asked for the month, which shows up at the top of the printout. Other than that, operation proceeds without operator intervention, except for loading the paper when asked.

Help, Print source document and Quit the program. The last three options are direct and to

the point. Option 6 simply displays at the screen a few reminders about the program in case the user is having some trouble. Option 7 prints the source document shown in Fig. 1, starting with the line item number specified by the user. Option 8 merely provides an orderly way to get out of the program and back to BASIC, so he can play games or whatever.

Conclusion

Keepbook is a simple book-keeping system that meets my needs for both personal and business financial management. It is written in North Star BASIC, release 4, but can easily be adapted to earlier versions

of that dialect, and perhaps not so easily to other BASIC dialects.

In its present form the program assumes that you have both a printer and a video display. If you have only a printer, you need only change the device numbers in the initialization block of the program so that both devices (D0 and D1) have the same value. If, on the other hand, you have only a video device, this may not be the ideal program for you.

I hope some of the readers of *Microcomputing* try Keepbook. I would be especially interested in hearing from anyone who adapts the program to another version of BASIC. ■

FOR TRS-80™ OWNERS T-PAL

Programming Amateur's Letter THE "DO-IT-YOURSELF" SOFTWARE NEWSLETTER

Published Monthly, We'll Teach You
All The Latest Wrinkles — How To Get
The Most Out of Your Computer

Graphics • Games • Personal
Home • Business • Finance
And Much More!

\$24/year . . . or write for FREE Details

THE MAIL MART ✓ M88

Box 11102K San Francisco, CA 94101

AD-68A ANALOG-TO- DIGITAL CONVERTER



- 8 analog input channels
- Occupies one SWTPC 6800 I/O slot
- Quality components and PCB
- Complete documentation
- 90 day full warranty
- Assembled and tested

Available from your local dealer or
factory direct. Write for additional
information.



INNOVATIVE TECHNOLOGY

510 Oxford Park
Garland, Texas 75043
(214) 270-8393

PET PERIPHERALS (FOR OTHER IEEE 488 BUS COMPUTERS, TOO)

NEW — RS-232 INTERFACE: \$229

The TNW-2000 Bidirectional Serial Interface allows keyboard input as well as printer output. The unit provides selectable automatic PET/ASCII character conversion, "throttled" output, baud rate adjustable from 110 to 9600 bits per second. \$229 price includes power supply, cabinet, PET/IEEE cable, built-in female EIA connector, full documentation. (For software controllable RS-232 control lines, and multiple RS-232 devices, TNW offers the TNW488/232 Serial Interface. Price is \$335, includes power supply, cabinet, PET cable, full documentation.)

MODEM

The TNW488/103 Low Speed Modem is Bell 103 compatible, provides auto originate/answer/dial capabilities. 75 to 600 bits per second interfaces to phone system via DAA. Price of \$385 includes power supply, cabinet, cables to PET and DAA, full documentation and software.



(The Net Works is now)

TNW Corporation ✓ T56

Ask your dealer or contact —
ASTRONICS • (714) 278-5441
4805 Mercury Street • San Diego CA 92111

GIVE YOUR TRS-80 WHAT IT DESERVES

All tapes \$10.00 each, on cassette.
plus \$1.00 postage & handling.
Choose Level I or II.

A television station in Florida chose our *Bioforecast* program (catalog # CS-1) to use in a special news broadcast during the November 1978 statewide political elections. Many think ours is the best biorythm program ever written. And it loads and executes in less than 4K!

One customer is using our *Orbit* programs (catalog # CS-2) to help him in the weather satellite work he does for the Air Force.

Recreation centers, schools, businesses, doctors, and housewives are using our *Learn Our Program* (catalog # CS-7) keeps track of things loaned out to people. Its high utility, together with its many features and ease of use, have made it a best seller.

And speaking of best sellers.

Our *Turkey Buzzard* game (catalog # GT-4) has made an even bigger splash than we expected. It is a game that has everything: a detailed scenario, character animation, and a general arcade style. It's chocked full of dangers and comic pitfalls. No wonder there are those who say it may be the most successful work ever to combine a continually changing plot with all TRS-80 graphics capabilities. Already it is becoming a classic among classics.

All of the above programs will execute in less than 4K RAM! You can't get those programs from any other company. We invented them and only we own the rights to them. Sure you can buy one of those cheap "software library" deals, but most of the programs they feature can be found in books. Books you can check out from your public library for nothing.

So for something truly different for your computer, look to the creative software company.

Send SASE to receive the product list faster.

Computrex



✓ C86

PO Box 536 Inman SC 29349

Scotch® Diskettes

Order Direct:

2 for \$11.75
5 for \$26.45
10 for \$49.75 (Hard Box)

Price Includes Shipping

(Hawaii, Alaska & Canada add \$1.00 shipping)
VISA, Master Charge, Check, Money Order

740-0 - 8" Soft Sector
740-32 - 8" Hard (32) Sector
744-0 - 5" Soft Sector
744-10 - 5" Hard (10) Sector
744-16 - 5" Hard (16) Sector

Mass. residents add 5% sales tax.

cpu

COMPUTER
PACKAGES
UNLIMITED

✓ C103

99 Reservoir St. Holden, MA 01520
(617) 829-2570 Div. of SCB Inc.

TRS-80-LEVEL II and Disk Programs

MICROSOFT™ TRS-80 ANSI FORTRAN 3.9 (except complex variables), Macro Assembler, Subroutine Library, Linking Loader, Disk Editor. \$299.00

ELECTRIC PENCIL by Michael Shroyer. \$69.00

MULTIPLE REGRESSION 2.0 — A disk based package of chained programs that permit model estimation using thousands of observations, user specified transformations (write them in BASIC during execution), X-Y plots, formatted for screen or printer — all features of Multiple Regression 1.0. \$45.00

MACHINE LANGUAGE PROGRAMS (disk required)

Factor Analysis. \$59.00

Integer Programming. \$49.00

Mixed Integer Programming. \$49.00

LEVEL II 16K PROGRAMS

Multiple Regression 1.0. \$29.95

Linear Programming. \$29.95

B-1 Programming. \$29.95

Transportation Algorithm. \$29.95

Heuristic Line Balancing. \$29.95

Stat. Pack—median, mode, mean (avg., harmonic, geometric), variance, histograms, Tests (T, F, D), one variable regression, one and two-way ANOVA. \$9.95

LOWER CASE MOD — Includes excellent documentation — all parts (nothing else in box), compatible with Electric Pencil. \$14.95

VERBATIM™ DISKETTES (box of 10). \$35.00

Available in Disk add \$5
S.C. residents add 4% sales tax
Overseas orders add \$5 for shipping



✓ Q8

p.o. box 628
charleston sc
29402



Vector Graphing Techniques (North Star with Merlin)

Wendell Brown, 18, has been active in the computer field for over 12 years. He is manager of Low-Cost Computer Services in Oneonta NY, and serves as a professional consultant.

Wendell Brown
88 1/2 Ford Ave.
Oneonta NY 13820

The computer will no doubt continue to share an increasing part in our everyday lives. The need for interaction between human and computer will be of greatest concern. This article will present some solutions to problems relating to computer graphics.

Specifically, the primary focus here is on vector graphics and how to obtain smooth and

continuous-looking lines on graphs. Efficient software techniques are used to fill gaps between data points in the creation of lines. Several different procedures to maximize program and drawing speed are also presented.

The Problem

Smooth-looking lines are a necessity for most business and quality hobbyist graphic systems. The hardware cost for excellent graphics is perhaps high, but you can get very good results using a little hardware and suitable software at a

lesser cost. The trick is designing the software to fully utilize the hardware.

An example of high-efficiency matching between hardware and software is the video arcade game. The graphics, analog-to-digital converters and sound output are all well designed into the software. The result is fabulous video output at minimal cost.

A common problem of graphics, often found in higher-level languages, is skip. This occurs when only line segments or dots are displayed to represent whole lines (see Program A and Photo 1). Skip not only distorts the curve but makes the display appear choppy as well. Although not all information can be smoothly shown (or should be), many displays can be greatly improved with little effort and time.

Another problem in curved graphics is the use of straight

lines to approximate the curve. This is more of a technique than a problem, and the ability to circumvent these lines is based solely on the extent of the hardware and software. Obviously, the more lines there are, the higher the approximation of the curve. However, the more lines there are (hence shorter lines), the more time required to draw out the curve.

Techniques of Solution

Eliminating skip requires filling in the gaps between dots. This can be done in several ways:

1. In the event that there is an equation, the domain of the equation (input) can be increased. This will result in more outputs calculated, and thus more dots represented.
2. Another way is to draw short lines between dots. These lines connect all the dots to-



Photo 1. Skip graphics.

```
10 FOR X = -15 TO 15 STEP .5
20 IF X = 0 THEN 80
30 Y = SIN(X)/X
40 X1 = INT(80 + 5 * X)
50 Y1 = INT(80 - 70 * Y)
60 REM NOW PLOT THAT POINT (A9 IS JUST JUNK)
70 A9 = FN(X1,Y1)
80 NEXT X
90 STOP
```

Program A. Run time—8 seconds.




Photo 2. Increasing the domain of the equation.




Photo 3. Decreasing skip.

gether, creating continuity.

3. Still another way is to evaluate the equation (or a line equation) in an inverse way. For example, the y-axis value is usually calculated from an equation using the x-axis value as its domain (input). In this inverse line method, the x-axis value would be calculated from a value on the y-axis.

Solutions

As described above, an increase in the number of points plotted will definitely decrease the occurrence of skip. Unfortunately, the more points you plot, the more time the program will take to plot the entire graph. This is especially true

with long, time-consuming equations. Moreover, the chance of skip is only reduced, not eliminated. No matter how often you plot calculated points, there is still an excellent chance of near-vertical lines, thus creating skip somewhere in the graph.

Program B shows increased domain. Note that over twice the number of points are calculated and plotted (line 10) and skip is reduced. However, skip still occurs, giving the graph an incomplete and inferior look (Photo 2).

To draw lines between dots, you must determine the equation of the line. If you know two points—in the form of Cartesian

```

10 FOR X = -15 TO 15 STEP .2
20 IF X = 0 THEN 80
30 Y = SIN(X)/X
40 X1 = INT(80 + 5*X)
50 Y1 = INT(80 - 70*Y)
60 REM NOW PLOT THAT POINT (A9 IS JUST JUNK)
70 A9 = FN(X1,Y1)
80 NEXT X
90 STOP

```

Program B. Run time—17 seconds.

```

5 X2 = 5:Y2 = 76
10 FOR X = -15 TO 15 STEP .1
20 IF X = 0 THEN 80
30 Y = SIN(X)/X
40 X1 = INT(80 + 5*X)
50 Y1 = INT(80 - 70*Y)
60 GOSUB 1000
70 X2 = X1:Y2 = Y1
80 NEXT X
90 STOP

1000 IF X1 = X2 THEN 1080
1010 A = (Y2 - Y1)/(X2 - X1)
1020 B = Y1 - A*X1
1030 FOR X3 = X1 TO X2 STEP SGN(X2 - X1)
1040 Y3 = INT(B + A*X3)
1050 REM NOW PLOT THAT POINT (A9 IS JUST JUNK)
1060 A9 = FN(X3,Y3)
1070 NEXT X3
1080 RETURN

```

Program C. Run time—46 seconds.

coordinates, (X_1, Y_1) and (X_2, Y_2) —then you can equate the line:

$$A = \text{slope} = \frac{Y_2 - Y_1}{X_2 - X_1}$$

$$B = Y - \text{intercept} = Y_1 - AX_1$$

In this case, you would draw the line from the first point (X_1, Y_1) to the second point (X_2, Y_2) . Program C is an example of this type of solution. A slight problem occurs with this method: to determine the number of points to plot on the line.

In the normal graphing of a line, the line equation is given a certain point on the x-axis as input. The equation then computes the corresponding value on the y-axis as output. The point with these X and Y coordinates is then plotted on the graph. If that y-axis value is close to the value of the previous point, then the graph in that neighborhood will look good.

However, in many equations the y-axis value is not numerically and graphically close to nearby y-axis values. This is especially true in functions that fluctuate rapidly. In these

functions the y-axis value may skip either up or down, thus creating skip in the graph.

The most effective way to avoid skip is to invert the line equations' input and output to enable drawing two short lines between the two dots... once using the x-axis as the line equations' domain, and again using the y-axis as domain. To do this, you must mathematically invert the line equation from above. This is a simple procedure.

First, you must calculate the slope and y-intercept of the line between the two dots as shown above. The program then plots that line in the normal way using the x-axis as domain. You then plot the inverted line using the y-axis as domain. To do this, you must derive the inverted line equation as below. For example, if you have the general line equation:

$$Y = AX + B$$

all you have to do to invert the equation is to solve it for X:

$$X = \frac{Y - B}{A}$$


```

5  X2=5:Y2=76
10 FOR X = -15 TO 15 STEP .1
20 IF X = 0 THEN 80
30 Y = SIN(X)/X
40 X1 = INT(80 + 5 * X)
50 Y1 = INT(80 - 70 * Y)
60 GOSUB 1000
70 X2 = X1:Y2 = Y1
80 NEXT X
90 STOP

1000 IF X1 = X2 THEN 1100
1010 A = (Y2 - Y1)/(X2 - X1)
1020 B = Y1 - A * X1
1030 FOR X3 = X1 TO X2 STEP SGN(X2 - X1)
1040 Y3 = INT(B + A * X3)
1050 REM NOW PLOT THAT POINT (A9 IS JUST JUNK)
1060 A9 = FNX(X3,Y3)
1070 NEXT X3
1100 IF Y1 = Y2 THEN 1180
1110 A = (X2 - X1)/(Y2 - Y1)
1120 B = X1 - A * Y1
1130 FOR Y3 = Y1 TO Y2 STEP SGN(Y2 - Y1)
1140 X3 = INT(B + A * Y3)
1150 REM NOW PLOT THAT POINT (A9 IS JUST JUNK)
1160 A9 = FNX(X3,Y3)
1170 NEXT Y3
1180 RETURN

```

Program D. Run time—54 seconds.

By drawing the line twice, you get a much better plot (see Photo 4). Because the line is dependent on both axes, the increment for the line calculations will be one on both axes. This, in effect, is insurance that we will avoid skip.

Moreover, this line technique will allow us to increase the spacing between calculated points, thus saving computer time. For example, if we change the STEP value in line 10 of Program D from .1 to 1, we still get an excellent-looking graph with a run time of only 15 seconds.

In sum, since we are drawing

lines and connecting all the dots, we can decrease the number of dots and still get a complete line. However, the fewer data points that there are, the less precise will be the continuous line.

The Program

Program D, written in 8-digit North Star BASIC version 6.3, is a general-purpose program useful in a variety of applications. This particular program uses MiniTerm's Merlin video interface board, set to use in its dense graphics mode.

The function FNX is a BASIC




Photo 4. Filling the gaps.

function used to calculate, FILL and thus graph the specific memory bit corresponding to whatever (X,Y) coordinate is input to the function (the Merlin uses a DMA display technique, that is, the data on the screen is directly representative of the memory being displayed or "mapped"). You can replace the FNX function by the SET function in Radio Shack's TRS-80 BASIC to accomplish the same thing (i.e., line 1060 in Program D would then become 1060 SET(X3,Y3)).


However, be careful not to exceed the display's edges. The Merlin, in its dense mode, has a graphics array of 160 x 100, while the TRS-80 has a 128 x 48 array. Similar com-

mands in most other BASICs will perform the same operation depending on what BASIC and what graphic equipment you have.

The way the programs were written requires an independent graphic display (memory). In other words, you must be able to access any point on the graph at any time. To run this program on a machine that displays (prints) only a portion of the graph at a time (e.g., TTY), you must make certain modifications to the program. A possible technique might be to set up an array and "graph" the array before any printing is done. After the graph is completed in memory, you would then plot out the entire array on paper. ■

NEW 32K EPROM/RAM MEMORY CARD

SS-50 BUS
5V only



DSD P/R-32K.....\$27.00
2716 EPROMS & TMS 4016 2K x 8 Static RAM.
4 Independent 8K memory blocks. Size 9" x 5 1/2"

DSD 2114-16K.....\$27.00
16K Static RAM memory card using the 2114 or
TMS 4045 1K x 4 Static RAMS. Size 9" x 5 1/2".
2 Independent 8K memory blocks. 5V Only.

NEW DSD U P 8255 (C&M)
.....\$14.00

Universal parallel interface card for Both the
SWTP 30 pin I/O BUS (M) and the DSD 27 pin BUS
(C). Utilizes INTEL's 8255 PROGRAMMABLE I/O
chip. Wire wrap area for full UTILIZATION of the
8255. Card sizes 5 1/2" x 5" (M) 5 1/2" x 4 1/2" (C).

All cards are bare board with edge connectors and Data.



DIGITAL SERVICE & DESIGN
P.O. BOX 741
NEWARK, OHIO 43055



Ohio residents add 4.5% sales tax.

TRS-80 / TRS-80 / TRS-80 / TRS-80 / TRS-80 ORIGINAL HARDWARE AND LEVEL II SOFTWARE FROM

MUMFORD MICRO SYSTEMS

Box 435-C, Summerland, California 93067 (805) 969-4557

MUSIC BOARD: The MB-1 plugs directly into the expansion port of the keyboard or expansion interface and will produce any note in a 4 octave chromatic range with just one command in Level II (must be addressed in machine code in Level I). Includes Level II program on cassette to play one tune and may be easily reprogrammed for others. Highly accurate (.15%) tunable scale. Assembled board with jacks for speaker and power supply (\$4 at Radio Shack).....\$74.95. Mounted in mahogany cabinet with speaker and power supply...\$94.95.

3 SPEED KIT: The SK-1 allows either a 50% increase or decrease in CPU speed. May be changed at any time without interrupting program execution. Only 4 connections to existing circuit. Kit includes all components, switches, PC board, and clearly illustrated instructions.....\$24.95.

CLONE is a machine code program for making duplicate copies of any tape written for Level II. They may be SYSTEM tapes or data lists. If you can load it you can CLONE it. Specify memory size...\$12.95.

DATA LIST is a 2 string information organizing program that alphabetizes, sorts for any sub-string, prints hard-copy, and features SPEEDED UP TAPE STORAGE. A typical list of 200 entries which normally takes over 16 minutes to dump can now be saved in 2 1/2 minutes. Specify memory size...\$16.95.

MAIL LIST is a 5 string version of the preceding program that features the same speeded-up tape storage. Alphabetize by name, state, zip code, or data string. Search for any sub-string. Print lists or labels. Specify memory size...\$19.95.

Add \$1.00 postage for hardware, 50¢ for software.
Calif. residents add 6% sales tax.

TRS-80 / TRS-80 / TRS-80 / TRS-80 / TRS-80

TREK-80 TRS-80 LEVEL II 16K

Mission: To protect your cruisers and bases from an enemy fleet of starships. You have 50 stardates and at least 2 starbases.

Commands: Warp drive, impulse drive, short range sensors, long range sensors, status report, damage report, engineering, computer, fire phasers, fire torpedos, lock phasers, lock torpedos, probes, galactic data, lock course, torpedo intercept and adjust reactorflow settings.

All action graphically displayed. 64 quadrants, 64 sectors per quadrant. Klingons move, fire phasers and torpedos. Cruisers move but are only armed with phasers. Very detailed I.E. Time and energy are function of speed and distance, fire and move any direction, 10 item damage report.

Instructions and game on Cassette \$15.00

SYSTEM BLACKJACK TRS-80 LEVEL II

Input dealer top card, your count and strategy. Computer then deals requested number of hands and records results. Reshuffles after four decks are dealt. Includes regular plays, double down and soft hands.

\$7.50

THE COMPUTER CONNECTION

10 Hickory Point Court Decatur, Illinois 62526
217-877-1500 C133

TRS-80* and PET** Owners With the Yen for Bucks

Could you use some extra money? Intrigued with the prospect of turning your hobby into a part time business that can line your pocket with ready cash? With the Bowling League Statistics System and Baseball Manager programs from Instant Software you'll be able to do just that—without leaving your home!

It takes money to make money. As microcomputer enthusiasts you've already made a significant investment in your hobby. But have you ever thought of your computer as a business investment? Hundreds of clubs, small businesses, high schools, colleges, and civic organizations would welcome the speed, versatility, and sheer convenience that your microcomputer can bring to their record keeping. The paperwork involved in maintaining records and computing statistics for baseball and bowling leagues is mind boggling—just ask any league manager or secretary. And after he's through sputtering, tell him about your computer and the services you can provide. If he's like most league managers, you'll find yourself in business for yourself right on the spot!

Bowling League Statistics System TRS-80* 16K—\$24.95

Bowling League Statistics System is a comprehensive program for the 16K TRS-80* microcomputer that puts an entire league's statistical data at the secretary's fingertips. Actually two separate programs, the STARTUP program stores an entire league's records and provides for 16 different scoring options, team data, and nine categories of statistical information on each and every bowler in the league. The WEEKLY program provides weekly scores, team cumulative scores, individual bowler scores, bowler cumulative scores, and individual leaders, with high average, high series, high game, and high points. Furnished complete with blank data cassettes.

Baseball Manager Pet** 8K—\$14.95

Can you imagine the look on a Little Leaguer's face (not to mention his parents) when the coach provides him with a complete accounting of his season's performance? A Little League manager can. And not just the Little Leagues; adult baseball and softball teams can also benefit from a ready reference to such information as highest to lowest fielding, batting, and on-base averages. By supplying a league secretary or team manager with individual or performance data, you'll not only be freeing him from hours of tedious calculations, but you'll be giving him the information he needs to ascertain the strengths and weaknesses of his team. In fact, you can even use the Baseball Manager program to keep tabs on your favorite Major League teams! Furnished complete with blank cassettes.

The most important thing to remember is that you'll be turning your hobby into a small business that is certain to grow. Baseball Manager and Bowling League Statistics System are only the first in a series of money-making programs for today's most popular microcomputers. And since it's Instant Software, you know that each program is the product of a lengthy and detailed process of review that insures consistently high quality, and comes complete with well written, easy to understand program documentation and instructions for use.

There's a whole new world of lucrative opportunities opening up to enterprising microcomputer owners who are willing to profit by giving others the benefit of their experience. So what are you waiting for?

* A trademark of Tandy Corporation

**A trademark of Commodore Business Machines Inc.

Master Charge, VISA and AMEX orders accepted. To order by phone, or to receive our free catalog, call toll free 1-800-258-5473.

Ordered by _____
Purchase Order No. _____ Company _____
Address _____
City _____ State _____ Zip _____
Signed _____ Date _____

Quantity	Order No.	Program name	Unit cost	Total cost
	0056R	Bowling League Statistics System	\$24.95	
	0062P	Baseball Manager	\$14.95	
		shipping and handling		\$1.00
Instant Software Inc. ✓ I32			Total order	

Dept. M-IS-F2
Peterborough NH 03458

Putting the 1802 on the S-100 Bus

1802 fans! If visions of simplified expansion are dancing in your heads, this one's for you.

Bob Petty
21205 Roscoe 56
Canoga Park CA 91304

Like a lot of people, I got started with microproces-

sors by building an Elf. The Elf is a simple computer based on RCA's CMOS microprocessor, the 1802. The original device provided for data entry with toggle switches and had a two-digit hex display for readout. All programming was done in

machine code. In other words, the computer was as simple and inexpensive as you could get.

Having been bitten by the microprocessor bug (or whatever it is that overcomes a person about these things), I im-

mediately began adding bits and pieces of hardware here and there, more or less at random, dreaming all the time of the day I would be able to play Star Trek.

I would like to be able to say that after a careful design study and making all the proper system trade-offs, etc., I determined that the most efficient means of upgrading my Elf was to adapt it to the S-100 bus. What really happened was that about the time I finished hand-wiring my first 4K of memory (those who have done this will appreciate the effort involved), a friend offered to sell me an S-100 motherboard and 8K of RAM for \$60.

I have since come to realize just how fortunate this was. Instead of an elaborate kludge, I now have a sensible little system. I have Tiny BASIC working on my system and am developing a general-purpose text editor.

Circuit Description

Fig. 1 is a block diagram of the CPU board. The system is based on a monitor ROM called UT4, which was developed by RCA for their evaluator board. UT4 contains a software UART that uses the Q output and the EF4 input to provide a serial data link to the terminal.

Other than the 1802 and UT4,



Mary Sunshine is playing a Tiny BASIC version of Tiger Trouble (sorry the display didn't show up—being a non-photographer I haven't the foggiest about how to do that).




Fig. 1. Block diagram of 1802 CPU board.




Fig. 2. Component layout on Vector 8800V board.

the board consists of simple control, latching, decoding and buffer circuits. In fact, the entire CPU consists of only 13 ICs, which can be wire-wrapped on a bare S-100 board in eight to ten hours. Fig. 2 shows the suggested board layout on a Vector board. Because of the low-power requirements of CMOS ICs, only one +5 V regulator is needed. The other regulator pad can be used to mount the crystal. A 16-pin DIP socket is used to take the control and serial interface signals off the board. Considerable space is left for future additions.

Fig. 3 shows the 1802 and associated control circuits. U2 serves to debounce the RUN and RESET switches and provides a RUN signal to the address latch to control start-up of the processor. The capacitor on the reset line provides power-up reset. The CLEAR line is used to select between the RUN and RESET modes of the 1802. The basic system makes no use of the LOAD or PAUSE modes, so the WAIT line is pulled high. Depending on the terminal device, the Q output and EF4 input may require buffering, the addition of an RS-232 interface or the addition of a 20

mA current loop interface. The circuitry as shown will interface directly with an SWTP TVT.

Because the 1802 multiplexes the address as two sequential 8-bit words, it is necessary to latch the higher-order eight bits as shown in Fig. 4. Normally the 1802 starts (after RESET) at address 000H; however, the starting address of UT4 is at 8000H.

So A7 is Ored with the RUN signal, which is high while the RUN switch is depressed. This allows direct entry into UT4.

Fig. 5 shows the address decoding for UT4. U6 uses MRD and the Q and \bar{Q} outputs of the address latch to enable UT4 during a memory read between addresses 8000H and 81FFH. The CS signal is sent to the bus control circuits to disable the bus buffers when UT4 is addressed. Because UT4 is completely decoded, the entire remaining memory is available for use.

The bus interface is shown in Fig. 6. The S-100 bus signals are TTL, so drivers are necessary to convert the CMOS signals. U11, 12 and 13 buffer the address,

MEMR and MWRITE signals. U9 and U10 are bidirectional bus drivers that buffer the data lines. Data input is enabled when the 1802 performs a memory read (MRD goes low), except when U14 is addressed (CS goes low).

This circuitry is all that is required for minimum CPU operations. The circuitry allows use of standard static RAM boards and I/O boards which are addressed as memory. Additional features of the 1802 and S-100 bus are not required initially. At the end of the article I have included some notes and suggestions about adding features.

Operation

Operation of the system is quite simple. After turning power on, the operator presses RUN and types in either a CR or an LF. CR initiates full duplex operation (the computer echoes input characters back to the terminal). LF initiates half duplex operation (no echo). UT4 automatically adjusts to the terminal baud rate and types an "*" as a command prompt. The 2 MHz crystal allows operation at 110, 150 or 300 baud.

UT4 Monitor

Use of the UT4 Monitor is also simple as there are only three commands—one to ex-




Fig. 3. CPU and control circuitry.




Fig. 4. Memory latch circuit.

amine memory, one to write into memory and one to initiate execution of a program. All numerical commands are in hex form; leading zeros are optional; and if more than four digits are entered, only the last four are used.

To examine memory enter the command:

?M address 'space' number 'CR'

where: address is a hex number specifying the starting address; number is a hex number specifying the number of bytes to be displayed. The monitor responds by typing out a four-digit address followed by data.

To modify memory enter the command:

!M address 'space' data CR

where: address is a hex number specifying the starting address;

data is any number of hex digit pairs.

Non-hex characters in the data stream are ignored. An odd number of hex digits will cause UT4 to type a ? after a CR is entered. Lines may be continued by preceding the CR with a comma or a semicolon. If a comma is used, simply keep typing hex pairs after the CR. If a semicolon is used, a new starting address must be specified after the CR (see Example 1).

The !M and ?M commands are designed to allow storage and retrieval of data through the terminal device. To record

Name	Address	Description
READ	813E	Input ASCII character to RF.1 and D.
READAH	813B	Same as READ. Also if character is a hex character it is converted to a 4-bit binary number and placed in RD. For instance, four inputs of hex characters 8000 from the terminal would leave RD with the value 8000H. This saves you the trouble of converting ASCII data to binary form.
TTYRED	8140	Same as READ. This routine is used to control a paper-tape reader. Calling this routine causes the CPU to issue a 67 instruction (OUT 7) and places 80H on the data bus. In the RCA system this turns on the paper-tape reader. After the character is read, a 67 instruction places a 40H on the data bus to turn off the paper-tape reader.
TYPE 5	81A0	Output ASCII character at M (R5) (memory location pointed to by R5), then increment R5. To use this function the character to be output is placed immediately following the SEP 3 instruction of the user program. Same as Type 5 except provides for a 1.5-bit delay of serial data. This is used when the preceding operation was a READ call.
TYPE 5D	819C	
TYPE	81A4	Output ASCII character at RF.1.
TYPE 2	81AE	Output hex digit pair in RF.1. This routine actually types out two ASCII characters. That is, each binary value in RF.1 is converted to an ASCII character and output to the terminal.
TYPE 6	81A2	Output ASCII character at M(R6) then increment R6. Use to output a data string.

Table 1.




Fig. 5. UT4 and decode circuit.

data use the following steps.

1. Enter ?M address space number (do not enter CR yet).
2. Start the recorder or tape punch.
3. Enter CR.

The monitor will output the desired data to the cassette or tape punch.

To load data, do the following.

1. Start up UT4 in the half duplex mode (no echo).
2. Enter !M0; (do not enter CR).
3. Start the recorder or tape reader.

The CR is recorded on the tape so the loading process will be preformed automatically.


The third monitor command is used to pass control to other programs. To use this command enter:

\$P Address CR

where: Address is a hex number specifying the starting address of the program. When execution of the program begins, R0 is the program counter.

User programs may use the READ and TYPE routines within UT4 to provide terminal I/O. Steps for using the routines are as follows.

1. Make R5 the program counter.
2. Load starting address of appropriate READ or TYPE routine into R3.
3. For character output, load the character as required by the selected TYPE routine.
4. SEP to R3 (makes R3 the program counter).
5. When the routine is finished, control is passed back to



Completed CPU board. Note the twisted-pair jumper cables used to connect to the control panel and the TVT. The extra sockets are for an expansion project I have in the works.




Fig. 6. Bus interface.

```

*IM100 0011 2233Z 4455 6677 8899,
AABB CCDD EEFF;
110 0011 2233
*?M100 14
0100 0011 2233 4455 6677 8899 AABB CCDD EEFF;
0110 0011 2233

```

The underlined characters are typed by UT4.

Example 1.

the program with R5 as the program counter.

6. For character input the character can be found as specified in the selected READ routine.

UT4 stores data used by these routines in registers RC and RE. Therefore, user programs must *not* use these registers. Also be aware that the READ and TYPE routines will change the contents of registers X, D, DF and RF.

Available routines and their entry points are shown in Table 1. READ and READAH exit with R3 pointing back at READAH.

This means you can make successive calls to READAH without reloading R3 prior to each call. All TYPE routines exit with R3 pointing at TYPE 5. Thus, TYPE 5 can be used for successive calls.

Notes on Expansion

The CPU board, as described, is adequate to support Tiny BASIC and any machine-level programs of a purely computational nature. Use of many S-100-bus-compatible products may require that additional signals be generated. Also, it may be desirable to make use of

some of the special features of the 1802. These features can be added piecemeal to fulfill specific requirements.

8080-type I/O works by addressing the I/O device with the lower eight address lines and providing I/O read (SINP) and I/O write (SOUT) signals. Fig. 7 shows how to simulate this operation. Whenever the memory immediately above UT4 (8200H to 8300H) is addressed for a memory read (or write), the MEMR (or MWRITE) signal is gated off and SINP (or SOUT) is generated. From a programming standpoint, the 8080 I/O instructions are shown in Table 2.

Note: The 8080 repeats the lower address byte to the upper address byte during an I/O operation. Unfortunately, some manufacturers decode the

upper byte rather than the lower. Use of one of these products requires adding logic to allow the decode signal to gate the lower address onto the upper address lines.

The 1802 input/output operations pose a minor problem when using a split data bus. The reason for this can be seen in Fig. 8. During the input instruction the 1802 expects data to flow directly from the I/O device (which outputs onto the Data In bus) to memory (which inputs from the Data Out bus). Therefore, it will be necessary to add logic as shown to connect the two buses during an input operation (the MEMR line is low during an input).

Interrupts can be handled by connecting the INTREQ Line (Pin 75) to the 1802 INTERRUPT

8080	1802
OUT XX	Any memory store instruction to 82XXH
INP XX	Any memory load instruction to 82XXH

Table 2.




Fig. 7. 8080 I/O port simulation.




Fig. 8. Using N lines to connect data buses.

10% OFF 20% OFF



YOUR OWN TRS-80 SYSTEM AT TREMENDOUS SAVINGS

TRS-80

Model	List Price	Our Price
Level II-4K	\$698.00	\$628.20
Level II-16K	\$988.00	\$889.20
Expansion Interface	\$299.00	\$269.10

COMPATIBLE PERIPHERALS

Item	Regular Price	Discount Price
Mini-Disk System— INC. P.S. and enclosure BASF 6106 (MTTF 8,000 hrs.)	\$489.00 \$599.00	\$385.00 \$495.00
Line Printer (Free Cable) Centronics 779 w/tractor feed Centronics 101 15" carriage GTE 560 (Selective) Extra Cables	\$1599.00 \$1595.00 \$1295.00	\$1299.00 \$1400.00 \$975.00 \$35.00
16K Memory Kit	Installed \$138.00	Kit only \$98.00

**1 MEG + OF DISK MEMORY
on line for TRS-80 \$2195**

Includes—Operating System (CP/M)

HUH Electronic S-100 Interface to TRS-80
Kit \$280.00 Assembled \$350.00

Classroom instruction offered in Level II Basic—\$49.95; and DOS/Disk Basic—\$69.95

Master Charge and VISA accepted

VR Data corp

V19

2201 H. Johnson Boulevard N-6, Folcroft, PA 19032 (215) 461-5300
In Washington, DC area: (703) 938-1099

pin. Use on AND gate to drive INTA (pin 96) high when SCO and SCI are both high.

The S-100 DMA operations are normally initiated by the HALT signal (Pin 74), which stops the processor and disconnects the CPU from the bus. This can be copied by connecting HALT to the 1802 WAIT pin as shown in Fig. 9. The 1802 stops on the first falling edge of the clock so the 4013 is used to Tri-state the bus drivers and generate the HLDA signal (pin 26). When designing a DMA device from scratch, you can save considerable hardware by using the built-in DMA features of the 1802.

Table 3 shows the suggested

strange things.

UT4 can be purchased through any RCA distributor. Ask for: UT4 Utility Program (CDP1832). Part No. CDP512CD (4-6 V) is \$13.30. Part No. CDP512D (3-12 V) is \$16.20.

Conclusion

I hope this article will help other 1802 users to upgrade their own systems with a minimum of effort. I have provided details on how to make an S-100 bus CPU board and described the use of a monitor ROM you can buy. The basic system is a "minimum" system in that it does not use all the features of either the 1802 or the S-100 bus. The idea is to keep things simple




Fig. 9. Using the HALT signal.

SIGNAL	PIN
DMA IN	61
DMA OUT	62
SCO	63
SCI	64
TPA	65
TPB	66
EF3	12
EF2	13
EF1	14
N0	15
N1	16
N2	17

Table 3. Assignment of 1802 signals to S-100 bus spare pins.

assignment of 1802 signals to the spare S-100 bus signals. In addition, Fig. 10 shows the suggested memory map for 1802 systems.

The 32-byte RAM at 8C00H to 8C1FH is used by UT4 to store the CPU registers when UT4 is entered. A long branch to 8000H can be inserted into a program for debugging purposes. The values stored in RAM for R0, R1 and R4.1 will not be correct. Also, the memory immediately above 8C1FH cannot be RAM, else UT4 does




Fig. 10. Memory map.

and allow for expansion as the need arises.




Other than the CPU board, you will need an S-100 bus motherboard, at least 4K of memory, power supplies and a terminal or TVT. Of course, you will want some software. For starters, Tiny BASIC is available from Itty Bitty Computers, PO Box 23189, San Jose CA 95153. ■

PET / TRS-80 / APPLE: Personal Software brings you the finest!



NEW! THE ELECTRIC PAINTBRUSH by Ken Anderson for 4K Level I and II TRS-80s: Create the most dazzling graphics displays you have ever seen with a minimum of effort. *The Electric Paintbrush* is actually a simple 'language' in which you can write 'programs' directing your paintbrush around the screen—drawing lines, turning corners, changing white to black, etc. Once defined, these programs may be called by other programs or repetitively executed, each time varying the parameters of brush movement.

The machine language interpreter executes your programs almost instantaneously, allowing you to create real-time, animated graphics displays. The screen photos above are actually 'snapshots' of the action of a single one-line program over about thirty seconds. Mesmerize your friends with visual effects they've never seen on a TV screen! There's no limit to the variety of exciting and artistic graphics displays you can create with *The Electric Paintbrush*. And it's available now for only **\$14.95**



MICROCHESS is the culmination of two years of chessplaying program development by Peter Jennings, author of the famous 1K byte chess program for the KIM-1. MICROCHESS 2.0 for 8K PETs and 16K APPLES, in 6502 machine language, offers 8 levels of play to suit everyone from the beginner learning chess to the serious player. It examines positions as many as 6 moves ahead, and includes a chess clock for tournament play. MICROCHESS 1.5 for

4K TRS-80s, in Z-80 machine language, offers 3 levels of play (both Level I and Level II versions are included and can be loaded on any TRS-80 without TBUG). MICROCHESS checks every move for legality and displays the current position on a graphic chessboard. You can play White or Black, set up and play from special board positions, or even watch the computer play against itself! Available now at a special introductory price of only **\$19.95**

BRIDGE CHALLENGER by George Dulsman for 8K PETs, Level II 16K TRS-80s, and 16K APPLES: You and the dummy play 4 person Contract Bridge against the computer. The program will deal hands at random or according to your criterion for high card points. You can review tricks, swap sides or replay hands when the cards are known. No longer do you need 4 people to play! **\$14.95**

TIME TREK by Brad Templeton with sound effects for 8K PETs is **Personal Software's** answer to the proliferation of Star Trek games. This is a real time action battle game which requires fast thinking as well as sharp wits. There are no 'turns' in *Time Trek*: your scanners and ship's status report are constantly updated on the screen, and you can enter commands as fast as you can press the keys. You use your shields, phasers and photon torpedoes against enemy Klingons in a game where you can move, steer and fire at the same time. Star Trek aficionado or not, you'll appreciate the excitement and excellence of this real time game. **\$14.95**

WHERE TO GET IT: Look for the **Personal Software™** display rack at your local computer store. Over 275 dealers now carry the **Personal Software™** line—more than any other brand. If your local dealer doesn't already carry **Personal Software™** products, ask him to call us at (617) 782-5932. Or you can order direct from us by check, money order or VISA/Master Charge. If you have questions, please call us first at (617) 783-0694. If you know what you want and have your VISA/MC card ready, you can use any telephone to



**DIAL TOLL FREE
1-800-325-6400**



24 hrs In Missouri dial 1-800-342-6600 7 days

Or you can mail your order to the address below. To add your name to our mailing list for free literature and announcements of new products, use the reader service card at the back of this magazine.

Personal Software™ P39

P.O. Box 136-K4, Cambridge, MA 02138



A Personal Finance System

This 3-part series of personal finance programs can be used to keep track of payments, prepare tax returns and generally balance your budget. Part 1 covers accounts payable.

James McClure
1019 Van Kirk St.
Philadelphia PA 19149

The wild bill reared its ugly head. It was a hideous sight, covered with numbers and punched holes. Somehow it had escaped from the other bills and lain undetected under a pile of old newspapers, growing by 5 percent every month. Now it would take both barrels of the old elephant gun filled with cash to subdue it. There must be a better way!"

With the advent of the personal computer, there is no longer any reason for allowing bills that escaped into the jungles of paper on your desk to run wild, terrorizing you and your loved ones. Properly equipped, a microcomputer can all but eliminate cluttered files, and in so doing, greatly reduce the chance of overdue bills.

And while it appears that no one else is doing it, balancing the budget is still an important step in staying financially alive, a task that is much easier if the computer

is keeping track of income and expenditure. Another advantage of the computerized bookkeeper is that it can help you prepare your tax return, and probably save you money in the process.

In this and subsequent articles, I will present a series of three programs that will keep track of due bills and the checks or cash by which they are paid, keep track of pay stubs and other income and provide several different reports that can be used in preparing tax returns and in balancing the budget.

All of these programs are written in ANSI standard CBASIC, a disk-based compiler sold by Digital Research. A minimum recommended system for running the programs consists of an 8080 microcomputer, a CRT console, a hard-copy printer, 24 kilobytes of memory and a single drive IBM-compatible floppy disk. Minimum required software includes the CP/M disk operating system and CBASIC, both from Digital Research.

If you have the recommended hardware, but do not have CP/M, I recommend it as probably the best and most

inexpensive disk operating system available for 8080 microcomputers. Furthermore, it will work with any eight-inch IBM-compatible disk drive on the market, and that gives you a lot of models to choose from.

Though all of this may sound like a lot of very expensive equipment, actually the prices of both memory and disks are dropping like flies, and the printer is not absolutely necessary. The system is even more affordable when you consider that it will be saving you time, which in many cases is much more important than money.

Operation

The program accompanying this article is a personal accounts-payable system for keeping track of bills and their payment. This program keeps two files — one for those bills currently due and one containing records of payment of previous bills. When the program is run, it will ask for the date, after which it will print a list of options. To select an option, type its corresponding letter followed by a carriage return. The computer will prompt

for all necessary information.

The first step in using the program is to make out a list of all companies from which you regularly receive bills. Enter the company names, one at a time, using the A option. As each company is entered, the computer will assign an account number, starting with the number one. Later, these numbers will be used in place of the company's full name.

It is best to enter bills as they are received. This will save having to go on a bill-hunting expedition at the end of each month. To enter a bill, invoke the F option. The computer will ask for the account number of the company that sent the bill. (This is the number that was assigned by the computer when the account was first created.) After you have entered the amount of the bill and the date it is due, the computer will print the new balance for that account. This is the sum of any previous outstanding balance and the amount of the bill just entered.

If you are a red, white and blue procrastinator like most sensible Americans, the G

A>CRUN ACC/PAY
CRUN VER 1.02

TODAY'S DATE? 03/04/78

ACCOUNTS PAYABLE SYSTEM

DATE: 03/04/78

ALLOWABLE OPTIONS ARE:

A=ENTER NEW ACCOUNT
C=LIST SPECIFIC ACCOUNT
E=PAY BILL
G=PRINT BILLS DUE THIS MONTH
I=EDIT AN ACCOUNT

B=LIST CURRENT ACCOUNTS
D=LIST ACCOUNT HISTORY
F=ENTER NEW BILL
H=WRITE CHECK (NOT FOR BILL)
J=RETURN TO DISK OPERATING SYSTEM

OPTION (?=LIST OPTIONS)? A
ACCOUNT NUMBER 5 ASSIGNED
ACCOUNT NAME? NOMICE EXTERMINATOR

OPTION (?=LIST OPTIONS)? B
PRINT ON TTY? Y

DATE: 03/04/78

ACN	ACCOUNT	TOTAL	BALANCE	DATE DUE
1	AQUA WATER WORKS	\$17.95	\$17.95	04/01/78
2	XENON POWER CO.	\$12.00	\$12.00	03/22/78
3	WATCHDOG INSURANCE	\$48.50	\$48.50	03/12/78
4	BAD GUYS DEPT. STORE	\$79.60	\$0.00	01/27/78
5	NOMICE EXTERMINATOR	\$0.00	\$0.00	

		\$78.45		

Sample 1. Initializations dialog and functions A and B.

option will be very handy. It lists only bills due the current month. However, if you are a more masochistic type, the B option will list all current accounts and print the total of your debts.

To pay a bill, use the E option. After you have entered the correct account number, the computer will print the balance due. Enter the amount of payment. If you are paying by check, also enter the check number. Finally, enter the date of payment. (If you wish to enter the current date as date of payment, simply type a space followed by a carriage return, and the computer will enter it for you.)

To record checks written for cash or miscellaneous, use the H option. If the check is of the miscellaneous type, enter the person or company who received it, as well as the check number, amount and date. (Again, to enter the current date as the date of

the check, simply type a space followed by a carriage return.)

In the case of an error, the I option will allow individual records to be edited. Editing is done by fields so that the entire record need not be retyped. Decide which field is to be changed and enter its corresponding number (see Fig. 1). Then, retype that field.

You may, at any time, examine the history of an account by invoking option D. This will list the amounts, dates and check numbers of checks written to that account, as well as provide a total of the amounts.

The Program

The accounts-payable program was written in a structured format using subroutines for major operations. Most statements are also ANSI standard. These two features should make modification easier if you are running the program on other than the recommended sys-

OPTION (?=LIST OPTIONS)? C
ACCOUNT NUMBER? 2
PRINT ON TTY? Y

ACN	ACCOUNT	TOTAL	BALANCE	DATE DUE
2	XENON POWER CO.	\$12.00	\$12.00	03/22/78

OPTION (?=LIST OPTIONS)? D
ACCOUNT NUMBER? 1
PRINT ON TTY? Y

DATE: 03/04/78

ACN	ACCOUNT	TOTAL	CHK NUM	CHK DATE
1	AQUA WATER WORKS	\$17.40	100	01/10/78
1	AQUA WATER WORKS	\$20.79	102	02/20/78

		\$38.19		

OPTION (?=LIST OPTIONS)? E
ACCOUNT NUMBER? 3
ACCOUNT NUMBER 3 IS WATCHDOG INSURANCE
BALANCE DUE \$48.50
AMOUNT OF PAYMENT? 25.00
PAYMENT BY CHECK? Y
CHECK NUMBER? 105
DATE OF CHECK? *** NOTE: SPACE ENTERED INSERTS CURRENT DATE ***

OPTION (?=LIST OPTIONS)? F
ACCOUNT NUMBER? 4
ACCOUNT NUMBER 4 IS BAD GUYS DEPT. STORE
AMOUNT OF BILL? 57.82
DATE DUE? 03/09/78
NEW BALANCE IS \$57.82

Sample 2. Functions C, D, E and F.

tem. In particular, two sub-routines at lines 10000 and 11000 will probably need modification. These are the disk read record and write record routines, respectively.

CBASIC offers many extended features, and I have used them often in the program. These features include optional line numbers, long variable names and con-

tinuation lines (indicated by a backslash '^'). For this reason, I don't recommend running the program in anything other than an extended BASIC.

With regard to disk operations, random file access was used exclusively throughout the program, mainly for speed. Record length was set to 72 characters, indicated by the RECL 72 clause of file open statements. Both of the above features may be changed without seriously affecting operation of the program.

Formatted print statements were also used in the program to enhance output. These may be replaced with conventional print statements if print using is not available in your version of BASIC. For more information on how print using statements work, along with information on random and sequential file access and other extended features of BASIC, I recommend *Advanced BASIC: Applications and Problems* by James S. Coan (Hayden Book Co., 1977, \$7.95).

I can't offer any guarantees, but it looks as though the program could be easily modified to run in the fol-

lowing BASIC languages:

- Disk Extended BASIC by Mits
- Disk BASIC etc. by Binary Systems
- BASIC-E by Digital Research
- Disk BASIC by North Star
- Disk BASIC by Ohio Scientific
- Disk BASIC by SWTP

For more information on special CBASIC statements and how to change them to suit your system, see Fig. 2.

Conclusion

In the coming years, microcomputers will have a tremendous impact on personal finance, an area of universal concern where a computer could be truly useful. Armed with this powerful tool and a little ingenuity, we may well make wild bills a thing of the past, something for the kids to see at the zoo. So come on, put your computer to a really worthy use. Happy hunting! ■

Field #2	Field #3	Field #4	Field #5
1 Sears Roebuck Co.	\$100.	\$100.	01/01/78
2 Automobile Insurance	\$75.	\$75.	01/20/78

Fig. 1. Fields used by edit option.

IF conditional operators:

CBASIC	STANDARD	MEANING
EQ	=	equal to
GT	>	greater than
LT	<	less than
GE	>=	greater than or equal to
LE	<=	less than or equal to
NE	<>	not equal to

Special CBASIC statements:

- OPEN "FILE" RECL 72 AS 1—Open a disk file named "FILE" for random access. Record length is fixed at 72 characters.
- READ # 1,1;A\$—Read into variable A\$ from record 1 of random access file 1.
- PRINT # 1,2;A\$—Write variable A\$ to record 2 of random access file 1.
- LPRINTER WIDTH 72—All data will be printed on hard copy device instead of console. Line length is a maximum of 72 characters.
- CONSOLE—All data will be printed on console device (opposite of above command).

In the routine beginning at line 7000 change:

IF MATCH(CHECK.DATES\$,DUE.DATES\$,1)GT 0

to:

IF LEFT\$(DUE.DATES\$,2)EQ LEFT\$(CHECK.DATES\$,2)

Fig. 2. A guide to modifications.

OPTION (?=LIST OPTIONS)? G
PRINT ON TTY? Y

ACN	ACCOUNT	TOTAL	BALANCE	DATE DUE
2	XENON POWER CO.	\$12.00	\$12.00	03/22/78
3	WATCHDOG INSURANCE	\$48.50	\$23.50	03/12/78
4	BAD GUYS DEPT. STORE	\$57.82	\$57.82	03/09/78
		\$93.32		

OPTION (?=LIST OPTIONS)? H
FOR CASH OR MISCELLANEOUS? MISC
CHECK FOR WHAT? KILOBAUD SUBSCRIPTION *** NOTE MISPELLING ***
AMOUNT OF CHECK? 195.00
CHECK NUMBER? 106
DATE WRITTEN? *** NOTE: SPACE ENTERED INSERTS CURRENT DATE ***

OPTION (?=LIST OPTIONS)? I
CURRENT ACCOUNT TO BE EDITED? NO
ACCOUNT NUMBER? -1

-1 KILOBAUD SUBSCRIPTION \$195.00 106 03/04/78

THIS TO BE EDITED? Y
CHANGE WHAT FIELD? 2
RETYPE FIELD 2 ? KILOBAUD SUBSCRIPTION *** MISPELLING CORRECTED ***
(Note my sense of humor.)

Sample 3. Functions G, H, I and J.

Program listing.

```

100 REM *****
101 REM PERSONAL ACCOUNT SYSTEM
102 REM JAMES MCCLURE
103 REM JANUARY 1978
104 REM *****
105 REM THESE NEXT FEW LINES CHECK TO SEE IF THE TWO DATA FILES
106 REM EXIST. IF NOT, THEY ARE CREATED AND INITIALIZED TO EMPTY.
107 IF END # 1 THEN 150
108 OPEN "CURRENT.DAT" RECL 72 AS 1
109 GOTO 175
110 CREATE "CURRENT.DAT" RECL 72 AS 1
111 PRINT # 1,172
112 CLOSE # 1
113 CREATE "HISTORY.DAT" RECL 72 AS 1
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150

```



```

175 PRINT # 1,1;2
    REM FORMAT STRINGS
    HD$="ACN ACCOUNT TOTAL BALANCE DATE DUE"
    F3$="ACN ACCOUNT TOTAL CHK NUM CHK DATE"
    F3$="ACCOUNT NUMBER ## IS /...../"
    F3$="....."
    F3$="...../SS###.## SS###.## /.....y
    F3$="## /...../SS###.## ### /.....y
    INPUT "TODAY'S DATE?";DATE$
200 PRINT
    PRINT "ACCOUNTS PAYABLE SYSTEM";TAB(50);"DATE: ";DATE$
    PRINT:PRINT:PRINT
    PRINT "ALLOWABLE OPTIONS ARE:"
    PRINT
    PRINT "A=ENTER NEW ACCOUNT";TAB(40);"E=LIST CURRENT ACCOUNTS"
    PRINT "C=LIST SPECIFIC ACCOUNT";TAB(40);"D=LIST ACCOUNT HISTORY"
    PRINT "E=PAY BILL";TAB(40);"F=ENTER NEW BILL"
    PRINT "G=PRINT BILLS DUE THIS MONTH";TAB(40); \
    PRINT "H=WRITE CHECK (NOT FOR BILL)"
    PRINT "I=EDIT AN ACCOUNT";TAB(40); \
    PRINT "J=RETURN TO DISK OPERATING SYSTEM"
    PRINT:PRINT:PRINT
    INPUT "OPTION (?=LIST OPTIONS)?";OPTIONS$
    IF OPTIONS$="" THEN 200
    OPTION=ASC(OPTIONS$)-64
    IF OPTION LT 1 OR OPTION GT 10 THEN 300
    ON OPTION GOSUB 2000,1000,3000,4000,5000, \
    6000,7000,8000,9100,9999
    GOTO 300
300 PRINT
    GOTO 300
    REM *****
    REM LIST CURRENT ACCOUNTS
    REM *****
    GOSUB 9000
    OPEN "CURRENT.DAT" RECL 72 AS 1
    READ # 1,1;RECORDS
    PRINT "DATE: ";DATE$
    PRINT
    GOSUB 9100
    TOTAL=0
    FOR RECORD=2 TO RECORDS-1
        GOSUB 10000 REM READ RECORD
        TOTAL=TOTAL+BALANCE
    NEXT RECORD
    PRINT TAB(38);"TOTAL USING "SS###.##";TOTAL
    PRINT
    CLOSE 1
    RETURN
    REM *****
    REM PAY A BILL
    REM *****
    INPUT "ACCOUNT NUMBER?";ACCOUNT.NO
    OPEN "CURRENT.DAT" RECL 72 AS 1
    RECORD=ACCOUNT.NO+1
    GOSUB 10000 REM READ RECORD
    PRINT USING F3$;ACCOUNT.NO,ACCOUNTS
    PRINT USING "BALANCE DUE SS###.##";BALANCE
    INPUT "AMOUNT OF PAYMENT?";PAYMENT
    INPUT "PAYMENT BY CHECK?";RESS
    IF LEFTS(RESS,1) EQ "N" THEN \
        CHECK.NO=0 : \
        INPUT "DATE OF PAYMENT?";CHECK.DATES : \
        GOTO 5100
    INPUT "CHECK NUMBER?";CHECK.NO
    INPUT "DATE OF CHECK?";CHECK.DATES
    IF LEN(CHECK.DATES) EQ 0 THEN CHECK.DATES=DATE$
    BALANCE=BALANCE-PAYMENT
    GOSUB 11000 REM WRITE ADJUSTED RECORD
    CLOSE 1
    OPEN "HISTORY.DAT" RECL 72 AS 1
    READ # 1,1;RECORD
    TOTAL=DUE+PAYMENT
    BALANCE=CHECK.NO
    DUE.DATES=CHECK.DATES
    GOSUB 11000 REM WRITE HISTORY RECORD
    RECORD=RECORD+1
    PRINT # 1,1;RECORD
    CLOSE 1
    RETURN
    REM *****
    REM ENTER NEW BILL TO BE PAID
    REM *****

```

```

3000 REM *****
    REM LIST SPECIFIC ACCOUNT
    REM *****
    INPUT "ACCOUNT NUMBER?";ACCOUNT.NO
    GOSUB 9000
    OPEN "CURRENT.DAT" RECL 72 AS 1
    RECORD=ACCOUNT.NO+1
    GOSUB 10000 REM READ RECORD
    PRINT HD$ REM PRINT HEADER
    PRINT
    GOSUB 11500 REM WRITE RECORD
    CLOSE 1
    RETURN
    REM *****
    REM LIST ACCOUNT HISTORY
    REM *****
    INPUT "ACCOUNT NUMBER?";ACCOUNT.NO
    GOSUB 9000
    OPEN "HISTORY.DAT" RECL 72 AS 1
    READ # 1,1;RECORDS
    TOTAL=0
    PRINT "DATE: ";DATE$
    PRINT
    PRINT HC$
    PRINT SP$
    PRINT
    FOR RECORD=2 TO RECORDS-1
        GOSUB 10000 REM READ RECORD
        IF ACCOUNT EQ ACCOUNT.NO THEN \
            PRINT USING F2$;ACCOUNT,ACCOUNTS,TOTAL,DUE,BALANCE,DUE.DATES : \
            TOTAL=TOTAL+TOTAL.DUE
    NEXT RECORD
    REM CONTINUE
    GOSUB 9200
    PRINT TAB(28);"PRINT USING "SS###.##";TOTAL
    PRINT
    CLOSE 1
    RETURN
    REM *****
    REM PAY A BILL
    REM *****
    INPUT "ACCOUNT NUMBER?";ACCOUNT.NO
    OPEN "CURRENT.DAT" RECL 72 AS 1
    RECORD=ACCOUNT.NO+1
    GOSUB 10000 REM READ RECORD
    PRINT USING F3$;ACCOUNT.NO,ACCOUNTS
    PRINT USING "BALANCE DUE SS###.##";BALANCE
    INPUT "AMOUNT OF PAYMENT?";PAYMENT
    INPUT "PAYMENT BY CHECK?";RESS
    IF LEFTS(RESS,1) EQ "N" THEN \
        CHECK.NO=0 : \
        INPUT "DATE OF PAYMENT?";CHECK.DATES : \
        GOTO 5100
    INPUT "CHECK NUMBER?";CHECK.NO
    INPUT "DATE OF CHECK?";CHECK.DATES
    IF LEN(CHECK.DATES) EQ 0 THEN CHECK.DATES=DATE$
    BALANCE=BALANCE-PAYMENT
    GOSUB 11000 REM WRITE ADJUSTED RECORD
    CLOSE 1
    OPEN "HISTORY.DAT" RECL 72 AS 1
    READ # 1,1;RECORD
    TOTAL=DUE+PAYMENT
    BALANCE=CHECK.NO
    DUE.DATES=CHECK.DATES
    GOSUB 11000 REM WRITE HISTORY RECORD
    RECORD=RECORD+1
    PRINT # 1,1;RECORD
    CLOSE 1
    RETURN
    REM *****
    REM ENTER NEW BILL TO BE PAID
    REM *****

```



```

INPUT "ACCOUNT NUMBER?";ACCOUNT.NO
OPEN "CURRENT.DAT" RECL 72 AS 1
RECORD=ACCOUNT.NO+1
GOSUB 1000
PRINT USING F3$;ACCOUNT.NO,ACCOUNT$
INPUT "AMOUNT OF BILL?";TOTAL.DUE
INPUT "DATE DUE?";DUE.DATES
BALANCE=BALANCE+TOTAL.DUE
PRINT USING "NEW BALANCE IS $$$$#.##";BALANCE
GOSUB 1100
CLOSE 1
RETURN
REM *****
REM BILLS DUE THIS MONTH
REM *****
GOSUB 9000
OPEN "CURRENT.DAT" RECL 72 AS 1
READ # 1,1;RECORDS
CHECK.DATES=LEFT$(DATES,3)*"##"/"+RIGHT$(DATES,2)
TOTAL=0
GOSUB 9100
FOR RECORD=2 TO RECORDS-1
    GOSUB 10000
    IF MATCH(CHECK.DATES,DUE.DATES,1)GT 0 THEN GOSUB 11500:
    TOTAL=TOTAL+BALANCE
NEXT RECORD
GOSUB 9200
PRINT TAB(38);
PRINT USING "$$$$#.##";TOTAL
PRINT
CLOSE 1
RETURN
REM *****
REM WRITE A CHECK FOR CASH OR MISC
REM *****
INPUT "FOR CASH OR MISCELLANEOUS?";ACCOUNT$
IF LEFT$(ACCOUNT$,1) EQ "C" THEN \
    ACCOUNT=0:ACCOUNT$="CASH" \
ELSE \
    ACCOUNT=-1
IF ACCOUNT=-1 THEN \
    INPUT "CHECK FOR WHAT?";ACCOUNT$
    INPUT "AMOUNT OF CHECK?";TOTAL.DUE
    INPUT "CHECK NUMBER?";BALANCE
    INPUT "DATE WRITTEN?";DUE.DATES
    IF LEN(DUE.DATES) EQ 0 THEN DUE.DATES=DATES
    OPEN "HISTORY.DAT" RECL 72 AS 1
    READ # 1,1;RECORD
    GOSUB 11000 REM WRITE RECORD
    PRINT # 1,1;RECORD+1
    CLOSE 1
    RETURN
REM *****
REM EDIT AN ACCOUNT RECORD
REM *****
INPUT "CURRENT ACCOUNT TO BE EDITED?";RESS
IF LEFT$(RESS,1) NE "Y" THEN 8200
INPUT "ACCOUNT NUMBER?";ACCOUNT.NO
OPEN "CURRENT.DAT" RECL 72 AS 1
READ # 1,1;RECORDS
RECORD=ACCOUNT.NO+1
IF RECORD GE RECORDS THEN 8900
GOSUB 10000
PRINT
GOSUB 11500
PRINT
INPUT "THIS TO BE EDITED?";RESS
IF LEFT$(RESS,1) EQ "N" THEN 8900
GOTO 8300
IF LEFT$(RESS,1) NE "N" THEN 8100
INPUT "ACCOUNT NUMBER?";ACCOUNT.NO

```

```

OPEN "HISTORY.DAT" RECL 72 AS 1
READ # 1,1;RECORDS
FOR RECORD=2 TO RECORDS-1
    READ # 1,RECORD;ACCOUNT
    IF ACCOUNT.NO EQ ACCOUNT THEN 8250
NEXT RECORD
GOTO 8900
GOSUB 10000
PRINT
PRINT USING F2$;ACCOUNT,ACCOUNT$,TOTAL.DUE,BALANCE,DUE.DATES
PRINT
INPUT "THIS TO BE EDITED?";RESS
IF LEFT$(RESS,1) EQ "N" THEN 8225
INPUT "CHANGE WHAT FIELD?";FIELD
PRINT "RETYPE FIELD";FIELD:
IF FIELD EQ 2 THEN INPUT ACCOUNT$
IF FIELD EQ 3 THEN INPUT TOTAL.DUE
IF FIELD EQ 4 THEN INPUT BALANCE
IF FIELD EQ 5 THEN INPUT DUE.DATES
GOSUB 11000
CLOSE 1
RETURN
PRINT "ACCOUNT NOT FOUND"
CLOSE 1
RETURN
STOP
REM *****
REM TTY QUESTION
REM *****
INPUT "PRINT ON TTY?";RESS
IF LEFT$(RESS,1) EQ "Y" THEN LPRINT WIDTH 72
PRINT
RETURN
REM *****
REM PRINT HEADER
REM *****
PRINT HD$
PRINT SP$
PRINT
RETURN
REM *****
REM PRINT TRAILER
REM *****
PRINT
PRINT TP$
RETURN
REM *****
REM RECORD READ SUBROUTINE
REM *****
READ # 1,RECORD;ACCOUNT,ACCOUNT$,TOTAL.DUE,BALANCE,DUE.DATES
RETURN
REM *****
REM RECORD READ FROM CRT SUBROUTINE
REM *****
INPUT "ACCOUNT NAME?";ACCOUNT$
INPUT "TOTAL AMOUNT DUE?";TOTAL.DUE
INPUT "DATE PAYMENT IS DUE?";DUE.DATES
BALANCE=TOTAL.DUE
RETURN
REM *****
REM RECORD WRITE ROUTINE
REM *****
PRINT # 1,RECORD;ACCOUNT,ACCOUNT$,TOTAL.DUE,BALANCE,DUE.DATES
RETURN
REM *****
REM RECORD WRITE TO CRT SUBROUTINE
REM *****
PRINT USING F1$;ACCOUNT,ACCOUNT$,TOTAL.DUE,BALANCE,DUE.DATES
RETURN
END

```


THE BOTTOM SHELF DOES IT ONCE AGAIN!

Library 100 49.50

One hundred useful programs on five cassettes for the Level II TRS-80. The Library 100 is packaged in a notebook size binder, and comes complete with a 46-page instructional documentation manual.

We will replace any tape you can not load. Some programs require 16K.

BUSINESS AND FINANCE - 25 PROGRAMS
EDUCATION - 15 PROGRAMS
GRAPHICS - 15 PROGRAMS
HOME - 15 PROGRAMS
GAMES - 30 EXCITING PROGRAMS

Checkbook II 18.50

In the tradition of quality software that looks as good as it works. The Bottom Shelf is proud to offer this exceptional new program.

FEATURING:

- * Five column keyboard inputs to \$100,000.00.
- * Checkbook balancing with balance brought forward always in memory and recorded on tape.
- * Search and Total by any field except amount.
- * Bank reconcile with listing of outstanding checks.
- * 75 checks held in memory in 16K and 400 in 32K.
- * Plus much more. Fun and easy to use.

Basic Toolkit 19.80

- Search a basic program, and print out to the screen or to paper, an alphabetized list of the variables used in the program and the line numbers they appear in.

- Search a basic program, and print out to the screen or to paper, a list of the Goto's/ Gosubs and the line number they appear in.

- Will MERGE PROGRAMS ON A CASSETTE BASED SYSTEM

Systems Extension 3.00

A MUST FOR EVERY COMPUTER OWNER

Systems Extensions is published and marketed by TBS, creators of the LIBRARY 100. The articles published in Systems Extensions were written by our staff of TOP QUALITY PROGRAMMERS at TBS, to aid you with your computer. Also incorporated in this publication is a group of over 300 items designed to support your computer system.

Cassettes 1.90 3 for 5.40

TBS QUALITY CASSETTES

Our cassettes are designed specially for use in RADIO SHACK'S TRS-80 and other audio based computers. TBS backs its cassettes with a 90 day warranty against parts and material defects. TBS has equipped its cassettes with special features for you: sliding write protect tabs, extra large pressure pad and a 5 screw assembly. These cassettes are of TBS quality, built for your convenience in your TRS-80 or other audio based computers.

Diskettes Box of 10 - 38.00

New from TBS and Wabash Tape Corp. TBS, the leading name in TRS-80 software, and Wabash, a leading name in computer magnetic recording materials, presents, for your microcomputer disk system, 5 1/4" mini diskettes.

Only TBS and Wabash can assure you that each diskette has been individually certified, and certified to 3200 BPI! Further, EACH one is guaranteed for one year after purchase.



The Bottom Shelf
P.O. Box 49104
Atlanta, Georgia
30359

✓ B33

Phone: 404-939-6031 (COD, MC, VISA)

Building a New Horizon

After scanning the microcomputer landscape, this computerist settled on the Horizon.

Michael D. O'Brien
509 Jersey Lane
Security CO 80911

My search for a computer has ended in the purchase of a North Star Horizon II. The reason for my selection is strictly another story. This article is confined to the construction of the system and its highlights and shortcomings.

Introduction

Upon opening the inner box, I found a neatly packaged box that contained all of the parts in plastic bags. The Shugart drive was packed in its own Styrofoam unit and placed within the "protective hands"

of the wood cover and the chassis sheet metal. Packaged in a double box, the unit was amply protected by two inches of space from all but the roughest shipper's hands. The quality is evident, right down to the heavy plastic parts bags.

Although the outer box was stamped "transformer may be in a separate box," the transformer was packed inside the inner box in a separate, heavy cardboard container. Presumably, the transformer would be packaged separately for a dual-risk configuration; the area vacated by the transformer would be used to pack the second disk drive.

I know, I said that I bought a Horizon II and you want to know why I only received one


drive. I bought a Horizon I and also bought the second drive at the same time to make a Horizon II. I also bought the system from a local source, and the only configuration they sell in one box is the single drive Horizon I. To get a Horizon II you must buy a Horizon I and buy the second disk unit at the

same time to get the price for a Horizon II.


From experience, I have found that few companies are capable of error-free documentation. For this reason, you should follow North Star's instructions and read the entire assembly manual making pencil notes for any errata sheets




The finished product. Note the clean design and walnut veneer cover. I chose to adhere the name plate in the upper instead of the lower left-hand corner.




The 16K dynamic RAM board. It runs with zero wait states at 4 MHz.



The completed Z-80 CPU board. The area enclosed within the dotted line in the central area of the board is for an optional, user-supplied PROM designed for "RESET and GO."



View of the fully populated motherboard. Note the heavy ground plane area between the 100-pin connectors.



The disk controller board with the ribbon cable attached must reside in slot nine. Note also the heavily heat-sinked regulators and the quick-disconnect power-supply leads.

included with your system. If ever I receive documentation without errata sheets, I write or call the company to verify that there are indeed no errors in their manuals. So far, I have not found an error-free manual.

Assembly


After I read the documentation, noting the errors, etc., it was time to clear a working area to build the system. Nothing fancy is required... just pick a place that is well-lighted and free from little gremlins and immaculate housekeepers.

As I proceeded to follow the directions, I found the instruc-

tions to be complete, with adequate photos of how the finished work should look. The only thing lacking, in my opinion, is little checkoff boxes to help you keep track of where you are (a la Heathkit).

The only tools required for assembly of the chassis/power supply are the usual assortment of screwdrivers, nutdrivers, pliers and a box wrench. The wrench is used to hold a couple of nuts in two or three hard-to-get-at places. It is also used to tighten the 1/4 inch bolts that are used to anchor the transformer to the chassis.

Locating the correct wire for the power supply is extremely



The completed disk controller board.



Rear panel view of the completed chassis. The upper-right side shows the eight cutouts for DB-25-type connectors and the four holes used for phono-type jacks. The lower-right area of the panel shows the two serial-port connectors on the right and the parallel-input and parallel-output connectors to the left of the serial port jacks.

simple. North Star has provided pre-cut and crimped wires and terminals. You are only required to locate the wire according to length, color and terminal type and put a wire marker on one end of the wire. Locating components is easy too. Each plastic bag is marked with the name of the section you are working on at the time.

A quick look when you take an inventory will show the quality of the individual components. The printed circuit boards are double-sided with plated-through holes, soldermask and component orientation silk screening. The contact fingers are gold-plated, as are the IC sockets.


The disassembly, should it ever be necessary to remove the motherboard, is very simple. You need only pull the quick-disconnect wires and unfasten the mounting screws.

The board slips right out of the chassis. This feature makes it easy to add a connector, serial or parallel I/O port (the motherboard handles two serial and a parallel input and parallel output port directly on the board itself).


The assembly manual, if followed to the letter, will step you through the assembly and, at the proper time, tell you to check component orientation or measure voltages.

The sequence of assembly usually proceeds in the following order:


1. Assemble a portion of the circuit and check for shorts or opens with a volt-ohm milliammeter.
2. Measure voltages without components (ICs) in their sockets.
3. Insert components into their sockets and check for correct orientation. (Only TTL ICs are



The chassis with my current circuit-board configuration. The compact design and efficient layout are quite evident.



This is the "minimum configuration" for a dual-disk Horizon: two disk drives, chassis, power supply, CPU, 16K of dynamic RAM and a disk controller board.



The famed Econoram II from Godbout. Using static RAMs, it runs without wait states at 4 MHz.

inserted to this point.)

4. Measure voltages again.
5. Insert MOS/LSI components and check orientation.
6. Measure voltages.

This procedure basically illustrates that it is cheaper to replace TTL than MOS/LSI components if you have made an error. Usually, if you have made it to step three, there is only one mistake that you can make, and that is to put a chip in backwards.

At this point, the chassis and power supply have been assembled, and the motherboard has been checked and installed. The assembly manual next instructs you to refer to the assembly manuals for the Z-80 processor board and the 16K RAM board for their assembly, configuration and checkout. These manuals step you through the assembly in the same fashion as the

Horizon assembly manual.

Checkout

To complete the assembly of your new system, build the disk controller board following the instructions in the main assembly manual. Again, the superb directions will just about prevent you from failing if you follow them exactly.

Now for the moment of truth. (Notice that I did not say "smoke test.") You continue to follow the instructions in the manual for the System Checkout Procedures.

Assuming that there are no errors in the software or any problems with the diskette itself, you are finally given directions to sit back, relax and pat yourself on the back for a job well done. And that, in truth, is exactly what happens. I know because I built a new Horizon and it worked the first time I tried.

Kudos and Criticisms


Kudos go to North Star for their vision in several areas: First, the use of DIP headers to allow the system to be configured to the individual's needs. This includes the I/O ports for EIA or TTY (20 mA), the baud rates and the real-time clock. You can even configure the serial ports for synchronous operation should you desire. The second area is the rear panel. It comes prepunched for no less than eight DB25-type connectors, none of which are used for the standard serial port that is included with the system. Also, the back panel has punched holes for

four circular connectors such as the RCS phono type.

If you are really going to expand, the addition of a third drive is easy. Although the third drive is not housed on the main-frame, expansion is a standard feature. There is a cutout on the rear panel for a connector into which the third drive's interface cable plugs. This will allow the system to be expanded without any messy cables between the cover and the metal chassis.

The Horizon has a cooling fan that is extremely quiet. In operation, the fan does its job without telltale offensive noise.

I mention a few criticisms as an addition to the documenta-



The cutout at the lower left is for the third disk-drive connector. The switch at the upper left is for reset. Just below that is the power switch. Under the fan is the integral ac connector and line filter.

tion rather than due to a lack of information. My opinion is that North Star needs to include more step-by-step information for the novice. I think this statement requires an elaboration of the specific shortcomings that a novice might find difficult to understand.


First, the manual refers to "personalization" and the "personalized version of BASIC" in several places. This might lead a newcomer to believe that several changes or modifications must be made to BASIC in order to get the system checked out. It may not be obvious to the novice that to make

for the right page of the manual.

My raising these points may make me appear a nitpicker, however, any time there is a possibility of confusion, the Gaelic lawmaker will strike.

I will reserve some other comments regarding the actual personalization of the software for a later time. North Star has announced the production of a manual called "North Star System Software," which will probably resolve those comments.

It is worth noting that I have personally witnessed the use of several S-100 compatible



BASIC Software

- 76 tested, working programs
- BASIC listings compatible with most micro-computer BASIC's
- Complete source listings, with remarks
- A general selection of math, statistics, personal finance and general interest topics

These programs are published in *Some Common BASIC Programs*, by Lon Poole and Mary Borchers. *Some Common BASIC Programs* is designed for people who can use a variety of practical BASIC programs. The book includes program descriptions, sample runs, and source listings with remarks. The documentation is complete so that a minimum of programming knowledge is required in order to use the programs. (200 pp., softbound, \$8.50.)*

For PET Users, the PET Cassette

If you use a Commodore PET, you have probably realized that many BASIC programs require modification in order to run optimally on the PET. We have done the reprogramming necessary for *Some Common BASIC Programs*' programs to conform to the PET's BASIC syntax, calculation accuracy and video display, and now offer these listings for purchase on our PET Cassette.

If you don't already own a *Some Common BASIC Programs* book, we urge you to purchase one for program documentation and user instructions. (PET Cassette - \$10.00 each.)

*** GUARANTEE ***

We warrant each PET Cassette to be free from defects in material and manufacture.

Osborne & Associates, Inc.

Name: _____

Address: _____

City: _____

State: _____ Zip: _____ Phone: _____

SHIPPING (Shipping for large orders to be arranged)

Books:

- ☐ All foreign orders \$4.00 per book airmail
- ☐ \$0.45 per book 4th class (allow 3-4 weeks)
- ☐ \$0.75 per book UPS (allow 10 days USA)
- ☐ \$1.50 per book rush shipment by air

Cassettes:

- ☐ All foreign orders \$1.50 per cassette
- ☐ No charge in the U.S.A.

PET Cassette - *Some Common BASIC Programs*

Some Common BASIC Programs book

Price	Quantity	Amount
\$10.00		
8.50		
		Shipping charges
		TOTAL


- ☐ Payment enclosed California residents tax (6-1/2% BART, 6% other)
- ☐ Bill me (\$70.00 minimum - approved accounts only)

OSBORNE & ASSOCIATES, INC.
630 Bancroft Way, Dept. D14
Berkeley, CA 94710

Dealer inquiries invited.

*Price increases to \$9.50 July 1, 1979.

S1027



The mighty power-supply filters. The pre-terminated wires make the assembly an easy task.

these changes to BASIC (to personalize it) requires an operational system.

Therefore, to check out the system, you must have the system properly configured and have a good copy of the software on diskette. Several possibly confusing points could be cleared up with the inclusion of a summary of items that must be accomplished prior to the actual start of the system checkout.

The addition of a table in the manual would also be helpful. This table should be a total listing of the possible DIP header configurations for the system. This would be useful because at the present time the configurations are scattered throughout the manual in different areas. The inclusion of a table would make it easier to change the configuration without bothersome searching

boards in a Horizon. These boards included an ac controller, a Compu-talker and an automatic dialing modem. In addition, I personally use two Godbout 8K Econoram II boards running at 4 MHz with zero wait states.

Summary

I am quite pleased with the performance and capabilities of my Horizon II. The ease of construction, quality of material, flexibility of use and reasonable price make the North Star system worth owning. This statement is borne out by a North Star advertisement in the October 1978 issue of *Kilobaud*: "Over 10,000 users during the past two years have proven that North Star hardware has the reliability for day-in, day-out computing."

For my money, this is the way to build a new Horizon. ■

Microcomputers and TVI

If you have ever encountered television interference—and what microcomputer owner hasn't had that happen at one time or another?—there is an effective way to combat it.

TVI does not stand for television Interface, nor does it mean intentionally using your home TV as a graphics terminal for your computer. TVI does stand for television interference, and, like bad breath, many of us have it but don't know it . . . others of us know it but don't know what to do about it.

Television interference is an old enemy to us amateur radio operators. Amateur, and other, radio transmitters send out voice modulated signals that can be heard and understood on stereos, broadcast band radios and telephones and can be heard and seen on televisions.

Objective investigation has proven that the vast majority of this interference is the "fault" of receivers (stereos, TVs, etc.) that are not properly protected from strong radio frequency energy fields. Despite this, hams (and, recently, CB operators) have become the victims of neighborhood harassment, assaults and lawsuits because of interference seemingly caused by their equipment. Computer operators are luckier in some ways, but our situation is more perilous in others.

The Real Foe

As a young second lieutenant in the U.S. Air Force, I was fascinated by the bumbles,

squeaks and bursts coming from an ordinary AM radio when it was placed anywhere near the SAGE computer. But SAGE was huge—it used thousands of tubes with high voltage and signal levels and lots of power. (A three-story-block square building in Montana was heated with just the air blown over the 60,000 tubes!)

I was quite surprised, a dozen years later, to hear the identical sounds out of a radio across the room from my sophisticated low-power home computer. I was even more surprised to see the wavy lines moving across the test patterns of several local TV stations. I have now come to understand that com-


puter CPUs, because of their high-speed operation, are dirty polluters of the radio energy spectrum. In several ways, this pollution, or interference, is worse than that caused by high-power radio transmitters.

Radio operators are only interested in transmitting on one narrow frequency at a time; therefore, they can use sharply tuned circuits to reduce all other frequencies being generated. Computer operators want high speed, which means wide bandwidth and, hence, many frequencies being generated and mixed together with little attenuation. Some of these frequencies fall right into the bands that television sets and AM radios were designed to receive.

We cannot fall back on the claim that consumer-marketed receiving equipment is not properly protected from interference. Instead, we must recognize that we are infringing where we don't belong. Fortunately, our neighbors (and even our families) usually don't associate the lines marching across Donny and Marie's perfectly chiseled, gleaming teeth with our home computers, but if they ever do . . . hell hath no fury like an irate TV viewer.


Combatting TVI

Testing to determine if you have TVI is easy. Turn on your computer and your family TV set. Start the computer loading a lengthy program and check all of the TV channels. Interference from the computer will usually show up as a pattern of fine wavy lines across the picture from one or more TV sta-





With the switch off on a commercial Z-80-based microcomputer in the same room, the TV picture is free from interference.



Power on the CPU puts cross-hatch on the screen.

tions. If you see any sort of interference, shut down the computer and look again. If the interference disappears, you have a problem. If you don't have any interference, you are lucky... this time.

There are two places to attack television interference: at the computer and at the TV itself. Certain actions can be taken during the design of the computer printed circuit boards, and some component quality-control checks will decrease harmonic generation and radiation. As the industry matures, these changes will come about. I hope they will not have to be legislated or regulated by a governmental agency.

We can keep the radio energy that is produced tucked away where it cannot radiate. Four actions can be taken to contain radio energy: shielding, bypassing, choking, grounding.

Shielding

Almost all microcomputers on the market can stand to have their shielding improved. Those with substantial metal cabinets have the best basis for a "clean" operation. The cabinet itself should make a solid electrical connection between all of its parts. It may be necessary to scrape some paint off of the mating pieces and drill some holes for additional sheet metal screws to ensure this.

Manufacturers worry about proper cooling (as well they should), so they usually put in

many holes or slots for air to pass through. These openings also let a lot of radio energy out.

The easiest way to plug these rf leaks is with good quality copper or aluminum window screen. The screen can be laid over the holes or slots without hampering the cooling; it should have plenty of overlap on the inside. The screen should be sturdily secured to the cabinet so that it makes a good electrical connection. Every gap or hole (including the fan hole) should be plugged the same way.

People with computers that have plain plastic or wonderful wood cabinets have a much larger task. Their best friend is heavy-duty aluminum foil. Aluminum foil and screening can be formed inside the cabinet and securely fastened with staples, tape or screws. Overlap and electrical connection between the shielding material and the cabinet is important. No space larger than one square centimeter should be left uncovered.

Bypassing/Choking

After the scraping, bonding and shielding, we can assume that the rf will stay in the cabinet if we don't provide it with any other means of escape. Unfortunately, we need to get data and power in and out of the machine. This means that connections and leads are needed for keyboards, tapes, disks, CRTs

and the ac line. These leads serve as antennas that broadcast unwanted signals far and wide.


The ac power cable is the easiest, but also the most important, challenge. Three wire plugs (with the center pin grounded to the chassis) and internal bypass capacitors seem to be standard in the industry. You should check the visual appearance of the .01 or .05 uF capacitors that go from each side of the ac line to chassis ground. If they appear cracked or scorched, then the high ac duty cycle may have gotten to them, and they should be replaced.

The bypass capacitors normally do a fine job of taking the rf off the ac line. If they aren't there or aren't functioning


properly, the house wiring can become an ideal transmission and antenna system for radiating unwanted signals.

The video cable feeding the typical TV monitor is shielded coax, so any stray radiation should be contained within the shield. If an rf converter is being used to feed a standard TV set, the converter should be housed in a shielded box, and the input and output circuits should be arranged so that a minimum of coupling can take place between them. Do not attempt to shield the TV set in any way. That could be dangerous and unnecessary.

The cable going to a keyboard is difficult to deal with, but the leads going to floppy disks and other peripheral devices are the most difficult of



The pattern on this screen is typical of an interfering signal on or near the frequency of the TV station. This interference is caused by the harmonics of the 8080A CPU.



Copper braid from RG-8 coaxial cable is expanded to hold ribbon cable. Even though these cables usually have alternate grounded wires, full shielding greatly reduces radiation.

all. We could go for fancy bypassing and/or choking of each lead going to these devices, but we may create some very real problems with wave shapes and delay. I prefer the less elegant, but just as effective, method of shielding the entire cable.

Shielded multiconductor cable is expensive and often difficult to find. An effective substitute is easily made using the shielding from RG-8 or any other .4 inch coaxial cable. Hams and CBers in the neighborhood will often have short lengths of this cable around the house. Tell them that it starts to age and change its electrical properties after a few years (it does!) and that you would be happy to take some of the old stale pieces off their hands.

Use a sharp knife to slit the outer covering of the cable and peel it back like a banana. You can then press the braid together from each end and easily pull out the white coaxial inner conductor. Keep this braid fat and don't let it get flat. By trading length for circumference, it can fit over many different kinds of leads, including multiconductor ribbon cable.

The shield should be firmly grounded to a chassis at both ends. Shielding the cable in this manner changes its characteristic impedance, but in actual operation with three different systems no electrical problems have been encountered. Also, the neat braid-covered

wire going to the keyboard and floppy disk drive doesn't detract from the appearance of my computer one bit.

Grounding

Grounding the rf energy, that is, sending it into the earth so that it doesn't radiate through space, is an important step in curing TVI. Your computer is probably grounded electrically through its three-wire plug, but some or all of your peripherals may not be. Either way, the ground path provided through the house wiring is certainly long, circuitous and probably not very effective for rf.

A short, heavy-gauge wire run directly to a metal cold-water pipe may be the solution. If you are blessed with only plastic water pipes, then a ground rod of copper or galvanized pipe driven into the soil at least 4-6 feet might do. The telephone company often connects to a ground somewhere near their entry point. Their connection might give you some ideas.

All of the transformer-powered elements of your computer system should have their chassis connected together by a single direct wire. Braid left over from shielding or braid from the smaller RG-58 type coax is ideal. This separate, direct connection avoids "loops" in the other electrical leads that might trap and radiate rf.

Getting at the "chassis" on some cassette recorders may

be tricky. Some units do not use chassis ground as either side of the audio circuit, so simply attaching to the outside jacks will not do. You may have to go in and look for the negative bus on the printed circuit board.

Beware of transformerless TV sets. Don't ever go near those things with any sort of ground lead. Half the time the results are shocking.

Stronger TV Signal

Your computer system should now be holding in all that nasty rf it is generating and sending it off through a ground lead into the earth so that it can't radiate into anyone's TV set. However, there are limits to the effectiveness of even these measures. There is another end to the problem that could use some attention. That is the end at the TV set itself.

With some types of TVI, traps or filters can be installed at the TV set, which would block out the offending signal. But in this case, the offending signal is at the same frequency as the TV signal we want, so filters on the antenna lead won't work.

The most effective thing that can be done at the TV is to increase the signal-to-interference ratio. The TV station signal is big and powerful compared to the radiations from a microcomputer. The computer is simply closer.


Any improvement that can be made in your TV antenna so



Cable shielded with external braid doesn't hurt the looks of this installation.

that it will deliver more of the desired signal from the TV station will be worthwhile. A stronger TV signal will reduce the automatic gain control in the TV, and the interfering signal may disappear from the set. Get rid of the rabbit ears and install a good outside antenna with some gain and directivity. Check the quality of your lead-in wires and antenna.

Does the lead-in pass just outside the wall where the computer sits? Buy cable TV if you have to, but give the TV station every opportunity to override any residual-radiated signal coming from the computer. The improvement in the TV picture even with the computer off will be worth the investment. ■



Copper screening over the vent holes cuts down on the radiation from this cabinet. Additional screw holes were made in the cabinet and front panel to hold the screen in place.

\$15
OFF

SAVE
50%

SAVINGS CERTIFICATE

ONE YEAR (12 ISSUES)
FOR ONLY \$15.

Invest in the new **Kilobaud Microcomputing!**
Earn big dividends every month and get one
year (12 issues) for only \$15 by taking advan-
tage of this discount offer. Mail this certifi-
cate now and save 50% off the \$30 newsstand
price. Rates apply in the U.S.A. & Canada on-
ly. Foreign one year subscriptions are \$23
payable in U.S. currency.

☐ Payment enclosed

☐ Bill me

Name _____


Address _____

City _____


State _____ Zip _____

Kilobaud Microcomputing
Subscription Services Department
P.O. Box 997 • Farmingdale NY 11737

B961



NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES



BUSINESS REPLY CARD
FIRST CLASS PERMIT NO. 17 PETERBOROUGH NH 03458

POSTAGE WILL BE PAID BY ADDRESSEE

kilobaud

MICROCOMPUTING

Subscription Department • Box 997
Farmingdale NY 11737

NEW!



**WHY CUT?
WHY STRIP?
WHY SLIT?**

WHY NOT...

JUST WRAP™



U.S.A.
FOREIGN
PATENTS
PENDING

- AWG 30 Wire
- .025" Square Posts
- Daisy Chain or Point To Point
- No Stripping or Slitting Required
-JUST WRAP™....
- Built In Cut Off
- Easy Loading of Wire
- Available Wire Colors:
Blue, White, Red & Yellow

***\$14⁹⁵**


JUST WRAP TOOL WITH
ONE 50 FT. ROLL OF WIRE

COLOR	PART NO.	U.S. LIST PRICE
BLUE	JW-1-B	\$14.95
WHITE	JW-1-W	14.95
YELLOW	JW-1-Y	14.95
RED	JW-1-R	14.95




REPLACEMENT ROLL OF
WIRE 50 FT.

BLUE	R-JW-B	2.98
WHITE	R-JW-W	2.98
YELLOW	R-JW-Y	2.98
RED	R-JW-R	2.98



DAISY CHAIN



POINT TO POINT



MACHINE & TOOL CORPORATION 3455 CONNER ST., BRONX, N.Y. 10475 (212) 994-6600/TELEX 125091

*MINIMUM BILLING \$25.00 / AD SHIPPING CHARGE \$2.00 / NEW YORK CITY / STATE RESIDENTS ADD APPLICABLE TAX.

Translating Between TTL and RS-232C Levels

The following article shows how to easily solve the problem of converting TTL-level signals to RS-232C and vice versa. The answer is to use a very low-cost circuit, and here's how.

F. R. Ruckdeschel
773 John Glenn Blvd.
Webster NY 14580

When Interfacing computer equipment made by various manufacturers, the computerist frequently experiences an annoyance related to the history of computer and communications development: the incompatibility of TTL and RS-232 level signals. The TTL/RS-232C interface problem is often apparent when you attempt to output (or input) serial data to (or from) an RS-232C terminal.

A TTL serial communications signal may originate in several similar ways:

1. TTL data may be loaded into a shift register and stepped out serially.
2. A fancy shift register, such as a UART (universal asynchronous receiver-transmitter), may be loaded with parallel data, which is subsequently transmitted serially.
3. One bit of a parallel output port may be used—in conjunc-

tion with software timing loops—to accept or produce serial TTL input/output signals.

The TTL situation occurs with several of the single board microcomputers, such as the SC/MP-II-based Nibbler sold by Digi-Key. In the case of the Nibbler, you simply add a +5 volt power supply and a reset switch to the single board microcomputer to operate with BASIC, if your terminal accepts TTL-level signals. However, the list of terminals that do not work with serial TTL I/O signals is extensive and includes the SWTP CT-1024 and CT-64, the Mits Compter and Compter II, etc.

My encounters with the problem have included both cases 2 and 3 described above. In case 2, the goal was to interface an old "surplus" Mits S-I/O B TTL-level serial interface to a CT-1024. Also, I wanted to convert to RS-232C the serial TTL signals on a Mits 88-ACR (audio cassette record interface) to check the tone decoding of the tape interface on-line by simply monitoring the decoded TTL signals with a terminal. In case

3, the level conversion involvement was associated with interfacing a Nibbler to a Diablo (and hiding the microcomputer in the base of the printer).

In the discussion that follows, I describe simple circuits for accomplishing the required conversion.

Circuit Design

There exist integrated circuits that are specifically designed to perform the conversion task. For example, the Motorola MC1488 and MC1489 chip set provides four pairs of such conversion units. However, these chips may not be readily available to the Sunday experimenter and are more expensive (about \$2.50 each at the local computer store) than the inexpensive 741 op amp and 7404 hex inverter chips used in the following circuit design.

The conversion to be accomplished is simple. TTL-logic "low" signals must be converted to +12 volts and logic "high" signals to -12 volts. These are not complete signal translator specifications, but they are good enough to work with. The reverse conversion must also be performed.

Fig. 1 shows a simple circuit that converts RS-232C signals

to TTL levels. When the input signal is +12 volts, pin 13 of the 7404 inverter is clamped at 5 volts, or a TTL-logic "high" state. Pin 12 then gives the desired TTL output signal. When the input is -12 volts, pin 13 is held at approximately -0.6 volts, giving a TTL-logic "high" state at pin 12, as required.

Two concerns exist with this design. The first concern is with the input line load. The maximum load occurs for a -12 volt signal—6 mA. This is within accepted load limits and can easily drive the input of the 7404 inverter, which demands about 1.6 mA. This current also does not represent much of a heat-dissipation problem for the zener diode—about 2 mW. However, you should remember that zener diodes are not really designed for forwards conduction. However, in this application there is no problem.

The second concern is the zener diode heat dissipation in the +12 volt input mode. In this case the input current is, perhaps, 3 mA with a zener diode reverse conduction voltage drop of 5 volts—.015 Watts. Again, this is no problem.

The second inverter was added as several are available on the 7404 chip, and it was easy




Photo 1. The completed unit. Note that an 8-pin 741 op amp was used.




Fig. 1. RS-232C-to-TTL-conversion circuit.




Fig. 2. Circuit to convert TTL-logic level signals to RS-232C.

to add the inversion flexibility. The 7404 hex inverter itself was chosen because of its negligible cost and ready availability.

The TTL-to-RS-232C-conversion circuit is shown in Fig. 2. The 741 operational amplifier is used as a comparator. It is powered by a simple ± 12 volt supply derived from a zener diode regulation circuit. A voltage divider provides a 2.1 volt reference input to the op amp. This is compared to the input logic level (or its inverse if desired). The amplifier has a gain of ten, a choice that will be explained later.

If a TTL signal of 3.3 volts or more is placed on the negative input of the op amp (pin 4), the output (pin 10) will go to -12 volts, the negative supply limit. If, instead, the input is 0.9 volts or less, the amplifier output will go to the other supply limit, $+12$ volts. Thus the operation of this circuit is simple; the component value choices are also based on simple considerations.

The operational amplifier feedback level was chosen such that the amplifier would not be

heavily driven into saturation. The reason for doing this is to maintain a reasonable amplifier frequency response. For example, if the 741 op amp has a large signal gain \times bandwidth product of 1 MHz, with a feedback ratio of 10:1, the amplifier can be used to roughly 100 kHz. Neglecting slew rate limitations (maximum rate of voltage change) and phase problems, we might expect to use such a configuration up to perhaps 30,000 baud. A more likely limit is five to ten kilobaud, which is more than sufficient for most microcomputer applications.

The 741 amplifier is capable of driving a 25 mA load. However, we may expect the RS-232C line load to be more on the order of a few milliamperes. The 220 Ohm output resistor was chosen for circuit protection and is the same value as that found in the Mits S-I/O A RS-232C interface board.

The reference voltage circuit is simply a voltage divider. It draws on the order of 4 mA. Thus the total load on the low-powered ± 12 volt supply is less than about 10 mA, includ-

Photo 2. The TTL/RS converter circuit mounted on the back of a Mits S-I/OB serial interface board.

ing the 1 or 2 mA used by the op amp itself. If the 470 Ohm resistor/12 volt zener circuit is regulating, the current through the resistor will be about 14 mA. Under no-load conditions, this would largely go through the zener diode, and the heat dissipation would be about 150 mW, which is acceptable. Shunting 10 mA to the voltage divider/op amp circuit would still allow regulation.

If more than roughly 8 mA is drawn by the output load, that, plus the voltage divider load and op amp quiescent current, can cause the supply voltage to drop. This serves as further output short-circuit protection. In fact, the circuit in the printed circuit board embodiment has been tested under shorted (to ground) output conditions and appears to be invulnerable.

One final note: The two 470 Ohm resistors connected to the operational amplifier inverting and noninverting inputs were chosen to be equal (design practice is usually to balance the inputs to equalize bias cur-

rent voltage drops) and consistent with the load/voltage divider configuration.

Printed Circuit Board

A foil etching pattern for the circuits shown in Figs. 1 and 2 is presented in Fig. 3. It is assumed that since TTL signals are to be converted, a $+5$ volt supply is available.

The final board is small and compact, with the RS-232C and TTL input/output lines grouped together. The component layout is also included on the board itself, simplifying construction.

Observe that a 14-pin DIP pattern is supplied for the 741 operational amplifier. The standard 14-pin 741 DIP will be accommodated by the foil pattern shown in Fig. 3; so will an 8-pin 741 package if it is positioned towards the back end of the hole pattern with pin 1 on the chip placed in hole #3. Fig. 4 shows the pin-out configuration for the two packages. Photo 1 shows a completed TTL/RS-232C converter.

Photo 2 shows a converter board mounted on the back of a

- (1) 741 operational amplifier (op amp)
- (1) 7404 hex inverter
- (1) 220 Ohm resistor
- (4) 470 Ohm resistors
- (2) 2.2k Ohm resistors
- (1) 4.7k Ohm resistor
- (1) 5 volt zener diode
- (2) 12 volt zener diodes
- (1) Printed circuit board

Etched but undrilled printed circuit boards are available from the author for \$1.50 each. A kit with all parts is also available for \$3.50. Include a self-addressed stamped envelope with your order to ensure rapid delivery.

Table 1.




Fig. 3. Foil etching pattern for the circuits shown in Figs. 1 and 2.



Photo 3. The TTL/RS converter mounted between the two boards that compose the Mits 88-ACR audio cassette recorder interface.

Mits S-I/OB serial interface. The Mits card produces only TTL I/O signals. The two leftmost wires from the converter are connected to these (TTL to STSO and TTLO to SRSI). The remaining connections are ground, +5, -18 and +18 volts.

Photo 3 shows a converter used in conjunction with the Mits 88-ACR audio cassette recorder interface. The ACR employs the serial board shown in Photo 2 connected to a modulator/demodulator. The converter is connected as shown in Photo 2, except that a switch is placed between TTLO (converter TTL output) and SRSI (S-I/O board input). When the switch is closed, the terminal (connected to the converter) controls the input to the computer. When open, the

modem reigns. Outputs from the computer go to both the modem and converter.

Thus programs can be saved on and loaded from the tape recorder in ASCII form by simply listing and playing back. Files can be easily concatenated. For example, subroutines may be added to a current program by playing them in. Programs recorded over the telephone from a BASIC-speaking computer can also be loaded and then later adjusted to the dialect of the receiving machine. When you perform the latter exercise, remember that long nulls between program statement lines are helpful in avoiding overlaps between those statements and possible error messages.




Fig. 4. Pin-out configuration of the 8- and 14-pin 741 operational amplifiers.

By bending out the IC pins on the S-I/OB board, which correspond to the A1 and A2 address line inputs to the SN7430 eight-input NAND gate decoder, and tying those inputs to +5 volts, you can make the 88-ACR respond to all port locations between 000 and 007. This is useful for operating Mits cassette BASIC because it uses ports 000 and 001 for the S-I/OA RS-232 serial interface (which we have duplicated with the addition of the TTL/RS converter to the ACR) communication with the terminal and ports 006 and 007 for the tape recorder. Thus both functions are possible using the modified ACR.

In addition, by connecting SRSI (input to the computer from the modem) to TTL (TTL input to the converter), you can monitor on the terminal what is being decoded by the modem

and adjust the modem accordingly. As many 88-ACR users may agree, this can be a very useful function.

Conclusion

I have used the above circuit design and printed circuit board in several projects with excellent results. Two of the boards were connected back to back (TTL to RS-232/out to RS-232/in to TTL) to determine the maximum baud obtainable with this design. I applied a symmetrical TTL signal to one unit and examined the TTL output of the second unit with an oscilloscope. The TTL output remained symmetrical to 16 kilobaud. At this point, the slew rate limitations of the 741 op amp caused the RS-232 output to become triangular instead of rectangular. To obtain a much healthier RS-232 signal I reduced the baud rate to 10K.

At .16 kilobaud and under these load conditions, the RS-232 signal level was ± 10 volts. Shunting this signal line with a 1k Ohm resistor reduced the swing to ± 8 volts. Thus, this circuit is capable of providing RS-232C-compatible signals driving a current in excess of 8 mA.

The above tests indicate that the converter should work under most conditions that you might encounter concerning TTL/RS-232 translation. ■

Stand Alone Video Terminal

aB75eB\pvmZpVwR0123456789:;<=>?
!"#\$%&'()*+,-./012456789:;<=>?
@ABCDEFGHIJKLMN0PQRSTUVWXYZ[\]^_
'`abcdefghijklmnopqrstuvwxyz{|}~&

SCT-100 VIDEO BOARD FEATURES

- 64x16 line format with 128 displayable characters
- Serial ASCII or BAUDOT with multiple Baud rates
- \$187 Assembled or \$157 Kit (Partial Kit \$95)
- Full cursor control with scrolling and paging
- On board power supply
- Serial interface RS232 or current loop
- Purchase SCT-100 alone or complete terminal

XITEX CORP.
 13628 Neutron P.O. Box 402110
 Dallas, Texas 75240 (214) 336-3650

ORDER BY PHONE/Overseas orders & dealers welcome

The Simple Up-Grade™


Trying to add computer memory is not much fun if you don't get everything you need.

step directions and diagrams. And if a personality jumper is required, *it's premade.*

The TRS-80* memory expansion was our first Simple Up-Grade. Now there are two more—for owners of Apple II† and Exidy Sorcerer‡ computers. Each kit is 100% guaranteed—if a part ever falls, we replace it FREE. Your Ithaca Audio dealer has them in stock, only \$140. Now you can afford to add high quality, high density memory to your system for remarkably little—far less than you would expect to pay from Radio Shack, Apple, or Exidy directly.

The Simple
16K APPLE II[†]
UP-GRADE™ KIT

Everything you need to up-grade your Apple II in blocks of 16K.



- 8 tested and guaranteed 16K RAMs.
- New Memory Select Units.
- Use only a household screwdriver.
- Easy instructions.

ITHACA AUDIO
P.O. Box 91 Ithaca, New York 14850

Apple II is a registered trademark of Apple Computer, Inc.

16K TRS-80^{*}
UP-GRADE KIT

Everything you need to up-grade your TRS-80 to a 16K system.



- 8 tested and guaranteed 16K RAMs.
- New programming jumpers.
- Easy-to-follow instructions.
- Only tool required is a household screwdriver.

ITHACA AUDIO
P.O. Box 91 Ithaca, New York 14850

Receiving unprogrammed jumpers and having to program them yourself is not much better. Most important, that's the place where the problems are introduced.

So Ithaca Audio's better idea is the Simple Up-Grade. Each Simple Up-Grade is specially designed to make adding memory foolproof. We include all the parts you'll need; 8 prime, tested 16K RAMs, along with concise step by

The Simple
16K SORCERER[‡]
UP-GRADE™ KIT

Everything you need to up-grade your Sorcerer in blocks of 16K.



- 8 tested and guaranteed 16K RAMs.
- New programming jumpers.
- Use only a screwdriver and soldering iron.
- Easy instructions.

ITHACA AUDIO
P.O. Box 91 Ithaca, New York 14850

Sorcerer is a registered trademark of Exidy, Inc.

These Simple Up-Grades are Ithaca Audio's first step in adding more capability and reliability to your computer at lower cost. Other Up-Grades are on the way to your dealer now.

ITHACA AUDIO

P.O. Box 91
Ithaca, New York 14850
Phone: 607/257-0190

*TRS-80 is a registered trademark of Tandy Corp.

†Apple II is a registered trademark of Apple Computer, Inc.

‡Sorcerer is a registered trademark of Exidy, Inc.

Data Files for Processor Tech 5K BASIC

What started as a routine project ended up producing a "Frankenstein's monster"!

John R. Stanton
7517 Jonquill
San Antonio TX 78233

The possibilities of this small modification to the PTCO 5K BASIC will amaze you! I started the project to enable me to save the results generated by a BASIC program on something other than paper. It ended up giving me that capability and the ability to create BASIC DATA statements that

could be loaded directly into any program plus the fantastic capability to create BASIC programs from a BASIC program. I'm not kidding, it can create its own programs! That means line numbers, statements, variables, etc., are all under program control, without human intervention—unless you want to intrude.

Introduction

My original idea was to take the product of a BASIC program—usually in an array of

some kind—and, instead of losing it every time the program terminated, figure out a way to dump the data to cassette tape in a form that I could use as input data for other BASIC programs.

Well, if BASIC has one overriding failing, it is in the area of data handling; I soon realized that the only way to save raw output data in a form that could be used by other programs was to actually create BASIC DATA statements, complete with line numbers, and record them on

cassette tape. The only way to do that was to use the PRINT statement to construct a DATA statement and then make the PRINT statements feed the tape recorder, instead of the normal CRT/printer output device.

Once recorded, the DATA statements could be fed into any program by making the computer think that the tape recorder input was the keyboard input. This last step had to be done while the BASIC interpreter was in the command mode (program not running) so that the DATA statements would be added to the program just as if they had been typed in on the keyboard.

Routine	CALL Statements	Use
OUTCS	B = CALL (6496)	Changes output from CRT to cassette
OUTCR	B = CALL (6507)	Changes output from cassette to CRT
INCAS	B = CALL (6518)	Changes input from keyboard to cassette
INKBD	B = CALL (6529)	Changes input from cassette to keyboard

Table 1. Subroutine CALL statements.

I/O Port Switching Subroutines

I needed four assembly-language subroutines to accomplish the I/O port switching required between the regular I/O devices and the cassette I/O. Fig. 1 contains all four subroutines that occupy the area between 1960H and 198BH, 44 bytes total.

Each of the four subroutines is accessed by a BASIC CALL (XXXXX) statement, where XXXXX is the decimal memory location of the subroutine to be called (Table 1). The first subroutine (OUTCS) switches the output port from the CRT/printer to the cassette recorder input. The second subroutine (OUTCR) switches the output port from the cassette recorder input back to the CRT/printer.

These two subroutines enable you to feed all PRINT statements to either the CRT/printer or to the cassette recorder simply by first calling the appropriate subroutine. The power of this capability is not readily apparent, but if you

```

1960      0010 .....
1960      0020 * DATA FILE MOD TO PTCO 5K BASIC  VERSION 1.0 12 OCT 78*
1960      0030 .....
1960      0040 *
1960      0050 * CHANGE OUTPUT FROM CRT TO CASSETTE
1960      0060 *
1960 21 E7 OF 0070 OUTCS LXI  H,0FE7H  LOAD ADDRESS OF STATUS BYTE
1963 36 08 0080      MVI  M,08H   MOVE NEW STATUS MASK TO LOC
1965 21 ED OF 0090      LXI  H,0FEDH  LOAD ADDRESS OF DATA PORT
1968 36 02 0100      MVI  M,02H   MOVE CASSETTE PORT NUMBER TO I/O ROUTINE
196A C9 0110      RET
196B      0120 *
196B      0130 * CHANGE OUTPUT FROM CASSETTE TO CRT
196B      0140 *
196B 21 E7 OF 0150 OUTCR LXI  H,0FE7H
196E 36 02 0160      MVI  M,02H
1970 21 ED OF 0170      LXI  H,0FEDH
1973 36 01 0180      MVI  M,01H
1975 C9 0190      RET
1976      0200 *
1976      0210 * CHANGES INPUT FROM KBD TO CASSETTE
1976      0220 *
1976 21 93 OE 0230 INCAS LXI  H,0E93H
1979 36 04 0240      MVI  M,04H
197B 21 3E OE 0250      LXI  H,0E3EH
197E 36 02 0260      MVI  M,02H
1980 C9 0270      RET
1981      0280 *
1981      0290 * CHANGES INPUT FROM CASSETTE TO KBD
1981 21 93 OE 0300 INKBD LXI  H,0E93H
1984 36 01 0310      MVI  M,01H
1986 21 3E OE 0320      LXI  H,0E3EH
1989 36 01 0330      MVI  M,01H
198B C9 0340      RET

SYMBOL TABLE
INCAS 1976  INKBD 1981  OUTCR 196B  OUTCS 1960

```

Fig. 1. I/O port switching subroutines.

think about it, the PRINT statement can produce just about any combination of constants, variables, quoted strings, statements, etc., that you might want.

Fig. 2 is an example of a PRINT statement that produces a DATA statement. This PRINT statement sends only the portion within the quote marks "" to the cassette recorder (1000 DATA 45,68,39,22 CR LF).

The carriage return (CR) and line feed (LF) are generated by the program at the end of a PRINT statement and are sent to the tape recorder. When fed back from the tape recorder to the computer while the BASIC interpreter is in the command mode, this line will load itself in as a DATA statement and will become line 1000 in whatever program resides in the BASIC interpreter.

The third subroutine (INCAS) switches the input port from the keyboard to the cassette recorder output, allowing the DATA statements to load themselves. The fourth subroutine (INKBD) switches the input port back to the keyboard from the cassette recorder output. With these two subroutines you will be able to take the recorded DATA statements and load them directly into a program and then return input control to the keyboard.

PRINT-to-DATA-Statements Conversion

By inserting variables in the PRINT statements I found that I could automatically assign line numbers and pluck data from anywhere in the data base in exactly the formats I needed. Fig. 3 is an example of a complex DATA statement constructor where even the number of data elements in the DATA statement is a variable. Inserting this constructor at the end of a BASIC program and aligning its variables with those that you wish to save will allow you to create any number of DATA statements with a variable number of elements all under software control.

Once you have recorded all of your DATA statements, load

```
LIST
64500 REM  VARIABLES TO BE INSERTED INTO DATA STATEMENTS MUST
64510 REM  BE LOCATED IN THE "V" ARRAY AND THAT ARRAY MUST BE
64520 REM  DIMENSIONED ACCORDINGLY!!!!!!!!!!!!!!!!!!!!!!
64530 REM  *****TEST DATA LOADER*****
64540 DIM V(100)
64550 FOR A=1 TO 100
64560 V(A)=RND(T)
64570 NEXT A
64580 REM  *****END OF TEST DATA LOADER*****
64590 PRINT
64600 REM  ***** DATA STATEMENT CONSTRUCTOR *****
64610 PRINT"INPUT NUMBER OF DATA STATEMENTS: ",INPUT,X
64620 PRINT"INPUT NUMBER OF DATA ELEMENTS IN EACH STATEMENT: ",INPUT,Y
64630 PRINT"INPUT STARTING LINE NUMBER: ",INPUT,L
64640 PRINT"INPUT LINE NUMBER INTERVAL: ",INPUT,P
64645 B=CALL (6496)
64650 FOR I=1 TO X
64660 L=L+(I*P)
64670 PRINTL,"DATA ",
64680 FOR J=1 TO Y
64690 K=I*J
64700 IF J=Y THEN PRINTV(K),
64705 IF J<>Y THEN PRINTV(K),"",
64710 NEXT J
64720 PRINT
64730 NEXT I
64740 PRINT"      B=CALL (6529)"
64750 B=CALL (6507)
64760 PRINT"DONE=CONTROL RETURNED TO KBD/CRT"
64999 END
```

Fig. 3a. DATA statement constructor.

```
100 PRINT "1000 DATA 45,68,39,22"
      RESULTS IN
1000 DATA 45,68,39,22
```

Fig. 2. Conversion of a PRINT statement to a DATA statement.

the program that will use the DATA statements, type in the single CALL statement in Fig. 4, start the recorder and hit the return key. Your DATA statements will load themselves just as though you were typing them in from the keyboard yourself. By always making the last statement inserted by the constructor the CALL statement in Fig. 5, you will ensure that control is returned to the keyboard after the last DATA statement is loaded. The assembly-language subroutines that do all of the switching (Fig. 1) are structured for my I/O scheme, so the port numbers and masks will need to be changed to reflect your I/O scheme.

A Frankenstein

At this point I had satisfied my original goal of saving and reusing data bases without having to type them in myself, but I soon became aware that if I could create DATA statements under software control, I could create any BASIC statement under software control.

Thus I could use my computer to create BASIC programs!

This stark realization scared me because it would allow the computer to alter its own algorithms as a result of experience and simulate the learning process. Simple experiments indicate that any of the BASIC statements can be constructed in the same manner as I have constructed the DATA statements, and, indeed, whole programs can be constructed. Programmers beware: This thing

could take over all software development!

At this point I will bow out and let your imagination run wild as mine has. I will probably be working on a universal program generator for the rest of my life, and I figured if I could get this published there would be a bunch of other fools right in there with me. Lots of luck!

Restrictions

This project has met all of the goals I set, but it does have one quirk that I must warn you about. The speed at which your computer can handle the tape input is limited by the speed of the output device to which that input is echoed. When a keyboard is used as an input device the speed usually does not matter, but when the charac-

```
INPUT NUMBER OF DATA STATEMENTS: 10
INPUT NUMBER OF DATA ELEMENTS IN EACH STATEMENT: 5
INPUT STARTING LINE NUMBER: 2000
INPUT LINE NUMBER INTERVAL: 500
2500 DATA .361117 , .040513 , .413016 , .058217 , .892233
3000 DATA .040513 , .058217 , .608079 , .264695 , .28444
3500 DATA .413016 , .608079 , .06347 , .116282 , .056439
4000 DATA .058217 , .264695 , .116282 , .853631 , .93187
4500 DATA .892233 , .28444 , .056439 , .93187 , .050816
5000 DATA .608079 , .116282 , .459175 , .400634 , .06051
5500 DATA .976036 , .197627 , .838286 , .288647 , .524859
6000 DATA .264695 , .853631 , .400634 , .777737 , .483325
6500 DATA .06347 , .459175 , .687667 , .547727 , .373242
7000 DATA .28444 , .93187 , .06051 , .483325 , .658397
      B=CALL (6529)
      DONE=CONTROL RETURNED TO KBD/CRT
```

Fig. 3b. Program run results with line 64645 deleted (output is sent to CRT instead of cassette).


```

LIST
2500 DATA .383522 , .708914 , .25595 , .510465 , .057526
3000 DATA .708914 , .510465 , .092433 , .244519 , .340362
3500 DATA .25595 , .092433 , .789559 , .177034 , .716639
4000 DATA .510465 , .244519 , .177034 , .357151 , .120418
4500 DATA .057526 , .340362 , .716639 , .120418 , .142469
5000 DATA .092433 , .177034 , .110157 , .831519 , .96294
5500 DATA .438685 , .630211 , .500514 , .048621 , .031472
6000 DATA .244519 , .357151 , .831519 , .619452 , .889222
6500 DATA .789559 , .110157 , .458788 , .048799 , .05362
7000 DATA .340362 , .120418 , .96294 , .889222 , .903577
64500 REM VARIABLES TO BE INSERTED INTO DATA STATEMENTS MUST
64510 REM BE LOCATED IN THE "V" ARRAY AND THAT ARRAY MUST BE
64520 REM DIMENSIONED ACCORDINGLY!!!!!!!!!!!!!!!!!!!!!!
64530 REM *****TEST DATA LOADER*****
64540 DIM V(100)
64550 FOR A=1 TO 100
64560 V(A)=RND(T)
64570 NEXT A
64580 REM *****END OF TEST DATA LOADER*****
64590 PRINT
64600 REM ***** DATA STATEMENT CONSTRUCTOR *****
64610 PRINT"INPUT NUMBER OF DATA STATEMENTS: ",INPUT,X
64620 PRINT"INPUT NUMBER OF DATA ELEMENTS IN EACH STATEMENT: ",INPUT,Y
64630 PRINT"INPUT STARTING LINE NUMBER: ",INPUT,L
64640 PRINT"INPUT LINE NUMBER INTERVAL: ",INPUT,P
64645 B=CALL (6496)
64650 FOR I=1 TO X
64660 L1=L+(I*P)
64670 PRINTL1,"DATA ",
64680 FOR J=1 TO Y
64690 K=I*J
64700 IF J=Y THEN PRINTV(K),
64705 IF J<>Y THEN PRINTV(K),"",
64710 NEXT J
64720 PRINT
64730 NEXT I
64740 PRINT" B=CALL (6529)"
64750 B=CALL (6507)
64760 PRINT"DONE-CONTROL RETURNED TO KBD/CRT"
64999 END

```

Fig. 3c. DATA statement constructor with the data it generated loaded back into it.

ters are coming in at 300 baud plus, it does matter. The most critical limitation is the time it takes the output device to process a carriage return.

Processor Technology 5K BASIC has a NULL XXX command that transmits XXX null characters after each carriage return, thus setting up a period of time to allow for carriage-re-

turn processing. In the case of my TVT-II, the NULL must be set to at least 12 or the data will overrun the carriage-return processing. Overrun will cause some of the DATA statements to be missing and will probably leave the input port connected to the cassette recorder instead of switching it back to the keyboard.

There are two ways to cure this last affliction: reload BASIC or have a cassette on hand with the recovery CALL statement on it (B=CALL (6507)) by itself. If you have a low- or medium-speed printer as your echo device, you will have to set the NULL relatively high (40 or so to prevent overrun). Higher NULL settings are required for cas-

B = CALL (6518)

Fig. 4. Cassette input CALL statement.

B = CALL (6529)

Fig. 5. Keyboard input CALL statement.

sette interfaces operating above 300 baud also.

Remember: If the null is not set right in both the original program and the one to which the data is to be loaded, you may hang up in the cassette mode with bad data in the data base.

Technical Details

The assembly-language sub-routines are loaded just above where PTCO 5K BASIC now stops, and it does alter the minimum starting location in the preamble questions when BASIC is initialized. FIRST ADDRESS should be at least 6550 (I use 6600 to be safe). Make sure to Insert the NULL command to prevent carriage-return overrun. Be certain that the last statement loaded on every tape is B=CALL (6507) to ensure that control is returned to the keyboard after a data load. ■

WEB ASSOCIATES

INS-80™

GET UNSTUCK!
with
TBUFF™

STOP YOUR CASSETTE WHEN
IT SHOULD WITH OUR TBUFF™
CASSETTE INTERFACE BUFFER
ONLY \$12.95 each



*Specify recorder make, model,
and mfg. code (in battery com-
partment).*

Dealer inquiries invited
Club discounts available
For more information circle ☒ W20

Send check or money order to:

WEB ASSOCIATES
P.O. Box 60-KW, Monrovia, CA 91016
(California Residents add 6% tax)

**Canadian
8K MEMORY KITS**

M1—Fast Signetics 21L02-1 RAMs with 20 pages of Documentation—solder mask Low power Schottky—S-100 Bus—Full Buffering
\$179.95

M2—as above with DIP switch address select and Robinson Nugent IC sockets only **\$199.95**

MEM1—WAMECO bare board as used in above kits **\$39.95**

Write for info on WAMECO CPU and other S-100 bare boards.

ORTHON COMPUTER
(ORTHON HOLDINGS LTD)
✓ O8

12411-Stony Plain Rd
Edmonton, Alberta Canada T5N3N3

REAL ESTATE

SOFTWARE
NORTHSTAR VERSION

- FULL FEATURED
- INSTANT RETRIEVAL
- POINTER CROSS REFERENCED
- LISTINGS, CUSTOMER FILES
- CURSOR CONTROLLED
- HAZELTIME DUAL BACKGROUND




Northstar Dos **\$299⁰⁰**
Basic With
Documentation **POWERFUL,
COMPLETE**

APOLLO SOFTWARE
41 Park Ave
Lockport, NY 14094 **✓ A84**




3-D ANIMATION

A-\$24.95




AUDIO ENGINEER

A-\$29.95




STRATOLASER

A-\$15.95



SUPER STARWARS

A-\$15.95



MAGIC SQUARES

A-\$ 9.95

6502 FORTH 6800 FORTH Z-80 FORTH

FORTH is a unique threaded language that is ideally suited for systems and applications programming on a micro-processor system. The user may have the interactive FORTH Compiler/Interpreter system running stand-alone in 4K to 6K bytes of RAM. The system also offers a built-in incremental assembler and text editor. Since the FORTH language is vocabulary based, the user may tailor the system to resemble the needs and structure of any specific application. Programming in FORTH consists of defining new words, which draw upon the existing vocabulary, and which in turn may be used to define even more complex applications. Reverse Polish Notation and LIFO stacks are used in the FORTH system to process arithmetic expressions. Programs written in FORTH are compact and very fast.

APPLE II COMPUTER	\$34.95
PET 2001 COMPUTER	\$34.95
TRS-80 COMPUTER	\$34.95
SWTP COMPUTER	\$34.95

Apple PIE TRS-80 PIE

PIE (PROGRAMMA IMPROVED EDITOR) is a two-dimensional cursor-based editor designed specifically for use with memory-mapped and cursor-based CRT's. It is totally different from the usual line-based editors, which were originally designed for Teletypes. The keys of the system input keyboard are assigned specific PIE Editor function commands. PIE includes the following features: blinking cursor; cursor movement up, down, right, left, home, plus tabs; character insert and delete; string search forwards and backwards; page scrolling; GO TO line number, plus top or bottom of file; line insert and delete anywhere on screen; append and clear to end of line; move and copy buffer.


APPLE II COMPUTER	\$19.95
TRS-80 COMPUTER	\$19.95

All orders include 3% postage and handling. Apple II is a registered trademark of Apple Computer, Inc. Pet is a registered trademark of Commodore International and TRS-80 is a registered trademark of Radio Shack. California residents add 6% sales tax. VISA & MASTERCARD Accepted.




APPLE II LIGHT PEN

\$34.95




STARTREK

P-\$ 9.95



DEPTH CHARGE

P-\$ 9.95



BATTLE SHIP

P-\$ 9.95



QUICKDRAW

P-\$ 9.95

PROGRAMMA
INTERNATIONAL, Inc.
3400 Wilshire Blvd.
Los Angeles, CA 90010
(213) 384-0579

✓ P48

Dealer Inquiries Invited

Little Bits

Rod Hallen
Road Runner Ranch
PO Box 73
Tombstone AZ 85638

John Walker
Marinchip Systems
16 St. Jude Rd.
Mill Valley CA 94941

Number Conversion

This routine asks for a decimal number between 1 and 225 and then prints the hex and octal equivalents. If a zero is entered, control reverts to BASIC. It is written in Processor Technology's Extended BASIC, which does not allow string arrays. If your BASIC does, then replace lines 20 and 80 with the statements contained in the remarks from 190 to 240.

```

10 REM-DECIMAL TO HEX AND OCTAL ROD HALLEN 21 JUNE 78
20 DIM A$(16): LET A$="0123456789ABCDEF"
30 FOR I=1 TO 255
40 INPUT "DECIMAL NUMBER ? ",N
50 IF N=0 THEN 150
60 LET X=INT(N/16)
70 LET X1=N-X*16
80 PRINT " HEX ";A$(X+1,X+1);A$(X1+1,X1+1),
90 LET Y=INT(N/64)
100 LET Y1=INT((N-(Y*64))/8)
110 LET Y2=N-((Y*64)+(Y1*8))
120 PRINT "OCTAL ";Y;Y1;Y2
130 PRINT
140 NEXT I
150 END
180 REM-CHANGES FOR STRING ARRAYS
190 REM-20 DIM A$(16)
200 REM-21 FOR J=1 TO 16
210 REM-22 READ A$(J)
220 REM-23 NEXT J
230 REM-24 DATA 0,1,2,3,4,5,6,7,8,9,A,B,C,D,E,F
240 REM-80 PRINT " HEX ";A$(X+1);A$(X1+1),
    
```

Program listing.

Easy Lowercase

At long last we can purchase low-cost computer peripherals that work in both uppercase and lowercase; yet virtually every keyboard I see is locked to use uppercase letters only. Why? It seems that in every system there is at least one piece of software that doesn't recognize lowercase letters. Lowercase so improves readability that we shouldn't give it up so willingly, especially since it's so easy to write a program that accepts both uppercase and lowercase. Here's how:

1. Write your program assuming the text it receives is all uppercase.
2. In your common-character load subroutine (you *did* use one, didn't you?), insert a translate to uppercase.

This will allow you to enter data in either uppercase or lowercase and still allow your program to recognize its keywords, commands or whatever. When your program stores text in memory, it should be stored as entered and retranslated each time the program looks at it. This allows it to be printed back as it was entered, not in (yukkk) ALL CAPS. Writing a subroutine to do the conversion from lowercase to uppercase is as easy as the two steps given above (see Figs. 1 and 2).

These subroutines leave the rub-out character (7F hex) unchanged. If you don't mind having rub-out changed to "_", you can delete lines 3 and 4 in both subroutines. It is usually easy to patch these routines into existing programs to make them case-insensitive, but it would be far better if vendors did this before they distributed their software. It's really very little trouble, and it does make things much nicer. Please?

'Bill McLaughlin, "ALL CAPS should be laid to rest," *Kilobaud*, December 1977, p. 60.

Assumes character in R0

1.	UC	CI	R0,060	Lowercase?
		JL	UC1	No. Don't translate
3.		CI	R0,07F	Is it a rub-out?
4.		JEQ	UC1	Yes. Leave it alone
5.		ANDI	R0,05F	No. convert to uppercase
6.	UC1	RT		Return to caller

Fig. 1. Lowercase-to-uppercase-conversion subroutine for the TMS 9900.

Assume character in Accumulator

1.	UC:	CPI	60H	Is character lowercase?
2.		RC	.	No. Return
3.		CPI	7FH	Yes. Is rub-out?
4.		RZ	.	Yes. Leave it alone
5.		ANI	5FH	No. Translate to uppercase
6.		RET	.	Return to caller

Fig. 2. Lowercase-to-uppercase-conversion subroutine for the 8080 or Z-80.

A "Sneaky Interrupt" for the 6502

Looking for a way to interrupt your 6502 other than through NMI or IRQ? If you use a 6502 microprocessor and need an additional method of getting your computer's attention, then read on.

About three years ago I wanted to learn more about digital electronics. What better way than to build my own microcomputer? But before I could begin I had to do a lot of investigating to determine what type of processor to use.

After much agonizing I settled on the 6502 since it seemed to be much more concise than the 8080 and, to me, was easier to program than either the 8080 or 6800. After all I have subsequently learned, I'm glad I made this choice. I feel there is no better microprocessor on the market than the 6502 (that ought to stir up all the 8080 people out there).

During the process of working up my system, I needed some way to get information to my processor other than through the normal NMI or IRQ interrupt methods. NMI was dedicated to the reset and stop functions, and IRQ was being used for a particular application.

The normal method of solving this problem would have been to set up a system of polled or priority interrupts. This seemed like a lot of work for only one additional requirement, so I began the

search for an easier and simpler way. That's when I discovered the 6502 "sneaky interrupt."

The 6502 sneaky interrupt can be found hiding on the S0 input pin. This is an input that sets the overflow flag in the processor whenever it detects a transition from high to low. The edge sensitive nature of this input makes it convenient and easy to use. All you have to do is provide this edge and software to interrogate the V flag periodically to detect an interrupt request.

Of course, if your program is performing arithmetic operations such as ADC, SBC or BIT instructions, you must be careful that no conflicts in the use of the overflow flag are created. In my experience so far, this has never been a problem.

I currently use this method to detect a keyboard input to my BASIC interpreter. When BASIC is ready for some input, it executes a JSR to a routine called KEYIN. If you are concerned about the previous status of the V flag, you can preserve it by pushing the status register onto the stack before the CLV and pulling it back before the RTS.

This method requires very little hardware (none in my case since S0 is tied to the keyboard strobe) and a minimum of software.

```
KEYIN      CLV          clear the V flag
            NOP          wait
            BVC-1        if V is not set, go back to wait
            JSR GETKEY    if V is set, go to GETKEY routine
            RTS
```

KEYIN routine.

E. M. McCormick
13100 Chapman, Apt. 3-113
Garden Grove CA 92640

Richard Wright
676 Coe Rd.
Tiffin OH 44883

Calculating Pi . . . The Leibnitz Method

Calculating the value of pi (3.14159 . . .) is a way of testing and comparing the number-crunching capabilities of various micros. It produces a familiar number, although most people will remember only the first few digits in the series.

The easiest method of computing pi uses this series discovered by Leibnitz in 1694:

$$\pi = 4 \left(\frac{1}{1} - \frac{1}{3} + \frac{1}{5} - \frac{1}{7} + \frac{1}{9} - \frac{1}{11} + \dots \right)$$

Although it is simple to program, this series requires many thousands of terms for even a few places of accuracy. However, it is easy to extend it so that it converges quite rapidly. The program listing shows the BASIC program to do this.

This program calculates pairs of terms in the series. Value S# (line 50) will fluctuate around pi/4. However, P# (line 60) makes two corrections to S#. First, by adding 2*M#, it calculates a value midway between that of the two terms. Since the value of the denominator is ever-increasing, this midpoint correction actually overcorrects. The final term, -2*M#12, compensates for this overcorrection.

A Level II TRS-80 will calculate pi to ten places in 37 seconds and to 13 places in eight minutes when using this program. Incidentally, the correct value to 15 places is 3.141592653589793.

MIKBUG Load . . . Show and Tell

Loading long programs from tape using the MIKBUG "L" function can be nerve-racking due to the lack of output to the terminal. You can overcome this problem by loading E013 at A048 and A049 and entering "G" instead of "L." Your program will now display on your terminal as it loads into memory.

```
10 REM PI CALCULATION, E. M. MC CORMICK, 8-11-78
20 S# = 0
30 X# = 1
40 M# = 1/(X# + 2)
50 S# = 1/X# - M# + S#
60 P# = 4*S# + 2*M# - 2*M#12
70 PRINT X#,P#
80 X# = X# + 4
90 GOTO 40
100 END
```

Program listing. Rapid calculation of pi using Leibnitz' series.



RONDURE COMPANY

2522 BUTLER ST.
DALLAS, TEXAS 75235
214-630-4621

the computer room



\$895.00
CLEAN & WORKING
\$1095.00
RECONDITIONED

TESTED WITH
NEW
ASCII
ELECTRIC

IBM Selectric with ASCII parallel receiver only electronics.
Immediate Delivery—Shipped from inventory.

ASCII SELECTRIC

Printer Mechanism: Heavy duty input/output, Series 745.


Weight: 120 lbs. Dimensions: 29"Hx35"Wx33"D.

Print Speed: (14.8 characters per second)

Platen: 15" wide, pin feed or form feed device optional (132 print positions).

Parallel output only—15 characters per second accepts 7 bit ASCII parallel w/strobe & prints on Selectric. The unit still works as a typewriter in off-line mode.

NOVATION DC3102A



Used
Working

\$150.00

RS232 Connection
300 Baud

TI 990/4 Micro



SALE

single board cpu **\$225.00**
256 WORDS RAM
SOCKETS FOR 1K ROM
DOCUMENTATION

NEW Novation Modems & Couplers

4102A—Acoustic—Originate \$275.00
4103A—Acoustic—Ans/Orig \$295.00
4102—Hard Wire—Orig. \$340.00
4103B—Hard Wire—Orig. & Auto Answer . . . \$385.00
4113B—Hard Wire—Auto Answer Only \$365.00

Write or call for our catalogue of many terminals & parts.

DATTEL SELECTRIC (IBM Selectric Mechanism)



Specifications:

- Size: 21"Wx21"Dx8"H.
- Power input 115 Volt Hz
- Interface: RS232
- Weight: 54 lbs.
(Shipping weight 65 lbs.)
- 15" Carriage
- 15 CPS
- Correspondence code
- Half Duplex
- 132 Print Positions, 10 Pitch

Used, As Is **\$395.00**
Clean & Working **\$495.00**
Refurbished **\$695.00**


Software to convert ASCII Output of 8080 Class Processor to Selectric Code **\$25.00**

Manufacturers Electronic & Mechanical Documentation **\$40.00**

NOTE: WE HAVE FLAT-PACK ACOUSTIC
Modem pickup **\$19⁵⁰**

Even though market SOLD OUT in catalog— we've got more.

SPECIAL



GE TERMINET 300 PRINTER

(used)
(good working condition)

\$450.00

- Receive only
- ASCII code
- RS-232 interface
- 30 CPS
- Upper & lowercase
- Shipping wt. 75#



ASCII Keyboard

(used)
with enclosure

\$35.00



Sony TV/Monitor

11" used

\$75.00

ORDERING INFORMATION:

We ship the same day we receive a certified check or money order. Texas residents add 5% sales tax. Please call if you have a question. Write for our CATALOG of many parts, terminals, printers, etc. All items subject to availability. Your money returned if we are out of stock.

SHIPPING INFORMATION:

Modems: \$2.00 each; 2 for \$4.00 UPS.
Large Items & Parts: Specify Freight or Air Freight Collect
Foreign Orders: Add appropriate freight or postage.
We now take Master Charge and Visa orders, Specify full number, bank number and expiration date.



This questionnaire is very important

... to you and to us. It's your opportunity to help us chart the future course of Kilobaud **MICROCOMPUTING** by telling us exactly what kinds of articles and features you want to read. We need your input to make Kilobaud **MICROCOMPUTING** an even better magazine. Please let us know what's on your mind by circling your answers on this postage-paid card and mailing it today.

- 1) What is your level of education?
 - A. High School
 - B. College
 - C. Post Graduate
 - D. Other
- 2) What is your income level?
 - A. \$10-15,000
 - B. \$15-20,000
 - C. \$20-25,000
 - D. \$25-30,000
 - E. Over \$30,000
- 3) What is your profession?
 - A. Management
 - B. Engineer
 - C. Technician
 - D. Data Processing
 - E. Programmer
 - F. Doctor
 - G. Lawyer
 - Other _____
- 4) What is your interest in computing?
 - A. Hobby
 - B. Professional
 - C. Business
 - D. Hardware
 - E. Software
 - F. School
 - Other _____
- 5) Which microcomputer(s) do you own?
 - A. I don't own one yet
 - B. AIM-65
 - C. Altair
 - D. Apple
 - E. CompuColor
 - F. Cromemco
 - G. Data General
 - H. Elf (Quest)
 - I. Elf (Netronics)
 - J. Exidy Sorcerer
 - K. Gimix Ghost
 - L. Heath H8
 - M. Heath H11
 - N. Imsai
 - O. KIM-1
 - P. Motorola
 - Q. North Star
 - R. Ohio Scientific
 - S. PET
- 6) How much RAM does your largest system contain?
 - A. Less than 4K
 - B. 4K-7K
 - C. 8K-11K
 - D. 12K-15K
 - E. 16K-23K
 - F. 24K-31K
 - G. 32K or more
- 7) How much have you invested in your microcomputer systems?
 - A. Less than \$500
 - B. \$500-1,000
 - C. \$1,000-1,500
 - D. \$1,500-2,000
 - E. \$2,000-3,000
 - F. more than \$3,000
- 8) How much will you spend on your system this year?
 - A. Less than \$500
 - B. \$500-\$1,000
 - C. \$1,000-1,500
 - D. \$1,500-2,000
 - E. \$2,000-3,000
 - F. more than \$3,000
- 9) Do you program mostly in:
 - A. BASIC
 - B. FORTRAN
 - C. Assembly language
 - D. Machine language
 - Other _____
- 10) Which of the following do you own?
 - A. Printer
 - B. Modem
 - C. Word Processor
 - D. Mini-Floppy
- 11) Where do you get most of your software?
 - A. Write it myself
 - B. Magazines
 - C. Friends
 - D. Software Companies
- 12) I read the following magazines:
 - A. Kilobaud/Microcomputing
 - B. Interface Age
 - C. Byte
 - D. Computerworld
 - E. Personal Computing
 - F. Creative Computing
 - G. Popular Electronics
 - H. Radio Electronics
 - Others _____
- 13) I subscribe to the following:
 - A. Kilobaud/Microcomputing
 - B. Interface Age
 - C. Byte
 - D. Computerworld
 - E. Personal Computing
 - F. Creative Computing
 - G. Popular Electronics
 - H. Radio Electronics
 - Others _____
- 14) Aside from the articles, what are your favorite features of Kilobaud Microcomputing? (choose 3)
 - A. Publisher's Remarks
 - B. Output from ISI
 - C. Pet-pourri
 - D. Calendar
 - E. Books
 - F. New Products
 - G. Computer Clinic
 - H. Dealer Directory
 - I. Letters
 - J. Classifieds
 - K. Legal/Business Forum
 - L. Club Calendar
 - M. BASIC Forum
- 15) What kinds of hardware articles do you like most? (choose 3)
 - A. Reviews of systems, boards, accessories
- 16) What types of software articles do you like best? (choose 3)
 - A. Business programs
 - B. Reviews of software packages
 - C. Patches for existing software
 - D. Games
 - E. Educational programs
 - F. Home applications
 - G. Operating systems and monitors
 - H. Techniques of programming
 - I. Word processing
 - Other _____
- 17) Are most of the articles:
 - A. Too complex?
 - B. Too simple?
 - C. About right?
- 18) What kinds of general interest articles do you like?
 - A. Humor
 - B. Reports on computer shows
 - C. Stories about computer people
 - D. I don't like general interest articles
- 19) What do you think of the 1979 cover design?
 - A. Like it
 - B. Liked the old ones better
 - C. Don't care



save \$15 off the yearly newsstand cost

Subscribe now to the new Kilobaud **Microcomputing**, and save 50% off the newsstand cost of \$30!

☐ Payment enclosed. ☐ Please bill me.

Name _____

Address _____


City/State/Zip _____

Rates apply in U.S. only. Add \$8 per year foreign. Payable in U.S. currency — one year subscriptions only.

kilobaud
MICROCOMPUTING

Subscription Services Department • P.O. Box 997 • Farmingdale NY 11737

196R



NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

MICROCOMPUTING
kilobaud


Peterborough NH 03458

BUSINESS REPLY CARD
FIRST CLASS PERMIT NO. 17 PETERBOROUGH NH 03458
POSTAGE WILL BE PAID BY ADDRESSEE



PLEASE FOLD HERE

PLEASE STAPLE OR ATTACH HERE



NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BUSINESS REPLY CARD
FIRST CLASS PERMIT NO. 17 PETERBOROUGH NH 03458
POSTAGE WILL BE PAID BY ADDRESSEE

kilobaud

MICROCOMPUTING

Subscription Department • Box 997
Farmingdale NY 11737



kilobaud
MICROCOMPUTING

12 \$15

save \$15 off the yearly newsstand cost

Subscribe to Kilobaud **Microcomputing** this month and take advantage of this half price offer. In addition, we'll guarantee your satisfaction: If you're not completely satisfied after reading your first issue or your *eleventh*, your money will be refunded on all remaining issues. We guarantee your satisfaction because Kilobaud **Microcomputing** is the small-computer magazine written for the beginner as well as the expert. Kilobaud **Microcomputing** is the forerunner of small business and home computing. Every month you'll read about the latest developments in

hardware, software, applications and new-product reviews.

So keep up to speed in the dynamic world of microcomputing by subscribing today, and save \$15 off the cover price for one year, or save even more on a three-year subscription at \$45 (you save \$45 off the cover price). No need to send money now—we'll bill you later if you prefer.

(This offer good in U.S. and Canada only. All other subscriptions \$23 for one year, payable in U.S. currency only.)

Subscribe now to the new Kilobaud **Microcomputing** and save 50% off the newsstand cost of \$30!

☐ Payment enclosed ☐ Please bill me

Name _____

Address _____

City _____

State/Zip _____

Payable in U.S. currency—one year subscriptions only.
Rates apply in U.S. only. Add \$8 per year foreign.

196S

Subscribe now to the new Kilobaud **Microcomputing** and save 50% off the newsstand cost of \$30!

☐ Payment enclosed ☐ Please bill me

Name _____

Address _____

City _____

State/Zip _____

Payable in U.S. currency—one year subscriptions only.
Rates apply in U.S. only. Add \$8 per year foreign.

196S

kilobaud
MICROCOMPUTING
P.O. Box 997 • Farmingdale NY 11737

What's so Magic about the Sorcerer?

It's no secret, but you have to read this article to find out.

You don't have to follow the yellow brick road to its end to find the Sorcerer of Exidy (Exidy, Inc., Data Products Division, 969 West Maude Ave., Sunnyvale CA 94086). He is probably in your friendly neighborhood computer store right now. But just in case you haven't yet seen this fabulous machine, let's take a quick look at the Sorcerer's array of special features and then spend some time investigating just how to use them.

The Sorcerer computer arrived on the personal-computer

scene in the fall of 1978, somewhat later than its competitors. As delivered at \$895 in the 8K byte RAM version, the Sorcerer does not include all the items shown in Photo 1. As a matter of fact, the basic machine doesn't even include a CRT monitor or a cassette tape deck, both of which are indispensable for its operation as a home/personal/hobbyist computer.

Adding the cost of these "options" increases the price of the Exidy machine to more than just above that of the competi-

tion. So how can you justify the higher expenditure for the Sorcerer? The special features of this computer have to provide the justification.

What Makes It Special

The minimum memory configuration of the computer includes 8K bytes of RAM, and, after the on-board monitor and ROM-PAC BASIC grab their stack and work space, 7400 bytes of program space are still available to the BASIC language programmer. RAM can later be expanded on-board to

16K or 32K bytes, or you can purchase the machine in these larger configurations if you know how much memory you are going to need ahead of time.

The microprocessor is the Z-80 running with a 2 MHz clock, and Table 1 shows how fast it executes the *Kilobaud* benchmarks (see "BASIC Timing Comparisons" articles in the June 1977 (p. 66) and October 1977 (p. 20) *Kilobauds*). The Z-80 CPU should enable the Sorcerer to run circles around the Altair, so the results of the benchmark programs are a little disappointing, as well as confusing.

Memory size and speed, however, are not the true measures of the value of this computer. Its built-in features not found on any other machine in its price range make this computer a first choice for the more serious user. The Sorcerer comes complete with:

- An instantly replaceable ROM-PAC cartridge (EPROM-PAC optional) allowing sudden swapping of programming languages or application programs.
- Complete interfaces for two cassette tape drives, including motor on-off controls and selectable 300 bps Kansas City Standard or 1200 bps Exidy format recording.
- Eight-bit-wide parallel input and output ports with hand-shaking controls accessible through a standard DB-25S



Photo 1. The Sorcerer computer with up to 32K bytes of RAM is contained completely within the keyboard housing, requiring only the addition of a CRT monitor and cassette tape deck. BASIC language in ROM is supplied in the cartridge plugged into the right side of the machine. (Photos courtesy of Exidy, Inc.)

- connector on the back panel.
- An additional 50-pin card edge connector interfacing with the Z-80 CPU, which can be used to attach an S-100 bus-compatible expansion chassis.
- An RS-232 serial I/O port with selectable 300 or 1200 baud rates.
- Uppercase and lowercase ASCII capability of both the keyboard and the 64 character by 30 line display.
- Built-in graphics characters and user-programmable graphics characters, both of which can be accessed from the keyboard or displayed by BASIC or machine-language programs.
- A complete 4K monitor program that includes I/O driver routines used by BASIC, which could also be called by machine-language user programs.

Using the Special Features

Without having to purchase the S-100 expansion unit, you can configure a real data-processing system with the Sorcerer. For example, in a small-business environment that requires processing account records and preparing statements, you could read in last month's data (one account at a time) from cassette #1. You could then key in the current month's activity. Updated account records could be written out on cassette #2; statements could be generated on a line printer interfaced to the parallel output port; and updated data could then be relayed to the home office through a modem connected to the RS-232 port, while date and time of day could be input from a digital clock through the parallel input port!

Of course, this scenario requires the purchase of the clock, modem, printer, tape decks and CRT monitor—as well as some interfacing and lots of software—but it does illustrate the immense capability of the basic machine.

These features make the Sorcerer a wise choice for the serious user of a small computer, while the experimenter can interface the computer to all sorts of external devices without jeopardizing the integrity




Photo 2. The ROM-PAC has been opened up, showing the four ICs containing an 8K version of Microsoft BASIC. The same package can be configured for the more popular EPROMs, permitting the user to change to an instantly loadable application program.

(or warranty) of the hardware.

With the latter type of use in mind, let's take a look at a couple of the features of the Sorcerer and see how easy it is to make use of them. We will be examining one user's experiences with the EPROM-PAC and the parallel I/O port, and you can profit from the solutions to the minor problems he encountered.

ROMs and EPROMs

Photo 2 shows an opened-up ROM-PAC supplied with the Sorcerer. This PAC contains an 8K version of Microsoft BASIC language in the four ROMs. These ICs are pin compatible with 2716-type EPROMs, so the same cartridge is supplied (with a different label and no

ROMs) as an optional EPROM-PAC. This allows the user with a suitable programmer to insert his own machine-language application program.

Included with the EPROM-PAC are instructions showing how you can change jumpers on the PAC's printed circuit board to alternately accommodate either 2708 or 2732 EPROMs. Currently, 2708s are the most cost-effective EPROMs for the small-quantity user, but they restrict the PAC capacity to 4K bytes. The user of 2716s can load up to 8K bytes, while a real high roller with a fat wallet can program 16K bytes into four 2732s.

In addition to this plug-in cartridge carrying either ROMs or EPROMs, the Sorcerer includes

an on-board monitor program in ROM. If no PAC is inserted into the machine at power-up time, the monitor will initialize the computer, clear the display screen, home the cursor and display a message announcing its presence and how much RAM is available. You can then use the monitor to load machine-language programs from tape, examine or alter memory locations, reassign I/O devices, etc.

Provided that a ROM- or EPROM-PAC has been inserted into the computer before power up, however, the monitor program will initialize things and then jump to a starting address at the top of the PAC's address space. This feature enables a user's EPROM-resident appli-

Software; Hardware	CPU	Benchmark Number						
		Type	1	2	3	4	5	6
Microsoft Standard BASIC; Exidy Sorcerer	Z-80		1.9	10.2	21.4	22.5	24.6	38.0
Altair 12K Extended BASIC; Altair 8800b	8080A		1.9	7.5	20.6	20.9	22.1	37.0
Microsoft 12K Extended BASIC; MSC 8080 +	8080		2.1	10.0	24.2	25.1	27.8	43.0
Microsoft 12K Extended BASIC; Intel MDS-800	8080A		6.2	17.0	34.5	36.8	46.1	87.4
								130.9

Table 1. Benchmark timings (in seconds). The Sorcerer runs neck and neck with an Altair (as reported in the October 1977 Kilobaud, p. 20). Two development systems not previously timed are included for reference. The Intel system has a complicated bus control logic that may be inadvertently hung up in a cycle-stealing mode. The MSC 8080 + is from Monolithic Systems Corp., Englewood CO, and uses an old, "slow" 8080.

DU D000 D0FF

ADDR	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
D000:	21	20	D0	7E	FE	FF	CA	03	E0	CD	1B	E0	23	C3	03	D0
D010:	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
D020:	8D	0A	45	58	49	44	59	20	53	4F	52	43	45	52	20	45
D030:	50	52	4F	4D	20	50	41	43	20	54	45	53	54	20	56	20
D040:	37	38	2E	31	20	20	20	20	20	20	0D	0A	0A	43	4F	50
D050:	59	52	49	47	48	54	20	28	43	29	20	31	39	37	38	20
D060:	42	59	20	42	4F	52	52	45	47	4F	20	45	4E	47	49	4E
D070:	45	45	52	49	4E	47	20	20	20	20	20	0D	0A	0A	20	20
D080:	20	20	20	41	20	4C	69	74	74	6C	65	20	53	74	6F	72
D090:	79	20	20	20	20	20	0D	0A	0A	20	20	4F	6E	63	65	20
D0A0:	75	70	6F	6E	20	61	74	69	6D	65	20	74	68	65	72	65
D0B0:	20	77	65	72	65	20	74	77	6F	20	6C	69	74	74	6C	65
D0C0:	20	43	6F	6D	70	75	74	65	72	73	2E	20	20	20	0D	0A
D0D0:	4E	4F	57	20	6C	6F	6F	6B	20	61	74	20	74	68	65	20
D0E0:	6D	65	73	73	20	77	65	27	72	65	20	69	6E	21	21	20
D0F0:	0D	0A	0A	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF

Fig. 1. Sorcerer's built-in monitor program has been called upon to "dump" the contents of the first 256 bytes of a user program in a 2708 EPROM. The monitor can be directed to write on to the CRT screen, or to a printer connected to the parallel output port, as in this example.

cation program to continue operation following a power interruption. The Sorcerer can therefore be readily configured as a stand-alone no-operator-needed dedicated controller.

This was one of the features of this computer that I found absolutely irresistible, since I've been designing control systems for over a decade. This same feature is used to initiate BASIC, if that ROM-PAC is inserted, so that the user of the higher-level language need never know that the monitor program exists, even though it is handling all his input and output operations for him. This is *real* flexibility!

My Sorcerer arrived a few weeks before my EPROM-PACs did, so I had time to dream up lots of nice applications for this instant-on feature. For a quick check I programmed the low-order 256 bytes of a 2708 with the code show in Fig. 1. (This memory dump was printed by the monitor on an ASR-33 Teletype interfaced through the parallel output—more details later!) Jumpering the EPROM-

PAC in accordance with Exidy's instructions for the 2708, I inserted the 2708 into the proper socket. I impatiently fired up the computer and looked for the proper display on the CRT. It wasn't there! The monitor announced that it was in operation, but my PAC program was nowhere to be found.

Using the memory dump facility of the monitor, which can be slowed down to a comfortable speed, I searched the entire memory address space for my EPROM program. It was not to be found.

Much research time later I had discovered that, of the 20 jumpers needed in groups 1 through 4 on the EPROM-PAC circuit board to configure it for 2708s, the data sheet had omitted seven! Fig. 2 shows *all* of the jumpers in these four groups which are needed for 2708s. I haven't yet had occasion to debug the documentation provided for the other chip types, but this drawing should save you 2708 users much grief.

With the proper jumpers in place, the program as listed ran




Fig. 2. A partial view of the jumpers required to configure the EPROM-PAC for 2708s. Seven of the 20 jumpers shown in groups 1 through 4 were missing from the original documentation.




Fig. 3. A partial schematic of the parallel port circuitry. Following a write to the output port (address 0FF, 255 in decimal) the handshake flip-flop presents a low level to the data-available line. The user's interface hardware must return a data-accepted strobe. The circuit shown on the right can be used to perform this function. Status of the handshake flip-flops is sensed through input port 0FE(254).

just fine. I'll leave it to the dedicated reader to discover what the screen displayed.

Parallel Port Principles

Even though the manufacturers of hand-held calculators have managed to solve the problem, to date there are no less-than-a-kilobuck computers with a built-in printer. Anyone who does more than just play space war games knows that the most desirable peripheral to add to the basic computer is a hard-copy device. The realization may come in minutes, or it may take days before the lack of hard copy becomes painfully apparent. But the pain is inevitable.

The Exidy Sorcerer is ready to have a Centronics printer attached to its parallel output port. The monitor is set up to enable the operator to assign the parallel output port as the output device in place of the CRT display. Handshaking signals ("output data available" and "output data accepted") are included in the interface, compatible with this printer.

What might not be so compatible with every user of the

Sorcerer is the price of a Centronics printer. In the event that you are like me and want to hang some other device(s) on the parallel input and output ports, you need a working knowledge of the hardware and software requirements. Let's examine the output port first, since it is the most likely to be used first.

The user's manual supplied with the computer is scanty on specific details concerning these ports. As of this writing the hardware reference manual is not yet in print, but Exidy was kind enough to supply me a set of schematics, allowing me to provide the following details.

A simplified diagram of the handshake hardware for the output port is shown on the left half of Fig. 3. When a byte of data is to be transmitted through this port, an internal write strobe (WR) causes the eight data bits to be latched into an octal latch. As far as the outside world is concerned, it is only necessary to know that these bits are latched at high-true TTL logic levels and will remain stable until the next character or byte is transmitted, no


```

10 REM OUTPUT A CR AND LF
20 OUT 255,13: GOSUB 100
30 OUT 255,10: GOSUB 100
40 RETURN

```

```

100 REM DELAY ROUTINE
110 FOR K = 1 TO 50
120 NEXT K
130 RETURN

```

Fig. 4. With the minimum handshake hardware shown in Fig. 3, the user must provide program delays to establish the character-to-character spacing. The BASIC language subroutine shown here will cause a carriage return and line feed to be output to the parallel port. The delay routine is consistent with a 110 baud (10 cps) printer.

matter how long this may be.

Concurrent with the latching of the data, the \overline{WR} strobe will cause the \overline{Q} output of the handshake flip-flop to switch to a logic low level. This "output data available" signal tells the outside world that a data byte has been placed in the latch. The outside world *must* respond with a low-going strobe to acknowledge "output data accepted."

As the schematic shows, this signal is connected directly to the RESET pin of the handshake flip-flop. A constant low level on this pin will inhibit any further change of state of the flip-flop. For this reason the data-accepted signal must be a strobe, not a constant low level.

Upon receipt of this strobe, the handshake flip-flop will return to its reset state, with the \overline{Q} output at logic high. This output can be sensed by the driver software to determine that the port is ready to accept more data. This is shown by the line labeled I0B6. This signifies that this line can be read as the seventh bit (of eight) of the internal status port, using the common convention of counting the eight bits from zero to seven.

All the user needs to know is that if this bit is high the output port is ready to accept data. This can be determined by a machine-language instruction of `IN A,0FE`, followed by `AND 40` to mask off this one bit, and then a test for nonzero.

A BASIC-language program can sense this bit also, with

some difficulty. Executing the statement `LET X = INP (254)` will set the variable X equal to the decimal value of all the bits read through the status port. The bit in question has a decimal value of 64, as read by BASIC.

Therefore, if this bit is on, the total value of all the bits read together could range from 64 to 127 or from 192 to 255, depending on the state of the other bits connected to this port. These other bits include the input port status and the keyboard switches, so we have to consider their state as being indeterminate. Since BASIC has no bit-masking capability, a test for this bit will require determining if X falls within either of the two ranges of values given above.

As a result, it is easier for a BASIC-language print-driver program to ignore this status bit and merely provide an adequate delay between the output of one character and the next. Fig. 4 gives an example of a BASIC subroutine that will output a carriage return and a line feed to a 10 cps printer connected to the output port.

This is not a neat solution, however, but often an experimenter will not be too concerned with making everything as neat as would, say, a manufacturer. The "proper" way to use the parallel port would be for the device connected to issue the data-accepted signal only when it was ready to receive the next character.

If you find that it simplifies things to just include the delay loop in your driver program, then the strobe-generating hardware shown on the user's side of Fig. 3 is all you need to reset the handshake flip-flop following transmission of each character.

The two inverters and the slow-up capacitor C1 are used to delay the falling edge of the \overline{Q} output for an interval of a few hundred nanoseconds to a few microseconds, depending on the value of C1 and the type of logic used. This delayed edge is then fed back to the flip-flop as its reset signal, causing the \overline{Q} output to go high and returning everything to a steady state.

We sell computers that make sense.



Data General microNOVA™

The Computer Store and its Affiliated Dealers feature the powerful microNOVA™ computer for commercial applications.

We can solve your data processing problems at a surprisingly affordable price!

Comprehensive Applications Software / In Stock - Available Now. Put It to Work for You.

✓ C100

See the microNOVA™:

theComputerStore™

MASSACHUSETTS
Burlington/120 Cambridge St. (617) 272-8770
Cambridge/1689 Mass. Ave. (617) 354-4599
Framingham/Deerskin Plaza, Rt. 9
CONNECTICUT (617) 879-3720
Windsor Locks/630 S. Main St. (203) 627-0188
FLORIDA
Clearwater/21 Clearwater Mall (813) 725-4717
Tampa Bay/Bradenton/1021 Manatee Ave. West
NEW YORK (303) 747-8223
Rochester/2423 Monroe Ave. (716) 244-5000

Affiliated Dealers:

COLORADO/Boulder
Automated Information Systems (303) 443-5199
FLORIDA/Orlando
Pelham Data Systems (305) 830-6282
ILLINOIS/Chicago
Compac Systems (Palatine) (312) 359-8566
MASSACHUSETTS/
Methuen/DP Small Business Sys (617) 683-8422
Sharon/MBL Associates (617) 784-5218
Worcester/Software Solutions (617) 799-4181
MISSOURI/St. Louis
Computer Consultants, Ltd. (314) 993-5000
NEW HAMPSHIRE/Nashua
Computer Mart (603) 883-2386
NEW JERSEY/Toms River
Shore computers (201) 341-2288
NORTH CAROLINA/Rocky Mount
Source One Corp. (919) 977-2784
TEXAS/Wichita Falls
The Computer Center (817) 723-6006
AUSTRALIA/New South Wales (Katora)
Sirasch Engineering 430-992

Dealerships * Franchise opportunities available.

From PERCOM

One-Drive System:

\$399. (40-track) & **\$675.** (77-track)


Two-Drive System:

\$795. (40-track drives) & **\$1350.** (77-track drives)

Three-Drive System:

\$1195. (40-track drives) & **\$2025.** (77-track drives)

Requires Expansion Interface, Level II BASIC & 16K RAM.



Low Cost Add-On Storage for Your TRS-80*. In the Size You Want.

When you're ready for add-on disk storage, we're ready for you.
Ready with six mini-disk storage systems — 102K bytes to 591K bytes of
additional *on-line* storage for your TRS-80*.

- Choose either 40-track TFD-100™ drives or 77-track TFD-200™ drives.
- One-, two- and three-drive systems immediately available.
- Systems include Percom PATCH PAK #1™, on disk, at no extra charge. PATCH PAK #1™ de-glitches and upgrades TRSDOS* for 40- and 77-track operation.
- TFD-100™ drives accommodate "flippy disks." Store 205K bytes per mini-disk.
- Low prices. A single-drive TFD-100™ costs just \$399. Price includes PATCH PAK #1™ disk.
- Enclosures are finished in system-compatible "Tandy-silver" enamel.

Whether you need a single, 40-track TFD-100™ add-on or a three-drive add-on with 77-track TFD-200™s, you get more data storage for less money from Percom.

Our TFD-100™ drive, for example, lets you store 102.4K bytes of data on one side of a disk — compared to 80K bytes on a TRS-80* mini-disk drive — and 102.4K bytes on the other side, too. Something you can't do with a TRS-80* drive. That's almost 205K bytes per mini-disk.

And the TFD-200™ drives provide 197K bytes of on-line storage per drive

— 197K, 394K and 591K bytes for one-, two and three-drive systems.

PATCH PAK #1™, our upgrade program for your TRSDOS*, not only extends TRSDOS* to accommodate 40- and 77-track drives, it enhances TRSDOS* in other ways as well. PATCH PAK #1™ is supplied with each drive system at no additional charge.

The reason you get more for less from Percom is simple. Peripherals are not a sideline at Percom. Selling disk systems and other peripherals is our main business — the reason you get more engineering, more reliability and more back up support for less money.

In the Product Development Queue . . . a *printer interface* for using your TRS-80* with any serial printer, and . . . the *Electric Crayon*™ to map your computer memory onto your color TV screen — for games, animated shows, business displays, graphs, etc. Coming PDQ!

™ TFD-100, TFD-200, PATCH PAK and Electric Crayon are trademarks of PERCOM DATA COMPANY.

*TRS-80 and TRSDOS are trademarks of Tandy Corporation and Radio Shack which have no relationship to PERCOM DATA COMPANY.

PERCOM

PERCOM DATA COMPANY, INC.
DEPT. K • 211 N. KIRBY • GARLAND, TX. 75042

To order add-on mini-disk storage for your TRS-80*, or request additional literature, call Percom's toll-free number: 1-800-527-1592. For detailed Technical information call (214) 272-3421.

Orders may be paid by check or money order, or charged to Visa or Master Charge credit accounts. Texas residents must add 5% sales tax.

Percom 'peripherals for personal computing'

Instant Software

Has It All . . .

Ask for Instant Software at your local computer store, use the handy order blank provided at right, or order your software by phone—call Toll Free 1-800-258-5473.

Action Games

SPACE TREK II Protect the quadrant from the invading Klingon warships. The Enterprise is equipped with phasers, photon torpedoes, impulse power, and warp drive. It's you alone and your TRS-80 Level I 4K, Level II 16K against the enemy. **Order No. 0002R \$7.95.**

SPACE TREK III Let yourself go to the far ends of the solar system—and beyond. This package includes:

- **Stellar Wars**—Shoot down the Tie fighters and destroy the Death Star.
- **Planetary Lander**—Land your spacecraft and plant your flag across the solar system.

These one player games require a TRS-80 Level I 4K. **Order No. 0031R \$7.95.**

SPACE TREK IV Trade or wage war on a planetary scale. This package includes:

- **Stellar Wars**—Engage and destroy Tie fighters in your attack on the Death Star. For one player.
- **Population Simulation**—A two player game where you control the economy of two neighboring planets. You decide, guns or butter, with your TRS-80 Level II 16K. **Order No. 0034R \$7.95.**

TREK-X Command the Enterprise as you scour the quadrant for enemy warships. This package not only has superb graphics, but includes programming for optional sound effects. A one player game for the PET 8K. **Order No. 0032P \$7.95.**

CAR RACE/RAT TRAP/ANTIAIRCRAFT Enjoy these challenging, fun filled programs:

- **Car Race**—You and a friend can race on a choice of two tracks.
- **Rat Trap**—Trap the rat in his maze with your two cats. For one player.
- **Antiaircraft**—Aim and shoot down the enemy airplane. Requires Level I 4K TRS-80. **Order No. 0011R \$7.95.**

PENNY ARCADE Enjoy this fun filled package that's as much fun as a real penny arcade—at a fraction of the cost!

- **Poetry**—Compose free verse poetry on your computer.
- **Trap**—Control two moving lines at once and test your coordination.

- **Poker**—Play five card draw poker and let your PET deal and keep score.
- **Solitaire**—Don't bother to deal, let your PET handle the cards in this "old favorite" card game.

- **Eat-Em-Ups**—Find out how many stars your gobbler can eat up before the game is over.

These six programs require the PET with 8K. **Order No. 0044P \$7.95.**


RAMROM PATROL/TIE FIGHTER/KLINGON CAPTURE Buck Rogers never had it so good. Engage in extraterrestrial warfare with:

- **Ramrom Patrol**—Destroy the Ramrom ships before they capture you.
- **Tie Fighter**—Destroy the enemy Tie fighters and become a hero of the rebellion.
- **Klingon Capture**—You must capture the Klingon ship intact. It's you and your TRS-80 Level II 16K battling across the galaxy. **Order No. 0028R \$7.95.**

QUBIC-4/GO-MOKU Play two ancient games on your modern PET. The two programs included are:

- **Qubic-4**—Play a multi-dimensional game of tic-tac-toe.
- **Go-Moku**—Line up five of your men while blocking the PET's moves.

These one player games require 8K of memory. **Order No. 0038P \$7.95.**



TANGLE/SUPERTRAP These two programs require fast reflexes, and a good eye for angles:

- **Tangle**—Make your opponent crash his line into an obstacle.
- **Supertrap**—This program is an advanced version of Tangle with many user control options.

Enjoy these exciting and graphically beautiful programs. For one or two players with an 8K PET. **Order No. 0029P \$7.95.**

CAVE EXPLORING/YACHT/CONCENTRATION These three programs are not only fun, but stimulating as well:

- **Cave Exploring**—Search for fabulous treasures as you explore the magic cave. For one player.
- **Yacht**—One player can enjoy this game based on Yahtzee.
- **Concentration**—Two players can pit their memories in this program based on the popular television show. You'll need a TRS-80 with Level I and 16K. **Order No. 0010R \$7.95.**

DESTROY ALL SUBS/GUNBOATS/BOMBER This package of three programs is fun for the whole family. Included are:

- **Destroy All Subs**—Hunt down enemy subs while avoiding mines and torpedoes. A one player game.
- **Gunboats**—One or two players can try to blow each others ships out of the water.
- **Bomber**—Carefully release your bomb to destroy the moving submarine. A one player game.

To enjoy these programs you'll need a TRS-80 Level I 4K. **Order No. 0021R \$7.95.**

KNIGHT'S QUEST/ROBOT CHASE/HORSE RACE This varied package of one player games will give you hours of fun.

- **Knight's Quest**—Battle demons to gain treasure and become a full fledged knight.
- **Robot Chase**—Destroy the deadly robots without electrocuting yourself.
- **Horse Race**—Place your bet and cheer your horse to the finish line.

These programs require a TRS-80 Level I 16K. **Order No. 0003R \$7.95.**

DEMO I This package is just the thing to show your friends what your TRS-80 can do. Included are:

- **Computer Composer**—Compose and play music using only a standard AM radio.
- **Baseball**—Play baseball with your computer while it does the scorekeeping.

- **Horse Race**—Place your bet and cheer your pony to the winner's circle.
- **ESP**—Test your powers of extrasensory perception.

- **Hi-Lo/Tic-tac-toe**—Guess the secret number or get three in a row.
- **Petals Around the Rose**—Can you figure out the secret behind the five dice?

- **Slot Machine**—Turn your computer into a one-armed bandit. These programs require a TRS-80 Level I 4K. **Order No. 0020R \$7.95.**

BASIC AND INTERMEDIATE LUNAR LANDER Bring your lander in under manual control. The Basic version is for beginners; the Intermediate version is more difficult, with a choice of landing areas and rugged terrain. For one player with a TRS-80 Level I 4K, Level II 16K. **Order No. 0001R \$7.95.**

Business

BUSINESS PACKAGE I Keep the books for a small business with your TRS-80 Level I 4K. The six programs included are:

- **General Information**—The instructions for using the package.
- **Fixed Asset Control**—This will give you a list of your fixed assets and term depreciation.
- **Detail Input**—This program lets you create and record your general ledger on tape for fast access.

- **Month and Year to Date Merge**—This program will take your monthly ledger data and give you a year to date ledger.
- **Profit and Loss**—With this program you can quickly get trial balance and profit and loss statements.
- **Year End Balance**—This program will combine all your data from the profit and loss statements into a year end balance sheet.

With this package, you can make your TRS-80 a working partner. **Order No. 0013R \$29.95.**

BUSINESS PACKAGE III This package can change your TRS-80 into a full working partner for any businessman:

- **Inventory**—Maintain a computer-based inventory for a constant inventory system.
- **Commissions and Percentages**—Let your computer figure out markup and discount calculations, sales tax and more. This is a perfect timesaving package for any small business.

For the TRS-80 Level I 4K. **Order No. 0061R \$7.95.**

DATA TAPES

Top quality high density audio cassettes for data storage. Each cassette runs 30 minutes, and is fitted with conveniently marked labels that make controlling your "data bank" a snap. Sold in lots of four. **Order No. 0067. \$7.95.**

Educational Games and Simulations

BOWLING Let your TRS-80 set up the pins and keep score. One player can pick up spares and get strikes. For the TRS-80 Level I 4K, Level II 16K. **Order No. 0033R \$7.95.**

CHECKERS/BACARRAT Play two old favorites with your PET.

● **Checkers**—Let your PET be your ever-ready opponent in this computer-based checkers program.

● **Bacarrat**—You have both Casino and Blackjack-style games in this realistic program.

Your PET with 8K will offer challenging play anytime you want. **Order No. 0022P \$7.95.**

CASINO II This craps program is so good, it's the next best thing to being in Las Vegas or Atlantic City. It will not only play the game with you, but also will teach you how to play the odds and make the best bets. A one player game, it requires a PET 8K. **Order No. 0015P \$7.95.**

AIR FLIGHT SIMULATION Turn your TRS-80 into an airplane. You can practice takeoffs and landings with the benefit of full instrumentation. This one-player simulation requires a TRS-80 Level I 4K, Level II 16K. **Order No. 0017R \$7.95.**

GOLF/CROSSOUT Have fun with these exciting one-player games. Included are:

● **Golf**—You won't need a masher or putter—or a caddy, for that matter, to enjoy a challenging 18 holes.

● **Crossout**—Remove all but the center peg in this puzzle and your neighbors will call you a genius.

You'll need a TRS-80 Level I 4K, Level II 16K. **Order No. 0009R \$7.95.**

GOLF Without leaving the comfort of your chair, you can enjoy a computerized 18 holes of golf with a complete choice of clubs and shooting angles. You need never cancel this game because of rain. One or two players can

enjoy this game on the Apple with Applesoft II and 20K. **Order No. 0018A \$7.95.**

DOW JONES Up to six players can enjoy this exciting stock market game. You can buy and sell stock in response to changing market conditions. Get a taste of what playing the market is all about. Requires a PET with 8K. **Order No. 0026P \$7.95.**

HEX PAWN/SHUTTLE CRAFT DOCKING/SPACE CHASE/BATTLESHIP This four-game package is sure to provide hours of fun for the whole family.

● **Hex Pawn**—Turn your TRS-80 into a model of artificial intelligence by playing a simple game.

● **Shuttle Craft Docking**—Land your shuttle craft on the starship—even through varying gravity fields!

● **Space Chase**—Seek out and destroy the enemy delta that's hidden in the star field.

● **Battleship**—You must find and destroy the enemy fleet.

This package requires a TRS-80 Level I 16K. **Order No. 0041R \$7.95.**

SANTA PARAVIA AND FIUMACCIO Become the ruler of a medieval city-state as you struggle to create a kingdom. Up to six players can compete to see who will become the King or Queen first. This program requires a TRS-80 Level I & II. **Order No. 0043R \$7.95.**

CARDS This one-player package will let you play cards with your TRS-80—talk about a poker face!

● **Draw and Stud Poker**—These two programs will keep your game sharp.

● **No-Trump Bridge**—Play this popular game with your computer and develop your strategy.

The package name says it all. Requires a TRS-80 Level II 16K. **Order No. 0063R \$7.95.**

MIMIC Test your memory and reflexes with the five different versions of this game. You must match the sequence and location of signals displayed by your PET. This one-player program includes optional sound effects with the PET 8K. **Order No. 0039P \$7.95.**

BOWLING/TRIOLOGY Enjoy two of America's favorite games transformed into programs for your Apple:

● **Bowling**—Up to four players can bowl while the Apple sets up the pins and keeps score. Requires Applesoft II.

● **Trilogy**—This program can be anything from a simple game of tic-tac-toe to an exercise in deductive logic. For one player.

This fun-filled package requires an Apple with 20K. **Order No. 0040A \$7.95.**

BACKGAMMON/KENO Why sit alone when you can play these fascinating games with your TRS-80?

● **Backgammon**—Play against the computer. Your TRS-80 will give you a steady challenging game that's sure to sharpen your skills.

● **Keno**—Enjoy this popular Las Vegas gambling game. Guess the right numbers and win big.

You'll need a TRS-80 Level I & II. **Order No. 0004R \$7.95.**

OIL TYCOON Avoid oil spills, blowouts and dry wells as you battle to become the world's richest oil tycoon. Two players become the owners of competing oil companies as they search for oil and control their companies. Requires a TRS-80 4K Level I & II. **Order No. 0023R \$7.95.**

CASINO I These two programs are so good, you can use them to check out and debug your own gambling system!

● **Roulette**—Pick your number and place your bet with the computer version of this casino game. For one player.

● **Blackjack**—Try out this version of the popular card game before you go out and risk your money on your own "surefire" system. For one player.

This package requires a PET with 8K. **Order No. 0014P \$7.95.**

BASEBALL MANAGER This pair of programs will let you keep statistics on each of your players. Obtain batting, on-base, and fielding averages at the touch of a finger. Data can be easily stored on cassette tape for later comparison. All you need is a PET with 8K. **Order No. 0062P \$14.95.**

BOWLING LEAGUE STATISTICS SYSTEM This package is the answer to the prayers of harried bowling league scorekeepers. The Bowling League Statistics System will keep a computerized list of league data, team data, and data for each bowler. It is extremely flexible and has a total of 16 different options to let you modify the program to suit your league's rules. The program is very easy to use and has extensive "built-in" aids to help you along. Requires TRS-80 Level II 16K. **Order No. 0056R \$24.95.**

Home and Personal

PERSONAL FINANCE I Let your TRS-80 handle all the tedious details the next time you figure your finances:

● **Personal Finance I**—With this program you can control your incoming and outgoing expenses.

● **Checkbook**—Your TRS-80 can balance your checkbook and keep a detailed list of expenses for tax time.

This handy financial control for the home requires only a TRS-80 Level I 4K. **Order No. 0027R \$7.95.**

MORTGAGE WITH PREPAYMENT OPTION/FINANCIER These two programs will more than pay for themselves if you mortgage a home or make investments:

● **Mortgage with Prepayment Option**—Calculate mortgage payment schedules and save money with prepayments.

● **Financier**—Calculate which investment will pay you the most, figure annual depreciation, and compute the cost of borrowing, *easily and quickly*.

All you need to become a financial wizard with an 8K PET. **Order No. 0006P \$7.95.**

STATUS OF HOMES/AUTO EXPENSES Two long awaited programs that have got to save you money at work or in the home:

● **Status of Homes**—This program will allow you to keep track of all the expenses involved in building one house or an entire subdivision.

● **Auto Expenses**—Find out *exactly* what it costs you to drive your car or truck.

These programs require a TRS-80 Level I 4K. **Order No. 0012R \$7.95.**

PERSONAL WEIGHT CONTROL/BIORHYTHMS Let your PET help take care of your personal health and safety:

● **Personal Weight Control**—Your PET will not only calculate your ideal weight, but also offer a detailed diet to help control your caloric intake.

● **Biorhythms**—Find out where your critical days are for physical, emotional, and intellectual cycles.

You'll need only a PET with 8K memory. **Order No. 0005P \$7.95.**

Electronics

HAM PACKAGE I This versatile package lets you solve many of the commonly encountered problems in electronics design. With your Level I 4K or Level II 16K TRS-80, you have a choice of:

● **Basic Electronics with Voltage Divider**—Solve problems involving Ohm's Law, voltage dividers, and RC time constants.

● **Dipole and Yagi Antennas**—Design antennas easily, without tedious calculations.

This is the perfect package for any ham or technician. **Order No. 0007R \$7.95.**

ELECTRONICS I This package will not only calculate the component values for you, but will draw a schematic diagram too. You'll need a TRS-80 Level I 4K, Level II 16K to use:

● **Tuned Circuits and Coil Winding**—Design tuned circuits without resorting to cumbersome tables and calculations.

● **555 Timer Circuits**—Quickly design astable or monostable timing circuits using this popular IC.

● **LM 381 Preamp Design**—Design IC preamps with this low noise integrated circuit.

This package will reduce your designing time and let you build those circuits fast. **Order No. 0008R \$7.95.**

Cut along dotted line and mail today

**Order your
Instant Software
today!**

To order by phone, call
toll free 1-800-258-5473
(MasterCharge, VISA
and AMEX order accept-
ed) or ask for Instant
Software at your local
computer store.

☐ Check ☐ Money Order ☐ VISA ☐ AMEX
☐ MasterCharge Expiration date _____

Card No. _____

Name _____

Address _____

City _____ State _____ Zip _____

Signed _____

**Send me the following
Instant Software:**

Quantity	Order No.	Program name	Unit Cost	Total cost
		Shipping		\$1.00
		Total order		

Instant Software Inc. DEPT MIS A2
Peterborough NH 03458

A Telephone Data Coupler for the TRS-80

Build a TDC for only about \$20, and exchange TRS-80 programs with friends and neighbors.

Fred G. Smith
194 Jane Circle
Athens GA 30606

Why not use the telephone to exchange your TRS-80 programs with your friends? You can easily build a Telephone Data Coupler (TDC) that looks and works like a commercial unit but costs only about \$20. The heart of the TDC is a Realistic telephone amplifier made by Radio Shack. This professional-looking amplifier is easily converted into a data coupler.

Large computers use a separate modulator/demodulator

(MODEM) to convert serial binary data to audio tones that can be transmitted over the telephone lines (see "Build the \$35 Modem," *Kilobaud*, November 1977, p. 94). Small-computer systems have similar modulators and demodulators in their cassette interfaces, so that you only have to add the telephone coupler.

A transformer can be used to connect the cassette interface output with Ma Bell (see "Mickey Modem," *Kilobaud*, November 1978, p. 52), but there may be local regulations that limit the use of direct-line connections. Direct-wired couplers

are also more difficult to disconnect if you move your system.

The Telephone Data Coupler described here uses simple acoustic and inductive coupling to link your computer to the handset of any standard (not GTE-type) telephone. A small speaker directs the cassette interface output into the handset mouthpiece, and an inductive pickup coil senses the incoming signals from the earpiece of the handset. Many commercial modems use this type of coupling because it is dependable and convenient.

Modification

The Realistic telephone amplifier (Radio Shack no. 43-230) has all of the essential parts needed for the TDC: a cradle to hold the handset, a pickup coil to receive data and an amplifier to boost the 800 mV TRS-80 output to speaker level. The only additional parts are two miniature phono jacks, a miniature phono plug and a 0.22 μ F tantalum capacitor. The total bill should be about \$20.

The telephone amplifier is easy to convert. Cut one inch off the back of the remote speaker case and mount the shortened case in the lower part of the mouthpiece chamber. Mount the two new jacks in the end panel of the amplifier

case in line with the speaker output jack that is already there (see Photo 1). Disconnect the pickup coil leads from the printed circuit board and connect these leads to one of the new jacks (OUTPUT).

Wire the other new jack to the volume control with the 0.22 μ F capacitor in the tip lead as shown in Fig. 1 (this is the TRS-80 jack). Wire the speaker to the amplifier output via the old speaker jack (now called TAPE).

Operation

The TDC is easy to use. There are three modes of operation: receiving, sending from the TRS-80 and sending from tape.

To receive, connect the OUTPUT jack of the TDC to the MIC (not the AUX) jack of your tape recorder (see Photo 2). Place the telephone handset on the TDC and record the incoming program as if it were coming from your computer.

To send from the TRS-80, insert the gray TRS-80 output plug into the TRS-80 jack on the TDC (see Photo 1). Load a program into the computer memory from tape or from the keyboard. Type CSAVE and press the enter key. Adjust the TDC volume control until the TRS-80 audio output is clearly audible in the TDC speaker. Place the telephone handset on the TDC,



Photo 1. The Telephone Data Coupler connected to send a program from the TRS-80 cassette interface output. Some modification of the Realistic telephone amplifier is needed to make it function as a data coupler.




Fig. 1. Circuit diagram for the converted telephone amplifier.

noises.

I have prepared a 4K, Level I TRS-80 cassette tape that has several TDC programs you might find useful. The first program is an illustrated, step-by-step conversion plan to help you build the TDC. The second program explains and diagrams the testing and opera-

tion of the TDC. The last program shows how to use the TDC as a recording monitor, a music (?) machine, an audible logic probe and as other handy TRS-80 peripherals. The multi-program cassette is available postpaid for \$5.50 (check or money order) from Gnosis, Inc., Box 1911, Athens GA 30603. ■

type CSAVE again and press "enter" to send the program.

To send from tape, disconnect the TRS-80. Connect the tape recorder EAR jack to the TAPE jack of the TDC. Insert a program tape in the recorder and start it. Adjust the tape-recorder volume control until the tape output is clearly audible in the TDC speaker. Rewind the tape, place the telephone handset on the TDC and start the tape to send the program.

Comments

The Telephone Data Coupler has added a lot of pleasure to my personal computing. Local transmissions are dependable,

but long-distance relays may not work; long-distance lines seem to have too much noise for reliable copying. Don't ever couple loud signals into the telephone, or annoying (and illegal) crosstalk can occur.

Transmissions from tape are not as reliable as transmissions directly from the TRS-80. The output of the computer has a more constant rate and amplitude than most tapes (see "Copying Computer Cassettes," *Kilobaud*, August 1978, p. 94). Use the TRS-80 whenever you can. It helps to place sponge rubber around the inside of the speaker chamber of the TDC to reduce the pickup of stray room



Photo 2. The Telephone Data Coupler connected to the recorder in the receive mode. The interconnecting cable is modified from parts of the Realistic telephone amplifier.

PASCAL PERFORMANCE.

The new Pascal Computer System is driven by a unique 16-bit Pascal MICROENGINE™ — the first microprocessor hardware designed exclusively for direct high-level language execution. ■ The processor is incorporated into a single board computer system, the WD/90, which directly executes Pascal intermediate code generated by the University of California at San Diego (UCSD) Pascal compiler, Release III.0. ■ Since P-code output by the Pascal compiler represents an ideal architecture for a computer executing Pascal programs and since the WD/90 directly executes P-code (no interpreter), these programs execute up to five or more times faster than equivalent systems.

WESTERN DIGITAL ✓ W25

3128 Redhill Avenue, Box 2180 • Newport Beach, CA 92663
(714) 557-3550, TWX 910-595-1139

The WD/90 Pascal MICROENGINE™ Computer includes: ■ Pascal MICROENGINE™ processor ■ 64K bytes of RAM Memory ■ Two RS-232 asynchronous/synchronous ports (110-19.2K baud-full duplex) ■ Two 8-bit parallel ports (500 kHz maximum data rate) ■ Floppy disk controller with direct memory access (DMA), switch selectable for: single or double density (IBM format); mini or standard floppy; 1 to 4 drives (same type) ■ Floating point hardware (proposed IEEE standard) ■ Memory Mapped I/O ■ Enclosed power supply Complete UCSD Pascal Operating System (Release III.0)

FOR FURTHER INFORMATION CONTACT
DISTRIBUTOR: CIT (714) 979-9920
RETAIL: Your **LOCAL COMPUTER** Store
OEM: Your **WESTERN DIGITAL** Sales Representative

The Cromemco Z-2D

A year of problem-free operation produced this hardware/software review of the Z-2D.

Steven K. Roberts
129 North Galt Avenue
Louisville KY 40206

I have wire-wrapped an 8008 system, written its monitor and spent lonely nights hand-assembling programs. As both a user and a dealer, I have done endless battle with a much-touted West Coast manufacturer of near-worthless hardware and nearly quit the microprocessor field as a result of the frustration. And, I have attempted to live entirely without a system.

The solution to the agonies of my existence (somewhere between the classifications of

"serious hobbyist" and "microprocessor engineering firm") has become clear in the last year—twelve months untroubled by downtime, inadequate system software and uninterested manufacturers. For one year, I have lived with a Cromemco Z-2D.

Cromemco has done an admirable job integrating various hardware and software components into an efficient computer system. Originally a producer of "add-ons" for the Altair and Imsai markets, the company began in 1977 to produce its own S-100-based processor, the Z-2. It was instantly evident that they were addressing existing deficiencies in the field, as the mechanical design was

not flimsy and the bus was quiet.

Encouraged by the Z-2's initial enthusiastic acceptance, Cromemco added the two Wangco minifloppies and their controller, which turn the mainframe into a Z-2D. An operating system called CDOS (originally a derivative of CP/M, now an enhancement thereof) was provided, supporting an excellent assembler, a comprehensive disk BASIC, FORTRAN IV, and recently, COBOL, a word processor, and a data base management system. In late 1977, when it was incorrectly assumed that the majority of microprocessor customers were hobbyists, most manufacturers would have long since engaged in the popular art of laurel-resting.

Throughout my involvement with Cromemco, the two most notable characteristics of the company have been its technical competence and its interest in helping users with problems. The latter is almost dizzying (in light of my hundreds of telephone and UPS dollars spent in the past in fruitless pursuit of factory support from one of the major entities in this strange new industry). Unhomogenized by longevity and complacency, the range of attitudes sported by the system manufacturers ranges from the "You bought it, it's yours" philosophy, which is most familiar, to Cromemco's almost embarrassing willingness to devote considerable energy to a problem and, yes,

even return phone calls.

But enough plaudits; let's look at specifics.

Hardware

Photo 1 shows the system, which includes an EPROM programming station, an extension of the Cromemco Bytesaver contained in the mainframe. This allows unrestricted programming of 2708s without tearing into the system to get at the board.

Photo 2 shows the basic system peripherals. The Hazeltine 1500 CRT is interfaced by the disk controller board, which conveniently includes a programmable serial I/O port for the console. Presently there are two CRTs on the system (the second is an HP 2645A). The Diablo printer on the right is interfaced with a carry-over from my past: an Imsai PIO 4-4 Parallel I/O board (the printer needs three output ports and one input port).

The only items in the photograph that may give rise to questions are on top of the system cabinet. Under the oscilloscope is a unit I affectionately call the "Kludge Box," a buffered and isolated S-100 bus extension that provides 180 wire-wrap sockets. This allows plenty of room for all those little odds and ends that seem to get added to the system, without the major surgery that is so often undertaken. (This, along with the EPROM panel, is probably a contributor to the exceptional repair history of this system—one year with not one glitch.)



Photo 1. Z-2D EPROM programming station. (Photos by Douglas Fowley)

The sloppy bit of hardware on the right is associated with an experimental music system that, undocumented, had to remain undisturbed for the photograph. (No, the system is rarely this neat.)

If you look inside the Z-2D, first from the back, you will see the view as shown in Photo 3. This power supply provides 30 Amps of +8 V and 15 Amps each of +18 V and -18 V. The vertically oriented backplane may be seen, adorned by various boards (21 are allowed).

Photo 4 is a view of the system from the front, after the front panel with its two drives has been removed. The configuration at the time of the photograph included: 48K of RAM (using three of Cromemco's 16KZ dynamic RAM boards), disk controller, Processor Technology VDM-1, Cromemco Dazzler, Bytesaver, another 4K of RAM (noncontiguous), the interface to the Kludge Box, a custom development tool dubbed the Ramport and, of course, the Z-80 CPU board. The generally over-worked bus lines with the system in action are unusually quiet, a major plus in the S-100 world.

The internal difference between the Z-2 and the Z-2D, apart from the presence of the disk drives and their controller, is that the entire card cage has been moved back from its original position near the front of the cabinet. This is not readily apparent in the photo, due to foreshortening, but it has the effect of changing airflow of the original design. Rather than pulling the air directly through the card cage, the fan now draws the air past the disk drives and over the top of the cards. This appears to be an adequate means of heat dissipation, but is probably less than optimal.

Assembly of the kit system was a surprise: It worked the first time, 48K of RAM included. Cromemco replaced a Wangcc drive with a bad write-protect sensor within four days, and I had a couple of minor problems interpreting their early documentation (that was late 1977—it has long since been pol-



Photo 2. The author's system with peripherals.

ished).

The architecture of the system is well defined by the Z-80 itself; the details of interfacing, interrupts, direct memory access and the like are better gleaned from the wealth of S-100 and Z-80 literature with which our industry abounds. The only comment I can make, as a microprocessor system designer, is that they did it well.

Software

Once a computer system is implemented and screwed into its cabinet, it should become more or less invisible to the user. When I am sitting at the terminal writing an article, I am not really concerned with the hardware; I merely have faith in its function. The real strength of a system lies in its software. Clumsily written code in crucial areas of an operating system has been the death of many a hot new product.

I should preface the discussion of the Z-2D's software with

a few comments about my use of the system, lest I be accused of esoterica-mongering or even wanton purism. Apart from all the fun things (music, graphics, games, etcetera, ad nauseam), I use my system heavily and daily for two types of tasks: the generation of article manuscripts and the development/simulation of software for custom products with single board computers inside. (The latter is the output of the microprocessor engineering firm known as Cybertronics, Inc.)

Word processing on the Z-2D was recently made possible by an impressive software package called the Text Formatter, a stand-alone program that accepts a raw text file (prepared with the Text Editor) as input and produces formatted pages as output. Title centering, underlining, page numbering, right-justification (tailored either to matrix or Diablo/Qume/NEC printers) and multi-

diskette files are all handled with ease. (My typewriter, dusty, fallen from glory, now dozes under the inevitable stack of papers, awaiting the occasional opportunity to address an envelope. I don't miss it, or the chalk paper.)

But word processing is a fairly pedestrian business function, associated with offices and IBM commercials. The area in which I am most frequently amazed at the quality of the software is in the system's use as a development tool.

It can be frustrating to develop code for single board processors. The ones we most frequently use—Intel SBC 80/04s—have no resident monitor, take their instructions from 4K of ROM space and offer a whopping 256 bytes of scratchpad RAM. At \$195, the SBC 80/04 is a multifaceted device, but devoid of frills. Obviously, a development system is necessary.

Intel suggests the MDS, an




Photo 3. Rear view of the Z-2D showing power supply and backplane.

excellent product which, with the software known as ISIS and its partners, makes a superb development tool for the single board processors. The only problem is the near-\$20,000 price tag.

The Z-80 assembler provided by Cromemco, along with a package called, appropriately, DEBUG, is a good start. Software can be produced on the system with the editor, assembled and burned into EPROMs, which are then plugged into the single board computer. However, I don't know about you, but a successful piece of custom software around here usually has a revision number between 30 and 60. That's a lot of EPROM burning.

So, the Ramport was born. 2K of RAM is wire-wrapped onto a Vector 8800V prototype card, along with some multiplexing and control logic. Normally, it looks like any other RAM in the system, but when a certain output instruction is issued, it becomes—voilà!—an exact imitation of a 2716 EPROM on the end of a 24 conductor DIP cable, which happens to be plugged into the SBC 80/04.

Issuance of a RESET to the SBC causes it to begin executing the code in what it assumes is its ROM, allowing revision after revision to be generated without using the EPROM programmer. And since it is RAM, its mode can be toggled back and forth between internal and

ability to produce relocatable code via an assembler, which allows such niceties as conditional assemblies and disk macro libraries, it is almost fun (well, let's not get carried away) to develop software for external processors or, of course, for the Z-2D itself.

A quick comment on macros is justified. With such a large portion of most assembly-level programs consisting of utilities and blocks of code that are universally handy, it is worthwhile to build a macro library of utilities and incorporate it on the assembler disk. When the assembler encounters a macro call, it checks for reference to the external file, then wanders off to the library and extracts the needed code. As the library grows, it becomes more and more possible to write entire programs consisting of nothing but macro calls. This is an ideal way to write your own high-level language, exquisitely tailored to your specific requirements.

It's easy to stray into the finer points of computer use when talking about the Cromemco system, and while questionable from a literary stand-

point, that is a good sign. The best index of a computer system's value is the extent to which it makes its presence felt: the less the better. The operation of the Z-2D is smooth, reducing to almost zero the occasions when it is necessary to pay attention to the system itself.

We're into this, most of us, because we see potential in the use of microprocessors as "thought amplifiers." We are aware that the marriage of the human mind, with all its abstraction and pattern-recognition capability, to the computer, with its swiftness of calculation and flawless memory, offers unprecedented opportunities for creative expression and practical enrichment of our lives.

The less we have to fiddle around with the interface between ourselves and our machines, the better we can address ourselves to the tasks at hand.

In the never-ending asymptotic approach to the *ideal*, the Cromemco Z-2D remains refreshingly in step with the state of the art. ■





Photo 4. Front view of the system.

DOUBLE DENSITY



SOLID SAVINGS!

Now you can put your S-100 system solidly into a full-size, single/double density, 600K bytes/side disk memory for just \$1149 complete.

DISCUS/2D™ single/double density disk memory from Thinker Toys™ is fully equipped, fully assembled, and fully guaranteed to perform perfectly.

DISCUS/2D™ is a second generation disk memory system that's compatible with the new IBM System 34 format. The disk drive is a full-size Shugart 800R, the standard of reliability and performance in disk drives. It's delivered in a handsome cabinet with built-in power supply.

The S-100 controller utilizes the amazing Western Digital 1791 dual-density controller chip . . . plus power-on jump circuitry, 1K of RAM, 1K of ROM with built-in monitor, and a hardware UART to make I/O interfacing a snap.

The DISCUS/2D™ system is fully integrated with innovations by designer/inventor George Morrow. Software includes BASIC-V™ virtual disk BASIC,

DOS, and DISK-ATE™ assembler/editor. Patches for CP/M* are also included. CP/M*, MicroSoft Disk BASIC and FORTRAN are also available at extra cost.

DISCUS/2D™ is the really solid single/double density disk system you've been waiting for. We can deliver it now for just \$1149. And for just \$795 apiece, you can add up to 3 additional Shugart drives to your system. Both the hardware and software are ready when you are.

Ask your local computer store to order the DISCUS/2D™ for you. Or, if unavailable locally, write Thinker Toys,™ 5221 Central Ave., Richmond, CA 94804. Or call (415) 524-2101 weekdays, 10-5 Pacific Time. (FOB Berkeley. Cal. res. add tax.)

*CP/M is a trademark of Digital Research.



Morrow makes disk memory for

Thinker Toys™

Personal Computing, Meet Photography

Personal computing relies on photography, and vice versa. This brings them together.

Did you ever have one of those days when you must get one good print from each of 12 negatives, but you only have 14 sheets of paper? Or did you ever have to produce one or two prints each of 100 negatives — today (and it's noon already)? Or did you ever want to start working on the display-quality print that you knew a negative could give, but you really didn't want to be bothered with making test prints? Well, then, this program is for you.

It runs in about 6K, including 4K of BASIC, but not including the REMs. It should run on any BASIC that handles decimal fractions. Although this program will not transform you into an excellent photo-printer, it will enable you to produce your usual-quality prints much more quickly. To fully utilize this program, you will have to own or have access to a transmission-type densitometer, a computer, a ruler or tape measure, and whatever other darkroom equipment you need to print black-and-white film. Furthermore, you will

need a knowledge of good photographic and densitometric practice.

Program Origin

The incubation of this program was fairly long. Not long ago, I was a free-lance photographer who also did a lot of lab work. I would have been happy to get print orders for hundreds of prints from one or two negatives; instead, I received orders for one or two prints from hundreds of negatives. Each print required a test print, or two, and this did not help my disposition or profits.

I wanted a densitometer to cut down my printing chores, but they were too expensive. I felt that although an on-easel printing meter would be cheaper, it would also be less versatile (you can print with a densitometer, but you can't read negative densities with an on-easel printing meter).

Then one day I was looking for a bottle of toner in a camera store I did not usually frequent and found, instead, a dusty old Kodak Model 1 Densitometer for \$25. (For any non-photographers: this

is like finding an ASCII-coded Selectric in good condition for about \$200.) I asked the clerk if it worked, and he replied, "If you'll tell me what it's supposed to do, I'll try to find out."

We plugged it in, turned it on, and tried it out on some negatives he had in the store; both lights lit, all of the controls and knobs turned and seemed to control what they were supposed to. So, I bought it, took it home and, after some cleaning and repairing, began using it. It took me about five minutes to read a negative and calculate the new exposure time (on a hand-held four-banger), but it still beat doing test prints.

Around the same time, I started seeing articles in magazines, and then entire magazines, devoted to microcomputers. I bought an SWTP 6800, and soon I was playing games on it. Then one day it dawned on me — let the computer do the number-crunching drudgery; so I wrote this program.

My goals were to write a program that *would*:

1. Determine correct exposure time and f-stop for four film formats, given the highlight density of the new negative and the size of the new print.
2. Attempt to keep the exposure time between 5 and 30 seconds.
3. Restrict the number of decimal places in the exposure time to the accuracy of my Heathkit photo timer (i.e., to the nearest 1/10 second below ten seconds and to the nearest second above ten seconds).
4. Give me the option of reprinting a negative at a new size with a minimum of keystrokes and mental effort.
5. Give me the option of letting the computer determine the paper grade, and adjusting the exposure time for the new paper grade. (This, I told myself, is for when I print other peoples' negatives, since I have deluded myself into thinking that all my negatives print on #2 paper — just as all my programs run the first time.)

Four Factors to Consider

Basically, four factors ef-

fect the exposure problem: (1) the standard printing time, (2) the highlight densities of the standard and the new negatives, (3) the size of the old and new prints, (4) the paper-grade correction factor.

Let's look at them one at a time.

The standard printing time. This, and all your standard data, is obtained in the process of making a good print. It is the reference point from which you work. It is important to realize that the prints this program produces will usually be of about the same quality as the standard print. If the standard print is too dark, the prints the program produces will be too dark.

The highlight densities of the standard and new negatives. Highlights are the lightest areas of the print and the darkest areas on the negative. The rendition of the highlights is controlled by printing time (a small change in printing time will change the rendition of the highlights, leaving the shadows basically unchanged). So, printing time is controlled by the highlight densities, and the relationship is this:

$$A = 10^{\uparrow} (\text{ABS } H(Y) - H(1))$$

where A is the density-correction factor, H(Y) is the standard highlight density for

the format being printed and H(1) is the new highlight density.

The size of the old and new prints. The print exposure time is further determined by the brightness of the light that falls on the paper, in turn controlled by the distance between the enlarging head and the paper. Like most projected light, the light leaving the enlarger describes a conical solid, so the intensity of the illumination is controlled by the inverse-square law. That is, when the distance between the enlarger head and the paper doubles, the diameter of the conical section doubles, and the area increases by a factor of 4. The same amount of light leaves the enlarger in either case, so the intensity decreases with the area being illuminated, or by a factor of 4, which in turn means that the exposure must be increased by a factor of 4 (see Fig. 1).

To simplify: If we measure the length of the *entire* projected image for both the standard and new negatives, the area of the projection will have changed according to the square of the sides. In the

$$C = (L(1) * L(1)) / (L(Y) * L(Y))$$

Example 1.




Fig. 1. The intensity of the light falling on the easel varies with the square of the distance, or in direct proportion to the projected area.

program, the relationship is expressed as in Example 1, where C is the size-correction factor, L(1) is the new print size, and L(Y) is the standard print size for the format being printed. To clarify: The entire projected length of the negative is measured, *not* just the part that you are printing!

The paper-grade correction factor. Just as the exposure time controls the highlights of the print, so the shadows, or dark areas of the print, are

controlled by the paper grade and developing time of the paper. The developing time is best left constant at a carefully controlled 2½ minutes. The print quality cannot be judged except in room (white) light; and if developing time has not been closely monitored, it is difficult to repeat or correct. The exception is when fine-contrast controls on the order of ½ paper grade or less are needed.

A more thorough dis-

Program listing.

```
*G
READY
#LOAD
0001 REM PHO-OPS VERSION 1.5
0002 REM TEST PRINT ELIMINATOR
0003 REM
0004 REM BY MICHAEL P. AVERY
0005 REM
0006 REM
0007 REM
0008 REM THE DATA IN THE LINES
0009 REM BELOW MUST BE CHANGED
0010 REM FOR YOUR SYSTEM.
0011 REM 35MM HI,TIME,F/,SIZE
0012 DATA .90,7.8,5.6,5.5
0013 REM 2 1/4 ^2
0014 DATA .95,8.2,8,8
0015 REM 2 1/4 X 3 1/4
0016 DATA .95,8.2,8,8
0017 REM 4X5
0018 DATA 1.1,18,8,5.875
0020 DIM H(6),S(6,6),T(6),V(6),L(6)
0021 M=0
0030 REM THE LINES BELOW HAVE
0031 REM CONTRAST LEVEL DATA
0032 REM FOR THE 6 PAPER GRADES
0033 REM AND THE 4 FILM FORMATS.
0034 REM GRADES 0,1,2,3,4,5
0035 REM 35 MM
0036 DATA .6,.5,.4,.3,.2,.1
0037 REM 2 1/4 ^ 2
0038 DATA 1.6,1.4,1.2,1.0,.8,.6
0039 REM 2 1/4 X 3 1/4
0040 DATA 1.6,1.4,1.2,1.0,.8,.6
0041 REM 4 X 5
0042 DATA 1.6,1.4,1.2,1.0,.8,.6
0099 REM THIS READS THE DATA IN LINES 10-20
0100 FOR Z=3 TO 6 STEP 1
0120 READ H(Z),T(Z),V(Z),L(Z)
0140 NEXT Z
0141 REM THIS READS THE SHADOW
0142 REM DENSITY MATRIX.
0143 FOR Y=3 TO 6
0144 FOR Z=1 TO 6
0145 READ S(Y,Z)
0146 NEXT Z
0147 NEXT Y
0150 GOSUB 2200
0160 PRINT "FILM FORMATS:"
0170 PRINT "1=35 M.M."
0180 PRINT "2=2 1/4 ^2"
0190 PRINT "3=2 1/4 X 3 1/4"
0200 PRINT "4=4 X 5"
0210 PRINT "WHICH FORMAT WILL YOU BE "
0220 PRINT "PRINTING (PLEASE TYPE A NUMBER"
0221 PRINT "FROM ABOVE)";
0230 INPUT Y
0239 REM THIS LINE MAKES Y A USEFUL POINTER
```



```

0240 Y=Y+2
0241 PRINT "DO YOU WANT THE PAPER GRADE"
0242 PRINT "OPTION (0=NO,1=YES) ";
0243 INPUT G
0249 GOTO 270
0250 PRINT "CONTROL COMMANDS ARE:"
0251 PRINT "1=NONE(CTRL STATUS REMAINS QUO). "
0252 PRINT "2=REPRINT NEG. AT NEW SIZE."
0253 PRINT "3=RESET CTRL STATUS."
0254 PRINT "CONTROL COMMAND ";
0255 INPUT W
0260 ON W GOTO 270,285,150
0270 PRINT "HIGHLIGHT DENSITY ";
0271 INPUT H(1)
0275 IF G=0 THEN 285
0280 PRINT "SHADOW DENSITY ";
0281 INPUT S(1,1)
0285 PRINT "PRINT SIZE ";
0286 INPUT L(1)
0287 IF H(Y)=H(1) THEN A =1
0288 IF H(Y)=H(1) THEN 320
0290 X=ABS(H(Y)-H(1))
0291 REM LINE 290 DETERMINES
0292 REM THE DIFFERENCE IN
0293 REM DENSITIES BETWEEN
0294 REM THE HIGHLIGHTS IN
0295 REM THE STANDARD NEGATIVE
0296 REM AND THE ONE YOU ARE
0297 REM PRINTING.
0300 GOSUB 3000
0305 REM LINE 310 CORRECTS FOR
0306 REM WHEN THE NEW NEG IS
0307 REM THINNER THAN THE STD.
0308 REM NEG.
0310 IF H(Y)>H(1) THEN A=1/A
0315 REM LINE 320 CORRECTS FOR
0316 REM DIFFERENT PRINT SIZES.
0320 C=(L(1)*L(1))/(L(Y)*L(Y))
0321 R=1
0325 REM R IS THE PAPER GRADE
0326 REM EXPOSURE MULTIPLIER FOR
0327 REM ILFORD PAPER, & CAN BE
0328 REM CHANGED IN SUBR. 5000
0329 REM FOR GRADE 5 ILFORDROM.
0330 IF G=1 THEN 5000
0340 V(1)=V(Y)
0341 REM LINE 350 CALCULATES
0342 REM EXPOSURE TIME BY
0343 REM MULTIPLYING BASE
0344 REM EXP. TIME X NEW
0345 REM DENSITY FACTOR
0346 REM X THE SIZE FACTOR.
0350 T(1)=T(Y)*C*R*A
0351 REM LINE 360 & 370 KEEP THE
0352 REM EXPOSURE TIMES BETWEEN
0353 REM 5 AND 30 SECONDS, WHEN
0354 REM POSSIBLE.
0360 IF T(1)<5 THEN 7000
0370 IF T(1)>30 THEN 7000
0371 REM LINES 380 & 381 KEEPS
0372 REM FROM SHOWING MORE
0373 REM PRECISION THAN MY TIMER
0374 REM CAN HANDLE.
0380 IF T(1)<10 THEN T(1)=(INT((T(1)*10)+0.5)/10)
0381 IF T(1)>=10 THEN T(1)=INT(T(1)+.5)
0382 GOSUB 2200
0383 PRINT "EXPOSURE TIME = ";T(1);" SEC."
0390 PRINT CHR(64);" F/";V(1);"."
0400 IF G=1 THEN PRINT "CONTRAST GRADE = ";Q
0401 M=M+1
0410 PRINT "ANOTHER PRINT (0=NO,1=YES)";
0420 INPUT Z
0430 IF Z=0 THEN 440
0431 IF M<3 THEN 250
0432 GOTO 254
0440 PRINT "I HOPE I WAS HELPFUL TO YOU."
0450 PRINT "SEE YA SOON."
0460 STOP
1999 REM LINES 2200-2201
2000 REM GENERATE A CLEAN
2001 REM SCREEN ON A SWTP CT-
2002 REM 1024. FOR 8K BASIC,

```

cussion of paper grade will appear later in this article. At present, what concerns us is that different paper grades have different printing speeds, just as different films have different film speeds. In fact, for most brands of paper, each paper grade has a different printing speed. This would really muddy the water — if there weren't an easy way out.

A British company, Ilford, makes an enlarging paper called Ilfobrom, which is available in grades 0, 1, 2, 3, 4 and 5. Grades 0-4 have exactly the same printing speed; grade 5 has exactly ½ the printing speed of the others.

Coupling this with an assumption that the standard print was *not* printed on grade 5 paper makes the paper-grade correction factor quite simple. If the new print is to be printed on #5 paper, then double the calculated exposure; otherwise use the calculated exposure. In the program it looks something like this:

```

R=1
If Q= 6 THEN R=2

```

where R is the paper-grade exposure-correction factor and Q is the paper grade (+1) being used.

Every time I think about rewriting the program to use paper other than Ilfobrom, I get a headache. It is fortunate that Ilfobrom is an excellent, easy-to-use paper. I used it long before I wrote this program, and long before I even thought of owning a densitometer. I encourage you to try Ilfobrom, even if you don't use this program to help you print.

The final exposure time formula looks like this:

$$T(1) = T(Y) * C * R * A$$

where T(1) is the new printing time, T(Y) is the standard printing time for the format being printed, C is the size correction factor, R is the paper-grade correction factor, and A is the highlight-correction factor.

The next problem is determining the "correct" paper grade to use. The first assumption made here is that you want a "normal" print, ranging from crisp, clean whites to deep, rich blacks. This is not always the case, though. Sometimes a high- or low-key print is desired, which is one reason the paper-grade selection subroutine was left as an option. The paper grade is determined by the contrast, or density range, of the negative to be printed — that is, the density difference between the highlight and shadow densities.

What negative range corresponds with which paper grade depends (among other things) on the following: (1) the film size being printed, (2) the enlarger type (i.e., condenser, diffusion, point source, etc.) and (3) the desired results. The program has been set up for four film formats, my condenser enlarger and my personal prejudices concerning print quality. You may need to change the data in lines 36, 38, 40 or 42 to correspond to your enlarger type, film formats and ideas about print quality.

The program is self-explanatory and self-prompting, so there should be no problem.

Program Construction

The subroutine at line 2200 generates a clean screen on an SWTP CT-1024. This may be deleted if you are using a Teletype, or changed for other TTVs (if necessary).

The subroutine at line 3000 is a base-10 anti-log subroutine, needed because density is the base-10 log of opacity, and opacity values are needed for the calculations. In SWTP 8K BASIC, the instruction "300 A = 10 ↑ X" would do what the subroutine does. However, the early versions of this program filled up my computer's memory when I used 8K BASIC, so I wrote the subroutine and still had enough

memory to finish writing the program. Since then, I have noticed that the subroutine seems to run faster than the 8K BASIC statement.

The subroutine from 4999 — 5100 determines the paper grade, and (if necessary) changes the paper-grade exposure-correction factor, R, based on the values in lines 36, 38, 40 and 42, as read by lines 143-147. The subroutine can be modified for your system and standards, but it is set up for Ilfobrom paper, and that is not easily changed (If I receive enough requests, I will rewrite the program to accommodate papers other than Ilford — even though I don't consider the conversion effort worthwhile.)

The subroutine between lines 6999 and 7200 attempts to keep the exposure time between 5 and 30 seconds. I feel that most timers are too erratic below five seconds (with a mechanical timer I would not use an exposure time of less than 10 seconds) and that a printing time over 30 seconds is too long to wait in a production-printing situation. Again, this subroutine has been set up for my enlarging lenses and may need to be changed for your lenses.

My lenses for 2¼ x 2¼ and larger formats have the same f-stop range, so in line 7000, the subroutine branches into two parts — 35mm and "other." By deleting the REMs between 7001 and 7011, the subroutine can be rewritten to branch to a different section for every unique lens.

The subroutine then assigns the f-stop (V(1)) a new value, K; increments or decrements K, depending on whether the exposure time is too long or short; adjusts the exposure time accordingly; and then converts K to an f-stop number assigned to V(1). Please note the care taken with the 2¼ X 2¼ and larger lenses, which in my system have a ½-stop increment between the maximum and next to maximum open-

ings, and exercise the same caution with your lenses.

The first step in using this program is to enter it into your computer, deleting all of the REMs after line 150 except for lines 3000, 4999 and 6999. If necessary, change or delete the subroutine at line 2200.

The second step is to make a good print on any grade of paper *except* grade 5, remembering that the quality of the calibration print determines the quality of the prints the program will produce. Then, carefully record the entire projected length as well as the highlight and shadow densities of the negative, along with the exposure time, f-stop and paper grade used. Check lines 11-18 to determine on which line the data for the format you are printing belongs, and change the line to hold your data in the following order: highlight density, exposure time, f-stop and print size (in decimal inches).

Type RUN, select the format you have been printing, exercise the paper-grade option, and reenter the standard data as it is requested. You should receive as output the exposure time and f-stop you were using, at the same paper grade you were using. If the paper grade is off, check lines 30-42 and find the lines containing the contrast data for the format you are printing. If the output paper grade was too high, increase all the numbers on that line by .10. If the output contrast is too low, decrease the numbers on the line by .10.

Repeat the above steps until the contrast is right. This calibration needs to be repeated for every film format you wish to print. Once the calibration is complete, you should not have to recalibrate the contrast selector subroutine, although it may be necessary to enter new values for the highlight density, exposure time, print size and f-stop. These change due to factors such as enlarging-lamp

```

2003 REM THE INSTRUCTION SHOULD
2004 REM BE CHANGED TO CHR$(16)
2005 REM ;CHR$(22);
2200 PRINT CHR$(16);CHR$(22);
2201 RETURN
2990 REM LINES 3000 - 4100 ARE
2991 REM A BASE 10 ANTI-LOG SUB-
2992 REM ROUTINE. THIS GENERATES
2993 REM THE CORRECTION FACTOR
2994 REM FOR VARYING NEGATIVE
2995 REM HIGHLIGHT DENSITIES.
3000 REM BASE TEN ANTI-LOG SUBROUTINE
3004 E=2.71828
3005 X=2.302582*X
3010 I=INT(X+.5)
3015 F=X-I
3020 IF F = 0 THEN 3040
3021 D=ABS(F)
3030 P=1+D*(1+.4926*D*(1+.4153*D))
3031 IF F<0 THEN P=1/P
3035 GOTO 3050
3040 P=0
3050 IF I<2 THEN 3080
3055 B=E
3060 FOR N=2 TO I
3065 B=B*E
3070 NEXT N
3075 GOTO 3086
3080 IF I=0 THEN B=1
3085 IF I=1 THEN B=E
3086 IF P=0 THEN 4000
3087 IF B=0 THEN 4002
3090 A=P*B
3095 A=(INT((100*A)+.5))/100
3099 RETURN
4000 A=B
4001 GOTO 3095
4002 A=P
4003 GOTO 3095
4080 REM LINES 4999-5100 ARE
4081 REM THE PAPER GRADE SUB-
4082 REM ROUTINE. IT IS SET UP
4083 REM ILFORD ILFEBROM PAPER.
4084 REM THE CONTRAST VALUES
4085 REM MAY NOT BE OPTIMUM FOR
4086 REM YOUR SET-UP & CAN BE
4087 REM EASILY CHANGED.
4088 REM SETTING UP THE EXPOSURE
4089 REM CHANGES FOR PAPERS
4090 REM OTHER THAN ILFORD
4091 REM WOULD BE VERY HARD TO
4092 REM DO. FORTUNATLY ILFORD
4093 REM IS A TRULY EXCELLENT
4094 REM PAPER, AS WELL AS CON-
4095 REM VIENT TO USE.
4999 REM PAPER GRADE SUBR.
5000 REM FIND CONTRAST RANGE
5001 O=H(1)-S(1,1)
5015 Z=1
5020 REM FIND PAPER GRADE
5021 IF O>=S(Y,Z) THEN Q=Z
5022 IF O>=S(Y,Z) THEN 5027
5023 IF Z=6 THEN 5026
5024 Z=Z+1
5025 GOTO 5021
5026 Q=Z
5027 ON Q GOSUB 5900,5902,5902,5902,5902,5952
5028 Q=Q-1
5029 GOTO 340
5900 PRINT "THIS NEGATIVE MAY BE TOO"
5901 PRINT "CONTRASTY TO PRINT WELL."
5902 RETURN
5952 PRINT "THIS NEGATIVE MAY BE TOO FLAT"
5953 PRINT "TO PRINT WELL."
5954 R=2
5955 RETURN
6080 REM LINES 6999-7200
6081 REM CORRECT THE EXPOSURE
6082 REM AND F/STOP IN AN
6083 REM ATTEMPT TO KEEP THE
6084 REM EXPOSURE TIME BETWEEN
6085 REM 5 & 30 SECONDS.

```



```

6086 REM THE TABLES ARE SET-UP
6087 REM FOR MY ENL. LENSES
6088 REM MAX. & MIN. APETURES
6089 REM AND MAY NEED TO BE
6090 REM CHANGED FOR YOUR
6091 REM LENSES. BE CAREFUL
6092 REM OF LENSES THAT HAVE
6093 REM 1/2 STOPS BETWEEN THE
6094 REM MAXIMUM AND NEXT TO
6095 REM MAXIMUM APETURE, AND
6096 REM ALLOW FOR THIS, AS I
6097 REM DID ON THE 2 1/4 SQR.
6098 REM & LARGER FILM SUB-R.
6999 REM F/STOP SUBR.
7000 IF Y=3 THEN 7170
7001 REM WHAT FORMAT? IF 35
7002 REM THEN GOTO 7170
7010 REM ASSIGN USABLE NUMBER
7011 REM TO F-STOPS.
7015 IF V(1)=4.5 THEN K=0
7020 IF V(1)=5.6 THEN K=1
7030 IF V(1)=8 THEN K=2
7033 IF V(1)=11 THEN K=3
7036 IF V(1)=16 THEN K=4
7040 IF V(1)=22 THEN K=5
7042 REM IS T TOO BIG, OR TOO
7043 REM SMALL?
7045 IF T(1)<5 THEN 7075
7048 REM IF LENS IS ALL THE WAY
7049 REM OPEN, THEN GO BACK TO
7050 REM MAIN PROGRAM.
7051 IF K=0 THEN 380
7054 REM ADJUST F/STOP.
7055 K=K-1
7059 REM 1/2 STOP INCREMENT?
7060 IF K=0 THEN 7105
7064 REM ADJUST TIME
7065 T(1)=T(1)/2
7070 GOTO 7130
7071 REM IF LENS IS SHUT DOWN
7072 REM ALL THE WAY THEN GO
7073 REM BACK TO MAIN PROGRAM.
7075 IF K=5 THEN 380
7080 K=K+1
7083 REM WATCH OUT FOR THE 1/2
7084 REM F/STOP INCREMENT!
7085 IF K=1 THEN 7125
7089 REM ADJUST TIME FOR NEW F/.
7090 T(1)=T(1)*2
7100 GOTO 7130
7105 T(1)=T(1)/1.5
7115 GOTO 7130
7125 T(1)=T(1)*1.5
7126 REM REASSIGN F/ NUMBERS
7130 IF K=0 THEN V(1)=4.5
7135 IF K=1 THEN V(1)=5.6
7140 IF K=2 THEN V(1)=8
7145 IF K=3 THEN V(1)=11
7150 IF K=4 THEN V(1)=16
7155 IF K=5 THEN V(1)=22
7160 GOTO 360
7170 IF V(1)=2.8 THEN K=0
7175 IF V(1)=4 THEN K=1
7180 IF V(1)=5.6 THEN K=2
7185 IF V(1)=8 THEN K=3
7190 IF V(1)=11 THEN K=4
7195 IF V(1)=16 THEN K=5
7210 IF T(1)<5 THEN 7235
7215 IF K=0 THEN 380
7220 K=K-1
7225 T(1)=T(1)/2
7230 GOTO 7250
7235 IF K=5 THEN 380
7240 K=K+1
7245 T(1)=T(1)*2
7250 IF K=0 THEN V(1)=2.8
7255 IF K=1 THEN V(1)=4
7260 IF K=2 THEN V(1)=5.6
7265 IF K=3 THEN V(1)=8
7270 IF K=4 THEN V(1)=11
7275 IF K=5 THEN V(1)=16
7280 GOTO 360

```

age, developer used, etc., though the contrast-level information remains relatively constant.

Now the program is calibrated, and you are ready to use it for further printing. In use, the program is self-prompting and largely self-explanatory, so there should be little trouble in using it.

I have enjoyed writing this program, and using it has

been a joy. I figure that after about 800 hours of printing this program will have paid for my system. There should be no problems in calibrating this program for use with darkroom setups different from mine. If you have trouble, send me a letter describing your problem and your setup (please enclose a stamped self-addressed envelope) and I'll try to help. ■

```

#RUN
FILM FORMATS:
1=35 M.M.
2=2 1/4 ^2
3=2 1/4 X 3 1/4
4=4 X 5
WHICH FORMAT WILL YOU BE
PRINTING (PLEASE TYPE A NUMBER
FROM ABOVE)? 1
DO YOU WANT THE PAPER GRADE
OPTION (0=NO,1=YES)? 1
HIGHLIGHT DENSITY ? 1.35
SHADOW DENSITY ? .87
PRINT SIZE ? 6.333
EXPOSURE TIME = 29 SEC.
@F/5.6 .
CONTRAST GRADE = 2
ANOTHER PRINT (0=NO,1=YES)? 1
CONTROL COMMANDS ARE:
1=NONE(CTRL STATUS REMAINS QUO).
2=REPRINT NEG. AT NEW SIZE.
3=RESET CTRL STATUS.
CONTROL COMMAND ? 2
PRINT SIZE ? 12
EXPOSURE TIME = 26 SEC.
@F/2.8 .
CONTRAST GRADE = 2
ANOTHER PRINT (0=NO,1=YES)? 1
CONTROL COMMANDS ARE:
1=NONE(CTRL STATUS REMAINS QUO).
2=REPRINT NEG. AT NEW SIZE.
3=RESET CTRL STATUS.
CONTROL COMMAND ? 3
FILM FORMATS:
1=35 M.M.
2=2 1/4 ^2
3=2 1/4 X 3 1/4
4=4 X 5
WHICH FORMAT WILL YOU BE
PRINTING (PLEASE TYPE A NUMBER
FROM ABOVE)? 4
DO YOU WANT THE PAPER GRADE
OPTION (0=NO,1=YES)? 0
HIGHLIGHT DENSITY ? 1.60
PRINT SIZE ? 8
EXPOSURE TIME = 26 SEC.
@F/8 .
ANOTHER PRINT (0=NO,1=YES)? 1
CONTROL COMMAND ? 1
HIGHLIGHT DENSITY ? 1.34
PRINT SIZE ? 5
EXPOSURE TIME = 23 SEC.
@F/8 .
ANOTHER PRINT (0=NO,1=YES)? 0
I HOPE I WAS HELPFUL TO YOU.
SEE YA SOON.
STOP 0460
READY
#

```

Sample run.

ITHACA AUDIO

THE OEM MARKETPLACE

Assembled and Tested Added at Ithaca Audio

Field-proven reliable engineering

Over 15,000 boards worldwide prove Ithaca Audio provides the quality and reliability you demand.

Ithaca Audio Boards are fully S-100 compatible, featuring gold edge connectors and plated-through holes. All boards (except the Protoboard) have fully buffered data and address lines, DIP switch addressing, solder mask and parts legend.

Z-80 CPU Board still the most powerful 8 bit central processor available. Featuring power-on-jump, provision for on-board 2708. Accepts most 8080 software.

A&T 4 mHz	\$205.00
A&T 2 mHz	\$175.00
Blank PC	\$ 35.00

Disk Controller Board controls up to 4 single or double sided drives. Supported by a host of reliable software packages: K2 FDOS, Pascal, Basic and complete diagnostics.

A&T	\$175.00
Blank PC	\$ 35.00

K2 FDOS Disk software in the DEC tradition. Includes character oriented text editor (TED), File Package (PIP), Debugger (HDT), Assembler (ASMBLE), HEXBIN, 1 COPY, System Generator (SYSGEN) and more. Command syntax follows Digital's OS-8/RT-11 format. First in a family of high level software. Basic and Pascal available now. Soon-to-be-released Fortran.

K2 Disk	\$ 75.00
---------	----------

Video Display Board features the full 128 upper/lower case ASCII character set. Easy-to-read 16 line x 64 character format can be displayed on an inexpensive video monitor or modified TV set. Includes TTY software. Add our powerful K2 FDOS to create a versatile operator's console.

A&T	\$145.00
Blank PC	\$ 25.00

8K Static RAM Board High speed static memory at a reasonable cost per bit. Includes memory protect/unprotect and selectable wait states.

A&T 250 ns	\$195.00
A&T 450 ns	\$165.00
Blank PC	\$ 25.00

2708/2716 EPROM Board Indispensable for storing dedicated programs and often used software. Accept up to 16K of 2708's or 32K of 2716's.

A&T (less EPROMs)	\$ 95.00
Blank PC	\$ 25.00
2708 EPROMs	\$ 11.00

The leading manufacturer of blank S-100 boards is adding a new wrinkle—now all their boards are available assembled and tested. "This is a natural progression for the company" according to Mr. James Watson, President. "Actually we've been supplying assembled and tested for some time to our volume customers and OEM's, particularly those overseas. Our production staff is now fully up to speed, so just about everything is available from stock." The company scheduled 6 months to phase in assembled and tested to allow time to build base inventories, before offering the boards to the public. "We feel this is quite important. A lot of companies have earned themselves a bad name in this business by announcing products they can't really deliver. We simply won't do that." Mr. Watson further explained that Ithaca Audio intends to remain leader in blank boards and expects to release a minimum of 6 new designs by August, which will be offered both blank and assembled and tested.

Memory Prices Tumble

Ithaca Audio first to break 1¢/Byte Barrier

By cutting prices for 32K of RAM to \$319 Ithaca Audio becomes the first computer vendor ever to offer high speed memory for less than a penny a byte. Commenting on the announcement, Steve Edelman, Director of Engineering said "Just a few years ago people were wishing for a penny a bit, and even now memory for most large computers costs about 2¢/byte and that's only in 1 Megabyte chunks." In fact it's the relative modest capacity of the 32K board that makes it so interesting. Users need not buy the full 64K to take advantage of the low price per bit. Furthermore, the board is available both as a kit and assembled and tested.

Delivery is stock to two weeks. Pricing is:

• 32K kit	\$319
• 32K A&T	\$359
• 64K kit	\$645
• 64K A&T	\$695

8" Disk Drives

Shugart compatible Memorex 550's are in stock.

Single and double density compatible, 330K bytes capacity with our controller or use your own.

Either way **\$456**

- **Protoboard** Universal wire-wrap board for developing custom circuitry. Room for three regulators. Accepts any size DIP socket.

Blank PC	\$ 25.00
----------	----------

Pascal/Z Ready

The first Pascal Compiler for the Z80, and the fastest Z80 Pascal ever is now ready. Over one year in development, Ithaca Audio was obviously pleased with the results. "We really have outperformed them" states Jeff Moskow, Director of Software Engineering, beaming over the recently released benchmarks, in which Pascal/Z averaged better than five times the speed of a recent P-code implementation.

"Pseudo-code means a vendor only has to supply one compiler to lots of people using lots of different machines, and that makes his life very easy, but it also means users' programs execute significantly slower. Therefore, we chose to write a native compiler that delivers fast re-entrant ROMable code, with no need for an intermediate language and interpreter. That's where our speed comes from." As a matter of fact, Pascal/Z is often twenty times as fast as UCSD's implementation and may well be faster than dedicated Pascal machines such as the recently announced Western Digital Pascal Micro-engine.™ Unlike the Microengine, Pascal/Z does not require any new special CPU hardware and has the added benefit of compatibility with existing Z80 software.

Operational requirements of Pascal/Z are the Ithaca Audio K2 Operating system and 48K of memory during compiles. The output is standard Z80 Macrocode which is linked and run through the Ithaca Audio Macro-assembler. Binary files may be as small as 2.5K, or even less if the full library is not used. The compiler, including the Macroassembler, is available on an 8" K2 floppy disk. Price including full documentation is \$175.00. The Macroassembler is available separately for \$50.00. Delivery is from stock.

More Software:

For those that don't require the speed of a compiler like Pascal/Z, Ithaca Audio also offers the convenience of BASIC. BASIC/Z, an extended version of TDL's Super Basic, runs in slightly over 12K and is supplied on an 8" K2 disk for \$75.00.

SAVE Even More -

When you buy your software as a package

K2 and Pascal/Z	\$225
	SAVE \$25
K2, Pascal/Z and Basic/Z	\$275
	SAVE \$50

HOW TO ORDER

Send check or money order, include \$2.00 shipping per order. N.Y.S. Residents include tax.

For technical assistance call or write to:

**ITHACA
AUDIO**

P.O. Box 91
Ithaca, New York 14850
Phone: 607/257-0190

Peripheral Interfacing

Specifically, this article tells you how you can inexpensively connect TTY (Teletype) or TTL (transistor-transistor logic) interfaces to the serial RS-232 port of your computer.

Rod Hallen
Road Runner Ranch
PO Box 73
Tombstone AZ 85638

Interfacing your personal computer to various peripheral devices is always an interesting proposition. All the microprocessors hobbyists commonly use are digital eight-bit parallel chips with instruction times of a microsecond or two. Peripheral devices can be analog as well as digital, serial as well as parallel, and their execution time is usually measured in milliseconds instead of microseconds.

Obviously, some kind of matching is needed. Unless your device includes the required matching, you'll have to provide it. This article is about some inexpensive and readily available interfaces that will

help you tie TTY or TTL peripherals to your computer's serial RS-232 port.

RS-232 to TTY

I was recently asked by a friend to help him connect a Teletype Model 33 with a 20 mA loop current interface to his computer. I thought that this would be a simple job since most computers provide a serial port for just such a purpose. However, his serial port was RS-232 only. My next thought was to modify the port, which is easy enough to do. But my friend said no... he didn't want any modifications to his brand new computer.

As I was contemplating throwing together an RS-232 to 20 mA (and vice versa) adapter, I recalled the Electronic Systems RS-232-to-TTL converter that I

had used (it had saved me over \$200) in my Teletype Model 43. The same company also makes a kit for just the situation I was faced with now (see parts list).

I wrote for one, received it in six days, spent a total of four minutes putting it together and had the 33 working less than 30 minutes after the kit came out of the box.

The four-minute construction time doesn't include the extra five minutes I spent removing the 2N2222A transistor from the board and turning it around because I had inserted the leads backwards. The transistor outline on the circuit board is for the metal can variety with a tab to indicate orientation. The 2N2222A supplied with the kit has a plastic case, and no information is given to tell you which way to plug it in.

If I had traced a couple of leads on the bottom of the board first, I'd have known which way

was which, but I was in too much of a hurry to show off. Fig. 1 displays the correct transistor orientation (schematics are courtesy of Electronic Systems).

The schematic drawing for the Electronic Systems RS-232 to 20 mA adapter is shown in Fig. 2. This also converts from 20 mA back to RS-232, and full duplex operation is possible since both directions are completely independent of each other. It is really a simple circuit that is built on a 1½ by 2½ inch glass board that can be tucked away just about anywhere.

RS-232 to TTL

Don't confuse TTL and TTY. TTL (transistor-transistor logic) is standard IC level where +5 volts equals a mark (1 or high) and ground equals a space (0 or low). TTY is short for Teletype, where 20 mA of current flowing is a mark and no current flowing is a space. Fig. 3 is the




Fig. 1. Parts layout for the TTY adapter circuit board. The flat side of the plastic 2N2222A transistor faces away from the tab printed on the board.




Fig. 2. The schematic diagram of the RS-232-to-TTY adapter. This is designed to interface the Teletype Model 33 and similar machines that require a 20 mA loop current for operation.




Fig. 3. The schematic of the RS-232-to-TTL converter. The +12 volts can be tapped off of your computer supply since the current requirements are very low.

schematic of the RS-232-to-TTL converter. Like the TTY adapter, this converter will also operate full duplex. I have been using it with my Model 43 for more than six months without any problems.

The board has a ten-contact edge, but rather than buy a connector I soldered wires directly to holes drilled in each contact. The TTL board is smaller than the TTY board but only because the latter provides mounting holes, while the former is designed to mount in an edge connector.

Conclusion

One important note: You can reverse the TTL board, but not

the TTY board, to suit two different situations. This means that the TTL board will interface a serial TTL port to an RS-232 peripheral or an RS-232 port to a TTL peripheral. I'm using two now—one in each of the above cases.

The TTY board can be used to connect an RS-232 port to a 20 mA device (Model 33), but you can't use it to interface a 20 mA port to an RS-232 device. It was my intention to use one to connect my RS-232 terminal to a KIM-1 Teletype port, but it won't work that way.

The KIM output port is a closure to +5 volts, and the TTY board input is looking for a short. The TTY board output is a

TTY & RS-232 Interface	Kit	\$7.00
	Bare Board	4.50
TTL & RS-232 Interface	Kit	7.00
	Bare Board	4.50
	Connector	2.00


Electronic Systems
PO Box 21638
San Jose CA 95151

Parts list.

closure to +12 volts, and the KIM input port is looking for a short. I guess I'll have to homebrew that one myself.

Electronic Systems has many other kits available at reasonable prices. See their

ads in most of the computer magazines or write them for a catalog. I am using a total of four of their kits and I'm considering their telephone line modem as one of my next projects. ■



Indianapolis IN

The Central Indiana Section of IEEE and the corresponding IEEE Computer Society Chapter will sponsor its fourth annual IEEE Indy Microcomputer Show Thursday, June 28, 1979, 9:30 AM to 9:00 PM, Sheraton Motor Inn East, located at I-465 and SR-67, Indianapolis. There will be exhibits, demonstrations and technical seminars addressing the engineering, industrial, scientific, medical, business and personal applications of microcomputer systems.

Harry D. Bostic, Publicity Chairman, IEEE Indy Microcomputer Show, Naval Avionics Center, D/810, 6000 E. 21st St., Indianapolis IN 46218. (317) 353-3047, 3218.

St. Paul MN

Amateur Fair '79. Dakota Division's largest Swapfest and Exposition for Computer Hobbyists and Amateur Radio Operators will be held Saturday, June 2, at the Minnesota State Fairgrounds, St. Paul. Free overnight parking for self-contained campers, June 1 only. Talk-in on 16/76 and 52/52. Sell from your car in the giant flea market. Inside space available. Many great prizes. AMSAT and microprocessor exhibits. FCC, ARRL and Minnesota Repeater Council booths. Admission \$2. For further information or reservations for commercial space, write Amateur Fair, PO Box 30054, St. Paul MN 55175.

Lexington VA

Introduction to Microcomputer Interfacing—A hands-on, short course, July 16 to 27, 1979. Tuition \$395. Contact Prof. Philip Peters, Dept. of Physics, Virginia Military Institute, Lexington VA 24450, for further information and application forms.

Las Cruces NM

The American Association of Physics Teachers announces its first national meeting. Theme is the use of microcomputers in physics teaching. The meeting will be held at New Mexico State University, Las Cruces NM, June 19-23, 1979. In addition to the planned activities, many computer manufacturers have been invited to exhibit their products at the meeting and to hold workshops on the use of their equipment.

Readers who wish further information on the meeting, contact: American Association of Physics Teachers, Graduate Physics Building, SUNY at Stony Brook, Stony Brook NY 11794, Attn: Summer Meeting. (516) 246-6840.

New York NY

Twenty-five sessions during four days will make up the program of the 1979 National Computer Conference Personal Computing Festival in New York. The June 4-7 program at the Sheraton Center Hotel, 52nd St., between 7th Ave. and Ave. of the Americas, will consider applications of microcomputers to art, education, fun and profit. The festival also will feature demonstrations of personal computer innovations and commercial exhibits.

Additional information, including housing and registration procedures, is available from AFIPS, 210 Summit Ave., Montvale NJ 07645. (201) 391-9810.

Chicago IL

Papers are being solicited for the November 6, 1979, Third International Conference on Computer Software and Applications—COMPSAC 79—sponsored by the IEEE Computer Society. For additional information, contact the general chairman: Dr. William Smith, Executive Director, Toll Electronic Switching and Operator Services Division, Bell Laboratories, Naperville IL 60540. (312) 690-2389.

Santa Ana CA

Swap Meet sponsored by North Orange County Computer Club, Sunday, June 17, 9 AM till 5 PM, Advanced Computer Products—rear parking lot—1310-B East Edinger, Santa Ana CA 92705. Free to all buyers (open to general public). Sellers' rates, per parking lot space (approximately 160 sq. ft.): NOCCC Member, noncommercial—\$2; nonmembers, noncommercial—\$5; commercial—\$10. Over 80 spaces are available—first come, first served. Send check to NOCCC Swap Meet, PO Box 3243, Orange CA 92665. Make check payable to NOCCC. Be sure to include your name, phone number(s), rate classification, number of spaces. NOCCC members, include your membership number.

For more information, contact Lorin S. Mohler, NOCCC Swap Meet chairman, 1391 W. Cerritos Ave. #69, Anaheim CA 92802. (714) 535-3339.

Chicago IL

The Society for Management Information Systems has announced a "Forum on Information Resource Management" to be held at the Drake Hotel, Chicago, June 25-26, 1979. Major industry spokesmen have been invited to discuss technological innovations in information resource management and to address the outlook for systems managers during the 80s.

For further information, contact Ken Burroughs, DBD Systems, 1500 N. Beauregard St., Alexandria VA 22311. (703) 820-3310.

Kenosha WI

University of Wisconsin—Parkside Computer Fair III, Kenosha WI, Saturday, June 2, 1979, 9:00 AM to 4:00 PM. If you would like to participate in any way, give a call to Don Piele, UW-P Computer Fair III, University of Wisconsin—Parkside, Kenosha WI 53141, (414) 553-2327.



"Poly want a nomial . . . aawk. Hey, Einstein, you've got an error in that FOR-NEXT loop!"



"I'm tired of your more-logical-than-thou attitude!"

BARGAIN

Part#	Price	Stock	Part#	Price	Stock
74C42	3/1.00	600	Rectifier-Full Wave		
7450	10/1.00	700	600 V @ 1.5 amp	2/1.00	1500
7447	3/1.00	1000	Rectifier-Diodes		
745112	5/1.00	2000	200 Volts 3 amp	10/1.00	4500
74116	2/1.00	1500	400 Volts 1 amp	10/1.00	4000
RCA Zero Voltage Switch			Zener Diodes		
CA 3079	2/1.00	2000	6.8 V @ 1W	10/1.00	2000
GE DPTO Isolator			12 V @ 1W	10/1.00	4000
H11A2	2/1.00	2000	24 V @ 1W	10/1.00	2000
T.I. JFET Op-Amp			33 V @ 1W	10/1.00	1000
TL071	2/1.00	1000	Transformers		
			6 or 8 V @ 12.25 amp	\$2.50	
			10 V @ 4 amp	\$5.95	
			52 V CT 4 amp	\$7.50	

All component 100% Prime and GUARANTEED.
Master Charge, Visa Accepted.

✓ D28

DELTRONIKS

5151 Buford Hwy.
Atlanta GA 30340
(404) 458-4690

TRS-80

TRS-80 Add-ons

- Floppy Drives
- Single Shugart or Pertec system

..... \$ 395

- Dual Sided Floppy System..... 695
- RAM Memory 9.75
- 32K Expansion Interface 599
- RS232 Serial I/O (simplex)..... 79
- RS232 Serial I/O (duplex)..... 95

PERIPHERAL PRODUCTS

- Floppy Kit for SA801 (8") Floppy (S-100) 599
- Add-on Floppy Drives
- SA800 or Pertec (8") unused ... 469
- SA400 or Pertec (5") unused ... 285
- Centronics 779 w/Tractors..... 1179

Ask for Free Product Line Catalog

(714) 979-9923 ✓ M82

MICROCOMPUTER TECHNOLOGY INC
2098 S. Grand Ave., Santa Ana, CA 92705

DIGITAL PLOTTER

FEATURING THE IEEE 488 BUSS
THE RS 232 SERIAL DATA INPUT
INTERFACE OPTIONS
OR DIRECT FROM ANY TTL PORT



BASIC AND MACHINE LISTING
SOFTWARE FURNISHED


KIT 15 \$ 195

✓ X2

ASSEMBLED - TESTED \$ 249,

WRITE FOR DETAILS TO
X-Y ENTERPRISES P.O. BOX 796
HUNTSVILLE, ALA. 35804

MID EAST MICRO



AVAILABILITY, PRICES MAY CHANGE WITHOUT NOTICE

HAZELTINE 1500 \$1039
HAZELTINE 1510 \$1139
LEAR-SIEGLER
ADM-3A(kit) \$750
ADM-3A \$850

Lower case. \$50

Numeric pad. \$75

HANDLING: Terminals add 3% for
shipping or freight collect

TO ORDER: Send certified check or
M.O. For personal or
business allow 2 weeks

INDIANA RESIDENTS: add 4%

SOROC 120 \$790
SOROC 140 \$1325
INTERTUBE \$784
HAZELTINE 1400 \$695
HAZELTINE 1410 \$CALL

Write or call for free catalogue for
terminals, computer systems, and
printers.

24 HR. ORDER SERVICE


Ph (219) 293-4316 Mon-Sat

MID EAST MICRO

P.O. Box 621 ✓ M94

Bristol, IN 46507

CompuSoft™ Publishing Proudly Announces



\$14⁹⁵

(360 pages - Soft Cover)

From the author of the highly acclaimed TRS-80 Learner's Manual comes the book you've been asking for! **THE BASIC HANDBOOK** is **THE** definitive reference and "idea" book which explains in detail the BASIC language as used in over 50 micros, minis and mainframes.

Not a dictionary, not a text, it is a virtual **ENCYCLOPEDIA** of the BASIC language. Explaining all you need to know about over 250 BASIC statements, functions, operators and commands, it is the "missing link" needed to convert programs from one computer to **RUN** on another.

YES, I need the BASIC Handbook!

COMPUSOFT PUBLISHING 8643 Navajo Rd., San Diego, CA 92119

✓ C109

Please send _____ copies of
The BASIC Handbook. My check for
\$14.95 each + \$1.35 P&H is enclosed.
(CA Addresses add 6% tax)

I understand my order will be shipped
promptly and there is a 30 Day
money-back guarantee.

Name _____

Address _____

City _____ Zip _____

My computer is a _____

Kilobaud Classified

Kilobaud Classified advertisements are intended for use by persons desiring to buy, sell or trade used computer equipment or software. No commercial ads are accepted.

Two sizes of ads are available. The \$5 box allows up to 5 lines of about 37 characters per line, including spaces and punctuation. The \$10 box allows up to 10 lines. Minimize use of capital letters to save space. No special layouts allowed. Payment is required in advance with ad copy. We cannot bill or accept credit.

Advertising text and payment must reach us 60 days in advance of publication (i.e., copy for March issue, mailed in February, must be here by Jan. 1). The publisher reserves the right to refuse questionable or not applicable advertisements. Mail copy with payment to: **Kilobaud Classified, Kilobaud, Peterborough NH 03458.** Do not include any other material with your ad as it may be delayed.

TRS-80 quality Word Processor. Helps prepare letters, memos, documents and even a book. Level II, \$25. DOS, \$35. Poi Pow, 96 Dothan St., Arlington MA 02174.

Smoke Signal Broadcasting & SWTP owners: Software now available for Chief-Tain I & II microcomputer systems & SWTP 5" disk systems. Random accessing software: A/R Inven, \$370; A/P, \$270; P/R, \$290; G/L, \$290; F/A Inven system, \$200. Application manuals are \$20 each if purchased separately. Steve Chavez, 2920 Carlisle N.E., Albuquerque NM 87110.

TRS-80 Level II programs on cassette. 4K: Kaleidoscope game of Life! Three dimensional Lunar/Martian Lander! Destroy the Russian ICBM! 1=\$6, 2=\$11, 3=\$15. 16K: You name teams in College/Pro Football! Shoot down attacking Kamikazes! Battle Romulans with Star Trek! 1=\$9, 2=\$17, 3=\$24. R. Fitzgerald, 3338 Sheila Ln., #292, Dallas TX 75220.

For Sale: TRS-80 software technical manual covering Level II BASIC ROM, DOS BASIC RAM. Documents the use of all internal sub-routines such as moves, floating math, I/O, graphics, functions (sin, exp) and more. Includes a program demonstrating their use. For more info, send SASE to Terry Smith, 16327 Cloverwick, Spring TX 77373.

H8 Owners: Save and restore disk files to and from cassette. Program tape and instructions, \$15. Double media disks, \$7.50. Karl K. Sidinger, 6967 W. Rancho Dr., Glendale AZ 85303.

TRS-80 Level II, 16K stock portfolio evaluation program. Keep up to date on your stocks, which broker to fire, etc. On tape, \$6. R. W. Carney, 1927 S. Dewey, Bartlesville OK 74003.

TRS-80 Software: Business programs written in 16K Level II. Available for cassette or disk files. Send for list & prices. L. Owens, Rt. 6, Box 336A, Thomasville GA 31792.

TRS-80 Yellow Page. A free catalog of software & hardware. For fast delivery, TRS-80 owners send 2 SASE envelopes and \$1. Vendors send \$20 & full prod. descrip. to share printing costs. Features business software & word processing. Write to: 96 Dothan St., Arlington MA 02174.

KISS is money making project via comp dating for schools, clubs. TRS-80 or any string BASIC 16K holds 400 surveys. (net \$100+) List, doc., surveys, admin. instr. for \$7. D. Bohlke, Coggon IA 52218.

Apple II Checkers, Tictactoe on cassette. Board shows all moves. Both for \$10. Others. Send SASE for free list. Ed Dixon, Progress St., Florence SC 29501.

TRS-80 16K Level II programs on tape. Stock portfolio evaluation, \$6. Itemized income tax deduction records, \$5. Both for \$8. Dick Carney, 1927 S. Dewey, Bartlesville OK 74033.

*Books of computer games in BASIC. ENIGMAS-1 (\$8): Gone Fishing, Concentration, Starship, Craps, Slot-Machine, Sherlock Holmes, Tank Attack. ENIGMAS-2 (\$8): Number Guess, Mortar Battle, In-Between, Shell Game, Safari, Starship-2, Dice Roll, Puzzle. *Catalog and test program Frog Race, \$1. Available in Standard BASIC, SWTP 8K BASIC or Radio Shack TRS-80 BASIC. Please specify. B. Erikson, PO Box 11099, Chicago IL 60611.

KIM-1 Single Pass Editor Assembler. No add-on hardware or memory req'd. 150 lines off tape or 50 resident on std. KIM. add min. 340 & 120 respectively for each K of addit'l memory. MOSTech mnemonics, compatible label/var. 18 pg documentation delivered immed. Super fast, flexible, efficient economical. \$6.50 check/money order to: T. Davis, 1521 Riverside Dr., Rainelle WV 25962.

Othello—The challenging game for all ages! Written in SWTP BASIC. No fancy statements used. With few mods will run on any system, even TRS-80 Level II! Will run on most systems with no mods. Plays a good game against one player or referees for two. Available on cassette in SWTP format for \$12 postpaid. Source listing only for \$5; both for \$15. Glenn Hitt, Box 149, Brightwood VA 22715.

SWTP Owners: 4K memory boards, fully socketed, \$60 each. Also KSR-33 Teletype, excellent condition, \$325. Mike Price, 8127 E. Fremont Ave., Englewood CO 80112.

Sacrifice! Digital Group components: 1 34K system includes Z-80 CPU with keyboard, dual 8" floppies, printer, monitor and software. Also following individual items: 1 10K Z-80 CPU, 4 digital cassette drives with cabinet, keyboard. Make offer. Call (803) 552-5963 or write 7713 Linsley St., Charleston SC 29405. Will consider trade for other equipment, i.e., PET or TRS-80.

For Sale: Used floppy disks BASF, FLEXY DISK I (standard 8"). Guarantee low usage: recorded on once and played back only once. \$3.50 each. T. Langel, PO Box 359, Forest Ranch CA 95942.

Seattle Computer Products 16K plus memory, \$350; Tarbell disk controller, \$255. Both are new, unused, factory assembled and tested. Glenn Nelson, 205 Meadows Rd., Whiteface MT 59937. (406) 862-3854.

You can make your TRS-80 run faster by speeding up the microprocessor (up to twice the speed). Send \$25 for step by step instructions to J. Pawloski, 10932 Palma Vista, Garden Grove CA 92640.

TRS-80 Owners! Tired of endlessly thumbing through your Level II manual? Send \$1 and a self-addressed, stamped envelope and receive a complete (over 275 entries!!) Level II Manual Index. You will not believe how much time this will save you. Send \$1 and SASE to Dave Rose, 3439 Harding Ave., Hapeville GA 30354.

S-100 system/components: chassis w.20 con. shielded, terminated bus, \$400; Merlin video (text, hi-res graphics, tape interface, 4K ROM monitor/editor/debugger), \$250; 4 MHz Z-80 CPU, \$90; several static 4 MHz RAMs 16K, \$200; 8K, \$90; disk controller, \$100; music synthesizer, \$100; 9511 arith. support \$200; I/O bd., \$50; compatible disk software; all working. G. Lyons, 280 Henderson St., Jersey City NJ 07302. (201) 451-2905.

SOL-20, DecWriter II printer, 52K, tape, extended cassette BASIC; over \$4500 for \$3000. Fred Petran, 4745 N. 158th St., Brookfield WI 53005. (414) 781-3494.

Altair 680b w/cassette + 17K RAM + 8K BASIC. Make offer. TRS-80 Level II payroll program, \$15 on cassette. Moving graphics program, \$5. Send for info. M. Engelhardt, 274 Mainzer St., St. Paul MN 55118. (612) 457-8911.

Heathkit H-8 system w/24K RAM, cassette, H-9 terminal and factory wired H-17 dual floppy disk. All documentation and much software. Fully assembled & working, \$2000. Also, Apple II w/48K RAM, rf converter and much software, \$1100. F. Graham, 7342 Vista Del Monte #4, Van Nuys CA 91405. (213) 787-0797.

For Sale: Technico Super System 16. TI TMS9900 16-bit CPU w/RS-323-C, EPROM prog., 2K PROM, 2K RAM and 2K EPROM plus additional 32K RAM. Also chassis, power supply, digital cassette tape drive and software. Factory assembled and tested. Only 1 year old. Asking \$1600. Contact: John M. Sullivan, 721 E. Harding Ave., Appleton WI 54911. (414) 734-3239.

TRS-80 Sticky Relay Problems. Instructions for the correct fix. For all TRS-80s, old and new. This one works. Send \$2 to Jim Creasy, PO Box 722, Pottstown PA 19464.

Service: TRS-80s and all Radio Shack equipment repaired at flat rate. Mods and memory installed. 16K—\$99 w/90-day warranty. Service contracts avail. Write G. Kelch, 201 Mint Ct., Balto. MD 21090.

Wanted: TRS-80 or Apple II. No mail order—So. CA only. Also looking to buy or trade games on North Star Disk. Bob Semko, 8188 Sherwood Pl., Riverside CA 92504.

Apple II Astronomer: rise and set of sun & moon, planetary positions, sidereal time, Julian date, precession, Documentation SASE. \$15. Bruce Bohannon, 2212 Pine, Boulder CO 80302.

Apple II Weaver simulates a fully functional loom. Drafts of up to 24 harnesses stored on disk. Info SASE. Diskette with 5 samples, \$20. B. Bohannon, 2212 Pine, Boulder CO 80302.

Elf-II, 8K, giant board, Tiny BASIC, power, cassette player, TVT-1, all documents, dual trace CRO, tracer, TTL tester, SWTP function gen. and digital main frame with all (4) plug-ins. Plus freebies like 8 channel mx, Kluge boards, etc., \$1000 or will split package. Send SASE to TLK, 334 Riverside, Palm Beach Gardens FL 33410.

Original PET Software! A variety of action games with graphics and sound effects, useful math routines, interfaces (Teletype, parallel printers and telephone) and a program for creating, saving and playing back music. Send for a free catalogue today. Peter Ruetz, 368 Albion Ave., Woodside CA 94062.

Digital Group System: Dual Phidecks, dress cabinets, Hitachi CRT, DG keyboard, 34K RAM, lots of software. Will sell for \$2200. Optional Selecterm printer, \$1475 with WOPROC. Irv, 14522 Acacia, Tustin CA 92680. (714) 731-4850.

TRS-80, 16K, Lev II, Expan. Intf. w/32K, one floppy dr, ed/asmbir, payroll, disk mail list, pers. finance, gen ledger, manuals. Paid over \$2800—Sell \$2300 + U pay 2 ship. T. Fritts, 4625 SE State, Bartlesville OK 74003.

PET: "Mill" a complex strategic board game from Europe, uses 8K. Board, men, moves, etc. on screen w/full graphics. Info, & game programs on cassette, \$8. R. Pres-tien, 6278 SW 14 St., Miami FL 33144.

Cassettes: quality G.E., leaderless. 10 min., shipd prepaid UPS. 10 for \$6; 50 for \$27.50; 100 for \$50. Rudolph Nelson W1HWY, POB 421, Merrimack NH 03054.

Digital Group System: 34K RAM, dual Phidecks, lots of software, homebrew main-frame cabinet with front panel. All documentation. This is a reliable system. Worth \$1700, asking \$1100. Larry, 3069 Copenhagen, Riverside CA 92504. (714) 687-6725.

For Sale: TRS-80 16K Level I w/CTR 21 cassette & controller, BASIC programs and Finance pkg. incl. \$850 firm. Ship UPS. J. A. Centko Jr., 1509 S. Vermillion St., Streator IL 61364.

TRS-80 Users: Memory test for Level II, up to 48K. In machine language. Prints out any errors. Runs 16K in 3 seconds. \$7.50. T. W. Davis, 1227 Mesa Rd., Mare Island CA 94592.

TRS-80 Owners—Small business software. Ledger posting program, gives totals by month, yrtld., allows printout for verification or account statements. Inventory control prgm., flexible for your needs. Check posting prgm., gives totals by category, month & yrtld. Plus more. Send SASE for more details & prices. Level II 16K tape or disk. R. Lynne, PO Box 447, Carrollton TX 75006.

For Sale: Three 32K static RAM boards. S-100, assembled and working perfectly. (with 2114s low power 250 ns) used for 300 hours. \$495 each. Also have 2114s for \$5 ea; 4116s 150 ns, \$15 ea; Dynamic NMOS ceramic 8K x 1 22 pin w/spec. sheets, \$4 ea, 8 for \$30; and 4K x 1 dynamic 16 pin, \$3 ea, 8 for \$22. Richard Smith, 3648 Madrid Dr., San Jose CA 95132. (408) 946-0735.

OAE OP-80A paper-tape reader (solid state), 0-5000 cps, interface to any 8-bit parallel port, works perfectly: supplied with full documentation, \$55 or B.O. Digital Cassette, National Multiplexer recorder model CC7 serial RS-232 or 20 mA loop up to 4800 baud. Works perfectly: supplied with full documentation, \$75 or B.O. Paul Ramos, PO Box 173, Woburn MA 01801. (617) 935-3758 after 6 PM.

F8 users: Fairchild/Veras (44-pin bus) CPU, 4K static memory and motherboards for sale cheap. Some assembled & tested, some kits & bare boards. Documentation & hardware/software manuals available. Details send SASE to Paul Ramos, PO Box 173, Woburn MA 01801 (617) 935-3758 after 6 PM.

TRS-80 Level I, 4K: \$475 with monitor & cassette. System is in exc. condition, complete with original cartons, manual and software. P. Ward, 1557 Yorktown, Detroit MI 48236. (313) 882-8195.

TRS-80 Software: Business programs written in 16K Level II. Available for cassette or disk files. Send for list & prices. L. Owens, Rt. 6, Box 336A, Thomasville GA 31792.

Morrow 8080 CPU, I/O, MB, Video bd, Keybd., Sup "tr" mod modulator and monitor, 16K dynamic RAM, 25 A pwr. supl., serial, par, cassette, TTL I/O: \$800 FOB Redding. Joe La Londe, 481 Twin View Blvd., Sp. 117. Redding CA 96001. (916) 246-2947.

PET 8K (\$700), 2nd cassette (\$75), 2023 printer (\$800), minimal use. Package deal possible. Sherwin, 8176 E. Hunters Hill Drive, Englewood CO 80112.

TRS-80/L2 MathStar: DS gets closer to zapping rebels each wrong answer! \$5 w/graphic. 80-Color: See-thru overlays give TRS-80 6 colors! \$1.50 Ppd. C. Simmons, 607 SPCH, Redondo CA 90277.

Do you have an a) PET, Apple or 6800; b) TRS-80; or c) North*, 8080/Z-80, CP/M or other micro? If so, then the Microcomputer Software Guide is for you! Over 100 listings for each letter (a, b or c) above. \$2 ea.; 3 for \$5. If you sell softwr. and want to be listed, send \$5 + name + address + type sold to V. Volkman, 1131 Lakepointe, Grosse Pointe Park MI 48230.

TRS-80 Telephone Dialer. Level II 16K program enables the computer to dial numbers from a directory in memory. Single-key redialing. Requires simple hardware installation. Cassette and complete instructions, \$12.95. J. H. Nestor, 39114 Route 303, Grafton OH 44044.

For Sale: 24 Kilobaud Mags from #1, 1-77, through #24, 12-78. \$30 includes postage. Send to Victor K. Chinn, 1618 Milvia St., Berkeley CA 94709.

Northstar—Stop scrambling disks. Use my disk compacting program. Handles out of order directories, 0 length & overlapping files unlike NS's—pays for itself—Z-80, 16K min., single dens. sys. only. \$7—hexdump, \$12—disk. Jim Kane, 19 Everett St., #3, Cambridge MA 02138.

For Sale: MMD-1 8080A-based micro system with MMD-1/M1 mem. interface board incl. Manuf. by E&L Instruments, costing \$775. Incl. 1.5K RAM, EPROM monitor, kybd entry, Teletype compat. serial I/O, audio cassette interface, manuals, schematics and software. A-1 condition. First certified check for \$395 takes all. J. Hise, 67727 SR13, Millersburg IN 46543. Any questions call (219) 642-3260.

TRS-80 16K Level II JBLOCK—partitions Mem—Have up to 8 prog. in mem. at once. Disassembler prog—6K—Zilog mne. Listing \$2 each, cassette \$3 extra. John B. Sweeney, 1 Victor Dr., Albany NY 12203.

Do you want to learn code for a ham license or just increase your speed and proficiency? My TRS-80 Level II 4K program will allow you to do both and the only additional equipment needed is a code practice oscillator! \$7 for cassette listing. D. Hammer, 29914 SW 148 Ave., Leisure City FL 33033. Phone (305) 248-5356.

PLAY \$\$\$\$NOPOLY. World famous board game for TRS-80 16K Level II. I to 4 players. Full graphics, \$12.95 U.F. Racine, 445 S. 72, Kansas City KS 66111.

For Sale: Heath H8 w/48K, 2 ea SIO/cass. int.; \$1975. Heath WH17 dual floppy-disk system; \$925. Heath H9 video terminal; \$550. Heath cass. pl/rec; \$45. All factory tested and running—some under fac. warranty. Reason selling: I have 2 computer systems. Buy package for \$3300 or separately. All offers considered. Ray King, 915 El Rancho, Pocatello ID 83201. (208) 237-0979.

In the interest of accuracy and efficiency we ask that all classified ads please be typed, double spaced. Please do not send in ads in all caps; use upper and lowercase where appropriate. We generally will lowercase all uppercased words in the interest of space.

Digital Group Z-80 system. 32K in beautifully matched cabinets by DG. Parallel IO, built to handle 64K memory. Includes CRT, keyboard, 4 PhiDeck cass. recorders and note: an unused DecWriter II Printer. Up & running except printer. All software including Business BASIC & documentation. Ideal for all applications. Price \$5000. DeGraff Associates, PO Box 18640, Salt Lake City UT 84118. Phone (801) 966-1451.

For Sale: PDP8L Minicomputer, \$600. PDP8L with BA08 mem ext. 8K and periph. adapter, \$1200. Checked out with DEC diagnostics. Certified checks only. O. Glaser, 508 3rd St., West Roundup MT 59072. (406) 323-2339.

TRS-80 SOFTWARE DIRECTORY Over 800 programs are listed in a directory of TRS-80 software. Programs are listed by company and classification. The company name and address are given as well as the price. Over 125 companies are listed. Send \$4 to: H. DiBlasi, Box 1664, Lake Havasu AZ 86403.

SWTP MP-A2 CPU board with SWTBUG, \$95. 4K RAM boards, 350 ns low power, \$65. AC-30 cassette interface, \$50. Assembled, running, 1/3 less than kits. Bob Levine, 32 King St., New York 10014.

TRS-80 Users—Play Monopoly against your Level II, 16K TRS-80. Entire board, including playing pieces, houses, etc., is displayed. Send SASE for more information, or send \$12.95 for the program on cassette. With the cassette you get an instruction booklet and a complete listing. Steven Sanders, 47-12 Jayson Avenue, Great Neck NY 11020.

Imesai 8080—CPU, dual serial I/O ports, 8K static RAM, 11 connectors. ASR-33 Teletype with paper tape rdr pnch. \$1600. R. Levinson, 124 Nashoba Rd., Concord MA (617) 369-8471.

TRS-80: TSTEP single-steps for T-BUG. TSTEP displays all instruction set aspects of CPU in before/after format as you space through ROM or RAM. 11.95 Super TLEGS, onboard 100H byte T-BUG relocator! Moves T-BUG any time to any RAM loc. Will move TSTEP too. \$9.95, Allen Gelder, 5914 California St., San Francisco CA 94121.

For Sale: Centronics #101 printer. Excellent condition. Guaranteed. \$850. Aaron Epstein, 5437 Laurel Canyon Blvd., N. Hollywood CA 91607. (213) 762-0020.

Apple II or TI-58. Astronomy, hams, navigation. Sidereal time, H0-211, pi-net, cw kbd. Hard copy, \$1 ea. R.A. planets—\$3, C'stte, \$6. SASE to W. Skeen, Rt. 1, Hornbrook CA 96044.

For Sale—6502 assembler program and hardware package to maximize the printing capabilities of your Diablo. So your Diablo will print bidirectional and at 45 cps. Complete with schematic for installation. Send \$250 Certified Check to Wayne R. Cole, 409 Washington Ave., Suite 714, Towson MD 21204. Phone (301) 321-7797.

Super Elf w/4K RAM, 8-bit I/O, RS-232, TTY, cassette I/O, ROM monitor, ASCII kybd, Tiny BASIC. \$300. Jess Hillman, Box 642, Columbus, MS 39701.

For Sale: 50 pg users manual with source/assembly listings for KONVERSE, HOL interpreter and compiler for 6800 systems with MIKBUG. Derived from FORTH, similar to IPS, Jan. '79, Byte. Mach. code 2.5K, rest in HOL for 4K total. Source file editor & DOS interface included in extra 1.7K. \$10 pp. R. Yost, 1825 E. Palo Verde Dr., Phoenix AZ 85016.

Quality TRS-80 Programs. Business, games, ham radio, Monopoly, Yahtzee, many more. Send SASE for information and complete list. Sandy Stange, Box 145, Lithonia GA 30058.

TRS-80 Software: Sales Analysis. Games; "Oil Baron" (16K Level II), Slot Machine & more. Will program to suit needs. Specify & send SASE to: P. Knechtel, S. 822 Ivory #2, Spokane WA 99202.

For Sale: 2 MHz 4K OSI memory board. Built at factory, burned in 500 hours, in good condition. With manual and shipping: \$100. Everett Rubel, S.R. 90574, Fairbanks AK 99701.

Make the TRS-80 do the dialing for you. Complete software and schematic for hardware to turn your Level II computer into a telephone dialer with almost unlimited capacity. Program in BASIC for easy modification. Assembled hdw. available or parts. Program & schem. \$5.50. with assembled unit \$36. Don Hiles, 15 Maple Ct., Beards-town IL 62618.

More and More!
BARGAINS GALORE!

CORRECTIONS

As printed, the BASEDIT program in "An Editor for 6800 BASIC Programs" (January 1979, p. 22) sometimes resequences only part of a BASIC program. This happens if a GOTO statement is at the very end of a program and is not followed by the customary nulls or any other characters. Though this will not happen in normal use, it can be fixed by changing lines 03130 and 03610 as shown.

```
03130 0381 FE 02ED SLOOPB LDX SAVESX
03610 03DB 7E 0381 JMP SLOOPB
```

Although BASEDIT worked just fine with SWTP 8K BASIC version 2.0, some people have had troubles reading the BASEDIT output tape because there is no delay after a carriage return/line feed, and their BASIC doesn't have enough time to store the line in memory. As a result, it sometimes garbles a line or drops it altogether. This may happen if their CPU clock speed is very slow or if their tape output has only one stop bit instead of two.

To fix this problem, change line 01240 as shown, and insert the patch given here. This patch fits into the monitor RAM on the CPU board, but is easily relocated anywhere in memory. It essentially inserts an extra delay after each line of the program.

```
change line 01240 to
01240 0209 BD A050 JSR GOSLOW
```

A version of BASEDIT for the SWTP mini-disk system is available from Lehigh Computer Works, 1132-2 Tilghman, Allentown PA 18102. Cost is \$10, which includes source and object code on a diskette, instructions, postage and handling. A Percom disk version is available through Percom, 318 Barnes, Garland TX 75042.

A050 36	GOSLOW	PSH A	SAVE THE CHARACTER
A051 BD E1D1	JSR	OUTEEE	PRINT IT
A054 32		PUL A	
A055 81 0A	CHP A	\$0A	CHECK FOR LINE FEED
A057 26 0E	BNE	EXIT	IF NOT, EXIT
A059 FF A070	STX	SAVEX	
A05C 86 05	LDA A	\$05	SET UP TIME DELAY
A05E 09	WAIT	DEX	
A05F 26 FD	BNE	WAIT	
A061 4A	DEC A		
A062 26 FA	BNE	WAIT	
A064 FE A070	LDX	SAVEX	
A067 39	EXIT	RTS	
A070	SAVEX	RMB 2	BASEDIT patch.

CP/M®+TRS-80®

**The CP/M Operating System now available
for Radio Shack's TRS-80**

CP/M OPERATING SYSTEM

- Editor, Assembler, Debugger, and Utilities
- For 8080 and Z-80 Systems
- Up to four floppy disks
- Documentation includes:
 - CP/M Features and Facilities
 - CP/M Editor Manual
 - CP/M Assembler Manual
 - CP/M Debugger Manual
 - CP/M Interface Guide
 - CP/M Alteration Guide

CP/M System Diskette and Documentation (Set of 6 manuals) for \$150.

CP/M Documentation (Set of 6 manuals) only \$25.

MAC™ MACRO ASSEMBLER

- Compatible with new Intel Macro standard
 - Complete guide to Macro Applications
- MAC Diskette and Manual for \$150.*

SID™ SYMBOLIC INSTRUCTION DEBUGGER

- Symbolic memory reference
 - Built-in assembler/disassembler
- SID Diskette and Manual for \$125.*

TEX™ TEXT FORMATTER

- Powerful text formatting capabilities
 - Text prepared using CP/M Editor
- TEX Diskette and Manual for \$125.*

HIGH-LEVEL LANGUAGES

- Basic
- Fortran
- Cobol
- Call or write for information

USER'S GROUP

- 35 disks with utilities, games and applications
- Call or write for information

FMG CORPORATION

P.O. Box 16020 • Fort Worth, TX 76133 • (817) 738-0251 ✓F15

CP/M is a registered trademark of Digital Research Corp.

TRS-80 is a registered trademark of Radio Shack.

FLOPPY DISK FOR PET!® - S100 EXPANSION

ALL IN ONE

PEDISK SYSTEM from CGRS provides both a FLOPPY DISK and an S100 ADAPTOR for the PET! The Floppy Disk allows the Pet to instantly load and save programs and information. The S100 Adaptor allows the Pet owner to use the extensive variety of S100 peripheral boards: Memory, I/O, Voice Generators, Analog I/O, Printers, and even Telephone Interface Cards.

PEDISK uses the standard IBM 3740 format.
(read disks from other systems I)



*PET is a trademark of Commodore.

PEDISK: SYSTEM

PACKAGE 1 \$ 799.95

MINIFLOPPY DISK DRIVE - 80 kb
EXS100 DISK CONTROL BOARD
DISK HOUSING- POWER SUPPLY
KM³ - WILSERV SOFTWARE PACK

Option 1 - Built in S100 mainframe: **\$95.00**

Option 2 - Software on EPROM : **\$60.00**

EXS100: DISK CONTROL BOARD

\$ 299.95

S100 size p.c. board, assembled and tested.
Connects to the PET memory expansion port.
Provides a Floppy Disk Controller and
Eprom socket, along with room for a
complete S100 Adaptor.

KM³: SOFTWARE

✓C116

From WILSERV INDUSTRIES: Allows you to
Save, Run, Load, and Update programs from
the disk. Disk Commands, executed directly
or from a program, use existing BASIC format
preceded by a special character string.

CGRS MICROTECH

P.O. BOX 368 SOUTHAMPTON, PA.

(215) 757-0284

18966

DEALER INQUIRIES WELCOME

Cmc

KIM ANALOG INPUT


Analog to Digital Conversion System for the KIM Computer



Give the KIM the ability to sense, measure, and control the world around it with DAM SYSTEMS modules. Just plug the KIMSET1 into the KIM to set 16 channels of analog input. Screw terminals are provided for each channel so you can hook up joysticks, pots, or whatever appropriate sensors you have.

Each of the 16 analog inputs, in the range of 0 to 5.12 volts, is converted to a decimal number between 0 and 255 (20 millivolts per count). Conversion time is 100 microseconds.

The KIMMOD provides one user port as well as a DAM SYSTEMS port. Software is provided.



- KIMSET 1**
- 1-AIM161 - 16 ANALOG INPUTS - 8 BITS - 100 MICROSEC
 - 1-KIMMOD - KIM ADAPTER - 1 USER PORT - 1 DAM SYSTEMS PORT
 - 1-CABLE A24 - 24 INCH INTERCONNECT CABLE
 - 1-MANMOD1 - MANIFOLD MODULE - SCREW TERMINALS FOR INPUTS, REFERENCE, GROUND
 - 1-POW1 - POWER MODULE

KIMSET1a for 110 VAC \$ 285
KIMSET1a for 230 VAC \$ 295

Order direct or contact your local computer store.

CONNECTICUT microCOMPUTER, Inc.

150 POCONO ROAD
BROOKFIELD, CONNECTICUT 06804

TEL: (203) 775-9659 TWX: 710-456-0052


✓ C107

VISA and M/C ACCEPTED - SEND ACCOUNT NUMBER, EXPIRATION DATE AND SIGN ORDER.
ADD \$3 PER ORDER FOR SHIPPING & HANDLING - FOREIGN ORDERS ADD 10% FOR AIR POSTAGE

THE HIGHEST QUALITY DISKETTES FOR YOUR SYSTEM

ONLY **\$ 5.95** EA
INCLUDING SHIPPING

SEND CHECK AND THE
NAME OF YOUR SYSTEM
WE WILL SELECT THE
RIGHT FLOPPY FOR YOU



**DIGITAL
LEARNING
MODULES CO.**

P.O. BOX 797, DERRY, N.H.

03038

✓ D54

Datapoint CRT Terminals



#3360

\$299.95

refurbished

Fully-Assembled — Guaranteed

- Add \$15 packing
 - Shipped FOB Santa Fe Springs, Ca 90670
 - Terms: Check, Money Order or Charge
 - 30-day guarantee • **Scrolling version \$349.95**
- Model 3360 speeds from 300-4800 Baud, numeric keypad, cursor controls, Edit, Block-Transmit, search modes. ASCII Keyboard with codeable options. Green phosphor, 24 80 ch lines, addressable cursor. RS232C serial interface.

Expiration Date _____ Charge on my
Card # _____ B of A Card _____ Mastercharge _____
Signature _____




14052 East Firestone Blvd. • Santa Fe Springs, CA 90670
(213) 921-2111 • (714) 739-0711

- BUSINESS
- EDUCATIONAL
- PERSONAL

✓ V19

COMPUCOVER®



COVER YOUR INVESTMENT Protection from Dust and Spills

Adds that professional touch
For TRS-80 Keyboard & cassette
Made from durable, washable, leatherette vinyl
for maximum protection
Available in sky blue, tan and white
\$6.95 for keyboard, \$3.95 for cassette or
\$9.95 for both, postage included

Send check or money-order to: CompuCover
P.O. Box 324
Mary Esther, FL 32569

✓ C122

NEW & IMPORTANT for TRS-80

DIAGNOSTIC SOFTWARE for TRS-80 level II

- Comprehensive circuit analysis for your system
- RAM—tests for Random Access Memory errors
- ROM—tests for Read Only Memory errors
- CPU—tests for errors in Processor functions
- I/O—tests for Input/Output errors in peripheral equipment

The one "necessity" for any TRS-80 system—use as preventive maintenance for detecting circuit malfunctions and as a diagnostic tool for pin-pointing hardware problems.

\$34.95

(specify tape or disk)

COMPATIBLE PERIPHERALS EXTERNAL CALCULATOR KEYPAD

Add calculator convenience to your TRS-80 system with a calculator-format keypad.

Our keypad offers more operations than other keypads available, and is comfortable for either right- or left-handed operators, as the external keypad may be placed on either side of your present keyboard.

- 14 keys: double-width zero key, #'s 1-9, "+", "-", "period, enter.
- 3 foot flexible multi-wire connector.

\$79.95

(ready to install into keyboard)

VRData corp. MORE DATA PER DOLLAR

Folcroft Industrial Park • Folcroft, PA 19032 • (215) 461-5300



KIMSI



The KIM to S-100 bus Interface/Motherboard

- Combines the power of the 6502 with the flexibility of the S-100 bus
- Attaches to any unmodified KIM
- Complete interface logic and fully buffered motherboard in one unit
- On-board regulation of power for KIM
- Eight slots of S-100 compatibility for additional RAM, Video and I/O boards, PROM Programmers, Speech processors . . .
- Includes all parts, sockets for ICs, one 100 pin connector, and full Assembly/Operating documentation


♦ Kit \$125, Assembled \$165

♦ All units shipped from stock

FORETHOUGHT PRODUCTS

87070 Dukhobar Rd. #H

Eugene, OR 97402 (503) 485-8575



Taranto & Associates

is setting the standards for quality in innovative

Small Business Software

TARANTO & ASSOCIATES provides a complete spectrum of quality, in-depth software specifically directed to the small business segment. Our uniquely developed, sophisticated keyed accessing and sorting techniques provide major system capabilities at the most practical of levels . . . at the most economical of costs. As the incredible market for personal and small business computers expands, you will find TARANTO & ASSOCIATES at the forefront of innovative programming.

TRS-80 conversions of
OSBORNE & ASSOCIATES systems:

ACCOUNTS PAYABLE
ACCOUNTS RECEIVABLE
GENERAL LEDGER
PAYROLL

\$99.95 EACH
ON DISKETTE

Add \$3.00 per order for shipping, handling. 6% sales tax in California. Mastercharge, Visa accepted.

Dealer Inquiries Invited.

Taranto & Associates

P.O. Box 6073
San Rafael, CA 94903
(415) 472-1415

The 1979 Atlanta HamFestival and Georgia State ARRL Convention June 16-17, 1979

Downtown Atlanta Marriott Hotel

- GIANT covered Fleamarket/Swapshop!
- More than 25 Forums/Meetings!
- FCC Exams!
- Parking for thousands of cars!
- 140 Major Exhibits!
- Special MICROPROCESSOR Section!
- Programs for Ladies & Children!
- Activities Galore!

Registration: \$3 per person IN ADVANCE, \$4 at the door
Children FREE!

If you do not receive a Preregistration Packet by May 1st, write:

Atlanta HamFestival 1979
100 Woodlawn Drive
Marietta, Georgia 30067

Hotel Rates: \$32 per day single OR double!

Write for Hotel Reservations to:

Marriott Hotel • Courtland at International Blvd. • Atlanta, GA 30303
or phone: Area 404/659-6500 and hurry, hurry, hurry!

THE BEST HAMFEST IN THE WORLD!

NEECO

PET 2001 — 32K



LARGE TYPEWRITER KEYBOARDS NOW AVAILABLE!

PROUDLY ANNOUNCES THE NEWEST PET MICROCOMPUTERS BY COMMODORE!

The PET™ is now a truly sophisticated
Business System with the
announcement of these Peripherals.

The PET™ incorporated with the Floppy Disk and Printer makes an ideal business system for most professional and specialized fields: medicine, law, dental, research, engineering, toolmaking, printing, education, energy conservation etc. The PET™ Business System as a management tool delivers information to all levels of business, previously attainable only with equipment many times more expensive. The PET™ Business System is one of the most cost efficient business tools

today. It offers a wide range of applications from logging management strategy in major corporations to organizing accounts and inventory control of small businesses. Here are just a few of the cost saving uses in the corporation, professional office or small business: stock control, purchasing, forecasting, manufacturing costing, customer records, making lists etc. The PET™ Floppy Disk and Printer, a compatible business system at a reasonable price. Take a closer look at these Peripherals

PRODUCT	DESCRIPTION	PRICE	AVAILABILITY
PET 2001 — 4K*	4K RAM	\$ 595	IMMEDIATE
PET 2001 — 8K*	8K RAM	\$ 795	IMMEDIATE
PET 2001 — 16K LARGE KEYS	16K RAM	\$ 995	IMMEDIATE
PET 2001 — 32K LARGE KEYS	32K RAM	\$1195	IMMEDIATE
PET 2041	SINGLE FLOPPY	\$ 595	JULY-AUGUST
PET 2022 PRINTER	TRACTOR/ROLL	\$ 995	JULY-AUGUST
PET 2023	ROLL FEED	\$ 850	JULY-AUGUST
PET 2040	DUAL FLOPPY	\$1095	IMMEDIATE
8 K RETROFIT ROM KIT		\$ 50	IMMEDIATE

* THESE UNITS INCLUDE THE C2N CASSETTE AND SMALL KEYBOARD. THE FULL SIZE KEYBOARD UNITS DO NOT INCLUDE A BUILT IN CASSETTE—ORDER C2N

NEECO IS NOW ACCEPTING \$25 DEPOSITS ON THE SYSTEM COMPONENTS OF YOUR CHOICE! PURCHASE ORDERS ARE ACCEPTED IN LIEU OF DEPOSITS. NEECO IS A FULL CUSTOMER SERVICE ORIENTED COMPANY. PLEASE CALL FOR ADDITIONAL INFORMATION

THE NEW commodore PET PERIPHERALS!




2040

Dual Drive Floppy Disk

The Dual Drive Floppy is the latest in Disk technology with extremely large storage capability and excellent file management. As the Commodore disk is an "Intelligent" peripheral, it uses none of the RAM (user) memory of the PET™. The Floppy Disk operating system used with the PET™ computer enables a program to read or write data in the background while simultaneously transferring data over the IEEE to the PET™. The Floppy Disk is a reliable low cost unit, and is convenient for high speed data transfer. Due to the latest technological advances incorporated in this disk, a total of 360K bytes are available in the two standard 5 1/4" disks, without the problems of double tracking or double density. This is achieved by the use of two microprocessors and fifteen memory I.C.s built into the disk unit. Only two connections are necessary — an A/C cord and PET™ interface cord.

IMMEDIATE DELIVERY



2022

Tractor Feed Printer

The Tractor Feed Printer is a high specification printer that can print onto paper (multiple copies) all the PET™ characters — letters (upper and lower case), numbers and graphics available in the PET™. The tractor feed capability has the advantage of accepting mailing labels, using standard preprinted forms (customized), cheque printing for salaries, payables, etc. Again, the only connections required are an A/C cord and PET™ connecting cord. The PET™ is programmable, allowing the printer to format print for: width, decimal position, leading and trailing zero's, left margin justified, lines per page, etc. It accepts 8 1/2" paper giving up to four copies. Bidirectional printing enables increased speed of printing.

NEW IBM SELECTRIC II TYPEWRITERS FOR PET! (BRAND NEW IBM II)



PLUG COMPATIBLE VIA USER
PORT! WORD PROCESSING
SOFTWARE AVAILABLE
FROM NEECO. CALL FOR
INFO! IBM FOR PET \$1995.



\$99⁹⁵

C2N SECOND CASSETTE

NEW ENGLAND AREA SUB-DEALERSHIP INQUIRIES INVITED!

NEECO NOW OFFERS A FULL SIX MONTH WARRANTY ON ALL PETS SOLD BY NEECO! FEEL FREE TO CALL US FOR THE LATEST INFORMATION ON THE NEW PET PERIPHERALS. REMEMBER, A \$25 DEPOSIT (OR A PURCHASE ORDER) WILL BACKORDER AND HOLD ANY SYSTEM COMPONENT OF YOUR CHOICE!—WHY NOT BUY FROM THE BEST!—NEECO OFFERS THE BEST IN CUSTOMER SERVICE!—NEECO OFFERS COMPLETE SOFTWARE (COMMERCIAL & CONSUMER) SUPPORT!—MANY PACKAGES AVAILABLE! CALL FOR MORE INFO!—ARE YOU ON OUR MAILING LIST?

NEECO

NEW ENGLAND ELECTRONICS CO., INC.
679 HIGHLAND AVE., NEEDHAM, MASS. 02194
MON.-FRI. 9:30-5:30

N12

(617) 449-1760

MASTER CHARGE/VISA ACCEPTED
TELEX 951021

SOFTWARE FROM ACS SERVICE

MACHINE LANGUAGE PROGRAMS

Z-80 Disassembler—\$14.95. Displays hexadecimal, ASCII, and symbolic instructions. Code reassembled using Editor/Assembler. Requires: Level II.

Monitor #3—\$39.95 A machine language monitor program for the TRS-80. Available commands in the Monitor #3 include: Find, Edit, Unload, Relocate, ASCII, Hex, and Symbolic Dump. Binary Math, Load, Punch, Identify, and Dump symbolic listing to cassette (will load into the EDITOR/ASSEMBLER for reassembly). REQUIRES: Level II, 16K RAM. Available on disk or cassette.

OBJECT CODE RELOCATER—\$15.95 Object code relocater is designed to relocate machine language programs that were written too far down in memory to be used with the Radio Shack disk drive system. This program permanently moves most of Radio Shack's machine language programs into higher area of memory, thus enabling the program to reside in memory along with DOS and DISK BASIC. The user does not have to reload the relocated program each time it is used as it can be permanently moved high enough to escape the disk system.

Selector III—\$345.00 Large data base management system including these sub-programs: Sales Activity, Inventory, Accounts Payable, Accounts Receivable, Name/Address (Appointments/Events), Client/patient file, Check/Expense Register, Library. These programs require CP/M and C BASIC.

Finally, true CP/M for the TRS-80. All CP/M software from Microsoft has been converted to run with CP/M on the TRS-80. Only \$145.00.

Memory 16, 32 & 48K RAM kits. Keyboard & Interface. Prices start at \$99.95.

779 Centronics Tractor Feed Printer—\$1100.00

701 Centronics Tractor Feed Printer—\$1549.95

SA-400 Shugart Disk Drives; Perfec Disk Drives Each \$399.00; 2 for \$785.00—buy two and get cable free!

19 Key Hex Numerical Key Pad 2 version—\$69.95, programmable—\$99.95.

**ALL HARDWARE
WARRANTED
FOR 90 DAYS**

**AUTOMATED COMPUTER
SOFTWARE SERVICE**

**2208 Dearborn Drive
Nashville TN 37214**

(615) 883-8845

(615) 885-1688 ✓ A75

BUSINESS PROGRAMS

Data Base Management No. 1—\$89.95 A complete DBM program. Employs five commands: Find, Add, Change, Video and Print. Requires: Level II Disk BASIC and one disk drive, 16K RAM.

Inventory for Very Small Business—\$49.95 Uses sequential files on disk to store inventory. Commands include: Check for item, Change item information, Add new items, and Print inventory. Requires: Level II Disk BASIC and one disk drive, 16K RAM.


Medium Size Business Inventory—complete \$250.00—4000 or more items and fully automatic, updates all files from one entry. NOT JUNK! Requires: 48K and 4 disk drives.

Note: All programs on cassette unless noted. For disk, please specify and add \$5.50 to order or send a diskette. All orders shipped same day. All programs guaranteed to RUN. MASTER CHARGE & VISA WELCOME.



**SPECIAL
PROMOTION
SALE**

Radio Shack



**SAVE 10%, 15%
or more on Compu-
ters, Peripherals,
Software and ALL other
fine Radio Shack®
Products.**

NO TAXES on out-of-
state shipments!
FREE delivery available
on most orders!
WARRANTIES will be
honored by your
local Radio Shack®
Store.

**Offered
Exclusively by**

Radio Shack
AUTHORIZED SALES CENTER

**512-585-2765
1117 Conway
Mission, Texas 78572**



electronic calculators

LIST HAM NET

\$299.95	\$269.95
124.95	112.45
59.95	53.95
49.95	44.95
59.95	53.95
69.95	62.95
750.00	\$675.00
450.00	405.00
275.00	247.50
175.00	157.50
325.00	292.50
100.00	90.00
80.00	72.00
60.00	54.00
495.00	445.50
120.00	108.00
75.00	67.50

TEXAS INSTRUMENTS ELECTRONIC CALCULATORS

T.I.-59, 960 STEP PROGRAMMABLE SCIENTIFIC
T.I.-58, 480 STEP PROGRAMMABLE SCIENTIFIC
T.I.-57, 150 STEP PROGRAMMABLE SCIENTIFIC
T.I.-55, 32 STEP PROGRAMMABLE SCIENTIFIC
T.I. PROGRAMMER, CONVERTS DECIMAL/OCTAL/HEX
T.I. MBA, SUPER PROGRAMMED FINANCIAL
H.P.-97, 224 STEP PROG SCIENTIFIC PRINT/VISUAL
H.P.-67, 224 STEP PROG SCIENTIFIC
H.P.-19C, 98 STEP PROG SCIENTIFIC PRINT/VISUAL
H.P.-29C, 98 STEP PROG SCIENTIFIC
H.P.-10 BASIC HAND HELD PRINTER/VISUAL
H.P.-91, PREPROGRAMMED SCIENTIFIC PRINT/VISUAL
H.P.-33E, 49 STEP PROG SCIENTIFIC
H.P.-32E, PREPROGRAMMED SCIENTIFIC WITH STAT
H.P.-31E, PREPROGRAMMED SCIENTIFIC
H.P.-92, PREPROGRAMMED FINANCIAL PRINT/VISUAL
H.P.-38E STEP PROGRAMMABLE SUPER FINANCIAL
H.P.-37E, PREPROGRAMMED FINANCIAL

WE STOCK ALL HEWLETT-PACKARD CALCULATOR SOFTWARE AND ACCESSORIES

SEND ME THE CALCULATOR(S) INDICATED BELOW, COMPLETE WITH INCLUDED ACCESSORIES, INSTRUCTIONS, AND MANUFACTURERS WARRANTY. I UNDERSTAND THAT IF I AM NOT COMPLETELY SATISFIED, I MAY RETURN IT WITHIN 10 DAYS FOR A COMPLETE REFUND (LESS SHIPPING).

MODEL(S) _____ QUANTITY _____ AMOUNT ENCLOSED \$ _____

WE HONOR _____ VISA _____ MASTERCHARGE _____ MONEY ORDERS _____ COD _____

ADD \$2.00 FOR POSTAGE AND HANDLING. PLEASE ALLOW 10 DAYS FROM DATE OF RECEIPT OF ORDER FOR DELIVERY. TEXAS RESIDENTS ADD 5% SALES TAX.

CARD NUMBER _____ EXPIRATION DATE _____

FULL NAME _____ CALL _____

STREET _____ CITY _____ STATE _____ ZIP _____


MORE LITERATURE MODEL(S) _____

*****DEALER INQUIRIES INVITED*****

Hartwell's ✓ H26
Office World, Inc.

MAIL TO: 6810 LARKWOOD
HOUSTON, TEX 77074
ATTN: STEVE, WASOEN
PHONE: A.C. (713) 777-2673

For new ideas in electronics read Radio- electronics



Save almost 1/2 off the newsstand on RADIO-ELECTRONICS, the magazine which keeps you up-to-date with the newest ideas and innovations in electronics. (If you already are a subscriber, do a friend a favor and pass this subscription card along to him.)

check offer preferred

- ☐ 1 Year—12 issues **ONLY \$7.77**
(Save \$7.23 on newsstand or \$2.21 off basic sub. price)
- ☐ 2 Years—24 issues **SAVE MORE \$15.50**
(Save \$14.50 on newsstand or \$3.50 off basic sub. price)
- ☐ Payment enclosed ☐ Bill Me ☐ Check here if you are extending or renewing your subscription
- ☐ Check here if this is a new subscription

Name _____

Company Name (If applicable) _____

Address _____

City _____ State _____ Zip _____

IMPORTANT

Extra Postage: Canada \$3.00
per year, all other countries \$5.00 per year.

4K30



NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BUSINESS REPLY MAIL

FIRST CLASS PERMIT NO. 597 BOULDER, COLORADO


POSTAGE WILL BE PAID BY ADDRESSEE

Radio-Electronics®


SUBSCRIPTION SERVICE

P.O. Box 2520


BOULDER, COLORADO 80321



**For new
ideas in
electron
read
Radio-
Electron**



See and Copy Tape Data



use TRcopy WITH YOUR LEVEL II TRS-80*

TRcopy is a cassette tape copying system that lets you SEE what your computer is reading.

COPY ANY CASSETTE TAPE**

With the TRcopy system you can copy any TRS-80 Level II cassette tape whether it is coded in Basic or in machine language. You can also copy data created by programs and you can copy assembler listings.

YOU CAN SEE THE DATA

As the tape is being loaded, you can SEE the actual data byte-for-byte from the beginning to the end of the program. Up to 320 bytes are displayed at one time. ASCII characters are displayed on the first line and hexadecimal code is displayed on the following two lines. Data is displayed exactly as it is input including memory locations and check sums.

IDENTIFY PROGRAMS

With TRcopy you can identify programs on cassette tapes without written documentation because you can SEE the filename. If you forget to label a tape, you can use TRcopy to display the tape contents and identify the cassette.

VERIFY CASSETTE TAPES

With TRcopy you can verify both the original tape and the tape copies. You can make certain that your machine reads the original tape correctly and that it makes byte-for-byte copies. TRcopy also counts as it reads giving you the exact length of the data.

MAKE BACKUPS FOR YOUR PROGRAMS

Now you can make backup copies of your valuable programs. Many times a cassette that you make will load better than one that is mass produced. The original can then be kept as a backup in case the copy is damaged.

MAKE COPIES OF YOUR SOFTWARE

If you are in the software business you can use TRcopy to make tested copies of your programs for sales distribution. TRcopy produces machine language tapes that are more efficient than those produced by the assembler itself.

RECOVER FAULTY DATA

With TRcopy you can experiment with the volume and level controls and you can SEE what the computer is reading—even if your computer will not read the data through normal read instructions! In this way it is possible to read and copy faulty tapes by adjusting the volume control until you SEE that the data is input properly.

SIMPLE - FASCINATING - FUN

TRcopy is not only a practical utility program. It is also a fascinating graphics program that lets you SEE, for the first time, cassette data as your computer is reading it. And it's as simple as 1-2-3. Just load, verify and copy. You will now be able to use cassette tapes with confidence knowing that TRcopy is there when you need it.

The TRcopy system is a machine language program with documentation explaining tape leaders, sync bytes, check sums and other formatting conventions. With the TRcopy system, you can SEE what you are doing!

TRcopy System Including
Cassette Tape and Documentation

39.95

POST
PAID

Orders accompanied by money order or cashier's check mailed same day. Orders paid by other check shipped in 14 days. No COD's. Return within 10 days for a full refund if you are not satisfied.

*TRS-80 is a trademark of the Tandy Corporation. **You cannot copy the TRcopy cassette.

ORDER FROM

Data/Print
DEPT. KB, BOX 903, FARGO, N.D. 58107

N15



Featuring RCA 1802 COSMAC CPU

Own a powerful home computer system, starting for just \$99.95—a price that gets you up and running the very first night...with your own TV for a video display. \$99.95 ELF II includes RCA 1802 8 bit microprocessor addressable to 64k bytes with DMA, interrupt, 16 registers, ALU, 256 byte RAM, full hex keyboard, two digit hex output display, stable crystal clock for timing purposes, RCA 1801 video IC to display your programs on any video monitor or TV screen and 5-slot plug-in expansion bus (less connectors) to expand ELF II into a giant!

ELF II Explodes Into A Giant!

Master ELF II's \$99.95 capabilities, then expand with GIANT BOARD... KLUGE BOARD... 4k RAM BOARDS... TINY BASIC... ASCII KEYBOARD... LIGHT PEN... ELFBUG MONITOR... COLOR GRAPHICS & MUSIC SYSTEM... TEXT EDITOR... ASSEMBLER... DISASSEMBLER... VIDEO DISPLAY BOARD... and—

More Breakthroughs Coming Soon!

Soon to be introduced: ELF II special application kits that give you the hardware and software you need to use ELF II for specialized purposes such as a telephone dialer... industrial controller... home photography... security system... police alert... motor controller... station output monitor on a conveyor belt assembly line... and some new, super-fantastic games!

Also coming soon: PROM Programmer... A/D, D/A Converter... Controller Board... and more! Unlike some heavily advertised hobby computers, ELF II doesn't limit you to pre-recorded programs. With ELF II you learn computing from the ground up... from machine language to assembly language to BASIC... in quick, clear and easy steps. ELF II is a powerful computing tool, but one that you can master with the same ease you once mastered a slide rule or pocket calculator.

Master This Computer In A Flash!

Regardless of how minimal your computer background is now, you can learn to program an ELF II in almost no time at all. Our *Short Course On Microprocessor & Computer Programming*—written in non-technical language—guides you through each of the RCA COSMAC 1802's capabilities, so you'll understand everything ELF II can do... and how to get ELF II to do it! Don't worry if you've been stumped by computer books before. The *Short Course* represents a major advance in literary clarity in the computer field. You don't have to be a computer engineer in order to understand it. Keyed to ELF II, it's loaded with "hands on" illustrations. When you're finished with the *Short Course*, neither ELF II nor the RCA 1802 will hold any mysteries for you.

In fact, not only will you now be able to use a personal computer creatively, you'll also be able to read magazines such as *BYTE*, *INTERFACE AGE*, *POPULAR ELECTRONICS* and *PERSONAL COMPUTING* and fully understand the articles. And, you'll understand how to expand ELF II to give you the exact capabilities you need!

If you work with large computers, ELF II and the *Short Course* will help you understand what they're doing.

Get Started For Just \$99.95, Complete!

\$99.95 ELF II includes all the hardware and software you need to start writing and running programs at home, displaying video graphics on your TV screen and designing circuits using a microprocessor—the very first night—even if you've never used a computer before.

ELF II connects directly to the video input of your TV set, without any additional hardware. Or, with an \$8.95 RF modulator (see coupon below), you can connect ELF II to your TV's antenna terminals instead.

ELF II has been designed to play all the video games you want, including a fascinating new target/missile gun game that was developed specifically for ELF II. But games are only the icing on the cake. The real value of ELF II is that it gives you a chance to write machine language programs—and machine language is the fundamental language of all computers. Of course, machine language is only a starting point. You can also program ELF II with assembly language and tiny BASIC. But ELF II's machine language capability gives you a chance to develop a working knowledge of computers that you can't get from running only

Write and run programs—the very first night—even if you've never used a computer before!

You're up and running with video graphics for just \$99.95 — then use low cost add-ons to create your own personal system that rivals home computers sold for 5-times ELF II's low price!

pre-recorded tape cassettes.

ELF II Gives You The Power To Make Things Happen!

Expanded, ELF II can give you more power to make things happen in the real world than heavily advertised home computers that sell for a lot more money. Thanks to an ongoing commitment to develop the RCA 1802 for home computer use, the ELF II products—being introduced by Netronics—keep you right on the outer fringe of today's small computer technology. It's a perfect computer for engineering, business, industrial, scientific and personal applications.

Plug in the **GIANT BOARD** to record and play back programs, edit and debug programs, communicate with remote devices and make things happen in the outside world. Add **KLUGE (prototyping) Board** and you can use ELF II to solve special problems such as operating a complex alarm system or controlling a printing press. Add **4k RAM Boards** to write longer programs, store more information and solve more sophisticated problems.

ELF II add-ons already include the **ELF II Light Pen** and the amazing **ELFBUG Monitor**—two extremely recent breakthroughs that have not yet been duplicated by any other manufacturer.

The **ELFBUG Monitor** lets you debug programs with lightning speed because the key to debugging is to know what's inside the registers of the microprocessor. And, with the **ELFBUG Monitor**, instead of single stepping through your programs, you can now display the entire contents of the registers on your TV screen. You find out immediately what's going on and can make any necessary changes.

The incredible **ELF II Light Pen** lets you write or draw anything you want on a TV screen with just a wave of the "magic wand." Netronics has also introduced the **ELF II Color Graphics & Music System**—more breakthroughs that ELF II owners were the first to enjoy!

ELF II Tiny BASIC

Ultimately, ELF II understands only machine language—the fundamental coding required by all computers. But, to simplify your relationship with ELF II, we've introduced an **ELF II Tiny BASIC** that makes communicating with ELF II a breeze.

Tiny BASIC saves you the time of having to code your individual instructions in machine language for ELF II. Instead, you simply type instructions on a keyboard—PRINT, RUN, LOAD, ETC. Your Tiny BASIC program automatically translates them into machine language for ELF II. Then it translates ELF II's output back into simple words and symbols for you.

Now Available! Text Editor, Assembler, Disassembler And A New Video Display Board!

The Text Editor gives you word processing ability and the ability to edit programs or text while it is displayed on your video monitor. Lines and characters may be quickly inserted, deleted or changed. Add a printer and ELF II can type letters for you—error free—plus print names and addresses from your mailing list!

ELF II's **Assembler** translates assembly language programs into hexadecimal machine code for ELF II use. The Assembler features mnemonic abbreviations rather than numerics so that the instructions on your programs are easier to read—this is a big help in catching errors.

ELF II's **Disassembler** takes machine code programs and produces assembly language source listings. This helps you understand the programs you are working with... and improve them when required.

The new **ELF II Video Display Board** lets you generate a sharp, professional 32 or 64 character by 16 line upper and lower case display on your TV screen or video monitor—dramatically improving your unexpanded \$99.95 ELF II. When you get into longer programs, the Video Display Board is a real blessing!

Ask Not What Your Computer Can Do... But WHAT CAN IT DO FOR YOU?

Don't be trapped into buying an expensive dinosaur, simply because you can afford it. ELF II is more advanced and more fun to use than big name computers that cost a lot more money. With ELF II you learn to write and run your own programs. You're not just a keypunch operator. No matter what your interests are, ELF II is the fastest way to get into computers. Order from the coupon below!

**Netronics R&D Ltd., Dept KB-6
333 Litchfield Road, New Milford, CT 06766**

Yes! I want my own computer! Please rush me—



☐ Power Supply (required), \$4.95 postpaid

☐ RCA 1802 User's Manual, \$5 postpaid

☐ Tom Pittman's *Short Course On Microprocessor & Computer Programming* teaches you just about everything there is to know about ELF II or any RCA 1802 computer. Written in non-technical

language, it's a learning breakthrough for engineers and laymen

☐ **GIANT BOARD™** kit with cassette I/O, RS 232 C/TTY I/O, 8-bit P/I/O decoders for 14 separate I/O instructions and a system monitor/editor. \$39.95 plus \$2 p&h

☐ **KLUGE (Prototype) Board** accepts up to 36 IC's \$17.00 plus \$1 p&h

☐ **4k Static RAM** kit. Addressable to any 4k page to 64k. \$89.95 plus \$3 p&h

☐ Gold plated 86-pin connectors (one required for each plug-in board). \$5.70 ea. postpaid

☐ **Expansion Power Supply** (required when adding 4k RAM). \$34.95 plus \$2 p&h

☐ **Professional ASCII Keyboard** kit with 128 ASCII upper/lower case set, 96 printable characters, onboard regulator, parity, logic selection and choice of 4 hand shaking signals to mate with almost any computer. \$64.95 plus \$2 p&h

☐ **Deluxe metal cabinet for ASCII Keyboard**, \$19.95 plus \$2 p&h

☐ **Video Display Board** kit lets you generate a sharp, professional 32 or 64 character by 16 line upper and lower case display on your TV screen or video monitor—dramatically improving your unexpanded \$99.95 ELF II. (Fits inside ASCII Keyboard cabinet.) \$89.95 plus \$2 p&h

☐ **ELF II Tiny BASIC** on cassette tape. Commands include SAVE, LOAD, ±, ×, ÷, !

☐ **Deluxe Metal Cabinet** with plexiglas dust cover for ELF II. \$29.95 plus \$2 p&h

☐ I am also enclosing payment (including postage & handling) for the items checked below!

☐ I want my ELF II wired and tested with power supply, RCA 1802 User's Manual and Short Course—all for just \$149.95 plus \$3 p&h.

☐ **ELFBUG™ Deluxe System Monitor** on cassette tape. Allows displaying the contents of all registers on your TV at any point in your program. Also displays 24 bytes of memory with full addresses, blinking cursor and auto scrolling. A must for the serious programmer! \$14.95 postpaid

☐ **Text Editor** on cassette tape gives you the ability to insert, delete or edit lines and words from your programs while they are displayed on your video monitor. (Add printer and you can use ELF II to type error-free letters plus insert names and addresses from your mailing list.) \$19.95 postpaid

☐ **Assembler** on cassette tape translates assembly language programs into hexadecimal machine code for ELF II use. Mnemonic abbreviations for instructions (rather than numerics) make programs easier to read and help prevent errors. \$19.95 postpaid

☐ **Disassembler** on cassette tape takes machine code

programs and produces assembly language source listings to help you understand and improve your programs \$19.95 on cassette tape

SAVE \$9.90—Text Editor, Assembler & Disassembler purchased together, only \$49.95! (Require Video Display Board plus 4k memory)

☐ **ELF II Light Pen**, assembled & tested, \$7.95 plus \$1 p&h

☐ **ELF II Color Graphics & Music System Board** kit, \$49.95 plus \$2 p&h

☐ ELF II connects directly to the video input of your TV set without additional hardware. To connect ELF II to your antenna terminals instead, order **RF Modulator**, \$8.95 postpaid

Coming Soon: A/D, D/A Converter, Controller Board and more!

**PHONE ORDERS ACCEPTED!
Call (203) 354-9375**

Total Enclosed \$

(Conn. res. add tax)

CHARGE IT! Exp. Date

☐ Visa ☐ Master Charge

(Bank #)

Account #

programs and produces assembly language source listings to help you understand and improve your programs \$19.95 on cassette tape

SAVE \$9.90—Text Editor, Assembler & Disassembler purchased together, only \$49.95! (Require Video Display Board plus 4k memory)

☐ **ELF II Light Pen**, assembled & tested, \$7.95 plus \$1 p&h

☐ **ELF II Color Graphics & Music System Board** kit, \$49.95 plus \$2 p&h

☐ ELF II connects directly to the video input of your TV set without additional hardware. To connect ELF II to your antenna terminals instead, order **RF Modulator**, \$8.95 postpaid

Coming Soon: A/D, D/A Converter, Controller Board and more!

Print Name

Address

City

State Zip

DEALER INQUIRIES INVITED

Announcing . . . Small Business Computers Magazine

The magazine for
users and potential users
of small business computer
products and services

**BUSINESS
SOFTWARE**

Pitfalls for the unwary;
opportunities for
the informed

An SBC Special Report



Small Business Computers Magazine (SBC) is the monthly magazine for businessmen who are in the process of purchasing or installing their first computers. It is the bridge between the world of business and the world of small computers.

Small Business Computers Magazine is a practical *how-to* publication . . . written in non-technical language . . . and stressing business applications for small computer systems. Each monthly issue includes:

FEATURE SURVEY REPORTS on particular areas of current interest, such as *Software Packages for Small Business Applications*, *Small Manufacturing Systems*, *Inventory Control Systems*, *Microcomputer Business Applications*, and so on.

APPLICATION STORIES: Real-life examples of computer applications in the small business environment — articles which stress computer capabilities and benefits, and what to watch for when purchasing and installing a computer.

COMPUTER PROFILES: Spotlight reviews of new computer systems for the small businessman.

IDEAS AND INNOVATIONS: Helpful items which enable more effective utilization of small business systems.

INFORMATIVE ADVERTISING: The leading mini and microcomputer companies are regular advertisers, and Small Business Computers Magazine is a showcase of small systems for the businessman.

SPECIAL CHARTER SUBSCRIPTION

\$9 for 12
monthly issues



Receive the next 12 issues of **Small Business Computers Magazine** at 50% off the cover price by entering your charter subscription today. Send your check along with the coupon to:

SMALL BUSINESS COMPUTERS Magazine

33 Watchung Plaza • Montclair, NJ 07042

SMALL BUSINESS COMPUTERS Magazine ✓ \$69
33 Watchung Plaza • Montclair, NJ 07042


KB-67

☐ YES. Enter my charter subscription at the 1/2-price cost of \$9 for 12 monthly issues.
☐ Check enclosed. ☐ Bill me.

Name _____
Organization _____
Address _____
City/State _____ Zip _____



SUPPORTING
6800
COMPUTERS



High Performance Cassette Interface

- **FAST** - 4800 Baud Loads 4K in 8 Seconds!
- **RELIABLE** - Error Rate Less Than 1 in 10⁴ Bytes.
- **CONVENIENT** - Plugs Directly Into The **SWTPC**.
- **PLUS** - A Fully Buffered 8 Bit Output Port Provided.
- **LOW COST** - \$49.95 For Complete Kit.

- **OPTIONAL** - CFM/3 File Manager.
Manual & Listing \$19.95
(For Cassette Add) \$ 6.95

TERMS: CASH, MC or VISA; Shipping & Handling \$2.00

JPC PRODUCTS CO. ✓ J12

P.O. Box 5615, Albuquerque, N. M. 87185
Order Phone (505) 294-4623

ATARI



TRS-80

THE
RECREATIONAL
PROGRAMMER

QUALITY SOFTWARE!

TI & HP Programmables
BASIC for most computers

GAMES · ALGORITHMS · PUZZLES
STOCK ANALYSIS · AND MORE!

OVER 30 PAGES BIMONTHLY!

ANNUAL SUBSCRIPTION ONLY:

\$12 within USA & APO/FPO's
\$24 Foreign by AIRMAIL

Single issue for \$3 incl P&H

VISA and MASTERCARGE OK!
CALL (616) 343-3546 NOW!

Box 2571 Kalamazoo MI 49003



PET



APPLE

TRS-80 ✓ T58

TRS-80 is a product of Radio Shack. A Tandy Corporation



Level II-4K — \$628.
Level II-16K — \$889.
Expansion Interface \$269.

DISCOUNT PRICES

★ ★ ★ ★ MAIL ORDER ONLY ★ ★ ★ ★

HAZELTINE 1400 TERMINAL
SPECIAL 649.49!

VERBATIM DISKS BOX OF 10

SOFT BOX \$3.20 EA
PLASTIC BOX \$3.70 EA

HORIZON I KIT..... \$1339.00
HORIZON II KIT..... \$1599.00
HORIZON I ASSM..... \$1629.00
HORIZON II ASSM..... \$1999.00

CENTRONICS 779

PRINTER—TRACTOR FEED

\$1050.00

DIABLO HYTYPE I RIBBON..... \$4.75 EA
DIABLO HYTYPE II RIBBON..... \$4.85 EA
CENTRONICS 700 SERIES RIBBON..... \$4.50 EA

DISK DRIVES..FLOPPY..INCLUDING TRS-80

ADD-ON

FIRST DRIVE WITH DOS AND CABLE..... \$415.00
ADDITIONAL DRIVES..... \$385.00
SA-400 DRIVE..... \$285.00
SEAMAN 8" DRIVE..... \$425.00
LSI ADM-3A TERMINAL KIT..... \$739.95
DIABLO PRINT WHEEL..... \$9.50 EA

TRS-80 ADD-ON

TRS-80 16K EXPANSION MANUAL..... \$9.95
16K EXPANSION KIT MANUAL INCLUDED..... \$89.95
CABLE..... \$38.95
RIBBON FOR TRS-80 TYPEWRITER..... \$4.50
NEW! ENCLOSURE FOR SA400, 2 TIER WALNUT FORMICA
ENCLOSURE..... \$39.95

WE ACCEPT BANK AMERICARD, VISA, MASTER CHARGE, ADD 3%

29-02 23RD AVENUE ASTORIA, NEW YORK 11105
(212) 932-3533

TRS - 80™

MAILING LISTER

DOES THE FOLLOWING:

- PRINTS MAILING LABELS (1 or 2 up)
- PRINTS CLIENT LISTS
- 2 SORTS 1) LAST NAME
2) ZIP CODE 8 DIGIT
(alpha/numeric)
- FULL EDITING FEATURES
- X-U-RUN

AUTOMATICALLY EXECUTES OUR MENU WITH
THE PRESS OF THE RESET BUTTON!

ONLY - \$49.00

FOR MORE INFORMATION

LEVEL IV PRODUCTS, INC.

32020 CHEBOYGAN ✓ L19

WESTLAND, MICHIGAN 48185

(313) 326-0386



TRS-80 means business! ! ! ...with CP/M, CBASIC2, & applications software.

CP/M ("the software bus") & CBASIC2 (the standard for business software) bring new power and versatility to the TRS-80 for practical use.

CP/M Operating System (w/Editor, Assembler, Debugger, Utilities & 6 manual set) \$145
CBASIC2 Compiler (w/manual) \$ 95
DESPOOL Print Spooler (w/manual) \$ 75

*Osborne & Assoc. **PAYROLL W/COST ACCTNG** \$250

*Osborne & Assoc. **ACCTS. RECEIVABLE & ACCTS. PAYABLE** \$250

*Osborne & Assoc. **GENERAL LEDGER** \$250

*=CBASIC2 source programs; add \$15 (each) for applicable O & A book.

APH - Self-administered Automated Patient History \$175

Write/call for additional software available & FREE "CP/M Primer".

CA residents add 6% tax. Visa, M/C, M/O, Check OK.



CYBERNETICS

(714) 848-1922



✓ C129

8041 NEWMAN AVENUE • SUITE 208 • HUNTINGTON BEACH, CALIFORNIA 92647

The Independent Newsletter of Heath Co. Computers

The independence of Buss is a crucial factor in its significance to users (and prospective users) of Heath Co. computers. Information on new products is presented to Buss readers as it leaks out of Benton Harbor, not held back to suit the marketing plans of the manufacturer. For example, word that Heath Co. was working on the H19 terminal based on the Z80 microprocessor appeared well over a year ago in the February 1978 Buss. News of compatible hardware and software from other vendors is also featured.

Buss is not a company-controlled publication, so it can deal with the weaknesses of Heath Co. computer products as well as their strengths. Buss emphasizes candid accounts of owners' experiences with their computers. Their discoveries save subscribers headaches--and money. That's the proven record of over two years of publication. So Buss can guarantee a full refund any time you're not satisfied.

Buss is mailed first class (by airmail outside North America). The 24-issue subscription gives you the choice of starting with the latest issue or with available back issues (about eight are still in stock). Send \$8.20 for 12 issues or \$15.40 for 24 (overseas, \$10.50/12; \$20.00/24 payable on a U.S. bank) to:

Buss ✓ B43

325-K Pennsylvania Avenue, S.E.
Washington, DC 20003

NOTE to Kilobaud Microcomputing Subscribers

From time to time Kilobaud Microcomputing makes its subscriber lists available to carefully-screened companies and organizations whose products, services or information may be of interest to you. In every case, we must approve all organizations wishing to mail to our subscribers. In every case they receive a list of names and addresses only--no other information we may have is divulged. Each organization may use the list only once and agrees never to make any personal or telephone solicitations from it.

The overwhelming majority of our subscribers appreciate this controlled use of our mailing lists--it helps them shop conveniently by mail for products and services they need, often at substantial savings. A few people prefer their names not be used. It is to them we address this message.

If you do *not* wish to be a part of this service, please complete the form below . . . your name will not be used in this manner for any reason.

(If you asked us in the past to remove your name from our lists, there is no need to repeat the request.) Please allow about six weeks for your request to take effect.

☐ Yes, I wish to remain on this list so that I may have the opportunity to take advantage of the offers that are sent to me.

☐ I wish to have my name removed from the list of subscribers receiving mail other than the regular subscription to Kilobaud Microcomputing.

Mr.
Mrs.

Send to: Ms. _____ Please Print

Address _____

City _____ State _____ Zip _____

Mail this form with your mailing label from the latest issue (or fill out the information as it appears on the label) to:

**Kilobaud Microcomputing
Subscription Services Dept.
P.O. Box 997**

Farmingdale NY 11737

BUSINESS SOFTWARE for CP/M

THE BEST ... AND WE CAN PROVE IT!

For \$30 we will send you a diskette with a complete Accounts Payable system (limited data files) and representative source. You can see for yourself why our software is the best:

ON-LINE

A single entry of each transaction updates all affected files.

FAST and EFFICIENT

Indexed sequential and chained files provide fast retrieval with efficient use of disk space.

EASY TO UNDERSTAND

The powerful file structures allow all applications to be programmed very similarly. Each application has one master file program, one transaction entry program, and one to three print programs.

Accounts Payable, Accounts Receivable, General Ledger, Inventory Control, Bill of Material, Payroll and Job Cost are available now, with more to come. CP/M, CBASIC2, 48K, dual drives and 80 column printer required. Source code provided.

CP/M is a Trade Mark of Digital Research.

COMPUTER SYSTEMS DESIGN
906 N. Main Wichita, KS 67214



IF YOU OWN A TRS 80 *

TRS-80 is a product of Radio Shack, A Tandy Corporation

SELECTRA-PRINT PUTS YOU JUST A CABLE LENGTH AWAY FROM A "HARD—COPY" (Typewriter Quality: clean, clear, high-fidelity) Word Processing System!

. . . just a simple hook-up with the supplied cables and your **SELECTRA-PRINT** is ready to run.

For Word Processing on a TRS-80, for example, just command "LPRINT" and **SELECTRA-PRINT** automatically outputs clear, clean, high-fidelity, hard copy. . . . and of course you can use it to print-out any other information you might need.

SPECIAL NOTE:

SELECTRA-PRINT is a Selectric II typewriter and although it has been modified for computer print-out, it may still be used as a standard office typewriter.

PRICE: \$1,850.00* *TRS-80 Version \$1925.00

OPTIONS:

Dual Pitch	\$125.00
Correction Feature	\$125.00
Noise Reduction Feature	\$50.00
RS-232 Interface	\$195.00

Direct International Sales:
International Sales Division
17648 Orna Drive
Granada Hills, CA 91344, USA

Discounts Available to
EDUCATIONAL ACCOUNTS
Contact: Delores Sun P.O. Box 8394
Ann Arbor, MI 48105 (313) 665-8514

*** SELECTRA-PRINT is VERSATILE!**

SELECTRA-PRINT is compatible with most micro- and mini-computers including **PET • Apple • Heath H8 • IMSAI • Cromemco • Alpha Microsystems • Space Byte • North Star Horizon • SWTP • Vector Graphic • Sol • Polymorphic • Digital Group • Ohio Scientific • Altair • Sorcerer Xitan • Rex • KIM • EXORcisor**

"From now on, PRINT-OUT takes on a new meaning"

**micro
computer
devices
inc.**

Dept. K1

960 E. Orangethorpe, Bldg. F
Anaheim, California 92801
Telephone (714) 992-2270



"Innovators to the Microcomputer Industry"

MICRODESK®



**The perfect home
for a personal or business computer**

MICRODESK \$159.50

48" x 24" x 26", Shelves 23" x 23", One adjustable.
See it at your computer store or order it from:

COMPUTER SYSTEMS DESIGN

906 N. Main Wichita, Kansas 67214

DEALER INQUIRIES INVITED

**DO
THESE
NUMBERS
MEAN
ANYTHING
TO
YOU?**

**44
PINS
4.5" x 6.5"
CARDS
5 VOLTS**

Wasatch delivers quality system components from stock

	Assem./Tested	Kit	PCB
• 4K x 8 RAM	\$89.95	\$79.95	\$22.50
• 2K/4K x 8 PROM		79.95/129.95	22.50
• 8-SLOT MOTHER	50.00	40.00	20.00
• 80 LINE DIGITAL I/O		59.95	20.00

New 5V system components under development

- 8K x 8 EPROM (2716)
- 16/32 Channel, 8 Bit A-D
- 4 Channel, 8 Bit D-A

Wasatch also delivers prime semiconductor memory at reasonable price, in addition to custom design services.

4K RAM

✓W13

SEND CHECK OR MONEY ORDER

WASATCH SEMICONDUCTOR PRODUCTS

25 South 300 East • Suite 215 • Salt Lake City, Utah 84111

For orders under \$25 add \$2 shipping & handling / Utah residents add 5% sales tax


ANNOUNCING



**New
from DEC
LA34 DECwriter IV
\$1,199.⁰⁰**

- 110 or 300 baud, RS 232C serial ASCII
- Friction feed, paper width to 15"

- Upper/lower case, 9 x 7 dot matrix
- 10, 12, 13.2, 16.5 characters /inch
- 2, 3, 4, 6, 8, or 12 lines/inch
- 22"W x 7"H x 15½"D, 25 lbs.



Teletype 43 \$ 999.⁰⁰

- RS 232C, 110 or 300 baud
- Upper/lower case full ASCII
- Pin feed, 12" x 8½" paper

**New
from DIABLO**

DIABLO 1640 \$2,690.⁰⁰

Receive-only \$2,331.⁰⁰

High-quality daisywheel printing at 45 cps.

DIABLO 1650 \$2,779.⁰⁰

Receive-only \$2,419.⁰⁰

Metal daisywheel printing at 40 cps.

T.I. 810 printer \$1,695.⁰⁰

- 150 characters per second
- RS 232C serial interface
- Adjustable forms tractor
- Upper/lower case option \$90.00




SOROC IQ 120 \$795.⁰⁰

- RS 232C, upper/lower case full ASCII
- Numeric keypad, protected fields
- Cursor keys plus addressable cursor
- Auxiliary extension port

SOROC IQ 140 \$1,250.⁰⁰

- RS 232C and 20mA current loop
- Extensive editing features
- 25th line terminal status display
- 16 function keys (32 with shift)



To Order: Send certified check (personal or company checks require two weeks to clear) including handling* and 6% sales tax if delivered within California.

*Handling: Less than \$2,000, add 2%; over \$2,000, add 1%. Everything shipped freight collect in factory cartons with manufacturer's warranty. Visit MICROMAIL at the National Computer Conference — Personal Computing Festival, New York City, June 5-7, Booth 128.

MICROMAIL

MICROMAIL • BOX 3297 • SANTA ANA, CA 92703
(714) 731-4338

✓M73

NOW! A Full Support System for TRS-80*

GPA's Motherboard is the key to unlimited expansion of your TRS-80's capabilities. Simply plug the Motherboard into your TRS-80, then plug in...

32K of RAM ... EPROM firm ware ...
Disk Control ... Data Acquisition ...
Parallel I/O ... Serial I/O ...


by inserting modular cards into the Motherboard.

No additional power supply is necessary.

GPA's Motherboard has its own!
Why pay more for less?

GPA's quality design includes:

- * 6-44 Pin Edge Connectors.
- * +5V, -5V, +12V, -12V External Power Supply.
- * 40 Pin Ribbon Connector to plug into the Keyboard Connector.
- * Active Termination on all Bus Lines.



The Motherboard is Only \$129⁹⁵

(F.O.B. California Residents Add 6% Sales Tax) Assembled & Tested



Only \$69⁹⁵
Assembled & Tested

TRS-80* HARDCOPY INTERFACE!

PRINT: Mailing lists, form letters, invoices, inventories, checks.... whatever you need to print! Using Level II Basic LPRINT and LLIST Commands.

No modification of your system is necessary. The GPA TRS-80 Hardcopy Interface plugs directly into the back of your TRS-80 (or your Expansion Interface). RS-232-C or 20 ma. current loop compatible.

PET* HARDCOPY INTERFACE

GPA's HARDCOPY INTERFACE plugs into the "IEEE-488" bus on the back of the Commodore "PET"* Computer.

The interface comes with Selectable baud rate (110, 300, 600, 1200, 2400, 4800, 9600) and a DB-25 female printer connector. Both RS-232C and 20 ma. current loop compatibility are contained in one.

Best of all you still retain the "IEEE-488" bus.

GPA has provided you with an "IEEE-488" edge connector, that allows you to extend the bus for additional devices. **ASSEMBLED & TESTED..\$79.95**

*TRS-80 TRADEMARK OF RADIO SHACK
*PET TRADEMARK OF COMODORE

The Sign of Integrity



✓ G24

Post Office Box 7410 - Oakland, CA 94601 (415) 459-1221

ALL PRODUCTS ASSEMBLED, TESTED and GUARANTEED

Take advantage of GPA-EXPANSION CARDS

MEMORY CARDS: Now, with Fortran compilers available for your TRS-80, additional expansion memory is a must!

- Cards with Sockets only \$119.95
- 16K of 4116 Dynamic Ram w/card 224.95
- 32K of 4116 Dynamic Ram w/card 329.95
- All cards come equipped with sockets to accommodate 32K of Ram

EPROM FIRMWARE CARD


- Put those valuable subroutines in firmware. Don't waste time loading and unloading tapes and disks
- 4 sockets for 2708 or 2716 Eeproms 79.95

SERIAL I/O CARD: Here's what you've been asking for, a full serial terminal interface, with RS-232C or 20MA. Current loop, Input/output capabilities 79.95

PARALLEL I/O CARD: Control functions in the outside world, monitor and store real time events 79.95

- Two parallel output ports.
- Dip switches select Ports (0-254)

Please Inquire about our Disk Controller & D/A Cards.




OUR VISIBLE MEMORY ADDS FUNCTION AND FUN TO YOUR 6502


This DOT MATRIX display board doubles as an 8K MEMORY. You can use it as a display, memory expansion or both with graphics and text display software available. You get resolution graphics with no wait states, no snow, and no processor overhead. K-1008 ASSEMBLED and TESTED \$240.00, BARE BOARD \$40.00 K-1008-1 GRAPHIC/TEXT UTILITY SOFTWARE LISTING \$20.00.




As a dot matrix formatted 200 high by 320 wide, it allows high resolution patterns to be displayed and evaluated. It enhances system performance for data acquisition displays, math equation plotting, etc.



For charts and graphs, it is valuable in the educational, research and business fields. Shown to the right is a single period of a complex frequency waveform and its frequency spectrum chart.



For text display, dot matrix is the ultimate. Any character set the user desires is possible. Even subscript and superscript in the same column, and—mixed text and graphics. The improved man-machine interface for an unskilled operator increases productivity.



Graphics allows you to program games with much more accurate representation of your game because YOU DETERMINE THE SHAPES on the display, not a ROM character generator. Our LIFE program allows tremendous creativity in creating complex colonies for observation of generation growth and decay.

Developed by a leading group of New England engineers for interface with the three 6502 KIM BUS systems (KIM, VIM, AIM). The K-1008 requires only the processor card and its power supply to function as a memory. Add a monitor and you have graphics and text display available. Micro Technology also makes K-1000 Power Supplies, K-1005 Card Files, K-1002 8 Bit Music Systems (with advanced software), K-1020 Regulated Wire Wrap card, K-1012 IO/COM/PROM/2708 Programmer card, K-1016 16K Memory, all sold assembled and tested or as bare boards. Write for technical information, prices and terms.

Overseas orders—include \$3.00 for shipping.

Micro Technology Unlimited

P.O. Box 4596 Manchester NH 03108

TRS-80 USERS

Centronics P1 Micro Printer \$450.00

Same as Radio Shack "Quick Printer" with cable!

Mini-Floppy Disk Drives \$339.00

Includes cable for connection to Radio Shack expansion interface

Centronics 779 Printer with tractor feed \$1179.00

Includes cable for connection to Radio Shack expansion interface, case & power supply. 2 drive cable \$25.00, 4 drive cable \$35.00

Expanded Mail List, on diskette \$59.95

Multiple file and full update capability. Alpha and zip code. Rapid sorting into labels or lists. Full select and suppression capabilities on up to a 10 digit key. Redundancy check and much more!

Send for free catalog of TRS-80 software and hardware.

Cost Effective Computer Services

P.O. Box 3543 C124 Hobbyist Hours 5-11 pm
Grand Junction, CO 81501 phone # 303-245-0980

TRS-80 BUSINESS SOFTWARE ON DISK

ACCOUNTS RECEIVABLE A menu oriented system for managing up to 200 accounts. The package features fast random access and allows you to add new accounts, change account information, search individual accounts, assign terms (e.g., 10 days), print statements, customer summaries, overdue listings, and mailing labels; and post charges and credits. Archive listings provide clear audit trail. Requires 16K, two disk drives, and line printer. Two diskettes and instruction manual \$79.95

DISK PAYROLL An interactive payroll system which handles any number of employees. The package features completely automated file handling, output options for the TRS-80 line printer, and comprehensive manual containing step-by-step instructions. Available output includes quarterly and YTD summaries (for filling out 941 and W-2 forms) and payroll check information. Requires 16K, and one disk drive. Supports line printer and additional drive. One diskette and instruction manual \$59.95

HEBBLER SOFTWARE SERVICES

7142 ELLIOTT DRIVE
DALLAS, TEXAS 75227 H41

Immediate delivery by first class mail. Send check, money order, or complete MC/VISA card information. Texas residents add 5% sales tax.



Dealer inquiry invited.



TRS-80

Assumes Radio Shack® Trademark

PRINT PROGRAM \$9.95

Copies text from screen to printer. It can be enabled or disabled easily. Level I or II.

INVENTORY CONTROL* \$89.95

Command Features — Load, Save, Build, Update, Delete, Insert, Summary, Examine, Help. (Disk Based - 1 Drive Min.)

ACCOUNTS RECEIVABLE* . . . \$89.95

Command Features — Load, Save, Build, Update, Delete, Insert, Summary, Initialize, Help. (Disk Based - 1 Drive Min.)

DISKETTES SCOTCH 3M \$3.99

Lots of 10 — Supplied in library case. Minimum Order One Lot. Also for Apple Computer.

*Programs in Level II Basic, Modular, Easily Modifiable Form. Add \$2.00 Shipping and Handling. 6% Sales Tax in Alabama.

The Computer Shack

913 Shadyview Lane C135
Adamsville, Alabama 35005

OSI 48 PIN BUSS COMPATIBLE

8K STATIC MEMORY
350ns. Low Power 2102 Rams. Two independent 4K blocks. Dip switch add 14 or 28 pin devices or 40 24 pin or 24 40pin devices. Complete documentation Assembled and Tested \$176.2 for \$335 Complete Kit \$145 Bare PC board \$33

NO. 96 PROTOTYPE BOARD \$25

Build that custom circuit today. No. 96 Prototype board holds up to 96 14 or 24 pin devices or 40 24 pin or 24 40pin devices. Use board in various combinations. Molex connectors used for 48 pin bus. 36 I/O connections using Molex connectors or 120 I/O connections using Dip Plugs. Space for 25 decoupling capacitors. Add \$1 for 4 female Molex connectors

NO. 106 SERIAL / PARALLEL PORTS

Crystal controlled serial port with DIP SWITCH selectable Baud Rates of 9600 to 110. RS-232 or current loop input/outputs. Input for Data Terminal Ready signal provided. Parallel interface for printers using Centronics type inputs. Complete with 10 ft. cable and plug.

NO. 106C Serial & Parallel port w/cable \$199

NO. 106P Parallel port w/cable \$110

NO. 106S Serial port \$105

NO. 116 REAL TIME CLOCK \$139

A true crystal controlled clock not just a counter string which the MPU must process. Once set no MPU activity required. Programmable interrupt time signals the computer when the time is reached. 4 DIP SWITCH selectable formats: 12 or 24 hr. Elapsed timer 99 hr. 59 Min. 59 Sec. or 99 Min. 59 Sec. 99 100ths. Software or switch run & stop inputs. 8 outputs for driving RELAYS, LEDs etc. 8 bi-directional ports for switching closures or driving TTL loads. Complete documentation with BASIC and ASSEMBLY language listings. Assembled and Tested

D&N MICRO PRODUCTS

3932 OAKHURST DR. FORT WAYNE, IND. 46815
(219) 485-6639

TERMS: Check or money order. Add \$1 shipping and handling. Indiana residents add 4% sales tax. DEALER INQUIRIES INVITED D34

BARGAIN

Part#	Price	Stock	Part#	Price	Stock
74C42	3/1.00	600	Rectifier-Full Wave		
7450	10/1.00	700	600 V @ 1.5 amp	2/1.00	1500
7447	3/1.00	1000	Rectifier-Diodes		
745112	5/1.00	2000	200 Volts 3 amp	10/1.00	4500
74116	2/1.00	1500	400 Volts 1 amp	10/1.00	4000
RCA Zero Voltage Switch					
CA 3079	2/1.00	2000	6.8 V @ 1W	10/1.00	2000
GE DPTO Isolator			12 V @ 1W	10/1.00	4000
H11A2	2/1.00	2000	24 V @ 1W	10/1.00	2000
T.I. JFET Op-Amp			33 V @ 1W	10/1.00	1000
TL071	2/1.00	1000	Transformers		
			6 or 8 V @ 12.25 amp	\$2.50	
			10 V @ 4 amp	\$3.95	
			52 V CT 4 amp	\$7.50	

All component 100% Prime and GUARANTEED. Master Charge, Visa Accepted.

D28

DELTRONIKS

5151 Buford Hwy.
Atlanta GA 30340
(404) 458-4690

TEXT WRITER II™

A TEXT FORMATTER FOR ALL YOUR WORD PROCESSING NEEDS

- PERFECT FOR FORM LETTERS—AUTOMATICALLY INSERTS NAMES AND ADDRESSES FROM A MAILING LIST OR THE KEYBOARD
- PERFECT FOR CONTRACTS OR REPORTS—INSERTS PARAGRAPHS, CHAPTERS, OR OTHER TEXT FRAGMENTS REFERENCED BY NAME
- FULL FORMAT CONTROL—JUSTIFIED MARGINS, TABS, PAGE NUMBERS, HEADINGS AND FOOTINGS
- WORKS WITH ANY TERMINAL AND PRINTER
- WORKS WITH ANY CP/M® COMPATIBLE EDITOR
- MANY VERSIONS AVAILABLE

CP/M ON 8" CP/M ON VECTOR MZ
CP/M ON MICROPOLIS CP/M ON NORTH STAR

CP/M ON TRS-80[®]

MICROPOLIS MDOS NORTH STAR DOS

\$75 For Diskette and Manual O14

ORGANIC SOFTWARE

1492 Windsor Way • Livermore, CA 94550
(415) 455-4034

©CP/M is a trademark of Digital Research
TRS-80 is a trademark of Radio Shack

★—Star Base Aries—★

In order to dock your space shuttle with Star Base Aries™ you must monitor and alter range, linear velocity, life support, angle of attack and fuel. This accurate real time simulation is currently available in a high resolution graphic format for the Apple II (16K tape \$15.00, disc \$18.00). Also available for the TRS-80 Level I (\$10.00). Please specify. Forward check or money order to:

ISDG Inc. ✓133
312 Highgate Avenue
Buffalo, New York 14215


(N.Y. State residents add 7% sales tax)
ALLOW 6 WEEKS FOR DELIVERY



Key Electronics



Full ASCII Professional
Keyboard Kit, Model 756



Model 756 Keyboard Kit.....\$64.95
Model 701 Plastic Enclosure.....\$14.95
Model 702 Steel Enclosure.....\$29.95

INTEGRATED CIRCUITS:

SN76477N Complex Sound Gen. \$2.95 2/\$5.50
CA3140 Op Amp......60
CA3240 Dual Op Amp.....\$1.10
uA555 Timer......45

SOCKETS:

8 pin Low profile.....15 8/\$1.00
14 pin Low profile.....19 6/\$1.00
16 pin Low profile.....22 5/\$1.00
Transistor Socket.....12 10/\$1.00

FREE: CA3140 with orders of \$5.00 or more.
Please include \$1.00 for postage and handling

N.Y.S. Residents Add 4% Sales Tax

Send to: Key Electronics
P.O. Box 3506
Schenectady, NY 12303 ✓K14

Low Cost EPROM Erasing System

Performance & Reliability
at an affordable price!



The **Byte Eraser** was designed with the small systems user in mind. It erases up to 32 EPROMs at a time, is easy to use, and affords a convenience not possible with units which hold only 4 or 5 EPROMs. The **Byte Eraser** is manufactured using commercial quality components, ensuring ruggedness & reliability, and at \$35 (about 1/2 the price of the competition) we think it's one of the best buys on the market. Isn't it time you enjoyed the convenience of your own EPROM eraser? The **Byte Eraser** is available now, off the shelf. Order yours today. Calif. res. please add 6%.

Dealer Enquiries Invited.



DVC Data Vector
Corporation ✓D32

P.O. Box 3141 Burbank CA 91504 (213) 842-2866

kilobaud

MICROCOMPUTING

secret ad phone numbers

(603) 924-7138/7296

Expand your TRS-80. Save \$100.

Meet the Vista V80 Mini Disk System. The perfect way to upgrade your TRS-80* system. Inexpensively. (Our \$395.00 price is about \$100.00 less than the manufacturer's equivalent.) Here's how it can help you.

23% more storage capacity. Useable storage is increased from 55,000 to 65,000 bytes on drive one.

8 times faster. While electronically equal to the TRS-80 Mini-Disk system, track-to-track access is 5ms versus 40ms for the TRS-80.

Better Warranty. The V80 carries a 120 day warranty—longer than any comparable unit warranty available.

The Vista V80 Mini Disk System comes complete with Minifloppy disk drive, power supply, regulator board and case. And it's ready to run—simply take it out of the box, plug it in and you're ready to go.

Vista

✓V20

1320 E. St. Andrews Place, I
Santa Ana, CA 92705
(714) 558-8813

At Vista, we mean business

*TRS-80 ©Tandy Corp.

SWTPC OWNERS

ANALOG-TO-DIGITAL CONVERTER

Connect EYES and EARS to your
M-6800 with a complete
12 BIT ADC SYSTEM.

The complete system kit includes the
12 bit ADC, one temperature sensor
and a power controller.



- OCCUPIES ONE SWTPC 30 PIN I/O SLOT
- FULL 12 BIT RESOLUTION PLUS SIGN AND OVERFLOW BITS
- 16 SINGLE ENDED OR 8 DIFFERENTIAL INPUTS
- CONTINUOUS OR DEMAND DATA CONVERSION
- INTERRUPT GENERATED AT END OF CONVERSION STRAP SELECTABLE
- 0.1MV RESOLUTION AS DIGITAL VOLTMETER
- TEMPERATURE SENSORS AVAILABLE NOW—ADDITIONAL SENSORS UNDER DEVELOPMENT
- 115VAC, 6A POWER CONTROLLER SUPPLIED WITH SYSTEM KIT OR SEPARATELY
- EXTENSIVE DOCUMENTATION AND SOFTWARE SUPPLIED WITH KIT

EXTENDER BOARDS WITH 5VDC LOGIC
PROBE POWER SUPPLY ALSO AVAILABLE

ADC SYSTEM KIT— Includes ADC,
solid state temperature
sensor and power controller \$109.95
ADC KIT— w/o accessories \$89.95
Additional Temperature Sensors \$12.95
Additional Controller Kit \$15.95
EXTENDER BOARDS— with 5vdc power supply
30 pin \$14.95 50 pin \$23.95

METAMICS, Inc. ✓M93
4324 SW 35th Terr
Gainesville, Fla 32608

Cash or COD
Fla Res Add 4% Tax


The "DATA DUBBER"

DUPLICATES ANY
PROGRAM TAPE

TRS-80

Yes, even those in machine language! Feed your cassette into the "Data Dubber" and get out exact replicas of the TRS-80 CSAVE data pulses. Obtain perfect CLOAD's even from tapes with hum, distortion, or minor dropouts... and without constantly adjusting the volume. Connect a second cassette to the "Data Dubber" and make perfect reproductions, just as if the data had come from the TRS-80.

The "Dubber" works with Level I or II and costs only \$39.95, postage paid. Start your own software business. Pays for itself in time saved and reduced tape cost. Order the "Data Dubber" today! If you are not completely satisfied with its performance simply return it for full refund.



THE PERIPHERAL PEOPLE ✓P52 PO Box 524, Mercer Island, WA 98040

AIM PLUS[™]

ENCLOSURE
WITH BUILT IN
POWER SUPPLY

SPECIFICATIONS:
INPUT: 110/220 VAC 50/60 Hz
OUTPUT: +5V @ 5A
+24V @ 1A

GROUNDING THREE-WIRE LINE CORD
ON/OFF SWITCH WITH PILOT LIGHT
Enclosure has room for the AIM and one
additional board: MEMORY PLUS or VIDEO PLUS



AIM PLUS: \$100⁰⁰ AIM and AIM PLUS: \$475⁰⁰

MEMORY PLUS[™] FOR


AIM/SYM/KIM

8K STATIC RAM LOW POWER

Sockets for 8K Eprom


6522 1/0 Port
ON BOARD REGULATORS

EPROM
PROGRAMMER



MEMORY PLUS: \$245⁰⁰

FULLY ASSEMBLED AND TESTED



✓ C94

PO Box 3
S Chelmsford, MA 01824

WHY

BE CONTROLLED BY A TIMESHARING SYSTEM
WHEN YOU CAN CONTROL A
CLUSTER/ONE?



Clustersharing is... several individual computers sharing a large program library, while preserving the individuality of each machine.

The CLUSTER/ONE[™] Concept offers each BASIC user his own computer rather than a small share of one central processor.

Nestar Systems' CLUSTER/ONE creates a new dimension in low-cost computing.

combining the power and economy of individual micro-computers with the ability to store and share a million byte source program library on two full-size flexible diskettes.

To find out more about CLUSTER/ONE, call us at 415/327-0125. Or write to Nestar Systems, Inc., 430 Sherman Avenue, Palo Alto, California 94306.

✓ N20

NESTAR SYSTEMS
INCORPORATED

FOR PET, TRS 80, COMPUCOLOR.



SOUNDWARE adds music and sound effects to your computer. Includes DEMO PROGRAM, SOUND COMPOSER (to create your own BASIC sound subroutines) and instructions. Unit has volume control, earphone jack, connectors. 1 year warranty. \$29.95 for PET & TRS-80. \$39.95 for CompuColor (includes diskette).

SOUNDWARE SOFTWARE FOR 8K PET!

Compatible with all CB-2 sound devices. Features sound, super graphics, instruction booklet. 90 day warranty.

1. ACTION PACK—Breakthru (8 versions) / Target / Caterpillar
2. THE CLASSICS—Checkers (8 versions) / Backgammon / Piano Player
3. WORD FUN—Speller (4 versions) / Scramble / Flashcard

\$9.95 per pack or 3 packs plus bonus program for \$29.00. More sound programs coming: TRS-80 and CompuColor, too! ✓ C131

To Order: Send to CAP Electronics, Dept. KB4, 1884 Shulman Ave., San Jose, CA 95124, or call (408) 371-4120. VISA / Master Charge accepted. No charge for shipping when payment is included. Please add 15% for C.O.D. Calif. residents add 6% tax.

Prices subject to change without notice.

DEALER & DISTRIBUTOR INQUIRIES WELCOME

The Independent Newsletter of Heath Co. Computers

The independence of Buss is a crucial factor in its significance to users (and prospective users) of Heath Co. computers. Information on new products is presented to Buss readers as it leaks out of Benton Harbor, not held back to suit the marketing plans of the manufacturer. For example, word that Heath Co. was working on the H19 terminal based on the Z80 microprocessor appeared well over a year ago in the February 1978 Buss. News of compatible hardware and software from other vendors is also featured.

Buss is not a company-controlled publication, so it can deal with the weaknesses of Heath Co. computer products as well as their strengths. Buss emphasizes candid accounts of owners' experiences with their computers. Their discoveries save subscribers headaches--and money. That's the proven record of over two years of publication. So Buss can guarantee a full refund any time you're not satisfied.

Buss is mailed first class (by airmail outside North America). The 24-issue subscription gives you the choice of starting with the latest issue or with available back issues (about eight are still in stock). Send \$8.20 for 12 issues or \$15.40 for 24 (overseas, \$10.50/12; \$20.00/24 payable on a U.S. bank) to:

Buss ✓ B43
325-K Pennsylvania Avenue, S.E.
Washington, DC 20003



SCELBI Publications

✓S1



Z80 Instruction Handbook

A complete guide to the Z80 instruction set. Machine codes presented in both octal and hexadecimal format. An index lists instructions alphabetically along with machine codes and timing information. Industry-standard mnemonics used throughout.

\$4.95* No. 20



Microcomputer Potpourri

Reference for beginner, technician, engineer. Glossary with all the jargon. Helps beginners understand computer magazines, mfg. literature and serves as reference for the pro. Reviews microprocessor chips in detail. Complete text on understanding microcomputers.

\$2.95* No. 70

8080 Galaxy Game Match wits against the logic of your 8080.

ONLY \$9.95* No. 15

SCELBI Byte Primer The ultimate handbook about microcomputers.

JUST \$10.95* No. 25

Take My Computer ... Please!

An uproariously funny full length novel.

JUST \$5.95* No. 35


Program Booklet Keep a permanent record of your own programs.

JUST \$2.49* No. 45

8080 Programmer's Pocket Guide

A handy, compact reference.


JUST \$2.95* No. 55



Personal Information Management System

Plain talk on what a computer can do for you. How to use a computer without knowledge of programming. 15 examples include


personal mailing list, accounts payable — even an intelligent ham radio log. For the TRS-80, PET and others. \$9.95* No. 10



Practical Antennas

You've never seen an antenna book quite like this! How to build practical beams, quads, wire antennas. Computer-generated beam headings to every

known country in the world. Charts and tables to eliminate tricky calculations. Tips on keeping your antenna up. \$9.95* No. 80



6800/8080 Software Cookbooks

Cook up mouthwatering programs. "How to" facts include 6800 or 8080 instruction sets. Manipulate stacks.

Flow charts. General purpose routines for multiple precision operation. Program time delays for real time. \$10.95 ea. * No. 50(6800) No. 60(8080)




Learn Microcomputers

Multimedia package. Includes text (Understanding Microcomputers) plus high-quality cassette. For the beginner. Covers basics quickly,

easily, enjoyably. Fundamentals for operation of many microcomputers. Clear. Concise. Companion tape includes chapter-by-chapter synopsis of the book.

\$14.95* No. 40



Special Offer

Now you can have a good laugh on us! That's right. If you buy Calculating with BASIC now, you'll get our hilarious book, Take My Computer ... Please! at 1/2 price — that's \$3 off, on us! And you'll be sure to laugh. With SCELBI's BASIC routines working in your computer, you'll have plenty of time to enjoy the knee-slapping humor of Take My Computer ... Please! Order now. That's Calculating with BASIC for only \$7.95; Take My Computer ... Please! just \$2.95 additional (sold separately for \$5.95).

Calculating with BASIC

Here's a variety of programs in BASIC language to help the student, scientist, engineer, technician or hobbyist apply the language to practical problems. Covers mathematics, finance and statistics, mechanical engineering and electronics. For fun between such serious applications, Hangman and Space Capture games.

Special offer, both books \$10.90* No. 32

Cal/BASIC only \$7.95* No. 30

SCELBI Publications, P. O. Box 3133, Milford, CT 06460 203-874-1573

***IMPORTANT ORDERING INFO!** Include 75 cents postage/handling for each item. Prices shown are for North American customers. Master Charge, VISA, Postal and Bank Money Orders preferred. Personal checks delay shipping up to 4 weeks.

☐ No. 10 ☐ No. 15 ☐ No. 20 ☐ No. 25 ☐ No. 30 ☐ No. 32 ☐ No. 35
☐ No. 40 ☐ No. 45 ☐ No. 50 ☐ No. 55 ☐ No. 60 ☐ No. 70 ☐ No. 80

Name (please print) _____

Card No. _____ Bank No. _____ Exp. _____

Address _____

City/State _____ Zip _____

Signature _____ Amt. Enc. _____

See SCELBI books at your favorite computer or electronics store.

Build your own microcomputer as you learn computer technology at home.

New from NRI! The Most Complete and Up-to-date Home Study Course Ever Offered

As the microprocessor revolutionizes the computer world and microcomputers appear almost everywhere, NRI brings you a new, convenient, and effective way to keep up with this expanding technology. It's NRI's Computer Technology Course, created and designed exclusively for learning at home in your spare time.

Featuring NRI's Exclusive Dual Language Microcomputer

NRI goes beyond book learning to give you practical, "hands-on" experience in designing circuitry, interfacing components, programming, and troubleshooting. As you learn, you actually assemble NRI's designed-for-learning microcomputer, incorporating the latest advances in the state of the art. It looks and operates like the finest of its kind, actually does more than many commercial units. But NRI engineers have designed components and planned assembly so it demonstrates important principles, gives you working experience in detecting and correcting problems. And it's yours to keep, put to work in your own home or business.

You also build and keep your own test instruments, including a transistorized volt-ohm meter and CMOS digital frequency counter. And NRI's Discovery Lab® broadens your horizons with specialized experiments and theory demonstrations.

The Proven Way to Learn at Home

You don't have to worry with travel, classes, or time lost from work when you learn the NRI way. As they have for more than 60



years of teaching technical subjects, NRI brings the material to you. You study in your spare time, at your convenience, using "bite-size" lessons that program material into logical segments for easier assimilation. You perform experiments and build equipment using kits we supply. And your personal NRI instructor is always available for consultation should you have questions or problems. Over a million students have already shown the effectiveness of NRI training.

Choice of Courses

Several courses are available, depending

upon your needs and background. NRI's Master Course in Computer Technology starts with the fundamentals, explores basic electronics and digital theory, the total computer world, and the microcomputer. The Advanced Course, for students already versed in electronics and general computers, concentrates on the microprocessor and microcomputer. In both courses, you build all instruments and your own computer.

Send for Free Catalog... No Salesman Will Call

Get the details on these exciting new courses in NRI's free, 100-page catalog. Shows all kits and equipment, lesson outlines, and full information, including facts on other electronics courses. Mail the coupon today and we'll rush your catalog. No salesman will ever call. Keep up with the latest technology as you learn on your own computer. If coupon has been removed, write to NRI Schools, Computer Department, 3939 Wisconsin Ave., Washington, D.C. 20016.



NRI Schools
McGraw-Hill Continuing
Education Center
3939 Wisconsin Avenue
Washington, D.C. 20016

NO SALESMAN WILL CALL
Please check for one free catalog only.

- ☐ Computer Electronics Including Microcomputers
- ☐ TV/Audio/Video Systems Servicing
- ☐ Complete Communications Electronics with CB • FCC Licenses • Aircraft, Mobile, Marine Electronics
- ☐ CB Specialists Course
- ☐ Amateur Radio • Basic and Advanced



All career courses approved under GI Bill.
☐ Check for details.

- ☐ Digital Electronics • Electronic Technology • Basic Electronics
- ☐ Small Engine Repair
- ☐ Electrical Appliance Servicing
- ☐ Automotive Mechanics
- ☐ Auto Air Conditioning
- ☐ Air Conditioning, Refrigeration, & Heating Including Solar Technology


Name _____ (Please Print) Age _____

Street _____

City/State/Zip _____

Accredited by the Accrediting Commission of the National Home Study Council

172-059




the TR-S100

S-100 BUS INTERFACE TO THE Radio Shack TRS-80

TRS-80 is a product of Radio Shack, A Tandy Corporation

... the "breakthrough" for TRS-80 Owners! Now you can make your TRS-80 compatible with the S-100 Bus systems... opening a whole new world of peripheral devices and applications to you!



We have opened the door to the S-100 world of unique devices for the TRS-80 owner/user. With the TR-S100 you get more than the S-100 interface! We have included sockets for memory expansion up to 32K Bytes. A parallel printer port is provided and provisions have been made for a floppy disk interface (either the 5" mini-floppy of the full size 8"). All this, and software compatibility with the TRS-80 System.

If you already have a TRS-80 expansion chassis, you won't need all the options on our card. But if you have our card, you won't need a TRS-80 expansion chassis. No matter how you put your system together, you can use our card.

For the adventurer, The TR-S100 module allows the TRS-80 to be reconfigured to run software written for the S-100 Bus.

**micro
computer
devices
inc.**

960 E. Orangethorpe, Bldg. F
Anaheim, California 92801
Telephone (714) 992-2270

✓ M30

Direct International Sales:
International Sales Division
17648 Orna Drive
Granada Hills, CA 91344, USA

Discounts Available to:
EDUCATIONAL ACCOUNTS
Contact: P.O. Box 8394
Ann Arbor, MI 48105 (313) 665-8514



"Innovators to the Microcomputer Industry"

TRS-80 OWNERS PUT SOME LEAD IN YOUR PENCIL WITH AN ELECTRIC SECRETARY

One of the most powerful word processing programs ever written for the TRS-80 (32-48K). Does all the conventional tasks, plus these exclusive features:

- Written in basic, permits user modification
- Disk based for rapid file access
- Hyphenates words and stores in dictionary
- Permits operator inserts while printing
- File coupling for long manuscripts
- Cross files for customizing form letters
- Echo makes printer an electric typewriter
- Uppercase shift lock (modified TRS-80)

THE ELECTRIC SECRETARY program is supplied on a formatted disk, complete with extensive documentation for \$75.00, documentation only \$10.00 refundable on order.

THE PERIPHERAL PEOPLE

P. O. Box 524 • Mercer Island, Washington 98040

VISA and Master Charge accepted, ✓ P52

TRS - 80

SPECIAL PROMOTION SALE

SAVE 10%, 15% or more on ALL Computers, Peripherals, Software, and ALL other fine Radio Shack® products.

NO TAXES on out-of-state shipments.

FREE Surface delivery in U.S.
WARRANTIES will be honored by your local Radio Shack® store.

Offered exclusively by
Radio Shack®

Authorized Sales Center

1117 Conway

Mission, Texas 78572

(512) 585-2765



✓ P38

VISA®

SPECIALS

PET 8K	\$695
PET 16K full keyboard	890
PET 32K full keyboard	1065
PET 2040 dual disk	1160
PET External Cassette	83
SYM-1 238 KIM-1	159
North Star Horizon 2	1590
double dens. 2 drive kit	
North Star 16K RAM kit	245
Prob Solver 16K Static	279

Write for out catalog of S-100, 6502, and software products.

AB Computers

115 E. Stump Road
Montgomeryville, PA 18936 ✓ A88
(215) 699-8386

SPECIAL

PET 2001-8K	\$ 699.
PET 2001-16N,16B	\$ 899.
PET 2001-32N,32B	\$ 990.
SYM-I \$239. KIM-I	\$ 159.
PET 2021 Printer	\$ 495.
PET 2023 Fast Printer	\$ 799.
PET 2022 Trac. Fd Printer	\$ 899.
PET 2040 Dual Disk Drs.	\$1099.
PET External Cassette	\$ 89.
HORIZON-II-16K-P, S(ASM)	\$2249.
CROMEMCO SYS-3	\$4895.
HAZELTINE 1400	\$ 695.
CENTRONICS 779-1	\$ 995.
(Trac. Feed) 779-2	\$1095.
Micro SI \$539. & PI	\$ 444.
SD SALES Expandoram Kit	\$ 189.
Z-80 Starter Kit	\$ 229.
SBC Computer Board Kit	\$ 220.
PET Big Keyboard & Plan	\$ 49.

Multi Business Computer Systems

28 Marlborough St.
Portland, Ct. 06480
203 342-2747 ✓ M83


apple tv & computing GRAND OPENING SALE!

An introductory sale! Every PET ordered this month will come with Full size . . .
BIG KEYBOARD . . . ONLY \$895
or, the standard 8k PET . . . \$775
NEW!! . . . PET MiniFloppy . . . \$595
We Have The **BALLY Computer System**
And SOFTWARE for BALLY BASIC on audio cassettes. Write for list of titles.

apple tv & computing

(213) 559-4268 ✓ A83

2606 S. Robertson Blvd.
Los Angeles, California 90034



MICRO MANAGEMENT SYSTEMS

MICRO-COMPUTER SPECIALIST
LARRY OWENS

★ 15% Discount: TRS-80's ★

RADIO SHACK DEALER - MINI MALL ✓ M95
DOWNTOWN SHOPPING CENTER
CAIRO, GA. 31728

(912) 377-7120

PRF-TEL COMPUTER ELECTRONICS

Used/Surplus Computer Related Assemblies/
Components and Peripherals for the Hobbyist

PRF-TEL COMPUTER ELECTRONICS ✓ P53

Its a division of:

PRF TELECOMMUNICATIONS, INC.

115 Vine St. Nashua, NH, 03080 (603) 882-8514

• PRINTERS •

3110/Singer Friden HSP-30

Ref: Kilobaud Microcomputing, April 1979 "How
About a Printer" pgs. 116-118

\$225.00 Complete only—no cover

\$295.00 Complete, with cover, runs internal tests

\$325.00 Complete, with cover, runs internal and external tests

• Above printers are used, non refurbished • We have a limited number of non-used

• Power supplies (5V3A) (5V5A) (5V10.5A) (5V21A) (6V1.4A) (12V1.4A) (28V3.5A) (others)

• Keyboards 7 BIT ASCII parallel output, in cases

• Peripheral dynamic card readers, model C301

• Modems, direct connect 201B equivalents, others

Terms: Check or money order—Item(s) price plus shipping/handling charges—Write for more info/flyer.

BASIC SUBROUTINE LIBRARY Volume 1

VM Professional Application
Software, Ltd.

✓ V22 2703 Bainbridge Avenue
BURNABY, B.C. V5R 2S7

- ARRAYS - minimum, maximum, sums, searching, sorting.
- MATRIX ALGEBRA - addition, subtraction, multiplication, transposition, determinant, inversion.
- SIMULTANEOUS EQUATIONS - non-symmetrical, symmetrical, banded, three-diagonal.

Any routine you'll ever need, involving arrays, matrix algebra or simultaneous equations, can be found in this comprehensive collection of subroutines, compactible with any version of BASIC having subscripted variables.

Numerous examples show how to incorporate those subroutines into your programs or how to use them as stand alone programs.

Order now and save days of work.

\$18.00 U.S. plus \$2.00 for handling and postage.

ATTENTION TRS-80 OWNERS Introducing The * SOUND-PAC * Level II 16k

Yes, Now have sound to go with your games. Games included are Space Wars, Pinball, plus 2 more games. Also included are complete and easy to follow instructions on how to turn your system into a total sound system. Price - \$14.95

BOWLING LEAGUE STATISTICS - Generates complete league statistics on league standing sheet and record sheet. Ideal for league secretaries with one or fifty leagues. Fast data entry, prompting, error detection and almost any handicapping method.

32k-DOS-Printer on diskette W/DOS \$34.95

Also many other simulations are available. Some examples are Pro Boxing, One on One Basketball, Home Run Derby, ect. For more info send for our free brochure:

✓ R32 REAL-LIFE Simulations
3107 Ridge Rd.
Warren, Ohio
44484

To Order Now Please add \$1.00 Shipping
Ohio Residents add 4% Sales Tax

CENTRONICS 779 FOR TRS-80

WHY SETTLE FOR SECOND BEST
WHEN YOU CAN HAVE A BRAND NEW
TRACTOR FEED PRINTER
WITH FACTORY WARRANTY AND
NATIONWIDE SERVICE FOR ONLY

\$995.00

DIRECT PLUG-IN
NO MODIFICATIONS NECESSARY
SAME MODEL PRINTER RADIO SHACK SELLS
MASTERCHARGE OR VISA ACCEPTED
C.O.D. WITH 10 PERCENT DEPOSIT

SHANNON-RICE ELECTRONICS
8909 WENONGA ROAD
LEAWOOD, KANSAS 66206
(913) 649-7105

✓S84

Floppy-Disc Power Supply

Will operate 4 Disc Drives
+ 24 Volts @ 3½ Amp.
+ 5 Volts @ 4 Amp.
- 5 Volts @ ½ Amp.

Fully Protected and Guaranteed

Ready to Ship \$113.00

For further information on this Power Supply and
others, Please Write Us. Dealer Inquiries Invited.



OLYMPIC ELECTRONICS

418 South Lincoln Street
Port Angeles, WA 98362
(206) 457-3315

✓O15

TRS-80 disc software

WORD PROCESSOR Avoid work processor
converted from other system. Hard to load
object file & cannot store text in disk. Ours is
specifically designed for the TRS-80. Written in
BASIC. No special hardware and text limit. \$39.
INVENTORY While others use inefficient
sequential file, we use 9-digit key for fast on-line
random access. Reports give order info,
performance summary, etc. \$39.

MAIL print report & labels sorted by any field.
Random access, special buffering technique.
\$35

DATA BASE MANAGER You can maintain a data
base & produce reports without any
programming. Define fields, types, screen &
report formats on-line. Almost use up the
required 32K memory. \$49.

KEY RANDOM ACCESS UTIL hashing, blocking,
buffering, auto I/O error retry. Put your disk into
optimal use. \$19.

ACCOUNT manage client accounts & account
receivable. Remark fields for general use.
Automatic billing & transaction recording. 32K
req. \$59.

Full documented. Fast delivery. Our competitors
offers \$99 cassette word processor, \$90 'on
memory' inventory, inflexible mail system, 16K
data base.

MICRO ARCHITECT
96 Dothan St.,
Arlington, MA 02174

✓M89

OSI SOFTWARE OSI OHIO SCIENTIFIC

OVER 20 GAMES ON TAPE
—WELL DOCUMENTED—
CATALOG \$1.00

'WITH FREE GAME LISTING AND
PROGRAM TIPS'

****SPECIAL****

SEAWOLFE \$4.95

—JOYSTICK PROGRAMS—
TANK AND FIGHTER PILOT
AND PLANS FOR \$10 JOYSTICK
CONVERSION—\$12.95

✓A90

AARDVARK TECHNICAL SERVICES

1690 BOLTON, WALLED LAKE
MI 48088 313-624-6316

Apple software from RAINBOW

NEW!

PIE TEXT EDITOR Machine language, cursor-based text editor
for 16K Apple.

- Features format capabilities of most text editors.
- All commands are control characters.
- Enables you to define your own function commands.

Order PIE on cassette: \$19.95 on diskette \$24.95

HIGH RESOLUTION CHARACTER GENERATOR Machine language
program for 16K Apple.

- Define your own character set and graphic shapes.
- Complete English upper/lower case character set.
- Complete Greek Alphabet with upper/lower character set.
- Scroll, vary window size, invert characters, switch back and forth between two character sets.

Order on cassette \$19.95 on diskette \$24.95

FORTE Music Interpreter in Machine Language for 16K Apple.


- Handles six voices.
- Single step capability.
- Full editing features.
- Trace line numbers or notes.
- Print words of any song.
- Save songs on cassette or diskette.

Order FORTE on Cassette \$19.95

Call or write today for your FREE Apple Software Catalog, B/A
and Mastercharge accepted. Sorry, no C.O.D.s. Add \$1.25 Shipping &
Handling. California residents add 6% sales tax. We ship promptly
on receipt of your p.p.d. order. Order from:

RAINBOW COMPUTING INC.
Garden Plaza Shopping Center, Dept. 6K1
9719 Reseda Blvd., Northridge, CA 91324
Telephone (213) 349-5560

Bytes books. argains



IMSAI et al

MARKETLINE SYSTEMS, Inc.

2337 Philmont Ave. ✓M17
Huntingdon Valley, Pa. 19006
215/947-6670 • 800/523-5355

SPOOLER for NORTHSTAR

Run Programs and Print Spooled
Files at the Same Time

The MASP-SPOOLER allows PRINTOUTS and LISTINGS to be diverted to
named DISK FILES. Under command, these files can be printed CONCUR-
RENT with a running BASIC program. MASP is completely transparent to
DOS and BASIC. It requires 4K at 0000, 8000, 9000, or A000 \$69.95

WORD PROCESSOR

This program features full justification, centering, tabs, underlining, paging
and more. It is written in BASIC so that it can be easily modified. Text files
are written using the BASIC editor, so you do not have to learn a new
system. It outputs at least 120 wpm with a 30 cps printer. \$49.95

DATA BASE and MAILING LIST

Structured as a mailing list, this program provides access to data at high
speed using fast sorting and search techniques. All fields for each record
are variable length so almost any type of data can be stored. Fields include:
LAST NAME, FIRST NAME, FAMILY MEMBERS, COMPANY, ADDRESS,
PHONE, and 6 more you define. Current balance and accounting data is also
kept so the system functions as an accounts receivable package. You can
also search on any field. \$129.95

Mini manuals for any system available for \$3.50 each

MICRO WORLD

COMPUTER STORE INC. ✓M61
435 Main Street Johnson City, N.Y. 13790

MAXELL DISKS

"THE QUALITY ALTERNATIVE"

Some computerists pay less but may not get
• Shugart® or IBM® approved disks or
• shipment may not be in hermetically sealed
packages or may take many months for shipment.

MAXELL® is the maker of the finest audio
tape and now disks also!

8" SINGLE DENSITY 10 FOR \$50.00
8" DOUBLE DENSITY 10 FOR \$65.00
5¼" MINI 10 FOR \$40.00

MONEY ORDERS
WE PAY FREIGHT IN U.S.A.



**CUSTOM
ELECTRONICS** ✓C132

238 EXCHANGE STREET
CHICOPEE, MASS. 01013

1-413-592-4761

HOURS: Tues. to Sat. — 9 to 5

Soften Your 1802 with

CUDDLY SOFTWARE

Unbreakable Systems/Support Software
for any 1802 system.

Development Aids (CSOS-31)

- aids machine language programming & debugging
- functions user-program accessible through Standard Call
- Add Byte—pushes down remainder of page
- Change Byte—in place
- Delete Byte—pulls up remainder of page
- Screen Driver—scrolls up; 10 lines @ 10 char/line
- Move Data—1 to 64K bytes at once
- Erase Page
- Displays 1, 2, or 4 pages

Trace Program (CSTP-24)

- simulates 1802, displays internal status except DMA pointer
 - RO and interrupt register R1, External Flags
 - user intervention capabilities; variable instruction rate
 - never visit 'East Hyperspace' again with this debugger
 - stand-alone package, requires 2.25K plus program under test
- Developed on 4K RCA COSMAC VIP system—no-cost tailoring to
your machine when you send in system configuration, especially I/O
to External Flag connections.

Got a unique problem? Custom software at off-the-shelf prices a
specialty.

CUDDLY SOFTWARE

98 Thorndale Terrace
Rochester, New York 14611 ✓C123


Sol-20 Software Catalog

Available Now! COMPUTER

Phone or Write for Free Catalog. **PORT**

- BUSINESS
- FINANCIAL
- UTILITIES
- DIAGNOSTICS
- GAMES

WRITTEN BY
E S V COMPUTER SERVICE



Sol System II-A

from Processor Technology

926 N. COLLINS
ARLINGTON, TX 76011
(817) 469-1502

✓ C80

**SMALL
SOFTWARE
SYSTEM**

TRS-80 PRODUCTS

**SMALL
SOFTWARE
SYSTEM**

RSM-1S: A MACHINE LANGUAGE MONITOR FOR 4K TRS-80'S - \$23.95
RSM-2: AN ADVANCED MONITOR FOR 16K TRS-80'S - 26.95
RSM-2D: THREE MONITORS FOR TRS-80 DISK SYSTEMS - 29.95 .

RSM monitors all have 22 commands to control your TRS-80 Z-80 processor. Examine your ROM's, test RAM, enter and execute machine language programs, read and write machine language tapes, and much more! A SYMBOLIC DUMP command disassembles memory into Z-80 mnemonics! Memory may be displayed in HEX or two ASCII formats, and can be EDITED, MOVED, EXCHANGED, VERIFIED, FILLED, ZEROED, TESTED, or SEARCHED for one or two-byte codes!

RSM-2/2D include all above features, plus read and write SYSTEM tapes, enter BREAKPOINTS, PRINT with our TRS232 or the expansion interface, and read and write disk sectors directly! RSM-2 loads at the top of 16K LEVEL I or II. RSM-2D, furnished on disk, has 3 versions for 16K, 32K and 48K.

BASIC-1P - LEVEL-1 BASIC WITH PRINTING! - \$15.95

Loads into the top 4K of 16K TRS-80's and uses any LEVEL-1 BASIC program or DATA tape (up to 12K in length) without conversion! Plus LLIST and LPRINT for TRS232, RS-232-C or Centronics printers. LPRINT ON and LPRINT OFF prints anything that you see on the screen! All LEVEL-I abbreviations and functions supported.

BARRICADE: MACHINE LANGUAGE ACTION GAME FOR TRS-80'S - \$14.95

Break through the 5-wall Barricade with the high-speed ball and keyboard controlled paddle! Trap the ball among the walls and watch it destroy the 100 blocks! Select from 8 speeds, 4 paddle sizes, and 3 ball-angle limits to challenge experts and beginners. 3 scores with the best of each saved to be challenged by other players. NOBODY can achieve the maximum WEIGHTED SCORE of 33,000! 4K LEVEL-I and II.

AIR RAID: A REAL-TIME TRS-80 SHOOTING GALLERY! - \$14.95

A high speed machine language game where large and small airplanes fly across the screen at different altitudes. A ground based missile launcher is pointed and fired from the keyboard. Aircraft explode dramatically when hit, sometimes destroying other nearby planes! Score is tallied for each hit or miss, and the highest score is saved to be challenged by other players. AIR RAID provides hours of fun for you, and is a super demonstration program for entertaining friends! 4K LEVEL I and II.

* CALIFORNIA RESIDENTS ADD 6 PER CENT SALES TAX * ✓ \$51

* SMALL SYSTEM SOFTWARE * P.O. BOX 366 * NEWBURY PARK, CALIF. 91320 *

THE ELECTRIC PENCIL FOR TRS-80 DISK SYSTEMS - \$150.00
THE ELECTRIC PENCIL FOR TRS-80 TAPE SYSTEMS - 99.95

Write text, delete, insert, or move words, lines or paragraphs, save your text on tape (or disk), then print formatted copy with our TRS232 or the Radio Shack Printer (plus RS-232-C with disk version). Right justification, page titling and numbering, transparent cursor and repeating keyboard. Uppercase only, or add lowercase entry and display with minor modification. Tape version runs in LEVEL-I or II 16K computers. A superior word processor for home or business use!

CP/M OPERATING SYSTEM WITH TRS232 DRIVER - \$145.00

CP/M is a file-oriented disk operating system that provides a common set of utilities for program development and operation. 6 built-in commands, plus many utilities called in from disk. A single editor (ED) is used to create and modify all files. Files may be much longer than your memory! The assembler (ASM) assembles files directly from disk, placing HEX object and assembled PRINT files back onto disk! Also includes DDT (Dynamic Debugging Tool), PIP (Peripheral Interchange Program), and more! CP/M will run on 16K TRS-80's with single disk drives, but 32K and 2 or more drives are recommended. CP/M is a trademark of Digital Research, Inc.

DCV-1: CONVERT SYSTEM PROGRAMS TO DISK FILES - \$9.95

RSM monitors, Barricade, Air Raid, RSL-1, ESP-1, T-BUG, or nearly any SYSTEM tape shorter than 5K (21K if you have 32K of memory) can now be executed from disk, even if it interferes with TRSDOS! DCV-1 loads system tapes into high memory and adds a block-move routine. TAPEDISK is then used to create a disk file. When accessed from disk, the program loads into high memory, moves itself to its correct address, then jumps there and executes!

TRS232 PRINTER INTERFACE - \$49.95 (+\$2.00 shipping)

A fully assembled self-contained software-driven output port for TRS-80 printing. Use any RS-232 or 20-mil current loop ASCII printer. The TRS232 is furnished with cassette software and works either with or without the expansion interface! Use the TRS232 with LEVEL-II BASIC, CP/M, BASIC-1P, ELECTRIC PENCIL, RSM-2/2D or your own programs!

OTHER TRS-80 PRODUCTS

ESP-1: \$29.95 Editor, assembler, and monitor using INTEL 8080 mnemonics.
RSL-1: 14.95 Draw patterns, then play Conway's LIFE in machine language.
LST-1: 8.00 A disassembled listing of LEVEL-1 BASIC with some comments.



* SMALL SYSTEM SOFTWARE * P.O. BOX 366 * NEWBURY PARK, CALIF. 91320 *

MOSCOW 1980

Make check payable to
U.S. Olympic Committee,
P.O. Box 1980-P, Cathedral Station,
Boston, MA 02118

Name _____

Address _____

City _____

State _____

Zip _____

A contribution of \$_____ is enclosed.



Please send me the
symbol of support
checked below.

- ☐ Stickpin (\$10)
- ☐ Pendant (\$25)
- ☐ Tote Bag (\$25)
- ☐ Visor Cap (\$25)
- ☐ Desk Spinner (\$50)

Your contribution is tax-deductible.



Without your help, we can't afford to win.

JUNE IS BUSTIN' OUT!



at Computer Corner
OF NEW JERSEY

with

APPLE II 16-K \$1029.

We are authorized dealers for the following name brand manufacturers, and we offer in-house service on all brands we sell.

- | | |
|--------------------------------------|---|
| • Southwest Technical Products, Inc. | • Newtech. Computer Sys. |
| • PolyMorphic Systems | • Ohio Scientific |
| • Micro Term | • Jim-Pak |
| • George Risk Ind., Inc. | • Kim-1 |
| • Hayden Books | • Sanyo |
| • Sybex Books | • Verbatim Removable Magnetic Storage Media |
| • Scelbi Books | • OK Tools |

MASTER CHARGE & VISA ACCEPTED!

Computer Corner of New Jersey

240 Wanaque Avenue, Pompton Lakes, N.J. 07442

(201) 835-7080

TRS-80

loves your
Favorite
houseplants



TIRED OF PLAYING GAMES?

MAKE YOUR TRS-80 WORK FOR YOU!

ALL NEW SOFTWARE CONTAINS BASIC INFORMATION ON THE CHARACTERISTICS, COMMON AND BOTANICAL NAMES, TYPE AND PROPAGATION, TEMPERATURE AND HUMIDITY, SOIL AND FERTILIZER, DISEASES AND PESTS OF 100 FAVORITE HOUSEPLANTS.

****100 FAVORITE HOUSEPLANTS****

FOR TRS-80 4K LI.....\$12.50

4K LII.....\$12.50

(Idaho Residents Add 3% Sales Tax)

MAKE CHECK OR MONEY ORDER PAYABLE TO:

CECDAT INC ✓ C128

P.O. BOX 8963 MOSCOW, ID. 83843

ATTENTION TRS-80 & APPLE USERS

A PRINTER FOR YOUR COMPUTER



TERMS: VISA, MASTERCARD, Cashier Check or Money Order. C.O.D. with 10% down. Shipping Via Air or Truck collect.

3 S SALES ✓ S55

P.O. BOX 45944
TULSA, OK 74145
918/622-1058

\$995⁰⁰

MODEL 3S-80 for TRS-80

Ready to plug into your expansion interface.

MODEL 3S-PP

for computers with 8 bit serial port.

MODEL 3S-SS

for computers with RS-232 port.

\$1095⁰⁰ for

MODEL 3S-AA

Includes RS-232 card for Apple II
Specify model number on order.

- Ready to plug into your computer
- Very high quality print
- Completely refurbished IBM 731 I/O Selectric terminal in a new table
- Upper & lower case removable type ball
- Special I/O interface
- Heavy duty re-mfg. IBM power supply

ADVANCED COMPUTER PRODUCTS ✓ A38
NOW IN STOCK LOW COST
HIGH RESOLUTION PLOTTING FOR THE SMALL SYSTEM!
SALE PRICE

HIPAD™
 DIGITIZER




Resolution and repeatability of 0.005 in., Origin is completely relocatable, RS232C and 8 bit parallel interface selectable at the connector, Accuracies of ± 0.015 in. (0.4mm), Optional LC display shows actual X-Y values Price \$295.00.

List Price\$795.00

ACP Sale Price.....\$735.00

HI PLOT™
 DIGITAL PLOTTER



Displays data in easy to read graphical format, Both serial and parallel inputs built-in, Uses standard 8 1/2" x 11" paper, Plotting speed up to 2.4 ips, Resolution of both 0.01 and 0.005 in., Baud rate and step size easily changed, Completely assembled and ready to use.


List Price\$1085.00

ACP Sale Price ...\$ 965.00

ADVANCED COMPUTER PRODUCTS

P.O. Box 17329 • Irvine, California 92713
 New Phone (714) 558-8813 • TWX: 910-595-1565

Tarbell 32K RAM Memory



- ★S-100 BUS ★ ★300ns ★ ★STATIC MEMORY ★
- ★9 REGULATORS PROVIDE EXCELLENT HEAT DISTRIBUTION ★
- ★EXTENDED ADDRESSING (Bank Switching) ★
- ★LOW POWER REQUIREMENT ★
- ★PHANTOM LINE ★
- ★20 PAGE OPERATING MANUAL ★
- ★FULL 1-YEAR WARRANTY ★

FULLY ASSEMBLED AND TESTED \$625.
 SAME BOARD WITH ONLY 16K INSTALLED . . . \$390.

Please send check or money order. No CODs or credit will be accepted on this item. California residents please add 6% sales tax.

✓ P49

Tarbell
 Electronics

950 Dovlen Place • Suite B • Carson, Calif. 90746
 (213) 538-4251 (213) 538-2254

Radio Shack Computer Owners:

TRS-80 MONTHLY NEWSLETTER

- GAMES
- EDUCATION
- PERSONAL FINANCE
- BEGINNER'S CORNER
- NEW PRODUCTS
- SOFTWARE EXCHANGE
- MARKET PLACE
- QUESTIONS & ANSWERS
- PROGRAM PRINTOUTS
- PRACTICAL APPLICATIONS
- BUSINESS
- GAMBLING . . . AND MORE!

FREE* WORD PROCESSING PROGRAM (Cassette or Disk)

For Writing Letters, Text, Mailing Lists, Files, Etc.
 With Each New Subscription Or Renewal

* This offer valid on orders placed after Dec. 1, 1978

- ☐ ONE YEAR SUBSCRIPTION—\$24
- ☐ TWO YEAR SUBSCRIPTION—\$48
- ☐ SAMPLE OF LATEST ISSUE—\$4

☐ START MY SUBSCRIPTION WITH ISSUE _____

(#1 = July 1978; #7 = January 1979)

- ☐ New Subscription ☐ Renewal
- ☐ Master Charge ☐ Visa

CREDIT CARD # _____ EXP. DATE _____

SIGNATURE _____

NAME _____

CITY _____

STATE _____ ZIP _____



24 HOUR ORDER LINE: (914) 425-1535



COMPUTRONICS INC.
 MATHEMATICAL APPLICATIONS SERVICE™

✓ M64

Box 149 New City, New York 10956

SEND FOR FREE SOFTWARE CATALOG (INCLUDING LISTINGS OF HUNDREDS OF TRS-80 PROGRAMS AVAILABLE ON CASSETTE AND DISKETTE).

STOCK MARKET • TRADER ENTREPRENEUR

STOCK MARKET ANALYSIS SYSTEM

Technical analysis for the market trader with little time (15 min/day). For \$25 you receive data base plus two programs on cassette and hard copy instructions written for the novice. Please indicate: TRS80 Level I or II 16K or PET 8K

STOCK MARKET FINANCIAL SYSTEM

Includes two programs and hard copy instructions for better control of your stock and option transactions. For \$20 you receive software with eight analysis routines. Two of these routines are stock transactions which made money and option transactions which made money. Six more program routines exist with some consideration given to taxes. Please indicate: TRS80 Level II 16K or PET 8K

ACCOUNTING ANALYSIS SYSTEM

Includes two programs and hard copy instructions for better control of your personal business affairs. From your data base a Profit and Loss Statement as well as a Balance Sheet are produced. In addition simple budget comparisons are made. Please remit \$20 and indicate: TRS80 Level II 16K or PET 8K

Distributed by: STEVE E. SHAW P.E.
Software Consultant
P.O. Box 1707
Tampa, Florida 33601 ✓S76

ATTENTION APPLE II OWNERS

Southeastern Software NEWSLETTER
\$10.00 for 10 issues per year. Back
issues available at \$1.00 each.

Send \$5.95 plus 50¢ p&h for
3 program demo tape. (Integer
or Applesoft II) and sample
NEWSLETTER.

Ask your local dealer for MAG FILES
for the Disk II and the NEWSLETTER

SOUTHEASTERN SOFTWARE
7270 Culpepper Drive ✓S52
New Orleans, LA 70126

Who regularly publishes more info on
APPLEs, PETs, KIMs, SYMs, AIMs, and
other 6502 based systems, products and
programs than

kilobaud **BYTE**
INTERFACE AGE™
creative computing

COMBINED?

MICRO™

✓M74
that's
who

the full size magazine devoted to 6502
information. Now published monthly \$12.00
per year in USA.

Now you can get all of MICRO by buying
"The BEST of MICRO Volume I" for \$7.00
(includes shipping) and starting your
subscription with issue #7.

PO Box 3, S. Chelmsford, MA. 01824
617/256-3649

P.S. SOFTWARE HOUSE

FORMERLY PETSHACK
PET™ SCHEMATICS

FOR ONLY \$24.95 YOU GET:
24" X 30" schematic of the CPU board, plus oversized schematics of the Video
Monitor and Tape Recorder, plus complete Parts layout - all accurately and
painstakingly drawn to the minutest detail.

PET™ ROM ROUTINES
FOR ONLY \$19.95 YOU GET:
Complete Disassembly listings of all 7 ROMs, plus identified subroutine entry
points, Video Monitor, Keyboard routine, Tape Record and Playback routine, Real
Time Clock, etc. To entice you we are also including our own Machine Language
Monitor program for your PET using the keyboard and video display.
You can have the Monitor program on cassette for only \$9.95 extra.
PET to PARALLEL INTERFACE with 5V 8A power supply \$74.95
PET to 2nd CASSETTE INTERFACE \$49.95

Send for our free SOFTWARE BROCHURE. Dealer inquiries welcome.

PET™ EXPANDOR PRINTER

PRINTER PRICE WITH PET INTERFACE \$525

- Small size of 4.5" H x 12 1/2" W x 9 1/2" D
- Impact printing - 3 copies
- Prints 80 columns wide
- Print Cylinder - not a matrix
- Uses 8 1/2" paper, pressure or pin feed
- Easy to maintain yourself, or return to us
- Regular Paper - Coated paper not required
- Lightweight, 11 1/2 lbs. with cover
- Prints 10 characters per second
- 64 Character ASCII Character Set
- Full Documentation Included




This is the ideal, low cost, reliable, self maintained
printer with which to complete your PET™ system.

P.S. SOFTWARE HOUSE ✓P37

P.O. Box 966 Mishawaka, IN 46544
Tel: (219) 255-3408



Datapoint CRT Terminals



Fully-Assembled — Guaranteed
#3360 \$649.50

- Add \$15 packing.
- Shipped FOB Washington, D.C. Terms check, M.O. or charge.
- 90-day guarantee
- Scrolling version \$695.00
- Model 3360 speeds from 300-4800 Baud, numeric keypad, cursor controls, Edit, Block-Transmit, search modes. ASCII Keyboard with codeable options. Green phosphor, 24 80 ch lines, addressable cursor; RS-232C serial interface; other speeds available. Manual \$10; cable kit \$9.95. Datashare/IBM-2260 compatible version \$1,100.00. • Model 3000 \$495.00. M-33 ASR Teletype \$895, KSR \$725, All M-28, 35 components available, also Modems, readers. QUANTITY DISCOUNTS AVAILABLE. Leasing, service at low prices.

TELECOMMUNICATIONS SERVICES CO.
Box 4117, Alexandria, Va. 22303 ✓T26
703-683-4019 / TLX 89-623

ANNOUNCING

NORTH-STAR™ BUSINESS SOFTWARE

INVENTORY CONTROL handles 1200 items per disk. Full prompting. Can be used by untrained personnel. Pays commissions & bonus based on profits, not gross sales! (Up to 5 salesmen.) Detailed reports. Includes SUP-R-SORT. 13 programs in reliable use over one yr. Requires 32 K, 1 drive, any printer, and any TV terminal.

INVENTROL w manual & listings \$89.00
MANUAL (refundable w. purchase) \$29.00
SUP-R-SORTs 100 items per min! \$39.00
ACCOUNTS RECEIVABLE \$89.00
ACCOUNTS PAYABLE w. manuals. \$89.00

Write for details. MC & Visa OK. Dealer plan.

YOUNG'S
P.O. BOX 5207 Stn. B, Victoria B.C. CANADA

GIVE YOUR TRS-80 WHAT IT DESERVES

All tapes \$10.00 each, on cassette.

plus \$1.00 postage & handling.

Choose Level I or II.

A television station in Florida chose our *Bioforecast* program (catalog # CS-1) to use in a special news broadcast during the November 1978 state-wide political elections. Many think ours is the best biorhythm program ever written. And it loads and executes in less than 4K!

One customer is using our *Orbit* programs (catalog # CS-2) to help him in the weather satellite work he does for the Air Force.

Recreation centers, schools, businesses, doctors, and housewives are using our *Legend* program. *Legend* (catalog # CS-7) keeps track of things loaned out to people. Its high utility, together with its many features and ease of use, have made it a best seller.

And speaking of best sellers...

Our *Turkey Buzzard* game (catalog # GT-4) has made an even bigger splash than we expected. It is a game that has everything: a detailed scenario, character animation, and a general arcade style. It's chocked full of dangers and comic pitfalls. No wonder there are those who say it may be the most successful work ever to combine a continually changing plot with all TRS-80 graphics capabilities. Already it is becoming a classic among classics.

All of the above programs will execute in less than 4K RAM! You can't get those programs from any other company. We invented them and only we own the rights to them. Sure you can buy one of those cheap "software library" deals, but most of the programs they feature can be found in books. Books you can check out from your public library for nothing.

So for something truly different for your computer, look to the creative software company.

Send SASE to receive the product list faster.

Compuirex



PO Box 536 Inman SC 29349

MICRO'S SHOULD EARN THEIR KEEP!

You liked Version 1 of our General Ledger, wait until you see Version 2.2! Some features include: (Version 1 owners, write for credit on Version 2.2)

New!

Our new "Skip-Sequential" (TM) file structure; Up to 100 (or more) custom accounts; Direct cursor control (for some video devices) or standard scrolling; Complete income statement and balance sheet with printer output; Complete audit trails; Expanded error checking; User oriented with expanded manual; much more! 16 programs totalling over 70K. Price: \$79.95

Check our documentation: \$5.00 (credited towards purchase). All programs on diskette and use North Star BASIC, IK of free memory, 1 or more drives.

Write for details

✓E34 **ECOSOFT**

P.O. Box 68602
Indianapolis, IN 46268

TRS-80

DUST
COVERS



Custom Fabric Dust Covers made from velour, corduroy, or denim. Three-Piece Set fits the keyboard, the Video, and the Tape Drive. Helps combat bounce-causing dust contamination. Slots for all cables so the covers just slip on. Colors to match your room decor. Machine washable. Pre-shrunk.

CHOICE:	VELOUR	CORDUROY	DENIM
	Gold	Brown	Blue
	Red	Royal Blue	
	Green	Gold	
	Maroon		
	Brown		

THREE-PIECE SET—\$19.95 DISK DRIVE COVER—\$7.95
KEYBOARD ONLY—\$7.95

TERMS: PREPAID. Check, Money-order, Master Charge, VISA. Add \$1 for shipping. Mass. Residents add 5% sales tax. Money-back guarantee. Write for club or dealer discounts.

AUGUST AUTOMATION ✓A89
28 Milk St.
Westboro MA 01581
(617) 366-0870

: PET and TRS-80 :

'Just LOAD and GO' Software
Pre-recorded Business Programs
USEFUL-PRACTICAL-LOW-COST!

NO PROGRAMMING EXPERIENCE REQUIRED!

- **GENERAL LEDGER**—For home businesses, sole proprietorships, small corporations—\$19.95 plus \$1.50 s&h, requires 8K min. user memory
- **CHECKING ACCOUNT**—For personal bank accounts—\$19.95 plus \$1.50 s&h, requires 8K min. user memory
- **RENT ACCOUNTS**—Records on rental properties—\$16.95 plus \$1.50 s&h
- **LEGAL DIARY**—For Attorneys (Client Accounts) \$16.95 plus \$1.50 s&h
- **TRUST ACCOUNTS**—For Attorneys (Client Accounts) \$16.95 plus \$1.50 s&h

Programs include 2 PerCom "Pilon-30" record cassettes—money back guarantee
HUSTLER Series 1 for PET(tm) are now available in Britain and Europe through:

PETSOFT

PO Box 9, Newbury Berks. RG13 1PB, England

Specify which computer is used.

Dealer Inquiries Invited All mail orders must be pre-paid.

c/o Kenneth Harris **COMPUTERS ONE** ✓ C81
1314 South King St. Honolulu, HI 96814
Suite 1156 808-536-7735

ATTENTION NORTH STAR USERS

TFS—

Text formatting system. At last a powerful, full-featured text processor for the Northstar Disc System!! "TFS" runs with virtually any system configuration and any terminal. (Note: Uses RAM from 0 to 2000H). Justifies left and right margins, page and chapter headings, page numbering, multi-copy, move text, search text, substitute, merge files, and append files from disc, and much much more! "TFS" is of great use by anyone that wants perfect text and typing with the minimum effort! Includes a 70-page user's manual complete with examples, plus a handy quick reference guide to the "TFS" commands. ---> \$75.00

RDA—

Data System. A very fast and reliable data base management system for Northstar. Access time of less than 0.5 sec (worst case we could find!) Unlimited cross-referencing, paged output, more. "RDA" automatically adjusts itself for the amount of memory you have! "RDA" is great for any one having to have quick access to data and cross-references! Includes user's manual with examples. ---> \$45.00

(Illinois residents add 5% sales tax)

217-344-7596

SUPER SOFT ✓ S61

P.O. Box 1628, Champaign, IL 61820

ATTENTION NORTH STAR USERS

- **TINY PASCAL:** The Chung/Yuen Tiny Pascal. Includes object and source! Needs only 24K to run! = = = >> \$40.00
- **ARIAN:** 8080/280 Operating System. Assembler, Text Editor Debugger, Dynamic File Capabilities, Save & Load Source/OBJ Files to Disk Resident and Custom Commands Truly a powerful, yet easy to use Operating System = = = >> \$50.00
- **INVESTMENT PACK:** Stocks, Bonds, etc. Statistical Analysis, Portfolio Management, Options, much more = = = >> \$30.00
- **FAMILY PACK:** Programs for home and family Includes Mail List, Phone List, Recipe Analysis, Home Budget, much more = = = >> \$30.00
- **ASSEMBLY LANGUAGE PROGRAMMING COURSE:** Level #1, beginners. Tired of not understanding Assem Lang programs? Get this course and begin writing your own code. = = = >> \$30.00
- **TYPING COURSE:** If you're still using "hunt and peck" then you need Supersoft's Typing Course! = = = >> \$30.00

(Illinois residents add 5% sales tax)

SUPER SOFT ✓ S61

P.O. Box 1628, Champaign, IL 61820

TRS-80 business software

We've got it or we'll get it.
All major brands software discounted.

OUR CUSTOM SPECIALS

- *Home Const Mats & Cost—\$100; Disk \$200
- *Block/Brick/Concrete Mats—\$75; Disk \$100
- *Job Cost Analysis—\$75; Disk \$100
- *A Better Realtor Program—L2 \$100; Disk \$150
- *Reservations—Hotel and Airline; Disk \$100

SALES/MANAGEMENT

- *Retrun on Time Invested
- *Account Analysis \$100 each program
- *Territory Call Scheduling
- *Workload Analysis

P M A TAPES. BUY THESE BEFORE ANYTHING ELSE:

- *Five Hours on Closing—Ziglar \$50
- *Think and Grow Rich—Hill \$22

The Computer Shop

217 Grand Spencer, IA 51301
Call 712-262-8535 M.C./VISA
IA Residents add 3% ✓ C134

RS232C Computer compatible Paper Tape Transmitter/Model 612



Stops and starts on character at all speeds, uses manual control or X-on, X-off 90-260 volt, 50-60 Hz power, 50-9600 baud, up to 150 char/sec synchronous or asynchronous; gated internal or external clock, RS-232C, current loop or parallel output, reads 5-8 level tape, 7-11 frames per character, even or odd parity. Desk top or rack mount.



ADDMASTER CORPORATION

✓ A73
416 junipero serra drive
san gabriel, ca 91776
(213) 285-1121 telex 674770
addmaster sgab

NEW!

The first microcomputer shopping guide!

The BIG NEW 2nd edition of the Computer Data Directory is the first microcomputer shopping guide! Perfect for businessmen, educators, and personal computer users. Complete with advertisements, photographs, and useful information on thousands of companies and products. You can find the best deals easier. Includes product/manufacture cross-reference, computer stores, consultants, software directory, publications, clubs, trade shows, entrepreneurs...the works! There's nothing else like it. Order your copy now. Paperback (8 1/2 x 11) only \$5.98, clothbound only \$11.98. Postage paid in US and Canada (foreign orders add \$2.00). Allow 8-10 weeks. Order Today!

Computer Data Publishing ✓ C77
P.O. Box 598
Cleveland, Ohio 44107
(216) 221-5440

Companies...

This guide will reach thousands of qualified buyers. Do we have your product information? Call or write today for details.

TRS-80 COMPUTING

non profit newsletter

12 Issues For \$15.00

(US)

and now

PEOPLE'S SOFTWARE

at popular prices

- 25 cents per program plus 1 dollar per tape
- Tape #1 includes 26 Level I business/home/education programs, just \$7.50 plus 50 cents postage and handling (CA residents add 45 cents tax)
- Write for information

CIE COMPUTER
INFORMATION
✓ C104 EXCHANGE

Box 158 San Luis Rey, CA 92068

★ APPLE OWNERS ★

APPLETIME, a Real Time Clock for the Apple II. Plugs directly into any slot and keeps time even when computer is off. Completely assembled and tested.

SPECIAL INTRODUCTORY PRICE
APT-1 Real Time Clock \$59.95

PROTOBOARD, with over 1300 holes on 0.1 centers for designing your own circuits.

APB-1 Protoboard \$16.95

Offer good this month only. ✓ W29

WEST SIDE ELECTRONICS
P.O. Box 636, Chatsworth, CA 91311
We pay all shipping in Continental U.S.A.
Others add 10%. California residents add 6% tax.

TRS-80 means business! ! !

...with CP/M, CBASIC2, & applications software.

CP/M ("the software bus") & CBASIC2 (the standard for business software) bring new power and versatility to the TRS-80 for practical use.

CP/M Operating System (w/Editor, Assembler, Debugger, Utilities & 6 manual set) \$145
CBASIC2 Compiler (w/manual) \$ 95
DESPOOL Print Spooler (w/manual)..... \$ 75

*Osborne & Assoc. PAYROLL W/COST
ACCTNG \$250
*Osborne & Assoc. ACCTS. RECEIVABLE &
ACCTS. PAYABLE \$250
*Osborne & Assoc. GENERAL LEDGER..... \$250

*=CBASIC2 source programs; add \$15 (each) for applicable O & A book.

APH - Self-administered Automated Patient History..... \$175

Write/call for additional software available & FREE "CP/M Primer".

CA residents add 6% tax. Visa, M/C, M/O, Check OK.



CYBERNETICS

(714) 848-1922



✓ C129

8041 NEWMAN AVENUE • SUITE 208 • HUNTINGTON BEACH, CALIFORNIA 92647

If you need Business Reports with fancy frills you have the wrong company. We don't put these in our Software or our Ads. Both cost *** You *** Money.

But if you need solid, Down-To-Earth Software for your North Star, Imsai, or other low cost Data Processing System written in Microsoft Basic or Cbasic including GL, AR, AP, Inventory, Payroll, Mailing List and Fixed Asset Accounting then you *** Do *** have the right company.

GIVE US A TRY - WE KNOW YOU'LL BE GLAD YOU DID

We honor Visa and Mastercharge

Saron Associates ✓ A82

102 Avenida Dela Estrella
Suite 208
San Clemente, CA 92672
(714) 492-7633

ADVANCED COMPUTER PRODUCTS

CENTRONICS®

LOW COST HARD COPY

Features:

150 Lines per Minute, 96 Characters - Upper and Lower Case, 5/10/20 Characters/Inch - Software Selectable, Elongated Characters, Underlining, Simplified Operation, Quiet, Audio Alarm, Long Life - Only 4 Moving Parts, Small Size and Light Weight, No Toners/Ribbons Required.




**MODEL P1
W/PARALLEL INTERFACE**

7-Bit ASCII, TTL Compatible Input/Output Signals, Compatible with Centronics and other Printer Product Lines.

List Price \$495.00

ACP Sale Price..... \$395.00

Paper (6/case) ... \$2.95/roll



**MODEL S1 W/SERIAL
(RS232) INTERFACE**

7 Bit ASCII, Serial RS232C Interface with Parity Selection, Switch-Selectable Baud Rate: 50 to 9600, 192 Character FIFO Buffer.

List Price \$595.00

ACP Sale Price..... \$525.00

ADVANCED COMPUTER PRODUCTS

P.O. Box 17329 • Irvine, California 92713 ✓ A38
New Phone (714) 558-8813 • TWX: 910-595-1565

EPROM PROGRAMMER—Model EP-2A-79



SOFTWARE AVAILABLE FOR F-8, 8080, 6800, 8085, Z-80, 6502, KIM-1, 1802, 2650.

EPROM type is selected by a personality module which plugs into the front of the programmer. Power requirements are 115 VAC, 50/60 HZ at 15 watts. It is supplied with a 36 inch ribbon cable for connecting to microcomputer. Requires 1 1/2 I/O ports. Priced at \$145 with one set of software, personality modules are shown below.

Part No.	Programs	Price
PM-0	TMS 2708	\$15.00
PM-1	2704, 2708	15.00
PM-2	2732	25.00
PM-3	TMS 2716	15.00
PM-4	TMS 2532	25.00
PM-5	TMS 2516, 2716, 2758	15.00

Optimal Technology, Inc. ✓ O10

Blue Wood 127, Earlysville, VA 22936
Phone 804-973-5482

SPINTERM^{T.M.}

MEANS QUALITY IN REVERSE



Introducing Bidirectional Printing At Affordable Prices

FASTER THAN THE DEVIL!

Using bidirectional printing the Spinterm can print up to 55 characters per second with the quality of a printing press. In fact, with more than 14 different optional printing "thimbles," each with up to 128 characters, there is no end to its printing capabilities. In addition, during communications, there are six user selectable baud rates to 1200. Untouchable!

MULTI-FUNCTIONAL

Spinterm's many standard features include 10 or 12 pitch spacing (user selectable), normal and absolute tabs from 1-136 (in either direction), adjustable line feed with subscript and superscript capabilities and enough power to imprint the original and five copies.

Spinterm boasts an incredible graphing resolution of up to 5760 plot points per square inch (120 horizontal — 48 vertical). Fantastic!

LONGER LIFE — QUIETER OPERATION

Having an MTFB of more than 2000 hours, the Spinterm will perform to the reliability you demand. The materials used in the "thimble" and print hammer extend their life by 50%. The "thimble" alone provides normal element life of more than 30 million impressions!

And when it comes to quiet, the Spinterm printers are —60dB with the standard die-cast aluminum cover; 67dB or less without cover — so they can be used in almost any application. Unbelievable!

TOTAL ADAPTABILITY

Means compatibility. The Spinterm features five optional interfaces (RS232-C, standard). In addition, Spinterm's options include Proportional Spacing — Tractor, Bottom and Pin Feed — Nylon fabric or Multi-strike film ribbon cartridges, plus too many more to mention. Outstanding!

Now instead of a printer playing catch-up, the computers gotta pitch. See it!

For complete information about Spinterm printers see your dealer or write: SPINTERM, Input Output Unlimited, 5922 Kester Avenue, Van Nuys, CA 91411, (213) 997-7791.



✓ 130

COMPUTER MAX ASSOCIATES INC. BUSINESS SOFTWARE For:

505 Hamilton
Palo Alto, CA
94301

APPLE II
MICROPOLIS
MICROSOFT
Vector MZ
CP/M
TRS-80

GENERAL LEDGER

MICROLEDGER performs the duties of bookkeeping and the matching of revenues and expenses.

LEDGER1—builds and maintains your **CHART OF ACCOUNTS** Master file. This file also holds current and accumulated totals in each account.

LEDGER2—sets up and updates **JOURNAL** Transaction file.

LEDGER3—lists both **JOURNAL** and **CHART OF ACCOUNTS** files.

LEDGER4—does **TRIAL BALANCE** and **POSTING**. It outputs an **AUDIT TRAIL** of all transactions.

LEDGER5—produces **PROFIT and LOSS STATEMENT**.

LEDGER6—produces **BALANCE SHEET**. Assets, liabilities and owners' equities are shown by account and by totals.

PAYROLL/PERSONNEL

PERS1 initializes the Master File. Adds and Updates Master Records. Does the Annual Restart of Master File.

PERS2 initializes Payroll File. Adds and Updates Payroll Records.

PERS3 lists an Employee Master Record. Lists Employee Master File. Lists Payroll Records. Lists Payroll Files.

PERS4 computes Payroll and prints Payroll Register. PRINTs Paychecks and Journalizes (entries into Microledger's Journal File).

PERS5 prints Job Cost Report, quarterly 941 run, Annual W-2 run.

PERS6 lists one Employee's History. Lists All Employees' Histories.

ACC'TS PAYABLE

PAY1 initializes A/P and adds records to Transaction file.

PAY2—changes or deletes Transaction and Master records.

PAY3—reports outstanding A/P broken down into four categories: under 30 days, 31-60 days, 61-90 days, over 90 days.

PAY4—reports all outstanding A/P for a single customer or all customers, followed by Cash Requirements.

PAY5—reports all outstanding A/P for a single date or a range of dates followed by Cash Requirements.

PAY6—lists both the Transaction and the Master files.

PAY7—PRINTs checks and accumulates and journalizes A/P (creates entries into the MICROLEDGER's JOURNAL file).

ACC'TS RECEIVABLE

REC1—initializes A/R, adds A/R records & PRINTs invoices.

REC2—enters receipt of customer payments, changes or deletes Transaction & Master records.

REC3—reports outstanding A/R broken down into four categories: under 30 days, 31-60 days, 61-90 days, over 90 days.

REC4—produces statements of A/R for a single customer or for all customers followed by Cash Projection.

REC5—produces a report of all A/R outstanding for a single date or a range of dates, followed by Cash Projection.

REC6—lists Transaction & Master files, and accumulates & journalizes A/R (creates entries into MICROLEDGER's JOURNAL file).

INVENTORY CONTROL

INV1—initializes both Transaction and Master files, adds & updates Transaction and Master records; initializes JOURNAL file, restarts Master file.


INV2—runs, issues or receives Transactions, creating inventory records. It also journalizes and accumulates Transactions (creates entries into MICROLEDGER's JOURNAL file).

INV3—lists both Transactions and Master files.

INV4—supplies Stock Analysis Report, and the ABC Analysis.

INV5—produces the report showing allocation of all materials used year-to-date by JOB Control Classification codes.

INV6—computes and provides the E.O.Q. (Economic Order Quantity).



That's right. The famous Computalker CT-1 Speech Synthesizer that produces highly-intelligible natural sounding speech can now be installed on your TRS-80.

Completely self-contained, the Model CT-1T comes with its own chassis and power supply, on-board audio amplifier (2 Watts), CSR1 software, and interconnect cable. The CT-1T comes with complete documentation and is avail-

able on either 5 1/4 inch diskette or cassette. TRS-80 Level II and 16K words memory required, 32K words recommended.

**SAVE \$100
SPECIAL INTRODUCTORY PRICE
\$495**

Suggested retail price is \$595
Calif. residents add 6% sales tax.



COMPUTALKER CONSULTANTS

1730 21st St., Suite A
Santa Monica, CA 90404
(213) 392-5230 ✓ C36

UNDER ATTACK !!!



Though the loose confederation of colonies in ORION had staved off the Stellar Union's bid for hegemony, would they do as well against the alien *Klottau*?

INVASION ORION

FOR TRS-80 ✓ A71

INVASION ORION uses the simple, but unique and challenging **STARFLEET ORION** game system, but since your opponent isn't human, we've programmed the computer to play the *Klottau*. **INVASION ORION** is complete with program cassette, 64 page Battlemat and control sheets. *10 all-new scenarios*. (Requires TRS-80, Level II, 16K).

Ask your local dealer or send \$19.95 to:
Automated Simulations, Dept. B, P.O. Box 4232,
Mountain View, CA. 94040.
California residents please add 6% sales tax.

APPLE][Business Software

Micro Software Systems has developed a small business turnkey system designated as the Financial Management System (FMS). The password protected system is comprised of 30+ programs which form the following modules: **INVENTORY**, **ACCOUNTS PAYABLES**, **ACCOUNTS RECEIVABLES**, **PAYROLL** and **GENERAL LEDGER**.

The FMS was designed and programmed so that the user does not have to run any programs. The system is totally interconnected through menus. Menus allow function and process selections by entering single characters.

Speed was a major design consideration; thus, a machine language routine called **Keyed Sequential Access Method (KSAM)** was developed and put on a ROM card that is put into Slot 7. The access time was cut down to less than 2 seconds per record. KSAM keeps the file in ascending order without having to go through a program to sort the file. KSAM allowed us to make the FMS an on-line system, one in which updates are done immediately.

INVENTORY - Complete file maintenance plus selective reporting by field. Reorder report of critical parts. Point of Sales generates sales slips and refund slips, updates the inventory file, sets up accounts receivables record for the customer who charges—all done immediately. List prices may be overridden. Appropriate accounting is done. The inventory file can contain over 1100 records.

ACCOUNTS RECEIVABLES - Complete file maintenance plus selective reporting by field. Receipt of payments by customer or invoice. Monthly billing and aged invoices. Appropriate accounting is automatic. Complete customer file maintenance.

ACCOUNTS PAYABLES - Complete file maintenance plus selective reporting by field. Report of invoices currently payable by user entered date. Ability to put an invoice on hold so that it will not be paid. Checks are printed on a user defined format. Check approval process before checks and Check Register are printed. Ability to enter manual checks. Appropriate accounting is done. Cycle and Net terms can be used.

GENERAL LEDGER - Complete account file maintenance allows all accounts to be user defined. Journal entries are easily made. The General Ledger, Balance Sheet, and Income Statement are printed using user defined accounts and titles. The General Ledger has 4 levels of totals.

PAYROLL - The payroll module pays at frequencies of weekly, bi-weekly, monthly and bi-monthly. It allows pay types such as hourly, salary, commission, commission/draw and salary/commission. It covers unique situations where an employee works at different pay scales in the same period. Handles up to 100 employees. Prints W-2, user defined checks and Form 914. The list goes on and on. Quarterly and yearly totals are maintained on various fields. The payroll module is password protected at program level.

All key fields are validated for correctness as they are entered. Such data as the vendor number, customer number, account number, part number and invoice numbers are checked immediately against their own file.

The minimum hardware needed is 48K, 2 disks, a 132-column printer with either of Apple's interface cards (Parallel or Serial), and Applesoft II ROM card.

The FMS can be purchased at all fine computer stores as a package for \$800.00 or by individual modules for \$200.00 each. Manuals are available for \$10.00 which is refundable when software is purchased.

Dealer inquiries are welcome.

Allow 3 weeks for personal checks to clear. Washington residents add 5.4% sales tax. C.O.D. orders include C.O.D. charges.

DARRELL'S APPLEWARE HOUSE ✓ D51

17838 187th AVE. S.E., RENTON, WA 98055

(206) 220-1224

ELZET 80

Modular Microcomputer-System Using Z 80 CPU

Based on the 'eurocard' standard pc-board size of 100x160mm, roughly 4x6 inches, ELZET 80 offers full expandability up to 40 boards (all cards fully LS-TTL buffered) and up to 1 MByte of semiconductor memory (mapping feature). The 20-slot 64-pole motherboard (KONTRON-Z80-bus) fits into standard 19"-sub-rack. High density packaging is used throughout (16K static RAM on a single board), bus-connections are made using reliable 64-pole male and female connectors.



All boards are designed to be 'stand-alone' and a hardware-solution is used where possible. Some examples: In the minimal version, no monitor program is necessary (it's even possible to write or read memory without CPU-board). Cassette-interface has own Usart and works on interrupt, video-board has own controller, page memory and baud-rate generator. Thus processor activity is kept at a minimum and software remains transparent. Start with the low-cost minimal configuration and build your individual system step-by-step.



Here comes a selection of the boards being available now, and we are just starting !

CPU-board	178,00 DM
Option serial-port	32,90 DM
Option power-on-jump	25,00 DM
Hex I/O with 3 slots, providing all bus-signals	198,00 DM
Console-style plastic box for Hex I/O	19,80 DM
20-slot motherboard (w/Z80 interrupt daisy-chain)	58,00 DM
10 female connectors 64-pole DIN 41612C	88,80 DM
Video-Interface 16x64, upper case, scrolling	399,50 DM
Video-Interface 16x64, u&l case, 4-page memory	680,00 DM
12"-Monitor	296,60 DM
Kansas-City cassette-interface, interrupt-logic, up to 2400 bd, relay for recorder-motor, PLL-input	129,00 DM
4K static RAM 21L02	250,00 DM
8K static RAM TMS4044	659,90 DM
16K static RAM 2114L	998,00 DM
2K static CMOS-RAM 5101L1, accu for 5 days	479,00 DM
32K dynamic RAM 4116*	698,00 DM
4K EPROM 2708, 1 Eprom incl. only*	131,80 DM
8K EPROM 2708, 1 Eprom incl. only*	168,00 DM
ASCII-KeyBoard, 63 Keys	173,00 DM
Frontpanel for big console with cutout	37,50 DM
19" sub-rack, with card-guides, fits into 19"-rack or top of big console below	70,90 DM
19" big console, orange/brown	172,50 DM
12K BASIC-Interpreter	250,00 DM
7K Assembler	250,00 DM
All boards need +5V, other voltages only for the boards marked *	

Starter-System:

CPU, Hex I/O, 1K RAM (on 4K-board), motherboard, PS 3A, handbook and some hardware 598,00 DM

ASCII-System:

CPU, motherboard, 4K RAM, keyboard, video, cassette-interface 4K Eprom w 1K-monitor, handbook and hardw. 1198,00 DM

If you don't like the above configurations, mix your own !

Take a CPU and any other board with a minimum total value of 500,00 DM and get a 10% introductory discount. The more you take with that initial order, the more you save !

Prices are kit-prices, add 25% for assembled and tested boards. All boards are supplied complete with all IC-sockets and male 64-pole-connectors, all have soldering mask and legend printing. Shipping will be charged at cost (f.o.b. Detmold, West Germany). Ask for our free flyer (airmail letters to Europe to be stamped 31c).

Watch for new boards to be introduced in late summer: Double-density floppy-controller with own RAM and 8"-drive, Eprom-programmer, various parallel and serial ports including true RS232 for machine-control applications or printer driving, small low-cost metalized paper 32col. printer...

ELEKTRONIKLADEN

✓E42

W.-Mellies-Str.88 4930 DETMOLD 18 West Germany
Telephone (05232) 8131 Telex 93 14 73 laden d

Shops in Münster (Tel.0251/795125), Amsterdam (NL, Tel. 020/728 543) and Paris (F, Tel. (1) 320-37-02)

your microcomputer can become a development system for only \$190

PRAGMATIC DESIGNS' NEW DBM-1 FEATURES:

- 2048 BYTE EPROM EMULATOR
- EMULATE 2708, 2758, 2716, TMS2716 EPROMS
- S-100 CARD FORMAT
- HARDWARE ADDRESS TRAP

DBM-1 helps you simplify program development for dedicated applications. It is a shared memory card which looks like RAM to an S-100 computer and like EPROM to an applications computer. Programs for the application computer are developed using the S-100 system, the program is loaded into the DBM-1, and the two computers are connected by one or two 24 line dip cables. DBM-1 now looks like the application computer's program memory. During debugging you use the S-100 computer's monitor or debugger to make program changes, so the program can be completely debugged before you place it in EPROMS.

DBM-1's hardware address trap can be set to trigger whenever the application computer reaches a specific point in the program. This trap signal turns on a trap LED and generates signals which can be used to halt or hold program execution.

--then you can develop programs for our new \$125 computer!

CPU-1 IS A COMPLETE CONTROL COMPUTER ON A SINGLE 4.5" X 7" CARD:

- 8085 MICROPROCESSOR WITH 256 BYTES OF RAM
- 22 I/O LINES; SERIAL I/O PORT
- PROGRAMMABLE COUNTER/TIMER
- SOCKETS FOR 1-4K OF EPROM
- USE 2708, 2758, 2716, or TMS2716 EPROMS
- WIRE WRAP AREA FOR SPECIAL FUNCTIONS

The system I/O and control signals are bussed to pads adjoining the wire wrap area, allowing you to easily customize CPU-1 for your application. The card is also laid out with space for you to add an on board power supply.

For larger applications CPU-1A has all the features of CPU-1 expanded to 512 bytes of RAM, 44 I/O lines, and two programmable counter/timers.

PRICES:

DBM-1 \$190 KIT, \$270 ASSEMBLED AND TESTED.
CPU-1 \$125 KIT, \$175 ASSEMBLED AND TESTED.
CPU-1A \$160 KIT, \$210 ASSEMBLED AND TESTED.
24 LINE DIP CABLE FOR USE WITH DBM-1 (1 OR 2 REQUIRED), \$10 EA. CRYSTAL OPTION FOR CPU-1 and 1A, \$10.

Please add \$2.00 for shipping and handling. California residents add 6% sales tax. Phone, VISA and MASTERCARD orders accepted.

ORDER NOW AND START USING DBM-1 AND CPU-1 TO HELP YOU DEVELOP YOUR OWN MICROCOMPUTER BASED SYSTEMS.

pragmatic designs

INC.

711 Stierlin Road
Mountain View, CA 94043
(415) 961-3800

SPACE WAR!!

TRS-80 APPLE II

Real time graphic SPACE WAR like that played on large computers is available for the TRS-80 and the APPLE II in machine language. Two players combat in space while orbiting the sun in individual space ships. Each ship can rotate left or right, accelerate, fire up to five missiles at a time, and enter hyperspace. The program has five levels of play, for beginner to advanced, as follows:

- MODE: (1) BEGINNER (No floating - ships move like tanks)
 (2) INTERMEDIATE (Floating - like real space ships)
 (3) ADVANCED (Adds Sun's gravity)
 (4) NO EDGE BOUNCE (Ships can move off screen edge)
 (5) REVERSE GRAVITY (Sun pushes ships and missiles away)

Available for 16K TRS-80 Level I and Level II or 16K APPLE II. TRS-80 version requires no additional hardware due to keyboard design. APPLE II version requires hi-resolution graphics and two four-button consoles - complete plans for building your own are included.

Please specify TRS-80 or APPLE II.
 Send \$9.95 check or money order for cassette tape and manual.
 All orders are postage paid.

Texas residents add 5% sales tax.
 *TRS-80 is a trademark of Radio Shack, a Tandy Company.
 *APPLE II is a trademark of APPLE Computers.



DEVICE ORIENTED GAMES, INC.

P.O. Box 400727
 Dallas, TX 75240 ✓ D52

\$9.95

Sawyer Software

Quality Business Software
 For PET[™] or TRS-80[™] (level II 16K)

AP1 is a general ledger package with check journal, income statement, balance sheet and checkbook reconciliation routine. Designed for the small business or homeowner. Up to 50 entries and 40 accounts per period.

..... \$25.00

"Accounting Pack I by SAWYER SOFTWARE can be described in one word: Fantastic. Any who has prepared a balance sheet manually will have a slight heart murmur upon using the Accounting Pack. It is amazing that the program fits in 8K. I would say the Accounting Pack is useful and could justify the price of a PET unto itself for any small business." Review in BEST OF PET GAZETTE.

AP2 has all the features of AP1, plus up to 250 entries per period, Menu, formatter for reports and more. Requires at least 16K in PET or TRS-80.

AP2 also utilizes a printer for the reports. Send device number of printer with order.

..... \$45.00

Payroll computes tax information and updates totals for quarterly and yearly reports. Employees can be salaried or hourly and pay periods can be either weekly, bi-weekly, semi-monthly or monthly. Any number of employees (8 per cassette).

..... \$30.00

B.A. allows management to have available to them information for financial planning decisions utilizing ratio and growth analysis.

..... \$30.00

Call or write for your free brochure on all our PET[™] & TRS-80[™] programs.



SAWYER SOFTWARE

201 Worley Rd., Dexter, Mo. 63841 ✓ S91
 (314) 624-7611



Telephone Orders Welcome

Dealer Inquiries are Invited.

MODEL 3400 DUAL DRIVE SUB-SYSTEM

Your system is only as good as the components that make it up. The heart of the 3400 Sub-System is the proven excellence of the Innotronics manufactured Model 410/420 Diskette Drives. They are complemented by a custom enclosure design made up of top quality components and featuring distinctive solid woods such as cherry and walnut for the desk top Model 3400 F.

If your system demands consistently high performance from your 8-inch Floppy Disks, then this equipment is the answer.

Available for the first time a fully integrated design that you can customize to your needs. We believe we manufacture the highest quality Diskette Drives and Integrated Sub-Systems on the market today.

INNOTRONICS

BROOKS ROAD, LINCOLN, MASS. ✓ 122
 01773 TEL. 617-259-0600



3400 Rack Mounted Subsystem



3400F Table or Desk Top Subsystem



PROGRAM LIBRARY

from

CASCADE ENTERPRISES ✓C121 ON CASSETTE TAPE

- * If you use Solost™ or have an 8080 Sol™ System, G2™ Extended Basic is faster and better than others requires (15.5K) \$49.95
- * For our 6800 users G2™ Standard Basic specifically for the S.W.T.P.C.™ 6800 requires (7K) \$34.95
- * Both G2 basics are by Microsoft™
- * We have the following games and entertainment which will run in these machines:

THE GAME TAPES ARE ONLY \$14.95 each

	SOL ™	SORCERER ™	PET ™	TRS-80 ™	APPLE ™	SWTPC ™
G2 BEAT THE HOUSE	*	*	*	*	*	*
G2 CLINIC	*	*	*	*	*	*
G2 OUTWIT	*	*	*	*	*	*
G2 THE MARKET	*	*	*	*	*	*
G2 ADVENTURE	*	*	*	*	*	*
G2 BLOCKADE	*	*	*	*	*	*
G2 OIL TYCOON	*	*	*	*	*	*
G2 PILOT	*	*	*	*	*	*

G2 Beat the House includes Blackjack, Craps, Roulette and Slot Machine. Craps is a very big program. Ours left 3K usable in Level II 16K TRS-80™. Allows a family to play as a group against the computer.

Call us anytime except Sunday (916) 926-5154 or write

As an introductory offer—the first 500 orders get a free 10 minute blank cassette.

CASCADE ENTERPRISES
Box 213
Mount Shasta, CA 96067

Cal. Res. add 6% tax
Bank Cards add shipping & handling \$2.00

☐ M/C ☐ B/A-Visa _____ Expires _____

Signature _____

ALPHA MICRO OWNERS

We Offer Quality Software At
Low Prices For Immediate Delivery:

PAC

- | | | |
|---|----------------------------------|---------|
| 1 | Some Common Basic Programs | \$15.00 |
| 2 | Alpha Micro Utilities | \$25.00 |
| 3 | Statistical Analysis | \$30.00 |
| 4 | Finance Calculator | \$15.00 |
| 5 | PLOT | \$20.00 |
| 6 | Mailing List System | \$35.00 |
| 7 | Deprec. & Amort. | \$15.00 |

Each package includes one floppy disk (with source and object code), and a well documented user's manual.

Write for more information, or see your local dealer.

Pac 1, 3, 4, 5, 7 also available for TRS-80/CBASIC / MBASIC / APPLE / PET / SORCERER.

BUSINESS
SOFTWARE

MICRO-COMPUTER
SYSTEMS CONSULTING



✓ B48

THE BASIC BUSINESS SOFTWARE COMPANY, INC.
POST OFFICE BOX 2032
SALT LAKE CITY
UTAH 84110 (801) 363-1199

Orcomp provides the perfect combination for your TRS-80*

Towers of Hanoi — a fascinating ancient puzzle played on modern man's most sophisticated invention.

Loan Analyzer — compute your own mortgage payments & loan costs.

New-to-Numbers — an entertaining introduction into the world of whole numbers.

Level I Re-Number — for tidying up those Level I programs.

Software *plus* documentation — just the right combination for your TRS-80*. Whether you're a businessman, an educator, a computer professional or hobbyist, Orcomp Data Systems professionals are there to help. We supply a variety of completely documented useful software — ready-to-order or made-to-order, with most of our materials available in both Level I and Level II Basic.

So combine with Orcomp to get the most out of your TRS-80*.

Orcomp


Specializing in Microprocessor Systems

Orcomp Data Systems
P.O. Box 1357
Beaverton, Oregon 97005

And much more... check our bingo number or send 25c today for a complete brochure.

*TRS-80 is a trademark of the Tandy Corporation.

MAD HATTER SOFTWARE



PROGRAM	DESCRIPTION	TRS-80	L1/2	L2	PET	PRICE
GALACTIC BLOCKADE RUNNER	• AN EXCITING SPACE WAR GAME WITH GRAPHICS					\$ 9.95
SCI-FI GAME SAMPLER	• 3 GAMES—LUNAR LANDER—STAR MONSTER—SPACE BATTLE					\$ 7.95
R/T LUNAR LANDER	• A REAL TIME LUNAR LANDER WITH GRAPHICS					\$ 7.95
MICRO-TEXT EDITOR	• FORMAT TEXT—SAVE & LOAD TO TAPE—OUTPUT TO PRINTER					\$ 9.95
OTHELLO III	• A STRATEGY BOARD GAME—PLAY AGAINST COMPUTER OR OTHERS					\$ 7.95
AIR RAID	• A REAL TIME, ARCADE TYPE SHOOTING GAME IN MACH. LANG.					\$ 14.95
MICRO-CHESS	• PLAY CHESS WITH YOUR COMPUTER—VARIOUS LEVELS OF DIFF.					\$ 19.95
BRIDGE CHALLENGER	• DON'T WAIT FOR OTHERS TO PLAY—YOUR COMPUTER'S READY					\$ 14.95
APPLE 21	• BLACKJACK WITH HIRES GRAPHICS					\$ 9.95
STAR WARS/SPACE MAZE	• SCI-FI GAMES FOR THE APPLE					\$ 12.95
RENUMBER	• RENUMBER YOUR BASIC PROGRAMS—RENUMBERS EVERYTHING					\$ 14.95
DISK RENUMBER	• SAME AS ABOVE, BUT ON DISK					\$ 19.95
PILOT 2.0	• THE EDUCATIONAL LANGUAGE, IN MACH. LANG.—INC. EDITOR					\$ 14.95
PILOT 3.0	• THE DISK VERSION OF THE ABOVE					\$ 24.95
APPLE TALKER	• YOUR APPLE SPEAKS! NO NEW HARDWARE REQUIRED					\$ 15.95
APPLE LIS'NER	• SPEECH RECOGNITION THE EASY WAY—GREAT WITH THE TALKER					\$ 19.95
TIC-TAC-TALKER	• TIC-TAC-TOE USING SPEECH SYNTHESIS AND RECOGNITION					\$ 19.95
FORTRAN	• FOR THE TRS-80—SEE MICROSOFT'S ADS					\$325.00
SYSCOP	• MAKE BACKUP TRS-80 SYSTEM TAPES THE EASY WAY					\$ 9.95
ANDROID NIM-2	• GAME OF NIM WITH ANIMATED ROBOTS AND SOUND					\$ 14.95
SNAKE EGG	• A BETTING GAME WITH ANIMATED SNAKES AND SOUND					\$ 14.95
LIFE 2	• 100 GEN. PER MIN. LIFE & BATTI F OF LIFE W/ANIMATION & SOUND					\$ 14.95
DCV-1	• PUT SYSTEM TAPES ON DISK EVEN IF IN SAME MEM AS DOS					\$ 9.95
MUSIC MASTER	• ENTER SHEET MUSIC—THE TRS-80 THEN COMPILES & PLAYS IT					\$ 14.95
DISK MUSIC MASTER	• SAME AS ABOVE BUT ON DISK W/MANY SELECTIONS					\$ 24.95
TRS-80 CP/M	• OPENS UP THE WHOLE WORLD OF CP/M SOFTWARE TO THE TRS-80					\$150.00
PET ASTROLOGY	• DOES ALL THE COMPUTATIONS FOR YOU					\$ 14.95
PERSONAL FINANCE PKG.	• KEEPS TRACK OF CHECKS, BUDGET, COMPUTES INTEREST					\$ 9.95
TRS-80 DISK LIB. "A"	• 9 PROGRAMS ON DISK—INC. BLOC. RUN, OTHELLO ETC.					\$ 39.95
BUSINESS AND APPLICATION SOFTWARE—CALL OR WRITE FOR DETAILS						\$ 94.95
16K MEMORY UPGRADE FOR TRS-80, APPLE & SORCERER COMPUTERS						10/\$ 34.95
C-10 HIGH QUALITY DATA CASSETTES W/SCREW HOUSINGS						10/\$ 10.00
VERBATUM 5-1/2 INCH BLANK DISKETTES						

10% OFF IF YOU ORDER 3 SOFTWARE PACKAGES OR MORE SEND FOR FREE CATALOG—GIVE TYPE OF COMPUTER


AVAILABLE FROM THESE FINE MICRO COMPUTER DEALERS

J&J ELECTRONICS LTD 28 COLLINGTON AVE. BEXHILL-ON-SEA, E. SUSSEX, ENG.	HOBBY WORLD ELECTRONICS 19355 BUSINESS CENTER DR. #6 NORTHridge CA 91324	CAPITOL COMPUTER SYSTEMS 3396 EL CAMINO AVE. SACRAMENTO CA 95821	COMPUTER CABLEVISION, INC. 2617 42ND ST. NW #2 WASHINGTON DC 20007
COMPUTER VILLAGE 931 SW 87TH AVE. MIAMI FL 33174	AUGUST AUTOMATION 28 MILK ST. WESTBORO MA 01581	TRS-80 SOFTWARE EXCHANGE 17 BRIARCLIFF DR. MILFORD NH 03055	KENNEDY SYSTEMS 74 BROAD ST. LYNDONVILLE VT 05851
L. C. SALES 100 HINCHEY AVE. #705 OTTAWA, ONT., CAN. K1Y4L9	THE CPU SHOP 39 PLEASANT ST. CHARLESTOWN MA 02129	OP AMP TECH BOOKS 1033 N. SYCAMORE AVE. LOS ANGELES CA 90038	ADVANCED COMPUTER PRODUCTS 13100 E. EDINGER SANTA ANA CA 92705



TO ORDER BY PHONE OR FOR DEALER INFO—CALL—(617) 682-8131
ADD 75c SHIPPING & HANDLING • MASS. RESIDENTS ADD 5% SALES TAX
MAD HATTER SOFTWARE • 900 K SALEM RD • DRACUT, MA 01826 ✓ M77





FREQUENCY COUNTER KIT

Outstanding Performance

Incredible Price

\$89⁹⁵

CT-50

The CT-50 is a versatile and precision frequency counter which will measure frequencies to 60 mHz and up to 600 mHz with the CT-600 option. Large Scale Integration, CMOS circuitry and solid state display technology have enabled this counter to match performance found in units selling for over three times as much. Low power consumption (typically 300-400 ma) makes the CT-50 ideal for portable battery operation. Features of the CT-50 include: large 8 digit LED display, RF shielded all metal case, easy pushbutton operation, automatic decimal point, fully socketed IC chips and input protection to 50 volts to insure against accidental burnout or overload. And, the best feature of all is the easy assembly. Clear, step by step instructions guide you to a finished unit you can rely on.

Order your today!


CT-50, 60 mHz counter kit
CT-50WT, 60 mHz counter, wired and tested
CT-600, 600 mHz scaler option add

\$89.95
159.95
29.95

CB-1 Color TV calibrator-stabilizer
DP-1 DC probe, general purpose probe
HP-1, High impedance probe non-loading

\$14.95
12.95
15.95

CAR CLOCK



The UN-KIT, only 5 solder connections

Here's a super looking, rugged and accurate auto clock, which is a snap to build and install. Clock movement is completely assembled—you only solder 3 wires and 2 switches, takes about 15 minutes! Display is bright green with automatic brightness control photocell—assures you of a highly readable display, day or night. Comes in a satin finish anodized aluminum case which can be attached 5 different ways using 2 sided tape. Choice of silver, black or gold case (specify).

DC-3 kit, 12 hour format **\$22.95**
DC-3 wired and tested **\$29.95**
110V AC adapter **\$5.95**

Under dash car clock



12/24 hour clock in a beautiful plastic case features: 6 jumbo RED LEDs, high accuracy (1min/mo), easy 3 wire hookup, display blanks with ignition, and super instructions. Optional dimmer automatically adjusts display to ambient light level.

DC-11 clock with mtg. bracket **\$27.95**
DM-1 dimmer adapter **2.50**

PRESCALER



Extend the range of your counter to 600 mHz. Works with any counter. Includes 2 transistor pre-amp to give super sens., typically 20 mv at 150 mHz. Specify +10 or +100 ratio.

PS-1B, 600 mHz prescaler **\$59.95**
PS-1BK, 600 mHz prescaler kit **49.95**

OP-AMP SPECIAL

741 mini dip **12/\$2.00**
B1-FET mini dip, 741 type **10/\$2.00**

VIDEO TERMINAL

A completely self-contained, stand alone video terminal card. Requires only an ASCII keyboard and TV set to become a complete terminal unit. Two units available, common features are: single 5V supply, XTAL controlled sync and baud rates (to 9600), complete computer and keyboard control of cursor, Parity error control and display. Accepts and generates serial ASCII plus parallel keyboard input. The 3216 is 32 char. by 16 lines, 2 pages with memory dump feature. The 6416 is 64 char. by 16 lines, with scrolling, upper and lower case (optional) and has RS-232 and 20ma loop interfaces on board. Kits include sockets and complete documentation.

RE 3216, terminal card **\$149.95**
RE 6416, terminal card **189.95**
Lower Case option, 6416 only **13.95**
Power Supply Kit **14.95**
Video/RF Modulator, VD-1 **6.95**
Assembled, tested units, add **60.00**

CALENDAR ALARM CLOCK

The clock that's got it all. 6-5" LEDs, 12/24 hour, snooze, 24 hour alarm, 4 year calendar, battery backup, and lots more. The super 7001 chip is used. Size: 5x4x2 inches.

Complete kit, less case (not available) **\$34.95**
DC-9

30 Watt 2 mtr PWR AMP

Simple Class C power amp features 8 times power gain. 1 W in for 8 out, 2 in for 15 out, 4 W in for 30 out. Max. output of 35 W, incredible value, complete with all parts, less case and T-R relay.

PA-1, 30 W pwr amp kit **\$22.95**
TR-1, RF sensed T-R relay kit **6.95**

FM MINI MIKE KIT



A super high performance FM wireless mike kit! Transmits a stable signal up to 300 yards with exceptional audio quality by means of its built in electret mike. Kit includes case, mike, on-off switch, antenna, battery and super instructions. This is the finest unit available.

FM-3 kit **\$12.95**
FM-3 wired and tested **16.95**

CLOCK KITS



our Best Seller
your Best Deal

Try your hand at building the finest looking clock on the market. Its satin finish anodized aluminum case looks great anywhere, while six 4" LED digits provide a highly readable display. This is a complete kit, no extras needed, and it only takes 1-2 hours to assemble. Your choice of case colors: silver, gold, bronze, black, blue (specify).

Clock kit, 12/24 hour, DC-5 **\$22.95**
Clock with 10 min. ID timer, 12/24 hour, DC-10 **27.95**
Alarm clock, 12 hour only, DC-8 **24.95**
12V DC car clock, DC-7 **27.95**
For wired and tested clocks add \$10.00 to kit price.

Hard to find PARTS

LINEAR ICs		REGULATORS	
301	\$ 35	78MG	\$1.25
324	1.50	723	.50
380	1.25	309K	.85
380-8	.75	7805	.85
555	.45	78L05	.25
556	.85	7905	1.25
566	1.15	7812	.85
567	1.25	7912	1.25
1458	.50	7815	.85
3900	.50	TTL ICs	
		74500	.35
		7447	.65
		7475	.50
		7490	.50
		74196TI	1.35
		SPECIAL ICs	
	1.25	11C90	13.50
	1.75	10116	1.25
TRANSISTORS		4511	2.00
2N3904 type	10 1.00	5314	2.95
2N3906 type.	10 1.00	5375AB	2.95
PNP 30W Pwr	3 1.00	7001	6.50
PNP 30W Pwr	3 1.00	4059 + N	9.00
2N555	.60	7208	17.95
UJT 2N2646 type	3 2.00	LEDS	
FET MPF102 type	3 2.00	Jumbo red	8 1.00
UJT 2N5179 type	3 2.00	Jumbo green	6 1.00
MRF 238 RF	11.95	Jumbo yellow	6 1.00
SOCKETS		Mini red	8 1.00
8 pin	10 2.00	Micro red	8 1.00
14 pin	10 2.00	BiPolar	.75
16 pin	10 2.00	FERRITE BEADS	
24 pin	4 2.00	With info, specs	15 1.00
28 pin	4 2.00	6 hole balun	5 1.00
40 pin	3 2.00		

Ramsey's famous MINI-KITS

FM WIRELESS MIKE KIT

Transmits up to 300' to any FM broadcast radio, uses any type of mike. Runs on 3 to 9V. Type FM-2 has added sensitive mike preamp stage.

FM-1 kit **\$2.95** FM-2 kit **\$4.95**

VIDEO MODULATOR KIT

Converts any TV to video monitor. Super stable, tunable over ch. 4-6. Runs on 5-15V, accepts std. video signal. Best unit on the market!

Complete kit, VD-1 **\$6.95**

TONE DECODER

A complete tone decoder on a single PC board. Features: 400-5000 Hz adjustable range via 20 turn pot, voltage regulation, 567 IC. Useful for touch-tone decoding, tone burst detection, FSK, etc. Can also be used as a stable tone encoder. Runs on 5 to 12 volts.

Complete kit, TD-1 **\$5.95**

SUPER SLEUTH

A super sensitive amplifier which will pick up a pin drop at 15 feet! Great for monitoring baby's room or as general purpose amplifier. Full 2 W rms output, runs on 6 to 15 volts, uses 8-45 ohm speaker.

Complete kit, BN-9 **\$5.95**

POWER SUPPLY KIT

Complete triple regulated power supply provides variable: 6 to 18 volts at 200 ma and +5V at 1 Amp. Excellent load regulation, good filtering and small size. Less transformers, requires 6.3V @ 1 A and 24 VCT.

Complete kit, PS-3LT **\$6.95**

COLOR ORGAN/MUSIC LIGHTS

See music come alive! 3 different lights flicker with music. One light for lows, one for the mid-range and one for the highs. Each channel individually adjustable, and drives up to 300W. Great for parties, band music, nite clubs and more.

Complete kit, ML-1 **\$7.95**

LED Blinky KIT

A great attention getter which alternately flashes 2 jumbo LEDs. Use for name badges, buttons, warning panel lights, anything! Runs on 3 to 15 volts.

Complete kit, BL-1 **\$2.95**

WHISPER LIGHT KIT

An interesting kit, small mike picks up sounds and converts them to light. The louder the sound the brighter the light. Completely self-contained, includes mike, runs on 110VAC, controls up to 300 watts.

Complete kit, WL-1 **\$6.95**

SIREN KIT

Produces upward and downward wail characteristic of a police siren. 5W peak audio output, runs on 3-15 volts, uses 3-45 ohm speaker.

Complete kit, SM-3 **\$2.95**

ramsey electronics

BOX 4072, ROCHESTER, N.Y. 14610

PHONE ORDERS CALL
(716) 271-6487

TERMS: Satisfaction guaranteed or money refunded. COD, add \$1.50. Minimum order, \$6.00. Orders under \$10.00, add \$7.50. Add 5% for postage insurance handling. Overseas, add 15%. NY residents, add 7% tax.

CBASIC BUSINESS SOFTWARE for MICROCOMPUTERS

Osborne & Associates is publishing its business systems in book form. These systems represent five years of development and testing by O&A programmers. Each book includes source listings, program and system documentation and user's manual.

What systems are we selling?

* PAYROLL WITH
COST ACCOUNTING

* ACCOUNTS PAYABLE AND
ACCOUNTS RECEIVABLE

* GENERAL LEDGER



The books sell for \$15.00 each. All three are available right now with listings in Wang BASIC. New editions of each book, with listings in CBASIC-2, will be published during the summer of 1979. These new editions will run on many floppy disk-based microcomputer systems.

Don't know programming? Don't want to key in thousands of lines of source code? We have over 130 dealers who will sell you the CBASIC-2 programs on ready-to-run floppy disks. Contact us for the name of your nearest dealer.

CBASIC or Wang BASIC won't work? Take a look at the list of consultants who have converted O&A programs to run on many popular systems, and are waiting to hear from you.

CONSULTANTS...

COMPUTER STORES...

SOFTWARE HOUSES GOOD NEWS...

*****CP/M CBASIC*****

You can be a dealer for the magnetic surface of O&A's CBASIC-2 software, which runs under CP/M on many floppy disk-based computer systems. We will sell the CP/M magnetic surface only to consultants, computer stores and software houses. Osborne & Associates prefers to write and sell books, not customize the programs or answer the end user's questions. The disk for each book sells for \$250.00. Once you buy the floppy disk you can copy it, resell it, change it or use it. We place no restriction on the magnetic surface; we copyright only the printed word in our books. CBASIC-2 Payroll is available now. The magnetic surfaces for all three systems are scheduled to be available in the first half of 1979; call or write for the exact availability of each system.

ALPHA MICRO:

Peter Burke
THE BASIC BUSINESS SOFTWARE CO., INC.
P.O. Box 2032
Salt Lake City, Utah 74110
(801) 363-1199

APPLE II:

Jimmy Walter
A.C.E. COMPUTER SYSTEMS
2449 North Westshore
Tampa, Florida 33607
(813) 872-2798
David McFarling
SMALL BUSINESS COMPUTER SYSTEMS
4140 Greenwood
Lincoln, Nebraska 68504
(402) 467-1878

CROMEMCO:

Richard French
THE NETWORK COMPUTER SYSTEMS
495 Third Avenue #8
San Francisco, California 94118
(415) 668-7777

I.B.M. 5110:

DATA WORKS
35 East Wacker Drive, Suite 1843
Chicago, Illinois 60601
(312) 726-2572

MICROPOLIS, PROCESSOR TECHNOLOGY, NORTHSTAR, VECTOR GRAPHIC, MICROMATION

David Price
DAP SYSTEMS
3901 Victoria Lane
Midlothian, Virginia 23113

NORTHSTAR BASIC:

Issac Bornstein
COMPUTER SERVICES OF ENCINITAS
341 Willowspring Drive
Encinitas, California 92024
(714) 436-2486

MICROSOFT disk BASIC:

Dan Kindred
GNAT COMPUTERS
7895 Conroy Court
San Diego, California 92111
(714) 560-0433

OHIO SCIENTIFIC:

William E. Stanfill
2232 Edinburgh Drive
Montgomery, Alabama 36116
(205) 279-0495

TRS-80:

Don French
APPLIED DATA CORPORATION
P.O. Box 16020
Fort Worth, Texas 76133
(817) 738-0251

Irwin Taranto
TARANTO & ASSOCIATES
P.O. Box 6073
San Rafael, California 94903
(415) 472-1415

WANG BASIC ON FLOPPY DISK:

R.A. Burel
DECOR, INC.
P.O. Box 111
Fairfield, Alabama 35213
(205) 785-8000

OSBORNE & ASSOCIATES, INC.
P.O. Box 2036, Dept. D14
Berkeley, CA 94702 USA
(415) 548-2805 TWX 910-366-7277

Name: _____

Address: _____

City: _____

State: _____ Zip: _____

Phone: _____

☐ I am an end user interested in running CBASIC programs on disk. Please notify me of the closest dealer for:

- ☐ CBASIC Payroll with Cost Accounting
- ☐ CBASIC Accounts Payable/Receivable
- ☐ CBASIC General Ledger

☐ I am a dealer interested in purchasing CBASIC programs for resale. Please send description and order information for:

Title	Price	Quantity	Amount
09-8 Payroll with Cost Accounting in Wang BASIC	\$15.00		
13-6 Accounts Payable/Receivable in Wang BASIC	\$15.00		
20-9 General Ledger in Wang BASIC	\$15.00		

Calif. residents add 6% sales tax.

S.F. BART residents add 6-1/2 % sales tax.

Shipping (Shipping for large orders to be arranged)

- ☐ All foreign orders \$4.00 per book for airmail
- ☐ \$0.45 per book 4th class in the U.S. (allow 3-4 weeks)
- ☐ \$0.75 per book UPS in the U.S. (allow 10 days)
- ☐ \$1.50 per book special rush shipment by air in the U.S.

California residents tax

Shipping

Total Amount Enclosed

Please send the following information:

- ☐ Becoming an O&A dealer
- ☐ School discounts
- ☐ List of foreign distributors

- ☐ Other O&A publications
- ☐ I am interested in the CBASIC business books.
- ☐ Please send me description and order information.

Payment in advance must be enclosed for purchases of up to \$70.00. Invoicing U.S. purchases over \$70.00 available upon approval of your account. All foreign orders must be prepaid in U.S. dollars drawn on a U.S. bank.

YOU ASKED FOR IT WE'VE GOT IT!

In the most versatile variety of Software yet!
We've got software for the TRS-80, I & II
Apple II, Commodore Pet, and Exidy Sorcerer
in both cassette and disk.

Affordable programs to suit your small business,
home and educational needs.

Call us today for a free catalogue, or better yet, stop
and visit us at the Simplicity Booth at the New York
PCC Convention. Dealer inquiries invited.

**SIMPLEXITY
SOFTWARE
SYSTEMS**

✓S86

P.O. BOX 501 HIRAM, OHIO 44234



HOBBY WORLD® CALL TOLL FREE: (800) 423-5387
CA, HI, AK: (213) 886-9200

✓ H25 **TRS-80 SOFTWARE
CASSETTES**

Cat No.	Description	Price
1093	SARGON CHESS, II	19.95
1041	STAR TREK, II	14.95
1036	SCIFI GAME SAMPLER, I II	5.95
1042	TAROT I II	5.95
1179	CRIBBAGE I II	9.95
1192	REAL TIME LUNAR LANDER II	7.95
1195	BRIDGE CHALLENGER II	14.95
1186	AIR RAID I II	14.95
1187	PILOT I II	14.95
1047	OTHELLO I II	5.95
1043	SMALL BUSINESS BOOKKEEPING I II	14.95
1051	DAILY BIORHYTHM PROGRAM I II	5.95
1049	MICRO TEXT EDITOR I II	9.95
1038	INVENTORY MODULAR I II	19.95
1153	EDIT-80, text editor II (32K)	39.95

TRS-80 LEVEL III BASIC \$42

As advertised in March
Interface. Loads on top
of level II, turns your
TRS-80 into a powerful
system. Solves loading
problems, cures keyboard
"bounce". Software cas-
sette, has the power of
a hardware modification!
Guaranteed satisfaction!
Cat No. 1332

VERBATIM 5 1/4" DISKETTES

\$27 box of 10

Cat No.	Type	Use
1147	Soft sector	TRS-80, Apple
1148	Hard, 10 hole	North Star
1149	Hard, 16 hole	Micropolis

8" DISKS

• Single density
• IBM Compatible
\$40 box of 10

Cat No.	Type	Use
1145	32 sector holes,	1 index hole
1146	IBM 32, 3740, 3540,	3770, 3790

ANADIX PRINTER Model DP-8000 \$999

Connects easily to most popular computers including TRS-80. 3 basis ASCII compatible interface configurations are provided. 80 columns, 112 cps. 84 lines per min, bi directional printing. Out-of-paper detector, uses standard low-cost papers. 96 character set, 9x7 dot mat-

rix characters. Original plus up to 3 copies. Skip-over-perforation control, double width printing. 8 program-mable vertical tab positions. Excellent readability. Superior to other printers costing three times as much.

TRS-80 FORTRAN \$340 PLUS

As advertised! Supplied on 2 mini-diskettes, and requires a 32K system with one disk drive. Written by Microsoft, designer of Level II and Level III. Includes Fortran compiler, Z-80 macro assembler, text editor, and linking loader. Adds speed and versatility.

**BUY 7,
GET 1 FREE!**
*Buy 7 of one type,
get the eighth of
that type free!

Order by type no.

1702A	\$1.50
2708	10.00
4116	11.00
21102-250	1.20
21102-450	1.00
21102-650	.65
2114-450	8.00
5203Q	1.25

California Computer Systems MEMORY ADD-ON 16K \$65

For APPLE, TRS-80, EXIDY

Everything you need!
Installs in minutes, no
special tools, no solder-
ing! 250 nsec.
Cat No. 1156

TRS-80 ELECTRIC PENCIL

Character oriented word processing system. Produce mailing lists, business forms, large numbers of original correspondence, camera ready copy for printing...all on your TRS-80. No carriage returns or hyphenations, line formatting is done by the Electric Pencil! Also features right margin justifying, page numbering,

and tilting, and many combinations of line length, page length, etc. For TRS-80 level I or 2, 16k, and virtually any printer.

\$95

SHUGART SA-400 MINIFLOPPY DRIVE \$295

Hard and soft sectoring, single density, 35 track. Requires power supply.
Cat No. 1154

DATA CASSETTES 10 for \$17

Highest quality, leader-less! With protective plastic case.
Cat No. 1142

FREE CATALOG!

New, hot off the press!
Top quality, low cost factory fresh IC's, leds, readouts, semis, computer add-ons, boards, test equipment, books, software, PC aids, and more!

Pay by check, COD, Visa, or Mastercharge. Order by phone or mail. Please include phone no. USA add \$1.50 for shipping/handling, or \$2.50 for air. Foreign add \$2.00 for surface, \$5.00 for air. COD's add 85c. All items guaranteed satisfaction for 120 days!

19355 BUSINESS CTR DR. - 6K6 NORTHRIDGE, CA 91324

WAMECO

W22

THE COMPLETE PC BOARD HOUSE EVERYTHING FOR THE S-100 BUSS

- * **FPB-1** FRONT PANEL BOARD
Hex Displays, IMSAI Replaceable\$54.95
- * **FDC-1** FLOPPY DISC CONTROLLER BOARD
Controls up to 8 Discs\$45.00
- * **MEM-1A** 8K BYTE 2102 RAM Board\$31.95
- * **MEM-2** 16K BYTE 2114 RAM Board\$31.95
- * **CPU-1** 8080A CPU Board
With Vector Interrupt\$31.95
- * **EPM-1** 4K BYTE 1702A EPROM\$29.95
- * **EPM-2** 16K or 32K BYTE EPROM
2708 or 2716 interchangeable\$30.00,
- * **QMB-9** 9 SLOT MOTHER BOARD
Terminated\$35.00
- * **QMB-12** 12 SLOT MOTHER BOARD
Terminated\$40.00
- * **RTC** REALTIME CLOCK
Programmable Interrupts\$27.95

FUTURE PRODUCTS: 80 CHARACTER VIDEO BOARD,
IO BOARD WITH CASSETTE INTERFACE.

DEALER INQUIRIES INVITED, UNIVERSITY DISCOUNTS AVAILABLE
AT YOUR LOCAL DEALER




WAMECO INC. 111 GLENN WAY #8, BELMONT, CA 94002 (415) 592-6141



CALIFORNIA COMPUTER SYSTEMS

16K RAM BOARD. Fully buffered addressable in 4K blocks. IEEE standard for bank addressing 2114's PCBD\$26.95
Kit 450\$259.95
PT-1 PROTO BOARD. Over 2,600 holes 4" regulators. All S-100 buss functions labeled, gold fingers. PCBD\$29.95
PT-2 PROTO BOARD. Similar to PT-1 except set-up to handle solder tail sockets. PCBD\$29.95



FORMERLY CYBERCOM/SOLID STATE MUSIC.

PB-1 2708 & 2716 Programming Board with provisions for 4K or 8K EPROM. No external supplies require textool sockets. Kit\$124.95
CB-1 8080 Processor Board. 2K of PROM 256 BYTE RAM power on/rest Vector Jump Parallel port with status Kit\$119.00 PCBD\$30.95
MB-6B Basic 8KX8 ram uses 2102 type rams, S-100 buss. Kit 450 NSEC\$139.95 PCBD\$26.95
MB-7 16KX8, Static RAM uses P410 Protection, fully buffered Kit\$299.95
MB-8A 2708 EROM Board, S-100, 8KX8 or 16KX8 kit without PROMS \$75.00 PCBD \$28.95
MB-9 4KX8 RAM/PROM Board uses 2112 RAMS or 82S129 PROM kit without RAMS or PROMS \$72.00
IO-2 S-100 8 bit parallel /IO port, 3/4 of boards is for kludging. Kit\$46.00 PCBD\$26.95
IO-4 Two serial I/O ports with full handshaking 20/60 ma current loop: Two parallel I/O ports. Kit\$130.00 PCBD\$26.95
VB-1B 64 x 16 video board, upper lower case Greek, composite and parallel video with software, S-100. Kit\$125.00 PCBD\$26.95
Altair Compatible Mother Board, 11 x 11 1/2 x 1/4". Board only\$39.95. With 15 connectors.....\$94.95
Extended Board full size. Board only\$ 9.49
With connector\$13.45
SP-1 Synthesizer Board S-100
PCBD\$42.95 KIT\$135.95



WAMECO INC.

FDC-1 FLOPPY CONTROLLER BOARD will drive shugart, pertek, remic 5" & 8" drives up to 8 drives, on board PROM with power boot up, will operate with CPM (not included). PCBD\$42.95
FPB-1 Front Panel. IMSAI size, hex displays. Byte, or instruction single step. PCBD\$47.50
MEM-1 8KX8 fully buffered, S-100, uses 2102 type rams. PCBD\$25.95
QM-12 MOTHER BOARD, 13 slot, terminated, S-100 board only\$34.95
CPU-1 8080A Processor board S-100 with 8 level vector interrupt PCBD\$26.95
RTC-1 Realtime clock board. Two independent interrupts. Software programmable. PCBD\$23.95
EPM-1 1702A 4K Eprom card PCBD\$25.95
EPM-2 2708/2716 16K/32K EPROM CARD PCBD\$25.95
QM-9 MOTHER BOARD, Short Version of QM-12. 9 Slots PCBD\$30.95
MEM-2 16K x 8 Fully Buffered 2114 Board PCBD\$26.95

8080A\$9.95	2114 (450 NS) low pwr. \$7.25
82122.49	2114 (250 NS) low pwr. 7.99
82144.49	2102A-2L1.50
82243.49	2102A-4L1.20
87089.49	1702A-64.50
5101-1P6.90	1702A INTEL(not prime)4.00
5101-8P8.40	41168/89.95



✓M39 (415) 592-1800
P. O. Box 424 • San Carlos, California 94070

Please send for IC, Xistor
and Computer parts list

JUNE SPECIAL SALE ON PREPAID ORDERS

(charge cards not included on this offer)
5% OFF ON WAMECO PCBD's
MIKOS PARTS ASSORTMENT
WITH BOARDS AND
CCS COMPUTER PRODUCTS
(sam not included)

MIKOS PARTS ASSORTMENT WITH WAMECO AND CYBERCOM PCBDs

MEM-2 with MIKOS #7 16K ram
with L2114 450 NSEC\$235.95
MEM-2 with MIKOS #13 16K ram
with L2114 250 NSEC\$269.95
MEM-1 with MIKOS #1 450 NSEC 8K
RAM\$119.95
CPU-1 with MIKOS #2 8080A CPU\$94.95
MEM-1 with MIKOS #3 250 NSEC 8K
RAM\$144.95
QM-12 with MIKOS #4 13 slot mother
board\$89.95
RTC-1 with MIKOS #5 real time clock\$54.95
VB-1B with MIKOS #6 video board less
molex connectors\$99.95
EMP-1 with MIKOS #10 4K 1702 less
EPROMS\$49.95
EPM-2 with MIKOS #11 16-32K EPROMS
less EPROMS\$59.95
QM-9 with MIKOS #12 9 slot mother
board\$79.95
FPB-1 with MIKOS #14 all parts
for front panel\$134.95

MIKOS PARTS ASSORTMENTS ARE ALL FACTORY PRIME
PARTS. KITS INCLUDE ALL PARTS LISTED AS REQUIRED
FOR THE COMPLETE KIT LESS PARTS LISTED. ALL SOCKETS
INCLUDED.

VISA or MASTERCHARGE. Send account number, interbank
number, expiration date and sign your order. Approx. postage
will be added. Check or money order will be sent post paid in
U.S. If you are not a regular customer, please use charge,
cashier's check or postal money order. Otherwise there will
be a two-week delay for checks to clear. Calif. residents add
6% tax. Money back 30 day guarantee. We cannot accept re-
turned IC's that have been soldered to. Prices subject to
change without notice. \$10 minimum order. \$1.50 service charge
on orders less than \$10.00.

10-DAY FREE TRIAL

Send for our
FREE Catalog



NCE COMPUMART'S PET WAREHOUSE

We have more PETs than anyone, call for quick delivery.

**AS LOW
AS \$595**

PET ACCESSORIES

4K - Keyboard C	\$ 595
8K - Keyboard C	\$ 795
16K - Keyboard B	\$ 995
16K - Keyboard N	\$ 995
32K - Keyboard C	\$1195
32K - Keyboard B	\$1195
32K - Keyboard N	\$1195

C — calculator keyboard (only version with tape deck)
B — large business keyboard without graphics symbols
N — large keyboard with graphics symbols

Commodore Dual Floppy Disk Drive	\$1295.00
New! PET Terminal Package	\$69.00
Second Cassette — from Commodore	\$95.00
Commodore PET Service Kit	\$30.00
Beeper - Tells when tape is loaded	\$24.95
Petunia - Play music from PET	\$29.95
Video Buffer - Attach another CRT	\$29.95
Combo - Petunia and Video Buffer	\$49.95
New Serial Printer Interface for PET	\$79.95
Integral Data Printer w/new interface	\$878.95
PET - Compatible Selectric in Desk	\$895.00
TTY KSR-33 Screen Printer for PET	\$395.00
Originate/Answerback Modem for PET	\$320.00
Bi-directional RS-232 Interface	\$280.00
Betsi 4-slot S-100 Motherboard	\$160.00
S-100 PET Interface was \$289.00 SALE	\$99.00

SAVE

UP TO \$100 ON READER/PUNCH

Our reconditioned paper tape Reader/Punches are reliable performers and now for a limited time they're all on sale! The Serial Reader/Punch which was \$950 is sale priced at \$850. The Reader/Punch alone is marked down from \$175 to \$157. prices with interface follow:

Interface Model	Interface Added	Interface and Power	Interface, Power and Enclosure
Serial	\$472	\$616	\$850
Parallel	\$355	\$598	\$675

EXIDY SORCERER

for \$895

- 2.46 Processor
- Full size ASCII keyboard
- User definable characters
- Up to 32K on-board RAM
- Interchangeable ROM PACs
- 30 x 64 display
- Resident 4K Monitor ROM
- Dual Cassette I/O
- Serial and Parallel I/O
- Complete Operators Manual
- Only \$895

Top value in our catalog, simply add a monitor and tape decks to complete the system. Can be used as a terminal. Later ROM PACs will offer 2.80 Assembly Language, APL, PILOT, Word Processing and a DOS PAC for disk based FORTRAN and COBOL. What a system for \$895!

Sorcerer 8K \$895
Sorcerer 16K \$1150
Sorcerer 32K \$1395
16K Expansion \$299

apple II

\$200 FREE ACCESSORIES

Buy a 48K Apple II, mention this ad and take \$200 in accessories free (if ordered together). This offer is good for \$150 on 32K and \$100 on 16K Apple II's. Now you can enjoy more of the best for less.

16K Apple II — \$1195 (take \$100 in free accessories)
32K Apple II — \$1345 (take \$150 in free accessories)
48K Apple II — \$1495 (take \$200 in free accessories)

Apple II Accessories

Disk and Controller	\$595
Second Disk Drive	\$495
Parallel Printer Card	\$180
Communications Card	\$225
Hi-Speed Serial Card	\$195
Firmware Card	\$200
Hobby/Proto Card	\$24
Microverter RF Mod.	\$35
Sanyo M2544 Recorder	\$55



Hazeltine 1400

**IN STOCK NOW Only
\$699.00**

Now a 5th Generation
in Terminals:
Immediate Delivery

Hazeltine 1500 full of features	\$999
Hazeltine 1510 with buffer logic	\$1149
Hazeltine 1520 with printer interface	\$1499

call or write for more information

SPECIAL OF THE MONTH

NEW PET TERMINAL OPTION

- FREE**
- Get a PET & a terminal in one
 - Data rates to 2400 baud
 - Full Duplex operation
 - Auto line wrap-around
 - With or without auto line-feed

Buy any model PET & get a free NCE PET terminal option, normally \$69. Now your PET can handle two different jobs. You can use the PET for a powerful BASIC computer or you can load our machine-code program to use the PET as a dumb terminal (not both at once). Please specify this option with order.

For those of you who already have a PET, you may order an NCE PET Terminal option separately for \$69.

<ul style="list-style-type: none"> • 28 Double Function keypad including up to 24 Special functions • Easy to use, 4-digit hex led display • 6M x 8 hardware compatibility • 5028 Speed system • 4K byte ROM resident monitor and operating system • Single 5 volt power • 18 bytes of 2514 static RAM or sockets provided for immediate expansion to 4K bytes • Enhanced software 	<p>SYM-1 From Synertek</p>	<ul style="list-style-type: none"> • Standard interfaces available • Audio Cassette Recorder Interface with Remote Control • Full Duplex Edna Teletype Interface • System Expansion bus interface • TV Camcorder Board Interface • CRT Compatible Interface • 50 I/O Lines in the basic system
--	---------------------------------------	---

\$269.00

NOW IN STOCK — SYM BASIC \$159

Datel/Selectric Table-top Terminals



SALE! \$395 AS IS \$295

SUPER SALE

List \$279.95

\$189.95

S-100 MPA

S-100 MPA gives your PET complete control of the S-100 bus (even DMA). Get an assembled unit at kit price.

- Michigan residents add 4% sales tax • Add 4% shipping and handling for all domestic orders
- Foreign orders (except Canada) add 10% additional handling (U.S. currency only) • P.O.'s accepted from D & B rated companies — shipment contingent upon receipt of signed purchase order
- Phones open from 9:00 a.m. to 7:00 p.m. EST Monday-Friday, 10:00 a.m. to 5:00 p.m. Saturdays

TI
PROGRAMMER
Hexadecimal, octal, decimal calculator converter
Reg. \$59.95 **NOW \$49.95**

CENTRONICS 779 PRINTERS

Selectable for 10 or 16.5 char/in. 80 or 132 char/8" line. Print speeds up to 110 cps. Parallel interface with handshake.

CENTRONICS 779-1
with friction feed

\$1035

CENTRONICS 779-2
with tractor feed

\$1140



CAT COUPLER

New 300 baud Originate/Answerback Acoustic Coupler. Looks good, works great and sale priced at **\$189.**

KIM-1

The original fully expandable single board computer

SALE Assembled **\$169.95**

with power supply **\$214.95**

EXPAND YOUR KIM SYSTEM:
KIMSI

KIM to S-100 Board

Assembled **\$169**

Connector Set **15**

KIM 4

Expansion board **89.95**

MICRO TECH. POWER SUPPLY

Assembled **\$34.95**

KIM ENCLOSURE

Give your KIM a professional appearance. No alterations required. sturdy Kydex 100 Black **\$23.50**

SALE \$225
SANYO MONITOR
VM4209 9" quality monitor **\$169**



NCE/CompuMart, Inc.

1250 North Main Street, Department KB69
P.O. Box 8610 Ann Arbor, Michigan 48107

10 DAY RETURN PRIVILEGE

(313) 994-3200

Just say charge it! Which card?



• Open accounts invited — call for credit application • Most items in stock for immediate shipment — call for delivery quotation • Sorry, no C.O.D.'s • All prices subject to change without notice • In the Ann Arbor area? Retail store open 11:00 a.m. to 7:00 p.m. Tuesday-Friday, 10:00 a.m. to 5:00 p.m. Saturdays (Closed Sunday and Monday)
SEND FOR FREE TERMINAL FLYER

for memory, the word is "CHOICE"




No matter what system you choose — S-100 based, Radio Shack-80, H8, Digital Group, or even the Intel/National single board computer system — we have the memory you want. You may choose from a variety of configurations and densities, at a variety of price levels.

We also give you the choice of buying your memory in **unkit** form (sockets, bypass caps pre-soldered in place); **assembled and tested**; or qualified under our **CSC (Certified System Component)** high-reliability program (200 hour burn-in, immediate replacement in event of failure within one year of invoice date, and more).

But there are some areas where we don't give you a choice. You can't choose between 2 and 4 MHz versions of our high density memories, because we only make the 4 MHz type. And you can't choose between low and high power versions — all our memories are designed for very low power operation. An example: our 32K bank select board's guaranteed *maximum* current spec is 3.5A, which is considerably lower than most other *typical* current specs.

We even give you a choice of non-memory products that offer exceptional value and performance, such as our I/O board, motherboards, and active terminator.

How do you get ahold of a CompuKit™ product? Well, there's a choice there too. Our products are available from many fine computer stores, or directly from us.



Name	Storage	Buss	Design	Speed	Configuration	Unkit	Assm	CSC
Econoram II	8K X 8	S-100	static	2 MHz	2-4K	\$149	\$164	N/A
Econoram IV	16K X 8	S-100	static	4 MHz	1-16K	\$295	\$329	\$429
Econoram VI	12K X 8	H8	static	2 MHz	1-8K, 1-4K	\$200	\$270	N/A
Econoram VII	24K X 8	S-100	static	4 MHz	2-4K, 2-8K	\$445	\$485	\$605
Econoram IX	32K X 8	Dig Grp	static	4 MHz	2-4K, 1-8K, 1-16K	\$649	N/A	N/A
Econoram X	32K X 8	S-100	static	4 MHz	2-8K, 1-16K	\$599	\$649	\$789
Econoram XI	32K X 8	SBC	static	4 MHz	2-8K, 1-16K	N/A	N/A	\$1050

BANK SELECT MEMORIES (for Alpha Micro Systems, Marinchip, etc.)

Econoram XII-16	16K X 8	S-100	static	4 MHz	2 ind. banks*	\$369	\$419	\$519
Econoram XII-24	24K X 8	S-100	static	4 MHz	2 ind. banks*	\$479	\$539	\$649
Econoram XIII	32K X 8	S-100	static	4 MHz	2 ind. banks**	\$629	\$699	\$849

*addressable on 8K boundaries

**addressable on 16K boundaries

Econoram is a trade mark of Godbout Electronics.

ALSO AVAILABLE: 16K MEMORY EXPANSION CHIP SET \$109 (3/\$320)

For Radio Shack-80, Apple, Sorcerer machines. 250 ns chips for 4 MHz operation, DIP shunts, 1 year limited warranty. With easy-to-follow instructions.

ACTIVE TERMINATOR KIT \$34.50

Our much imitated design plugs into any S-100 motherboard to reduce noise, ringing, overshoot, and other buss-related problems.

DUAL CHANNEL/DUAL FUNCTION S-100 I/O BOARD

\$189 unkit, \$249 assm

This one does things the others can only dream about. Two independently addressable serial ports with full RS232C current loop (20 mA) and TTL signals on both ports, crystal controlled Baud rates to 19.2 KBaud, hardware UARTS, compatible with 2 or 4 MHz systems, low power consumption, and a whole lot more... we'll be glad to give you more info, just write.

2102 MEMORY SPECIAL 10/\$9.90

That's only 99¢ each for very low power, static 1K RAMs suitable for use with any 2 MHz system. Price only good on orders of 10 or more.

16 pin lo-profile sockets also available at the special price of 12/\$2.00.

TERMS: Allow 5% shipping, excess refunded. Cal res add tax. VISA®/Mastercharge® call our 24 hour order desk at (415) 562-0636. COD OK with street address for UPS (UPS COD charge applies). Prices good through cover month of magazine. Orders under \$15 add \$1 handling.

CompuKit™
BOX 2355, OAKLAND AIRPORT, CA 94614

1791 MOS LSI DUAL DENSITY DISC CONTROLLER CHIP \$59

Just in. Prime Western Digital parts, with pinout and data.

HEATH H8 BARE BOARD MEMORY SPECIAL — \$35!

Don't need the full 12K of our standard H8 memory? We now offer the board, mounting bracket, edge connector, and schematic for only \$35. Populate it with a few support chips and readily available, low cost 2102s to build your memory up to a full 12K whenever your budget permits.

11 SLOT MOTHERBOARD UNKIT

With 11 edge connectors pre-soldered in place for easy assembly, as well as integral active terminator circuitry. Dimensions: 8.5" X 11" **\$90**

18 SLOT MOTHERBOARD UNKIT

Same as above, but 18 slot version with 18 edge connectors. Dimensions: 8.5" X 16.7" **\$124**

from **GODBOUT**
ELECTRONICS

✓ G4

FREE FLYER: We'll be glad to tell you more than the space of this ad allows. Just send your name and address, we'll take care of the rest. If you're in a hurry, enclose 41c in stamps and we'll send it out first class.

WALLEN

ELECTRONICS CO. INC. Tel: (617) 588-6440-6441
108 SAWTELL AVE., BROCKTON, MASS. 02402

TEST EQUIPMENT
CONNECTORS-WIRE
ELECT. COMPONENTS



POWER SUPPLIES

5 volts @ 8 amps + 12 volts, 2 amps + 6 volts @ 75 MA. Ideal for Micro and Mini computers. These units have been removed from equipment and rechecked out and guaranteed. Power supply has a 3-wire line cord and fused. Spec: 10-1/2" x 5-1/2" x 4-1/2". Shipping weight 16 lbs.


REGULATED
COMPUTER

37.50
2 FOR 70.00

Wire Wrap **BOARDS**

These boards are pre-wired and removed from equipment. Easy to unwrap for setting up your own board. Contains mostly 14-pin IC sockets with individual pin connections. Each board has VCC and ground planes.

Smaller board measures 6 1/2" x 6" and has 40 to 50 sockets. PRICE \$11.00 ea. 2/\$20.00
Larger board measures 13 1/2" x 6" and has 75 to 100 sockets. PRICE \$17.50 ea. 2/\$33.00



CRYSTAL OSCILLATORS

Vectron type CO-231T
crystal freq. 4.9152, MHZ
w/tuning option for
accuracy of .0001 %
1-1/2" x 1-1/2". R.F.E.



13.95

ROTRON Whisper Fans

115V, AC, 7 watts, 50-60 Hz.
Guaranteed.
4-1/2" x 4-1/2" x 1-1/2". Re-
moved from equipment,
checked and guaranteed.

6.95

TEKTRONIX 535A OSCILLOSCOPE

Used equipment. Freq. DC to
15 Mhz. These scopes come
w/B, D, K or L plug-in units.
Checked out and operating.

\$199

W/1
PLUG-IN

(Shipped freight collect)

DUAL TRACE PLUG-INS

Model CA available.
Checked out and operating.

\$100

LINE CORDS

LINE CORDS— with ground
wire. 6-ft. length, 16/3 type SJ

75¢

TRANSFORMERS ISOLATION/STEP- DOWN TYPE

Primary: 230/115V, 50/60 CPS,
Secondary: VA output 250 V.

13.95 EACH

SEMI-CONDUCTOR COOLERS (heat sinks)

ALUMINUM BLANKS

NOT
DRILLED



1.75

EACH

5" x 4 3/4" x 1 1/4"

ANODIZED ALUMINUM FOR TO-3 or TO-66 TRANSISTORS

Chassis
Mounting



20¢ EA

1 7/8" x 1 1/8"

For TO-5 series transistors (gear type)



\$15



SOLD IN PKG. OF 100s

INCADESCENT READOUT ASSEMBLY

Readouts assembled of the 710
series modules. Character 1" high.
w/lamps. Type No. 344. By Dialco.



2.75 each

DIABLO SYSTEM Disk Drive



SERIES 40 MODEL 43

100 tracks per inch, total
capacity of 50 megabits,
w/Model 429 power supply,
sector counter, 24 sectors, 1
fixed disc, 1 removable disc,
average access time 38 ms,
RPM: 2400, dimensions: 10
5/16" high, fits in standard rack,
equipped with full extension
slides.

\$2495

Minimum order \$25.00. Items offered subject to prior sale, FOB, Brockton,
Mass. Money order or check w/order. Shipping and handling add 5 %.
Shipments by parcel post or UPS. No CODs. Mass. residents add 5 % sales tax.

DIODES/ZENERS			
QTY.			
1N914	100v	10mA	.05
1N4005	600v	1A	.08
1N4007	1000v	1A	.15
1N4148	75v	10mA	.05
1N4733	5.1v	1 W Zener	.25
1N753A	6.2v	500 mW Zener	.25
1N758A	10v	"	.25
1N759A	12v	"	.25
1N5243	13v	"	.25
1N5244B	14v	"	.25
1N5245B	15v	"	.25

SOCKETS/BRIDGES			
QTY.			
8-pin	pcb	.20 ww	.35
14-pin	pcb	.20 ww	.40
16-pin	pcb	.20 ww	.40
18-pin	pcb	.25 ww	.95
20-pin	pcb	.35 ww	.95
22-pin	pcb	.35 ww	.95
24-pin	pcb	.35 ww	.95
28-pin	pcb	.45 ww	1.25
40-pin	pcb	.50 ww	1.25
Molex pins	.01	To-3 Sockets	.25
2 Amp Bridge	100-prv		.95
25 Amp Bridge	200-prv		1.50

TRANSISTORS, LEDS, etc.			
QTY.			
2N2222	(2N2222 Plastic .10)		.15
2N2222A			.19
2N2907A	PNP		.19
2N3906	PNP (Plastic Unmarked)		.10
2N3904	NPN (Plastic Unmarked)		.10
2N3054	NPN		.45
2N3055	NPN 15A 60v		.60
T1P125	PNP Darlington		1.95
LED Green,	Red, Clear, Yellow		.15
D.L.747	7 seg 5/8" High com-anode		1.95
MAN72	7 seg com-anode (Red)		1.25
MAN3610	7 seg com-anode (Orange)		1.25
MAN82A	7 seg com-anode (Yellow)		1.25
MAN74	7 seg com-cathode (Red)		1.50
FND359	7 seg com-cathode (Red)		1.25

9000 SERIES			
QTY.		QTY.	
9301	.85	9322	.65
9309	.35	9601	.20
9316	1.10	9602	.45

MICRO'S, RAMS, CPU'S, E-PROMS			
QTY.		QTY.	
8T13	1.50	2107B-4	4.95
8T23	1.50	2114	9.50
8T24	2.00	2513	6.25
8T97	1.00	2708	10.50
74S188	3.00	2716 D.S.	34.00
1488	1.25	2716 (5v)	59.00
1489	1.25	2758 (5v)	23.95
1702A	4.50	3242	10.50
AM 9050	4.00	4116	11.50
		6800	13.95
MM 5314	3.00	6850	7.95
MM 5316	3.50	8080	7.50
MM 5387	3.50	8212	2.75
MM 5369	2.95	8214	4.95
TR 1602B	3.95	8216	3.50
UPD 414	4.95	8224	3.25
Z 80 A	22.50	8228	6.00
Z 80	17.50	8251	7.50
Z 80 PIO	10.50	8253	18.50
2102	1.45	8255	8.50
2102L	1.75	TMS 4044	9.95

C MOS	
QTY.	
4000	.15
4001	.15
4002	.20
4004	3.95
4006	.95
4007	.20
4008	.75
4009	.35
4010	.35
4011	.20
4012	.20
4013	.40
4014	.75
4015	.75
4016	.35
4017	.75
4018	.75
4019	.35
4020	.85
4021	.75
4022	.75
4023	.20
4024	.75
4025	.20
4026	1.95
4027	.35
4028	.75
4029	1.15
4030	.30
4033	1.50
4034	2.45
4035	.75
4037	1.80
4040	.75
4041	.69
4042	.65
4043	.50
4044	.65
4046	1.25
4048	.95
4049	.45
4050	.45
4052	.75
4053	.75
4066	.55
4069/74C04	.35
4071	.25
4081	.30
4082	.30
4507	.95
4511	.95
4512	1.10
4515	2.95
4519	.85
4522	1.10
4526	.95
4528	1.10
4529	.95
MC 14409	14.50
MC 14419	4.85
74C151	1.50

LINEARS, REGULATORS, etc.			
QTY.		QTY.	
MCT2	.95	LM323K	5.95
8038	3.95	LM324	1.25
LM201	.75	LM339	.75
LM301	.45	7805 (340T5)	.95
LM308	.65	LM340T12	.95
LM309H	.65	LM340T15	.95
LM309K (340K-5)	1.50	LM340T18	.95
LM310	.85	LM340T24	.95
LM311D	.75	LM340K12	1.25
LM318	1.75	LM340K15	1.25
LM320H6	.79	LM340K18	1.25
LM320H15	.79	LM340K24	1.25
LM320H24	.79	LM373	2.95
7905 (LM320K5)	1.65	LM377	3.95
LM320K12	1.65	78L05	.75
LM320K24	1.65	78L12	.75
LM320T5	1.65	78L15	.75
LM320T12	1.65	78M05	.75
LM320T15	1.65		
		LM380 (8-14 Pin)	1.19
		LM709 (8-14 Pin)	.35
		LM711	.45
		LM723	.40
		LM725	2.50
		LM739	1.50
		LM741 (8-14)	.35
		LM747	1.10
		LM1307	1.25
		LM1458	.65
		LM3900	.50
		LM75451	.65
		NE555	.45
		NE556	.85
		NE565	.95
		NE566	1.25
		NE567	.95

- TTL -			
QTY.		QTY.	
7400	.10	7482	.75
7401	.15	7483	.75
7402	.15	7485	.55
7403	.15	7486	.25
7404	.10	7489	1.05
7405	.25	7490	.45
7406	.25	7491	.70
7407	.55	7492	.45
7408	.15	7493	.35
7409	.15	7494	.75
7410	.15	7495	.60
7411	.25	7496	.80
7412	.25	74100	1.15
7413	.25	74107	.25
7414	.75	74121	.35
7416	.25	74122	.55
7417	.40	74123	.35
7420	.15	74125	.45
7426	.25	74126	.35
7427	.25	74132	.75
7430	.15	74141	.90
7432	.20	74150	.85
7437	.20	74151	.65
7438	.20	74153	.75
7440	.20	74154	.95
7441	1.15	74156	.70
7442	.45	74157	.65
7443	.45	74161	.55
7444	.45	74163	.85
7445	.65	74164	.60
7446	.70	74165	1.10
7447	.70	74166	1.25
7448	.50	74175	.80
7450	.25	74176	.85
7451	.25	74180	.55
7453	.20	74181	2.25
7454	.25	74182	.75
7460	.40	74190	1.25
7470	.45	74191	1.25
7472	.40	74192	.75
7473	.25	74193	.85
7474	.30	74194	.95
7475	.35	74195	.95
7476	.40	74196	.95
7480	.55	74197	.95
7481	.75	74198	1.45
		74221	1.00
		74367	.95
		75108A	.35
		75491	.50
		75492	.50
		74H00	.15
		74H01	.20
		74H04	.20
		74H05	.20
		74H10	.35
		74H10	.35
		74H11	.25
		74H15	.45
		74H20	.25
		74H21	.25
		74H22	.40
		74H30	.20
		74H40	.25
		74H50	.25
		74H51	.25
		74H52	.15
		74H53	.25
		74H55	.20
		74H72	.35
		74H74	.35
		74H101	.75
		74H103	.55
		74H106	.95
		74L00	.25
		74L02	.20
		74L03	.25
		74L04	.30
		74L10	.20
		74L20	.35
		74L30	.45
		74L47	1.95
		74L51	.45
		74L55	.65
		74L72	.45
		74L73	.40
		74L74	.45
		74L75	.85
		74L93	.55
		74L123	.85
		74LS00	.30
		74LS01	.30
		74LS02	.35
		74LS03	.25
		74LS04	.25
		74LS05	.35
		74LS08	.35
		74LS10	.35
		74LS11	.35
		74LS20	.25
		74LS40	.20
		74LS50	.20
		74LS51	.25
		74LS64	.15
		74S74	.35
		74S112	.60
		74S114	.65
		74S133	.40
		74S140	.55
		74S151	.30
		74S153	.35
		74S157	.75
		74S158	.30
		74S194	1.05
		74S257 (8123)	1.05
		8131	2.75

✓19

INTEGRATED CIRCUITS UNLIMITED

7889 Clairemont Mesa Blvd., San Diego, California 92111

24 Hour Toll Free Phone 1-800-854-2211

(714) 278-4394 California Residents 1-800-542-6239

CABLE ADDRESS ICUSD

CUSTOMER NAME _____

STREET ADDRESS _____

CITY _____ STATE _____ ZIP _____

PHONE _____ CHARGE CARD # _____ AE Visa BA MC _____ EXP. DATE _____

C.O.D. _____ WILL CALL _____ UPS _____ POST _____ NET 10th OF THE MONTH _____ PO # _____

ALL ORDERS SHIPPED PREPAID - NO MINIMUM - COD ORDERS ACCEPTED - ALL ORDERS SHIPPED SAME DAY
OPEN ACCOUNTS INVITED - California Residents add 6% Sales Tax. PRICES SUBJECT TO CHANGE WITHOUT NOTICE.

We accept American Express / Visa / BankAmericard / Master Charge

SPECIAL DISCOUNT

Total Order	Deduc
\$35-\$99	10%
\$100-\$300	15%
\$301-\$1000	20%

HICKOK LX303 \$74.95

HICKOK LX303

\$74.95*



• 5%, 3 1/2 digit 19 Range DVM. 1/2" LCD displays runs 200 hrs on 1 battery. 10 Meg Ohm Input. 1 yr. guarantee, made in U.S.A., test leads included.

Available Accessories

RC-3 115V AC Adapter \$7.50
CC-3 Deluxe Padded Vinyl Carrying Case \$7.50
VP-10 X10 DCV Probe Adapter/ Protector 10Kv \$14.95
VP-40 40Kv DC Probe \$35.00
CS-1 10 AMP Current Shunt \$14.95

*FREE

Just for Asking.
FREE BATTERY with your meter.



\$318.
MS-15
MINISCOPE



With Rechargeable Batteries & Charger Unit

- 15 megahertz bandwidth.
- External and internal trigger.
- Time base — 1 microsec. to 0.5 Sec/div. 21 settings, $\pm 3\%$.
- Battery or line operation.
- Automatic & line sync modes.
- Power consumption < 15 watts.
- Vertical Gain — 0.1 to 50 V/div. 12 settings $\pm 3\%$.
- Viewing area 11" x 10".
- Case size 2 7/8" x 6 1/4" x 7 5/8" D, 3 pounds.
- Parts & Labor guaranteed 1 year.
- 10 to 1, 10 meg probe.
- Leather carrying case.



PROBE 1¢ with the purchase of SCOPE and the MENTION of this MAGAZINE

\$27.
\$45.

• MS-215 Dual Trace Version of MS-15 \$435.

SALE S-100 BUS EDGE CONNECTORS SALE

\$100-WWG 50/100 Cont. 125 cts 3	\$100-STG 50/100 Cont. 125 cts
LEVEL WIRE WRAP 025 sq posts on 250 spaced rows GOLD plated	DIP SOLDER TAIL on 250 spaced rows for VECTOR and MASI mother boards GOLD plated
1-4 5-9 10-24	1-4 5-9 10-24
\$4.00 \$3.75 \$3.50	\$3.50 \$3.25 \$3.00
RG81C 50/100 Cont. 125 cts DIP SOLDER TAIL on 140 spaced rows for ALTAIR motherboards GOLD plated	R681-3 50/100 Cont. 125 cts PIERCED SOLDER EYELET tails GOLD
1-4 5-9 10-24	1-4 5-9 10-24
\$5.00 \$4.75 \$4.50	\$4.00 \$3.75 \$3.50


Other Popular Edge Connectors

R644-D 22/44 Cont. 156 cts	R644-3 22/44 Cont. 156 cts WIRE PIERCED SOLDER EYELET tails
GOLD plated	GOLD
1-4 5-9 10-24	1-4 5-9 10-24
\$3.00 \$2.75 \$2.50	\$4.00 \$3.75 \$3.50

CG-1 MSAI Style Card Guides \$5/1.00
ATTN: OEM's and Dealers, many other connectors available call or quotation

SD EXPANDORAM

The Ultimate S-100 Memory



The EXPANDORAM is available in versions from 16K up to 64K, so for a minimum investment you can have a memory system that will grow with your needs. This is a dynamic memory with the invisible on-board refresh, and IT WORKS!

- Bank Selectable
- Phantom
- Power 8VDC, ± 16 VDC, 5 Watts
- Lowest Cost Per Bit
- Uses Popular 4116 RAMS
- PC Board is doubled solder masked and has silk-screen parts layout.

- Extensive documentation clearly written
- Complete Kit includes all Sockets for 64K
- Memory access time: 375ns, Cycle time: 500ns.
- No wait states required.
- 16K boundaries and Protection via Dip Switches
- Designed to work with Z-80, 8080, 8085 CPU's.

EXPANDO 64 KIT (4116)

16K	\$245.00
32K	\$310.00
48K	\$375.00
64K	\$440.00

- Kit includes 12 tantalum capacitors for +5, +12, -12 buses and insulated mounting spacers
- Wiring side shown. Component side bare epoxy glass with white markings for component locations
- C10 epoxy glass board with 2 ounce copper solder plated and .038 diameter holes for leads
- Solder mask with solder windows on etched circuits to avoid accidental short circuits
- Mounts 11 receptacles with 100 contacts (12 rows) on 125 centers with 250 row spacing. Vector part number R681-2 or mounts 10 receptacles plus interconnections to smaller mother board for expansion
- Includes etched circuits and instructions for option of active pull-up or floating terminations
- Large buses: +5V and GND (10 AMP); ± 12 V or 16V (7 AMP). Current ratings are per MIL-STD-275 with 10°C rise
- Fits in Vector pak enclosures
- Fits in MSAI 8080 microcomputer as expander board




Price: \$29.50



Plugboards


8800V	8801-1
Universal Microcomputer/processor plugboard, use with S-100 bus. Complete with heat sink & hardware 5 1/2" x 10" x 1/16"	Same as 8800V except plain; less power buses & heat sink
1-4 5-9 10-24	1-4 5-9 10-24
\$19.95 \$17.95 \$15.95	\$14.95 \$13.45 \$11.95



3677 9.6" x 4.5" \$10.90
3677-2 6.5" x 4.5" \$9.74



3662 6.5" x 4.5" \$7.65
3662-2 9.6" x 4.5" \$11.45



CARD EXTENDER
Card Extender has 100 contacts 50 per side on .125 centers. Attached connector is compatible with S-100 Bus Systems. \$25.83
3690 6.5" 22/44 pin .156 cts. Extenders \$13.17

1/16" Vector BOARD

.042 dia holes on .01 spacing for IC's

Phenolic	SIZE	PRICE
PART NO.		
64P44XXXP	4.5x6.5"	\$1.56 \$1.40
169P44XXXP	4.5x17"	\$3.69 \$3.32

Epoxy Glass	SIZE	PRICE
PART NO.		
64P44	4.5x6.5"	\$1.79 \$1.61
84P44	4.5x8.5"	\$2.21 \$1.99
169P44	4.5x17"	\$4.52 \$4.07
169P84	8.5x17"	\$8.03 \$7.23

TRS-80 MEMORY EXPANSION KITS

4116's RAMS (16Kx1 200ns)


8 for \$69.00

2708 8K 450 ns

EPROM FACTORY PRIME \$12.00 EA.
25 + Call For Price

14 & 16 PIN GOLD 3 LEVEL WIRE WRAP SOCKETS

14 - G3 100 for \$30.00
16-G3 100 for \$30.00
50 of each for \$32.00
Sockets are End & Side stackable, closed entry



IM-10A List \$89.00
SPECIAL \$56.95 with tube
Perfectly balanced fluorescent lighting with precision magnifier lens. Tough thermoplastic shade. Easy lens removal. New wire clip design permits easy installation and removal of fluorescent tube. Comes with plastic shield to protect tube from soiling and damage.
Colors: Gray, Black, and Chocolate Brown. Comes with one 22 watt T-9 Circine fluorescent tube, 3 diopter lens.

ORDER TOLL FREE
1-800-423-5633
except CA., AK., HI., Call (213) 894-8171

WRAP POST for .042 dia. holes (all boards on this page) T44/C pkg. 100 ... \$2.34 T44/M pkg. 1000 \$14.35 A-13 hand installing tool \$2.94



P21 **PRIORITY ONE ELECTRONICS**
16723K Roscoe Blvd. Sepulveda, CA 91343
Terms: VISA, MC, BAC, check, Money Order, C.O.D., U.S. Funds Only. CA residents add 6% sales tax. Minimum order \$10.00. Orders less than \$75.00 include 10% shipping and handling; excess refunded. Just in case please include your phone no.
Good Thru May 1979
phone orders welcome (213) 894-8171 OEM and Institutional inquiries invited

24 PIN DIP PLUGS WITH COVERS
3 / \$1.00
40 / \$10.00

HICKOK LX303 \$74.95

HICKOK LX303 \$74.95

HICKOK LX303 \$74.95

7400 TTL			
SN7400N	16	SN7470N	29
SN7401N	18	SN7471N	35
SN7402N	18	SN7472N	35
SN7403N	18	SN7473N	35
SN7404N	18	SN7474N	35
SN7405N	20	SN7475N	49
SN7406N	29	SN7476N	35
SN7407N	29	SN7477N	35
SN7408N	20	SN7478N	5.00
SN7409N	20	SN7479N	5.00
SN7410N	18	SN7480N	5.00
SN7411N	25	SN7481N	5.00
SN7412N	25	SN7482N	99
SN7413N	40	SN7483N	59
SN7414N	10	SN7484N	59
SN7415N	25	SN7485N	99
SN7416N	25	SN7486N	99
SN7417N	25	SN7487N	99
SN7420N	20	SN7488N	99
SN7421N	29	SN7489N	99
SN7422N	39	SN7490N	45
SN7423N	25	SN7491N	59
SN7424N	29	SN7492N	43
SN7425N	29	SN7493N	43
SN7426N	29	SN7494N	65
SN7427N	25	SN7495N	65
SN7428N	39	SN7496N	65
SN7429N	20	SN7497N	3.00
SN7430N	25	SN74100N	89
SN7431N	25	SN74107N	35
SN7432N	25	SN74108N	59
SN7433N	25	SN74116N	95
SN7434N	25	SN74121N	35
SN7435N	25	SN74122N	39
SN7436N	25	SN74123N	49
SN7437N	25	SN74125N	49
SN7438N	25	SN74126N	49
SN7439N	25	SN74130N	75
SN7440N	25	SN74136N	75
SN7441N	89	SN74141N	79
SN7442N	49	SN74142N	95
SN7443N	75	SN74144N	2.95
SN7444N	75	SN74145N	79
SN7445N	75	SN74146N	95
SN7446N	69	SN74148N	129
SN7447N	59	SN74150N	89
SN7448N	79	SN74151N	59
SN7449N	20	SN74152N	59
SN7450N	20	SN74153N	59
SN7451N	20	SN74154N	99
SN7452N	20	SN74155N	79
SN7453N	20	SN74156N	79
SN7454N	20	SN74157N	65
SN7455N	20	SN74158N	65
SN7456N	20	SN74159N	65
SN7457N	20	SN74160N	85
SN7458N	20	SN74161N	85
SN7459N	20	SN74162N	95
SN7460N	20	SN74163N	95
		SN74164N	65
		SN74165N	85
		SN74166N	95
		SN74167N	150
		SN74168N	150
		SN74169N	125
		SN74170N	79
		SN74171N	79
		SN74172N	60
		SN74173N	125
		SN74174N	45
		SN74175N	79
		SN74176N	79
		SN74177N	79
		SN74178N	95
		SN74179N	95
		SN74180N	95
		SN74181N	95
		SN74182N	95
		SN74183N	95
		SN74184N	95
		SN74185N	95
		SN74186N	95
		SN74187N	95
		SN74188N	95
		SN74189N	125
		SN74191N	125
		SN74192N	79
		SN74193N	79
		SN74194N	85
		SN74195N	85
		SN74196N	85
		SN74197N	85
		SN74198N	145
		SN74199N	140
		SN74200N	95
		SN74201N	175
		SN74202N	175
		SN74203N	225
		SN74204N	395
		SN74205N	395
		SN74206N	395
		SN74207N	395
		SN74208N	395
		SN74209N	395
		SN74210N	395
		SN74211N	395
		SN74212N	395
		SN74213N	395
		SN74214N	395
		SN74215N	395
		SN74216N	395
		SN74217N	395
		SN74218N	395
		SN74219N	395
		SN74220N	395
		SN74221N	395
		SN74222N	395
		SN74223N	395
		SN74224N	395
		SN74225N	395
		SN74226N	395
		SN74227N	395
		SN74228N	395
		SN74229N	395
		SN74230N	395
		SN74231N	395
		SN74232N	395
		SN74233N	395
		SN74234N	395
		SN74235N	395
		SN74236N	395
		SN74237N	395
		SN74238N	395
		SN74239N	395
		SN74240N	395
		SN74241N	395
		SN74242N	395
		SN74243N	395
		SN74244N	395
		SN74245N	395
		SN74246N	395
		SN74247N	395
		SN74248N	395
		SN74249N	395
		SN74250N	395
		SN74251N	395
		SN74252N	395
		SN74253N	395
		SN74254N	395
		SN74255N	395
		SN74256N	395
		SN74257N	395
		SN74258N	395
		SN74259N	395
		SN74260N	395
		SN74261N	395
		SN74262N	395
		SN74263N	395
		SN74264N	395
		SN74265N	395
		SN74266N	395
		SN74267N	395
		SN74268N	395
		SN74269N	395
		SN74270N	395
		SN74271N	395
		SN74272N	395
		SN74273N	395
		SN74274N	395
		SN74275N	395
		SN74276N	395
		SN74277N	395
		SN74278N	395
		SN74279N	395
		SN74280N	395
		SN74281N	395
		SN74282N	395
		SN74283N	395
		SN74284N	395
		SN74285N	395
		SN74286N	395
		SN74287N	395
		SN74288N	395
		SN74289N	395
		SN74290N	395
		SN74291N	395
		SN74292N	395
		SN74293N	395
		SN74294N	395
		SN74295N	395
		SN74296N	395
		SN74297N	395
		SN74298N	395
		SN74299N	395
		SN74300N	395
		SN74301N	395
		SN74302N	395
		SN74303N	395
		SN74304N	395
		SN74305N	395
		SN74306N	395
		SN74307N	395
		SN74308N	395
		SN74309N	395
		SN74310N	395
		SN74311N	395
		SN74312N	395
		SN74313N	395
		SN74314N	395
		SN74315N	395
		SN74316N	395
		SN74317N	395
		SN74318N	395
		SN74319N	395
		SN74320N	395
		SN74321N	395
		SN74322N	395
		SN74323N	395
		SN74324N	395
		SN74325N	395
		SN74326N	395
		SN74327N	395
		SN74328N	395
		SN74329N	395
		SN74330N	395
		SN74331N	395
		SN74332N	395
		SN74333N	395
		SN74334N	395
		SN74335N	395
		SN74336N	395
		SN74337N	395
		SN74338N	395
		SN74339N	395
		SN74340N	395
		SN74341N	395
		SN74342N	395
		SN74343N	395
		SN74344N	395
		SN74345N	395
		SN74346N	395
		SN74347N	395
		SN74348N	395
		SN74349N	395
		SN74350N	395
		SN74351N	395
		SN74352N	395
		SN74353N	395
		SN74354N	395
		SN74355N	395
		SN74356N	395
		SN74357N	395
		SN74358N	395
		SN74359N	395
		SN74360N	395
		SN74361N	395
		SN74362N	395
		SN74363N	395
		SN74364N	395
		SN74365N	395
		SN74366N	395
		SN74367N	395
		SN74368N	395
		SN74369N	395
		SN74370N	395
		SN74371N	395
		SN74372N	395
		SN74373N	395
		SN74374N	395
		SN74375N	395
		SN74376N	395
		SN74377N	395
		SN74378N	395
		SN74379N	395
		SN74380N	395
		SN74381N	395
		SN74382N	395
		SN74383N	395
		SN74384N	395
		SN74385N	395
		SN74386N	395
		SN74387N	395
		SN74388N	395
		SN74389N	395
		SN74390N	395
		SN74391N	395
		SN74392N	395
		SN74393N	395
		SN74394N	395
		SN74395N	395
		SN74396N	395
		SN74397N	395
		SN74398N	395
		SN74399N	395
		SN74400N	395
		SN74401N	395
		SN74402N	395
		SN74403N	395
		SN74404N	395
		SN74405N	395
		SN74406N	395
		SN74407N	395
		SN74408N	395
		SN74409N	395
		SN74410N	395
		SN74411N	395
		SN74412N	395
		SN74413N	395
		SN74414N	395
		SN74415N	395
		SN74416N	395
		SN74417N	395
		SN74418N	395
		SN74419N	395
		SN74420N	395
		SN74421N	395
		SN74422N	395
		SN74423N	395
		SN74424N	395
		SN74425N	395
		SN74426N	395
		SN74427N	395
		SN74428N	395
		SN74429N	395
		SN74430N	395
		SN74431N	395
		SN74432N	395
		SN74433N	395
		SN74434N	395
		SN74435N	395
		SN74436N	395
		SN74437N	395
		SN74438N	395
		SN74439N	395
		SN74440N	395
		SN74441N	395
		SN74442N	395
		SN74443N	395
		SN74444N	395
		SN74445N	395
		SN74446N	395
		SN74447N	395
		SN74448N	395
		SN74449N	395
		SN74450N	395
		SN74451N	395
		SN74452N	395
		SN74453N	395
		SN74454N	395
		SN74455N	395
		SN74456N	395
		SN74457N	395
		SN74458N	395
		SN74459N	395
		SN74460N	395
		SN74461N	395
		SN74462N	395
		SN74463N	395
		SN74464N	395
		SN74465N	395
		SN74466N	395
		SN74467N	395
		SN74468N	395
		SN74469N	395
		SN74470N	395
		SN74471N	395
		SN74472N	395
		SN74473N	395
		SN74474N	395
		SN74475N	395
		SN74476N	395

C/MOS			
CD4000	23	CD4028	89
CD4001	23	CD4029	1.19
CD4002	25	CD4030	49
CD4003	1.19	CD4031	49
CD4004	49	CD4032	49
CD4005	49	CD4033	99
CD4006	49	CD4034	1.19
CD4007	49	CD4035	1.19
CD4008	49	CD4036	1.19
CD4009	49	CD4037	1.19
CD4010	23	CD4038	1.19
CD4011	25	CD4039	1.19
CD4012	25	CD4040	99
CD4013	39	CD4041	99
CD4014	49	CD4042	99
CD4015	1.19	CD4043	89
CD4016	49	CD4044	1.79
CD4017	49	CD4045	1.79
CD4018	49	CD4046	1.79
CD4019	49	CD4047	1.79
CD4020	1.19	CD4048	1.35
CD4021	1.19	CD4049	49
CD4022	1.19	CD4050	49
CD4023	23	CD4051	1.19
CD4024	79	CD4052	1.19
CD4025	79	CD4053	2.95
CD4026	2.25	CD4054	1.35
CD4027	69	CD4055	1.35
		CD4056	1.35
		CD4057	1.35
		CD4058	1.35
		CD4059	1.35
		CD4060	1.35
		CD4061	1.35
		CD4062	1.35
		CD4063	1.35
		CD4064	1.35
		CD4065	1.35
		CD4066	1.35
		CD4067	1.35
		CD4068	1.35
		CD4069	1.35
		CD4070	1.35
		CD4071	1.35
		CD4072	1.35
		CD4073	1.35
		CD4074	1.35
		CD4075	1.35
		CD4076	1.35
		CD4077	1.35
		CD4078	1.35
		CD4079	1.35
		CD4080	1.35
		CD4081	1.35
		CD4082	1.35
		CD4083	1.35
		CD4084	1.35
		CD4085	1.35
		CD4086	1.35
		CD4087	1.35
		CD4088	1.35
		CD4089	1.35
		CD4090	1.35
		CD4091	1.35
		CD4092	1.35
		CD4093	1.35
		CD4094	1.35
		CD4095	1.35
		CD4096	1.35
		CD4097	1.35
		CD4098	1.35
		CD4099	1.35
		CD4100	1.35
		CD4101	1.35
		CD4102	1.35
		CD4103	1.35
		CD4104	1.35
		CD4105	1.35
		CD4106	1.35
		CD4107	1.35
		CD4108	1.35
		CD4109	1.35
		CD4110	1.35
		CD4111	1.35
		CD4112	1.35
		CD4113	1.35
		CD4114	1.35
		CD4115	1.35
		CD4116	1.35
		CD4117	1.35
		CD4118	1.35
		CD4119	1.35
		CD4120	1.35
		CD4121	1.35
		CD4122	1.35
		CD4123	1.35
		CD4124	1.35
		CD4125	1.35
		CD4126	1.35
		CD4127	1.35
		CD4128	1.35
		CD4129	1.35
		CD4130	1.35
		CD4131	1.35
		CD4132	1.35
		CD4133	1.35
		CD4134	1.35
		CD4135	1.35
		CD4136	1.35
		CD4137	1.35
		CD4138	1.35
		CD4139	1.35
		CD4140	1.35
		CD4141	1.35
		CD4142	1.35
		CD4143	1.35
		CD4144	1.35
		CD4145	1.35
		CD4146	1.35
		CD4147	1.35
		CD4148	1.35
		CD4149	1.35
		CD4150	1.35
		CD4151	1.35
		CD4152	1.35
		CD4153	1.35
		CD4154	1.35
		CD4155	1.35
		CD4156	1.35
		CD4157	1.35
		CD4158	1.35
		CD4159	1.35
		CD4160	1.35
		CD4161	1.35
		CD4162	1.35
		CD4163	1.35
		CD4164	1.35
		CD4165	1.35
		CD4166	1.35
		CD4167	1.35
		CD4168	1.35
		CD4169	1.35
		CD4170	1.35
		CD4171	1.35
		CD4172	1.35
		CD4173	1.35
		CD4174	1.35
		CD4175	1.35
		CD4176	1.35
		CD4177	1.35
		CD4178	1.35
		CD4179	1.35
		CD4180	1.35
		CD4181	1.35
		CD4182	1.35
		CD4183	1.35
		CD4184	1.35
		CD4185	1.35
		CD4186	1.35
		CD4187	1.35
		CD4188	1.35
		CD4189	1.35
		CD4190	1.35
		CD4191	1.35
		CD4192	1.35
		CD4193	1.35
		CD4194	1.35
		CD4195	1.35
		CD4196	1.35
		CD4197	1.35
		CD4198	1.35
		CD4199	1.35
		CD4200	1.35
		CD4201	1.35
		CD4202	1.35
		CD4203	1.35
		CD4204	1.35
		CD4205	1.35
		CD4206	1.35
		CD4207	1.35
		CD4208	1.35
		CD4209	1.35
		CD4210	1.35
		CD4211	1.35
		CD4212	1.35
		CD4213	1.35
		CD4214	1.35
		CD4215	1.35
		CD4216	1.35
		CD4217	1.35
		CD4218	1.35
		CD4219	1.35
		CD4220	1.35
		CD4221	1.35
		CD4222	1.35
		CD4223	1.35
		CD4224	1.35
		CD4225	1.35
		CD4226	1.35
		CD4227	1.35
		CD4228	1.35
		CD4229	1.35
		CD4230	1.35
		CD4231	1.35
		CD4232	1.35
		CD4233	1.35
		CD4234	1.35
		CD4235	1.35
		CD4236	1.35
		CD4237	1.35
		CD4238	1.35
		CD4239	1.35
		CD4240	1.35
		CD4241	1.35
		CD4242	1.35
		CD4243	1.35
		CD4244	1.35
		CD4245	1.35
		CD4246	1.35
		CD4247	1.35
		CD4248	1.35
		CD4249	1.35
		CD4250	1.35
		CD4251	1.35
		CD4252	1.35
		CD4253	1.35
		CD4254	1.35
		CD4255	1.35
		CD4256	1.35
		CD4257	1.35
		CD4258	1.35
		CD4259	1.35
		CD4260	1.35
		CD4261	1.35
		CD4262	1.35
		CD4263	1.35
		CD4264	1.35
		CD4265	1.35
		CD4266	1.35
		CD4267	1.35
		CD4268	1.35
		CD4269	1.35
		CD4270	1.35
		CD4271	1.35
		CD4272	1.35
		CD4273	1.35
		CD4274	1.35
		CD4275	1.35
		CD4276	1.35
		CD4277	1.35
		CD4278	1.35
		CD4279	1.35
		CD4280	1.35
		CD4281	1.35
		CD4282	1.35
		CD4283	1.35
		CD4284	1.35
		CD4285	1.35
		CD4286	1.35
		CD4287	1.35
		CD4288	1.35
		CD4289	1.35
		CD4290	1.35
		CD4291	1.35
		CD4292	1.35
		CD4293	1.35
		CD4294	1.35
		CD4295	1.35
		CD4296	1.35
		CD4297	1.35
		CD4298	1.35
		CD4299	1.35
		CD4300	1.35
		CD4301	1.35
		CD4302	1.35
		CD4303	1.35
		CD4304	1.35
		CD4305	1.35
		CD4306	1.35
		CD4307	1.35
		CD4308	1.35
		CD4309	1.35
		CD4310	1.35
		CD4311	1.35
		CD4312	1.35
		CD4313	1.35
		CD4314	1.35
		CD4315	1.35
		CD4316	1.35
		CD4317	1.35
		CD4318	1.35
		CD4319	1.35
		CD4320	1.35
		CD4321	1.35
		CD4322	1.35
		CD4323	1.35
		CD4324	1.35
		CD4325	1.35
		CD4326	1.35
		CD4327	1.35
		CD4328	1.35
		CD4329	1.35
		CD4330	1.35
		CD4331	1.35
		CD4332	1.35
		CD4333	1.35
		CD4334	1.35
		CD4335	1.35
		CD4336	1.35
		CD4337	1.35
		CD4338	1.35
		CD4339	1.35
		CD4340	1.35
		CD4341	1.35
		CD4342	1.35
		CD4343	1.35
		CD4344	1.35
		CD4345	1.35
		CD4346	1.35
		CD4347	1.35
		CD4348	1.35
		CD4349	1.35
		CD4350	1.35
		CD4351	1.35
		CD4352	1.35
		CD4353	1.35
		CD4354	1.35
		CD4355	1.35
		CD4356	1.35
		CD4357	1.35
		CD4358	1.35
		CD4359	1.35
		CD4360	1.35
		CD4361	1.35
		CD4362	1.35
		CD4363	1.35
		CD4364	1.35
		CD4365	1.35
		CD4366	1.35
		CD4367	1.35
		CD4368	1.35
		CD4369	1.35
		CD4370	1.35
		CD4371	1.35
		CD4372	1.35
		CD4373	1.35
		CD4374	1.35
		CD4375	1.35
		CD4376	1.35
		CD4377	1.35
		CD4378	1.35
		CD4379	1.35
		CD4380	1.35
		CD4381	1.35
		CD4382	1.35
		CD4383	1.35
		CD4384	1.35
		CD4385	1.35
		CD4386	1.35
		CD4387	1.35
		CD4388	1.35
		CD4389	1.35
		CD4390	1.35
		CD4391	1.35
		CD4392	1.35
		CD4393	1.35
		CD4394	1.35
		CD4395	1.35
		CD4396	1.35
		CD4397	1.35
		CD4398	1.35
		CD4399	1.35
		CD4400	1.35
		CD4401	1.35
		CD4402	1.35
		CD4403	1.35
		CD4404	1.35
		CD4405	1.35
		CD4406	1.35
		CD4407	1.35
		CD4408	1.35
		CD4409	1.35
		CD4410	1.35
		CD4411	1.35
		CD4412	1.35
		CD4413	1.35
		CD4414	1.35
		CD4415	1.35
		CD4416	1.35
		CD4417	1.35
		CD4418	1.35

74C00	39	74C00	74C163	2.49	
74C02	39		74C164	2.49	
74C04	39	74C85	2.49	74C163	2.49
74C08	39	74C90	1.95	74C162	2.49
74C10	39	74C93	1.95	74C163	2.49
74C14	1.95	74C95	1.95	74C165	2.49
39	74C20	74C107	1.25	74C922	5.95
74C30	39	74C151	2.90	74C923	6.25
74C42	1.95	74C154	3.00	74C925	8.95
74C48	2.49	74C157	2.15	74C926	8.95
74C73	89	74C160	2.49	80C95	1.50
74C74	89	74C161	2.49	80C97	1.50

78MG		1.75	LINEAR		LM710N	79
LM100H	99		LM340N-1.8	1.35	LM723H	99
LM100H	99		LM340N-2.4	1.35	LM710N	79
LM301CN/H	99		LM340N-2.5	1.35	LM739N	1.15
LM301CN/H	75		LM340N-3.5	1.35	LM741CN/H	99
LM304H	100		LM340N-4.5	1.25	LM741N	79
LM305H	99		LM340N-5	1.25	LM747H/H	79
LM305H	100		LM340N-7.2	1.25	LM748H/H	99
LM308CN/H	100		LM340N-15	1.25	LM3410N	2.95
LM309H	1.10		LM340N-18	1.25	LM1450CN/H	55
LM309H	99		LM350N	1.00	MC1488N	3.95
LM311H/H	99		LM350N	1.00	MC1489N	3.95
LM312H	99		LM370N	95	LM1496N	95
LM312H	99		LM373N	3.75	LM1550N	1.75
LM312H	99		LM377N	4.00	MC1741CP	99
LM318CN/H	1.50		LM380N	1.25	LM211TN	1.95
LM318H	1.30		LM380N	99	LM212TN	99
LM320K-5	3.5		LM380N-1	1.79	LM3003N	5.00
LM320K-5	3.5		LM382N	1.79	LM3003N	5.00
LM320K-12	3.5		LM390N	1.25	LM3909N	89
LM320K-15	3.5		LM390N	1.25	LM3909N	89
LM320K-25	3.5		NE510A	6.00	LM3909N(3401)	45
LM320N-18	3.5		NE529A	4.95	LM3909N	89
LM320N-24	3.5		NE531H/H	3.95	LM3909N	89
LM320T-5	3.5		NE540N	6.00	MC6585V	99
LM320T-5	2.125		NE540N	6.00	80388	4.95
LM320T-12	3.5		NE544N	4.95	LM7450N	45
LM320T-15	3.5		NE550N	1.30	7451CN	36
LM320T-15	3.5		NE553N	4.95	7451CN	36
LM320T-18	3.5		NE556N	99	7453CN	36
LM320T-24	2.25		NE560B	5.00	7454CN	36
LM320N-4.5	3.5		NE561B	5.00	7454CN	36
LM339N	99		NE562B	5.00	74582CN	36
LM339N	1.80		NE565N/H	1.25	74593N	89
LM339N	99		NE566N	1.25	74594CN	89
LM340K-8	3.5		NE567B/H	3.99	RC145N	5.95
LM340K-8	3.35		NE570N	4.95	RC145N	5.95
LM340K-12	3.35		LM703CN/H	69	RC149A	5.95

74LS00	29	74LS07H	29	74LS138	89
74LS01	29			74LS139	89
74LS02	29	74LS47	89	74LS151	89
74LS03	29	74LS51	29	74LS155	89
74LS04	35	74LS54	29	74LS157	89
74LS05	29	74LS55	29	74LS160	1.1
74LS06	29	74LS73	45	74LS161	1.1
74LS09	35	74LS74	45	74LS162	1.1
74LS10	29	74LS75	59	74LS163	1.1
74LS11	35	74LS76	45	74LS164	1.2
74LS12	35	74LS78	49	74LS175	89
74LS13	35	74LS83	89	74LS181	2.4
74LS14	35	74LS85	1.25	74LS190	1.1
74LS15	35	74LS86	1.1	74LS191	1.1
74LS16	35	74LS90	59	74LS192	1.1
74LS17	35	74LS92	75	74LS193	1.1
74LS18	35	74LS93	75	74LS194	1.1
74LS19	35	74LS95	99	74LS195	1.1
74LS20	35	74LS96	1.15	74LS253	99
74LS21	35	74LS107	45	74LS257	89
74LS22	35	74LS109	45	74LS258	89
74LS23	45	74LS112	45	74LS260	69
74LS24	35	74LS123	1.25	74LS279	75
74LS25	35	74LS125	89	74LS307	35
74LS26	35	74LS132	75	74LS308	75
74LS27	35	74LS136	49	74LS370	29

Transistor Checker



— Completely Assembled —
— Battery Operated —

The ASI Transistor Checker is capable of checking a wide range of transistor types, either "in circuit" or out of circuit. To operate, simply plug the transistor to be checked into the front panel socket, or connect it with the alligator clip test leads provided. The unit safely and automatically identifies low, medium and high-power PNP and NPN transistors. Size: 3 1/2" x 6 1/4" x 2 1/2". "C" cell battery not included.

NEW

Trans-Check \$29.95 ea.

Custom Cables & Jumpers



Part No.	Cable Length	Connectors	Price
DB25P-4-P	4 ft.	2-DP25P	\$15.95 ea.
DB25P-4-S	4 ft.	1-DP25P/1-25S	\$16.95 ea.
DB25S-4-S	4 ft.	2-DP25S	\$17.95 ea.

Dip Jumpers			
DJ14-1	1 ft.	1-14 Pin	\$1.59 ea.
DJ16-1	1 ft.	1-16 Pin	1.79 ea.
DJ24-1	1 ft.	1-24 Pin	2.79 ea.
DJ14-1-14	1 ft.	2-14 Pin	3.95 ea.
DJ16-1-16	1 ft.	2-16 Pin	3.19 ea.
DJ24-1-24	1 ft.	2-24 Pin	4.95 ea.

For Custom Cables & Jumpers, See JAMECO 1979 Catalog for Pricing

CONNECTORS			
25 Pin-D Subminiature			
DB25P (as pictured)	PLUG (Meets RS232)		\$2.95
DB25S	SOCKET (Meets RS232)		\$3.50
DB51226-1	Cable Cover for DB25P or DB25S		\$1.75

PRINTED CIRCUIT EDGE-CARD			
156 Spacing-Tin-Double Read-Out — Bifurcated Contacts — Fits 054 to 070 P.C. Cards			
15/30	PINS (Solder Eyelet)		\$1.95
18/36	PINS (Solder Eyelet)		\$2.49
22/44	PINS (Solder Eyelet)		\$2.95
50/100 (.100 Spacing)	PINS (Wire Wrap)		\$6.95
50/100 (.125 Spacing)	PINS (Wire Wrap)		R681-1 \$6.95

Solar Cells 2x2cm


- 0.4 volts
- 100mA
- 41 MW

Can be added in series for higher voltage or parallel for higher current.

#SC 2x2 \$1.95 ea. or 3/\$5.00

the 3rd Hand

MAKES CIRCUIT ASSEMBLY A BREEZE!
Lets you work with both hands.
Sturdy Aluminum Construction. \$9.95 ea.



- Clamp "3rd Hand" on edge of bench, table or work-board. Insert circuit board, position components.
- Flip circuit board to flat position for soldering and clipping.
- Bright .300 ht. comm. cathode display
- Uses MM5314 clock chip
- Switches for hours, minutes and hold modes
- Hrs. easily viewable to 20 ft.
- Simulated walnut case
- 115 V AC operation
- 12 or 24 hr. operation
- Incl. all components, case & wall transformer
- Size: 6 3/4" x 3 1/8" x 1 3/4"

JE701

6-Digit Clock Kit \$19.95

REMOTE CONTROL TRANSMITTER & RECEIVER

• Can be used as remote control for TV
• Use it on your own car stereo
• Transmitter & Receiver, both on 1 channel
• Transmitter & Receiver, both on 2 channels
• Transmitter & Receiver, both on 4 channels
• Transmitter & Receiver, both on 8 channels
• Transmitter & Receiver, both on 16 channels
• Transmitter & Receiver, both on 32 channels
• Transmitter & Receiver, both on 64 channels
• Transmitter & Receiver, both on 128 channels
• Transmitter & Receiver, both on 256 channels
• Transmitter & Receiver, both on 512 channels
• Transmitter & Receiver, both on 1024 channels
• Transmitter & Receiver, both on 2048 channels
• Transmitter & Receiver, both on 4096 channels
• Transmitter & Receiver, both on 8192 channels
• Transmitter & Receiver, both on 16384 channels
• Transmitter & Receiver, both on 32768 channels
• Transmitter & Receiver, both on 65536 channels
• Transmitter & Receiver, both on 131072 channels
• Transmitter & Receiver, both on 262144 channels
• Transmitter & Receiver, both on 524288 channels
• Transmitter & Receiver, both on 1048576 channels
• Transmitter & Receiver, both on 2097152 channels
• Transmitter & Receiver, both on 4194304 channels
• Transmitter & Receiver, both on 8388608 channels
• Transmitter & Receiver, both on 16777216 channels
• Transmitter & Receiver, both on 33554432 channels
• Transmitter & Receiver, both on 67108864 channels
• Transmitter & Receiver, both on 134217728 channels
• Transmitter & Receiver, both on 268435456 channels
• Transmitter & Receiver, both on 536870912 channels
• Transmitter & Receiver, both on 1073741824 channels
• Transmitter & Receiver, both on 2147483648 channels
• Transmitter & Receiver, both on 4294967296 channels
• Transmitter & Receiver, both on 8589934592 channels
• Transmitter & Receiver, both on 17179869184 channels
• Transmitter & Receiver, both on 34359738368 channels
• Transmitter & Receiver, both on 68719476736 channels
• Transmitter & Receiver, both on 137438953472 channels
• Transmitter & Receiver, both on 274877906944 channels
• Transmitter & Receiver, both on 549755813888 channels
• Transmitter & Receiver, both on 1099511627776 channels
• Transmitter & Receiver, both on 2199023255552 channels
• Transmitter & Receiver, both on 4398046511104 channels
• Transmitter & Receiver, both on 8796093022208 channels
• Transmitter & Receiver, both on 17592186044416 channels
• Transmitter & Receiver, both on 35184372088832 channels
• Transmitter & Receiver, both on 70368744177664 channels
• Transmitter & Receiver, both on 140737488355328 channels
• Transmitter & Receiver, both on 281474976710656 channels
• Transmitter & Receiver, both on 562949953421312 channels
• Transmitter & Receiver, both on 1125899906842624 channels
• Transmitter & Receiver, both on 2251799813685248 channels
• Transmitter & Receiver, both on 4503599627370496 channels
• Transmitter & Receiver, both on 9007199254740992 channels
• Transmitter & Receiver, both on 18014398509481984 channels
• Transmitter & Receiver, both on 36028797018963968 channels
• Transmitter & Receiver, both on 72057594037927936 channels
• Transmitter & Receiver, both on 144115188075855872 channels
• Transmitter & Receiver, both on 288230376151711744 channels
• Transmitter & Receiver, both on 576460752303423488 channels
• Transmitter & Receiver, both on 1152921504606846976 channels
• Transmitter & Receiver, both on 2305843009213693952 channels
• Transmitter & Receiver, both on 4611686018427387904 channels
• Transmitter & Receiver, both on 9223372036854775808 channels
• Transmitter & Receiver, both on 18446744073709551616 channels
• Transmitter & Receiver, both on 36893488147419103232 channels
• Transmitter & Receiver, both on 73786976294838206464 channels
• Transmitter & Receiver, both on 147573952589676412928 channels
• Transmitter & Receiver, both on 295147905179352825856 channels
• Transmitter & Receiver, both on 590295810358705651712 channels
• Transmitter & Receiver, both on 1180591620717411303424 channels
• Transmitter & Receiver, both on 2361183241434822606848 channels
• Transmitter & Receiver, both on 4722366482869645213696 channels
• Transmitter & Receiver, both on 9444732965739290427392 channels
• Transmitter & Receiver, both on 18889465931478580854784 channels
• Transmitter & Receiver, both on 37778931862957161709568 channels
• Transmitter & Receiver, both on 75557863725914323419136 channels
• Transmitter & Receiver, both on 151115727451828646838272 channels
• Transmitter & Receiver, both on 302231454903657293676544 channels
• Transmitter & Receiver, both on 604462909807314587353088 channels
• Transmitter & Receiver, both on 1208925819614629174706176 channels
• Transmitter & Receiver, both on 2417851639229258349412352 channels
• Transmitter & Receiver, both on 4835703278458516698824704 channels
• Transmitter & Receiver, both on 9671406556917033397649408 channels
• Transmitter & Receiver, both on 19342813113834066795298816 channels
• Transmitter & Receiver, both on 38685626227668133590597632 channels
• Transmitter & Receiver, both on 77371252455336267181195264 channels
• Transmitter & Receiver, both on 154742504910672534362390528 channels
• Transmitter & Receiver, both on 309485009821345068724781056 channels
• Transmitter & Receiver, both on 618970019642690137449562112 channels
• Transmitter & Receiver, both on 1237940039285380274899244224 channels
• Transmitter & Receiver, both on 2475880078570760549798488448 channels
• Transmitter & Receiver, both on 4951760157141521099596976896 channels
• Transmitter & Receiver, both on 9903520314283042199193953792 channels
• Transmitter & Receiver, both on 19807040628566084398387907584 channels
• Transmitter & Receiver, both on 39614081257132168796775815168 channels
• Transmitter & Receiver, both on 79228162514264337593551630336 channels
• Transmitter & Receiver, both on 158456325028528675187103260672 channels
• Transmitter & Receiver, both on 316912650057057350374206521344 channels
• Transmitter & Receiver, both on 633825300114114700748413042688 channels
• Transmitter & Receiver, both on 1267650600228229401496826085376 channels
• Transmitter & Receiver, both on 253530120045645880299365217072 channels
• Transmitter & Receiver, both on 507060240091291760598730434144 channels
• Transmitter & Receiver, both on 1014120480182583521197460868288 channels
• Transmitter & Receiver, both on 2028240960365167042394921736576 channels
• Transmitter & Receiver, both on 4056481920730334084789843473152 channels
• Transmitter & Receiver, both on 8112963841460668169579786946304 channels
• Transmitter & Receiver, both on 16225927682921336339155738932608 channels
• Transmitter & Receiver, both on 32451855365842672678311477865216 channels
• Transmitter & Receiver, both on 64903710731685345356622955730432 channels
• Transmitter & Receiver, both on 129807421463706890713245811460672 channels
• Transmitter & Receiver, both on 259614842927413781426491628221312 channels
• Transmitter & Receiver, both on 519229685854827562852983256442624 channels
• Transmitter & Receiver, both on 103845937170965512570596651289344 channels
• Transmitter & Receiver, both on 207691874341931025141193302578688 channels
• Transmitter & Receiver, both on 415383748683862050282386605157376 channels
• Transmitter & Receiver, both on 830767497367724100564773210314752 channels
• Transmitter & Receiver, both on 1661534994735448201129546420629504 channels
• Transmitter & Receiver, both on 3323069989470896402259092841259008 channels
• Transmitter & Receiver, both on 6646139978941792804518185682518016 channels
• Transmitter & Receiver, both on 13292279957883585609036371275235328 channels
• Transmitter & Receiver, both on 26584559915767171218072742550470656 channels
• Transmitter & Receiver, both on 53169119831534342436145485100941312 channels
• Transmitter & Receiver, both on 10633823966306868487229097020188224 channels
• Transmitter & Receiver, both on 21267647932613736974458194040376448 channels
• Transmitter & Receiver, both on 42535295865227473948916388080752896 channels
• Transmitter & Receiver, both on 850705917304549478978327761615157792 channels
• Transmitter & Receiver, both on 1701411834609098957956655523231155584 channels
• Transmitter & Receiver, both on 3402823669218197915913311046463111168 channels
• Transmitter & Receiver, both on 6805647338436395831826622092926222336 channels
• Transmitter & Receiver, both on 13611294676872791663645244185852444672 channels
• Transmitter & Receiver, both on 27222589353745583327290488371704889344 channels
• Transmitter & Receiver, both on 5444517870749116665458097674340977888 channels
• Transmitter & Receiver, both on 10889035741498233330916195348681955776 channels
• Transmitter & Receiver, both on 21778071482996466661832390697367911552 channels
• Transmitter & Receiver, both on 43556142965992933323664781394735822304 channels
• Transmitter & Receiver, both on 87112285931985866647329562789471644416 channels
• Transmitter & Receiver, both on 174224571863911733294659135778943288832 channels
• Transmitter & Receiver, both on 348449143727823466589318267557886577664 channels
• Transmitter & Receiver, both on 696898287455646933178636535115773155328 channels
• Transmitter & Receiver, both on 1393796574911293866357273070235462710656 channels
• Transmitter & Receiver, both on 278759314982258773271454614047092421312 channels
• Transmitter & Receiver, both on 557518629964517546442909228094184842624 channels
• Transmitter & Receiver, both on 1115037259929035092885818056188369685248 channels
• Transmitter & Receiver, both on 2230074519858070185771637132353739370496 channels
• Transmitter & Receiver, both on 4460149039716140351553274267075478741952 channels
• Transmitter & Receiver, both on 8920298079432280703110664534150957438944 channels
• Transmitter & Receiver, both on 1784059615886456140622133286830191487888 channels
• Transmitter & Receiver, both on 3568119231772912281242666567663822975776 channels
• Transmitter & Receiver, both on 7136238463545824562485333135326555951552 channels
• Transmitter & Receiver, both on 142724769270916451249706662706651111104 channels
• Transmitter & Receiver, both on 2854495385418329024994133242133022222208 channels
• Transmitter & Receiver, both on 570899077083665804998826648426604444416 channels
• Transmitter & Receiver, both on 114179815416733160997753296845208888896 channels
• Transmitter & Receiver, both on 228359630833466321995506593690417777792 channels
• Transmitter & Receiver, both on 456719261666932643991013187380835555584 channels
• Transmitter & Receiver, both on 913438523333865287982026374761671111168 channels
• Transmitter & Receiver, both on 1826877046667730575964052749523342222336 channels
• Transmitter & Receiver, both on 3653754093335461151928105499046684444672 channels
• Transmitter & Receiver, both on 730750818667092230385621099809336888896 channels
• Transmitter & Receiver, both on 1461501637334184460771242199618677777792 channels
• Transmitter & Receiver, both on 292300327466836892154248439923735555584 channels
• Transmitter & Receiver, both on 584600654933673784308496879847471111168 channels
• Transmitter & Receiver, both on 116920130986734756861697759769482222336 channels
• Transmitter & Receiver, both on 233840261973469513723339519538964444672 channels
• Transmitter & Receiver, both on 46768052394693902744667903907792888896 channels
• Transmitter & Receiver, both on 9353610478938780548933780781557777792 channels
• Transmitter & Receiver, both on 187072209578775610977675615631135555584 channels
• Transmitter & Receiver, both on 374144419157551221955351232622271111168 channels
• Transmitter & Receiver, both on 748288838315102443910702465244542222336 channels
• Transmitter & Receiver, both on 149657767663020487822140493048904444672 channels
• Transmitter & Receiver, both on 29931553532604097564428098609780888896 channels
• Transmitter & Receiver, both on 598631070652081913288561921195617777792 channels
• Transmitter & Receiver, both on 1197262141304163826777124233913135555584 channels
• Transmitter & Receiver, both on 2394524282608327653554248467826271111168 channels
• Transmitter & Receiver, both on 4789048565216655307108969357652542222336 channels
• Transmitter & Receiver, both on 9578097130433310614217938715305084444672 channels
• Transmitter & Receiver, both on 1915619426086662122843877439061016888896 channels
• Transmitter & Receiver, both on 3831238852173324245687754878122135555584 channels
• Transmitter & Receiver, both on 7662477704346648491375509756244271111168 channels
• Transmitter & Receiver, both on 153249544086932969827510195124884444672 channels
• Transmitter & Receiver, both on 30649908817386593965502039024976888896 channels
• Transmitter & Receiver, both on 61299817634773187931004078049953777792 channels
• Transmitter & Receiver, both on 1225996352695463758620081600999075555584 channels
• Transmitter & Receiver, both on 245199270539092751724001601998151111168 channels
• Transmitter & Receiver, both on 490398541078185503448003203996302222336 channels
• Transmitter & Receiver, both on 980797082156371006896006407992604444672 channels
• Transmitter & Receiver, both on 196159416431272201379201201598520888896 channels
• Transmitter & Receiver, both on 392318832862544402758402403997041777792 channels
• Transmitter & Receiver, both on 78463766572508880551680800799409555584 channels
• Transmitter & Receiver, both on 15692753314501776113361616015988191111168 channels
• Transmitter & Receiver, both on 313855066290035522267232320319773555584 channels
• Transmitter & Receiver, both on 6277101325800710445344646406395471111168 channels
• Transmitter & Receiver, both on 1255420265160014090688929201399094444672 channels
• Transmitter & Receiver, both on 251084053032002818137785840275818888896 channels
• Transmitter & Receiver, both on 50216810606400563627557168051633777792 channels
• Transmitter & Receiver, both on 1004336212128011225451135360102675555584 channels
• Transmitter & Receiver, both on 2008672424256022450902270720205351111168 channels
• Transmitter & Receiver, both on 4017344848512044901804541440410702222336 channels
• Transmitter & Receiver, both on 803468969702408980360908288082040444672 channels
• Transmitter & Receiver, both on 1606937939404817960721817568164080888896 channels
• Transmitter & Receiver, both on 3213875878809635921443635136328161777792 channels
• Transmitter & Receiver, both on 6427751757619271842887270272656323555584 channels
• Transmitter & Receiver, both on 12855503115238537695775405445312671111168 channels
• Transmitter & Receiver, both on 25711006230477075391551080890025442222336 channels
• Transmitter & Receiver, both on 51422012460954150731101617780050884444672 channels
• Transmitter & Receiver, both on 1028440251219083014622203235601016888896 channels
• Transmitter & Receiver, both on 20568805024381660292440647120202135555584 channels
• Transmitter & Receiver, both on 41137610048763320584881214240404271111168 channels
• Transmitter & Receiver, both on 822752200975266411697696244808084444672 channels
• Transmitter & Receiver, both on 16455044019505328233953894896161777792 channels
• Transmitter & Receiver, both on 3291008803901065646790778979232335555584 channels
• Transmitter & Receiver, both on 6582017607802131293581557958464671111168 channels
• Transmitter & Receiver, both on 131640352156042625871611191692928888896 channels
• Transmitter & Receiver, both on 26328070431208525174322238338585777792 channels
• Transmitter & Receiver, both on 5265614086241705034864447667717135555584 channels
• Transmitter & Receiver, both on 1053122817483341006972895333543471111168 channels
• Transmitter & Receiver, both on 2106245634966682013945779066686842222336 channels
• Transmitter & Receiver, both on 4212491269933364027891558133373735555584 channels
• Transmitter & Receiver, both on 84249825398667280557831162666754671111168 channels
• Transmitter & Receiver, both on 1684996517773345611556623253335094444672 channels
• Transmitter & Receiver, both on 336999303554669122311326566667018888896 channels
• Transmitter & Receiver, both on 67399860710933824462226513333403777792 channels
• Transmitter & Receiver, both on 1347997214216774492445310266680675555584 channels
• Transmitter & Receiver, both on 2695994428433548984890620533370135555584 channels
• Transmitter & Receiver, both on 5391988856867097969781241066740271111168 channels
• Transmitter & Receiver, both on 107839777337341959396248213334804444672 channels
• Transmitter & Receiver, both on 21567955467468391879329642666880888896 channels
• Transmitter & Receiver, both on 43135910934936783758659285333761777792 channels
• Transmitter & Receiver, both on 862718218698735675173185706675235555584 channels
• Transmitter & Receiver, both on 17254363773974713513463714133504444672 channels
• Transmitter & Receiver, both on 34508727547949427026927428267008888896 channels
• Transmitter & Receiver, both on 6901745509589885405385485653401777792 channels
• Transmitter & Receiver, both on 1380349101917971010777091130688035555584 channels
• Transmitter & Receiver, both on 276069820383594202155418226137135555584 channels
• Transmitter & Receiver, both on 552139640767188404311084452274271111168 channels
• Transmitter & Receiver, both on 110427920153437680822217689448442222336 channels
• Transmitter & Receiver, both on 2208558

Boards . . . or Complete Systems

The best price and delivery is from MiniMicroMart!



BANTAM 550 from PERKIN-ELMER

Small in size, light in weight, and low in price — but top of the list in features and performance.

- Upper and lower case
- Full 24 x 80 format
- Sharp 7 x 10 dot matrix

Get everything you want without paying for things you don't need — List \$996

NOW FROM US AT **\$799**

Add \$20 for anti-glare screen
(specify gray or green)

SHIPPING: Add \$5 for East Coast; \$7.50 for Midwest; \$8.50 if you are in Pacific Time Zone.

FLOPPY DISK INTERFACES

	LIST	OUR PRICE
Morrow Discus I	\$995	\$849
Discus I (dual drive)	1795	1499
Discus 2D (Double Density)	1149	979
Disk Jockey I Controller Bd		169
Tarbell Floppy Disk Interface	\$190	\$169
Micromation Doubler, double-density controller	\$495	\$419
Megabox dual-drive dbl. density system, over 1 megabyte	2295	2054
Mega II, over 2 megabytes	2995	2695
SD Computer VersaFloppy floppy disk controller board, kit	\$159	139
Micropolis 1041 MacroFloppy	\$695	\$625
1042 MacroFloppy w/case & P.S.	709	
1053 Dual MetaFloppy	1895	1695

INTRODUCTORY SPECIAL

fantastic new Xitan Disk Controller Board single and double density, handles mini- and standard-size drives simultaneously, complete with CP/M compatible DOS and Xitan disk BASIC. Assm./tested
List \$595 OUR PRICE \$499

CLOSE-OUT SPECIAL TDL SMB BOARD

Provides for Zapple ROM, 2K RAM, parallel interface, 2 serial interfaces, and tape cassette interface.

Bare Board only, w/documentation	\$ 49.95
Complete Kit	147.50
Assembled and Tested	197.50
None of above include Zapple ROM or RAM.	
Zapple Monitor ROM	29.95

NORTH STAR HORIZON



Now Double Density

Horizon 1 Kit List \$1599	\$1349
Assembled/Tested List \$1899	1599
Horizon 2 (w/2 drives) Kit List \$1999	1699
Assembled/Tested List \$2349	1939

4 MHz Z-80 CPU Board, Kit \$199	169
Assembled/Tested List \$259	209

Complete Minifloppy Disk System w/BASIC and drive, Kit List \$699	589
Assembled/Tested List \$799	689

MEMORY BOARDS

	LIST	OUR PRICE
North Star 16K Dynamic, Kit	\$399	\$269
Assembled & Tested	\$459	309
Dynabyte 16K Static RAM, 250ns	\$359	
32K Static RAM, 250ns	\$995	796
Morrow SuperRAM 16K Static 450ns, Kit	\$299	\$269
450ns, Assembled	334	304
4 MHz, Kit	334	304
4 MHz, Assembled	369	339
32K Static, 4 MHz, Kit	\$649	579
32K Static, 4 MHz, Assm.	699	629
Cromemco 16K RAM Card w/Bank Select, Kit	\$495	\$399
Assembled	595	495
SD Computer ExpandoRAM w/o RAMS	\$139	
32K Dynamic w/8K, Kit	189	
32K Dynamic w/16K, Kit	237	
32K Dynamic w/32K, Kit	Special	\$329
Vector 48K Assm.	\$695	\$589

SPECIAL — SAVE \$300

Xitan (TDL) D-32 32K Dynamic Memory Board, List \$869

OUR PRICE: \$569

Prices in this ad include 2% cash prepayment discount (bank transfer, check, money order, etc.). VISA and Master Charge accepted, but 2% cash discount does not apply. Slightly higher prices apply to government and institutional purchase orders when not prepaid.

Above prices subject to change and all offers subject to withdrawal without notice.


SHIPPING, HANDLING & INSURANCE: Add \$2 for boards, \$7.50 for floppy disk systems, \$12 for Horizons.

OEM and dealer inquiries invited.

— WRITE FOR FREE CATALOG —

MiniMicroMart, Inc.

1618 James Street, Syracuse, NY 13203 (315) 479-7620 TWX 710 541-0431



THE PRINTERM 879

Best Printer Buy for '79

Unbelievable speed at low price — 120 cps, printing in upper and lower case with a 9 x 7 dot matrix in a bi-directional mode. Micro-processor-controlled RS232 or optional parallel interface directly compatible with TRS-80 or Cromemco System 2 or 3. Friction or pin-feed models available. Friction-feed model can use standard Teletype roll.

Friction Feed Model, List \$1395	\$1099
Pin-Feed Model, List \$1495	\$1199

TERMINALS AND PRINTERS

Hazeltine 1500	\$1049
1510	1149
1400	699
Soroc 120	\$849
Intertube	\$784
Lear Siegler ADM3A, assm.	\$849
Kit	775
Teletype 43 RO, TTL (serial)	\$874
43 KSR/Terminal, TTL (serial)	979
T.I. 810 Printer	\$1695
Centronics 779 w/tractor	\$995
IP-125 Brightwriter w/1210 print control option	\$754
IP-225 w/1210 & 1250 options	889
DecWriter II	\$1490
RS232 Cables	\$25

Call or write for price and delivery information on EXIDY SORCERER

If you own a TRS-80 or Heath H-8, write for our special catalog. Many unique offerings — Save 10%-20% on TRS-80 accessories.

SOFTWARE

Complete stock of Xitan software (formerly TDL) in inventory at substantial savings.

MORE SPECIALS

Xitan VDB Board	our price \$314
Xitan SMB-II, List \$395	\$339
The fantastic new Xitan ZPU-II	\$319

SYM-1, 6502-BASED MICROCOMPUTER

- FULLY-ASSEMBLED AND COMPLETELY INTEGRATED SYSTEM that's ready-to-use
- ALL LSI IC'S ARE IN SOCKETS
- 28 DOUBLE-FUNCTION KEYPAD INCLUDING UP TO 24 "SPECIAL" FUNCTIONS
- EASY-TO-VIEW 6-DIGIT HEX LED DISPLAY
- KIM-1* HARDWARE COMPATIBILITY
- The powerful 6502 8-Bit MICROPROCESSOR whose advanced architectural features have made it one of the largest selling "micros" on the market today.
- THREE ON-BOARD PROGRAMMABLE INTERVAL TIMERS available to the user, expandable to five on-board.
- 4K BYTE ROM RESIDENT MONITOR and Operating Programs.
- Single 5 Volt power supply is all that is required.
- 1K BYTES OF 2114 STATIC RAM onboard with sockets provided for immediate expansion to 4K bytes onboard, with total memory expansion to 65, 536 bytes.
- USER PROM/ROM: The system is equipped with 3 PROM/ROM expansion sockets for 2316/2332 ROMs or 2716 EPROMs
- ENHANCED SOFTWARE with simplified user interface
- STANDARD INTERFACES INCLUDE:
 - Audio Cassette Recorder Interface with Remote Control (Two modes: 135 Baud KIM-1* compatible, Hi-Speed 1500 Baud)
 - Full duplex 20mA Teletype Interface
 - System Expansion Bus Interface
 - TV Controller Board Interface
 - CRT Compatible Interface (RS-232)
- APPLICATION PORT: 15 Bi-directional TTL Lines for user applications with expansion capability for added lines
- EXPANSION PORT FOR ADD-ON MODULES (51 I/O Lines included in the basic system)
- SEPARATE POWER SUPPLY connector for easy disconnect of the d-c power
- AUDIBLE RESPONSE KEYPAD

QUALITY EXPANSION BOARDS DESIGNED SPECIFICALLY FOR KIM-1, SYM-1 & AIM 65

These boards are set up for use with a regulated power supply such as the one below, but, provisions have been made so that you can add onboard regulators for use with an unregulated power supply. But, because of unreliability, we do not recommend the use of onboard regulators. All I.C.'s are socketed for ease of maintenance. All boards carry full 90-day warranty.

All products that we manufacture are designed to meet or exceed industrial standards. All components are first quality and meet full manufacturer's specifications. All this and an extended burn-in is done to reduce the normal percentage of field failures by up to 75%. To you, this means the chance of inconvenience and lost time due to a failure is very rare; but, if it should happen, we guarantee a turn-around time of less than forty-eight hours for repair.

Our money back guarantee: If, for any reason you wish to return any board that you have purchased directly from us within ten (10) days after receipt, complete, in original condition, and in original shipping carton; we will give you a complete credit or refund less a \$10.00 restocking charge per board.

VAK-1 8-SLOT MOTHERBOARD

This motherboard uses the KIM-4* bus structure. It provides eight (8) expansion board sockets with rigid card cage. Separate jacks for audio cassette, TTY and power supply are provided. Fully buffered bus.

VAK-1 Motherboard \$129.00

VAK-2/4 16K STATIC RAM BOARD

This board provides 2114 RAMs is configured in two (2) separately addressable 8K blocks with individual write-protect switches.


VAK-2 16K RAM Board with only 8K of RAM (1/2 populated) \$239.00

VAK-3 Complete set of chips to expand above board to 16K \$175.00

VAK-4 Fully populated 16K RAM \$379.00

VAK-5 2708 EPROM PROGRAMMER

This board requires a +5 VDC and +12 VDC, but has a DC to DC



Synertek has enhanced KIM-1* software as well as the hardware. The software has simplified the user interface. The basic SYM-1 system is programmed in machine language. Monitor status is easily accessible, and the monitor gives the keypad user the same full functional capability of the TTY user. The SYM-1 has everything the KIM-1* has to offer, plus so much more that we cannot begin to tell you here. So, if you want to know more, the SYM-1 User Manual is available, separately.

SYM-1 Complete w/manuals \$269.00

SYM-1 User Manual Only 7.00

SYM-1 Expansion Kit 75.00

Expansion includes 3K of 2114 RAM chips and 1-6522 I/O chip.

SYM-1 Manuals: The well organized documentation package is complete and easy-to-understand.

SYM-1 CAN GROW AS YOU GROW. It's the system to BUILD-ON.

Expansion features that are available:

BAS-1 8K Basic ROM (Microsoft Basic) \$159.00

KIM-2 (Complete terminal less monitor) 349.00

multiplier so there is no need for an additional power supply. All software is resident in on-board ROM, and has a zero-insertion socket.

VAK-5 2708 EPROM Programmer \$269.00

VAK-6 EPROM BOARD

This board will hold 8K of 2708 or 2758, or 16K of 2716 or 2516 EPROMs. EPROMs not included.

VAK-6 EPROM Board \$129.00

VAK-7 COMPLETE FLOPPY-DISK SYSTEM (May '79)

VAK-8 PROTOTYPING BOARD

This board allows you to create your own interfaces to plug into the motherboard. Etched circuitry is provided for regulators, address and data bus drivers; with a large area for either wire-wrapped or soldered IC circuitry.

VAK-8 Prototyping Board \$49.00

POWER SUPPLIES

ALL POWER SUPPLIES are totally enclosed with grounded enclosures for safety, AC power cord, and carry a full 2-year warranty.

FULL SYSTEM POWER SUPPLY

This power supply will handle a microcomputer and up to 65K of our VAK-4 RAM. ADDITIONAL FEATURES ARE: Over voltage Protection on 5 volts, fused, AC on/off switch. Equivalent to units selling for \$225.00 or more.

Provides +5 VDC @ 10 Amps & +12 VDC @ 1 Amp

VAK-EPS Power Supply \$125.00

*KIM is a product of MOS Technology

KIM-1* Custom P.S. provides 5 VDC @ 1.2 Amps and +12 VDC @ .1 Amps

KCP-1 Power Supply \$41.50


SYM-1 Custom P.S. provides 5 VDC @ 1.4 Amps

VCP-1 Power Supply \$41.50

RNB ENTERPRISES
INCORPORATED


✓ R20

2967 W. Fairmount Avenue
Phoenix AZ. 85017
(602)265-7564



Prices in effect Nov. '78

16K EPROM CARD-S 100 BUSS



\$59.95

KIT

OUR
BEST
SELLING
KIT!


USES 2708's!

Thousands of personal and business systems around the world use this board with complete satisfaction. Puts 16K of software on line at **ALL TIMES!** Kit features a top quality soldermasked and silk-screened PC board and first run parts and sockets. All parts (except 2708's) are included. Any number of EPROM locations may be disabled to avoid any memory conflicts. Fully buffered and has WAIT STATE capabilities.

OUR 450NS 2708'S
ARE \$8.95 EA. WITH
PURCHASE OF KIT

ASSEMBLED
AND FULLY TESTED
ADD \$25

8K LOW POWER RAM KIT-S 100 BUSS 250 NS SALE!



ADD \$5
FOR
250NS!

\$129 KIT

(450 NS RAMS!)

Thousands of computer systems rely on this rugged, work horse, RAM board. Designed for error-free, NO HASSLE, systems use.

KIT FEATURES:

1. Doubled sided PC Board with solder mask and silk screen layout. Gold plated contact fingers.
2. All sockets included.
3. Fully buffered on all address and data lines.
4. Phantom is jumper selectable to pin 67.
5. FOUR 7805 regulators are provided on card.

Blank PC Board w/Documentation
\$29.95

Low Profile Socket Set...**13.50**
Support IC's (TTL & Regulators)
\$9.75


Bypass CAP's (Disc & Tantalums)
\$4.50

ASSEMBLED AND FULLY
BURNED, IN ADD \$30

16K STATIC RAM KIT-S 100 BUSS

\$295 KIT

FULLY
STATIC, AT
DYNAMIC PRICES



WHY THE 2114 RAM CHIP?

We feel the 2114 will be the next industry standard RAM chip (like the 2102 was). This means price, availability, and quality will all be good! Next, the 2114 is FULLY STATIC! We feel this is the **ONLY** way to go on the S-100 Bus! We've all heard the HORROR stories about some Dynamic RAM Boards having trouble with DMA and FLOPPY DISC DRIVES. Who needs these kinds of problems? And finally, even among other 4K Static RAM's the 2114 stands out! Not all 4K static Rams are created equal! Some of the other 4K's have clocked chip enable lines and various timing windows just as critical as Dynamic RAM's. Some of our competitor's 16K boards use these "tricky" devices. But not us! The 2114 is the **ONLY** logical choice for a trouble-free, straightforward design.

KIT FEATURES:


1. Addressable as four separate 4K Blocks.
2. ON BOARD BANK SELECT circuitry. (Cromemco Standard!). Allows up to 512K on line!
3. Uses 2114 (450NS) 4K Static Rams.
4. ON BOARD SELECTABLE WAIT STATES.
5. Double sided PC Board, with solder mask and silk screened layout. Gold plated contact fingers.
6. All address and data lines fully buffered.
7. Kit includes ALL parts and sockets.
8. PHANTOM is jumpered to PIN 67.
9. LOW POWER: under 2 amps TYPICAL from the +8 Volt Bus.
10. Blank PC Board can be populated as any multiple of 4K.

BLANK PC BOARD W/DATA—\$33

LOW PROFILE SOCKET SET—\$12 ASSEMBLED & TESTED—ADD \$30
SUPPORT IC'S & CAPS—\$19.95 2114 RAM'S—8 FOR \$69.95

COMPLEMENTARY POWER TRANSISTORS

SILICON NPN AND PNP. TO-220 CASE.
VCEO - 40V PD - 30 WATTS
FOR AUDIO POWER AMPS, ETC.



TIP29 - NPN
TIP30 - PNP

YOUR CHOICE
3 FOR \$1

16K DYNAMIC RAM CHIP

16K X 1 Bits. 16 Pin Package. Same as Mostek 4116-4. 250 NS access. 410 NS cycle time. Our best price yet for this state of the art RAM. 32K and 64K RAM boards using this chip are readily available. These are new, fully guaranteed devices by a major mfg.

VERY LIMITED STOCK!

8 FOR \$89.95

NOT ASSOCIATED
WITH
DIGITAL RESEARCH
OF CALIFORNIA,
THE SUPPLIERS OF
CPM SOFTWARE.

450 NS!

2708 EPROMS

Now full speed! Prime new units from a major U.S. Mfg. 450 N.S. Access time. 1K x 8. Equiv. to 4-1702 A's in one package.

~~\$15.75 ea.~~

\$9.95

~~4 FOR \$50.00~~

PRICE CUT

NATIONAL SEMICONDUCTOR

CAR CLOCK MODULE - #MA6008

\$6.99

each

Originally used by HYGAIN to indicate time and channel on an expensive C.B. Mini size, self contained module. Not a Kit. Four digits plus flashing indicator for seconds. Includes MM5369 and 3.58 MHZ crystal for super accurate time base. With hookup data.

INCLUDES CRYSTAL TIMEBASE!
WORKS ON 12 VDC!

MFGR'S CLOSEOUT
LIMITED QTY.

Z-80 PROGRAMMING MANUAL

By MOSTEK, or ZILOG. The most detailed explanation ever on the working of the Z-80 CPU CHIPS. At least one full page on each of the 158 Z-80 instructions. A MUST reference manual for any user of the Z-80. 300 pages. Just off the press.

\$12.95

GENERAL INSTRUMENT

FULL WAVE BRIDGE
4 AMP 600 PIV

3/4 IN. SQUARE - WITH LUGS

75¢ ea. **3 FOR \$2**

LOOK!

#LM-1

EXPERIMENTER'S HEATING PLATE

Large Manufacturers Surplus. 5 1/4 x 10 1/2 in. Made of 3/8 in. tempered glass with heating element laminated on back. Works off 120 VAC. Protected by thermostat and two thermal fuses. Rated 120 Watts. Use for any heating applications. Perfect for heating ferric chloride to increase PC Board etching efficiency. Units are brand new, non-submersible.

WHILE THEY LAST—**\$2.99** each

MALLORY COMPUTER

GRADE CAPACITOR

30,000 MFD 15 WVDC

Small: 3 x 2 Inches

\$1.99 ea. 3 For \$4.99

New! REAL TIME

Computer Clock Chip

N.S. MM5313. Features

BOTH 7 segment and

BCD outputs. 28 Pin

DIP. **\$4.95** with Data

"THE COLOSSUS"

FAIRCHILD SUPER JUMBO LED READOUT

A full .80 inch character. The biggest readout we have ever sold! Super efficient. Compare at up to \$2.95 each from others!

YOUR CHOICE

FND 843 Common Anode

FND 850 Common Cathode

\$1.49 ea (6 for \$6.95)

Digital Research Corporation

(OF TEXAS)

P.O. BOX 401247K GARLAND, TEXAS 75040 • (214) 271-2461

✓ D20

TERMS: Add 30¢ postage, we pay balance. Orders under \$15 add 75¢ handling. No C.O.D. We accept Visa, MasterCard, and American Express cards. Tex. Res. add 5% Tax. Foreign orders (except Canada add 20% P & H. 90 Day Money Back Guarantee on all items.

DEALER DIRECTORY

Shop the store nearest you!

Peoria AZ

Discount prices: North Star, Pertec disk drives, Integrand mainframes, Godbout memories, Tarbell disk controllers, TEI mainframes, Verbatim diskettes, custom hardware/software, service, repairs & consulting. **Thought Works**, 10425 W. Seldon Ln., Peoria AZ 85345, 972-4065.

Los Angeles CA

Featuring: PolyMorphic, North Star, Imsai, Cromemco, Extensys, Speechlab products and Poly-88 Users Group software exchange. All products 10-20% off list. We won't be undersold! **A-A-A Discount Computer How's**, 1477 Barrington, Suite 17, Los Angeles CA 90025, 477-8478.

Palo Alto CA

Systems available for immediate delivery: word processing; multiprogramming, multi-user work in process; business; medical/dental billing and accounts receivable. Software and hardware guaranteed. **Byte of Palo Alto**, 2233 El Camino Real, Palo Alto CA 94306, 327-8080.

San Leandro CA

From personal computers to small systems: North Star, Horizon, DD, Sorcerer, Godbout, TRS-80, Imsai, Verbatim, terminals, printers, floppies, boards, software, books, magazines. Custom programming. **Computer Store of San Leandro**, 701 MacArthur Blvd., San Leandro CA 94577, 569-4174.

Torrance CA

If you're serious, come see us! Complete systems for business, special and personal applications. Packaged and proprietary software. Custom programming. Quality: Apple II, Exidy, Alpha Micro and CP/M systems. Serving southern California better. **Omega Micro Computers**, 3535 Torrance Blvd., Suite 10, Torrance CA 90503, 370-9456.

Denver CO

Experimenters' Paradise. Electronic and mechanical components. Computer People, Audio People, Hams, Robot Builders, Experimenters. Open six days a week. **Gateway Electronics Corp.**, 2839 W. 44th Ave., Denver CO 80211, 458-5444.

Wilmington DE

Turnkey biz system. Hardware and software. Custom formatting available; checks, invoices, reports. Micropolis drives/MDOS/BASIC. FORTRAN/CP-M/CBASIC possible. SASE for our low prices. **ComputerEASE, Inc.**, PO Box 4156, Wilmington DE 19807, 998-5589.

Pompano Beach FL

Business systems, personal systems, whatever the application, we can help. Consulting, programming, education and maintenance. Service, support and professionalism at affordable prices. **Computer Age Inc.**, 1308 N. Federal Hwy., Pompano Beach FL 33062, 946-4999.

Arlington Hts. IL

Lowest prices, never undersold, postpaid in USA—Teletype 43 keyboard printers & SS-50 bus peripherals—open 6-11 PM daily. **Data Mart**, 914 East Waverly Drive, Arlington Heights IL 60004, 398-8525.

Chicago IL

Staffed by computer professionals. Largest selection of books and magazines in the Chicago area. Specialists in CP/M, Apple Computer and Alpha microsystems. **Data Domain of Schaumburg**, Plaza de las Flores, 1612 E. Algonquin Rd., Schaumburg IL 60195, 397-8700.

Naperville IL

Discount Prices: Creed Teletypes, optical scanners, Solid State Music products, Integrand mainframes, Vista floppy-disk systems, many other items, complete hardware and software systems. **Wilcox Enterprises**, 25W178-39th St., Naperville IL 60540, 420-8601.

Laurel MD

Exidy Sorcerer & accessories, Central Data memory boards, G2 software library, full line of ham & SWL equipment. **The Comm Center, Inc.**, Laurel Plaza, Rte. 198, Laurel MD 20810, 792-0600. Washington: 953-9535.

Boston MA

Largest computer store in New England with widest selection of microprocessor and LSI II-based systems. Two miles north of the Mass. Pike, just off Route 128, exit 49. **Computer Mart of Massachusetts**, 1395 Main Street (Rt. 117), Waltham MA 02154, 899-4540.

Westboro MA

Supplies and accessories for the TRS-80. Minidisks; printer paper and forms. Colorful fabric dust covers. Line filters, programs. Custom programming and consulting. Computerized bookkeeping service. **August Automation**, 28 Milk St., Westboro MA, 366-0870.

Grand Rapids MI

Full-line microcomputer store. Ohio Scientific—Equinox—PolyMorphic Systems—Digital Systems—Godbout—Dynabyte—Thinker Toys—Meca—North Star. **Micro Computer World**, 313 Michigan St., N.E., Grand Rapids MI 49503, 451-8972.

St. Paul MN

Ohio Scientific Authorized Dealer. Complete business and personal computer systems. Store hours: Mon-Sat 9-5. Custom software design and programming. To take advantage of our many years of computer experience call, write or visit: **Frisch Computer Systems, Inc.**, 1415 Arcade St., St. Paul MN 55106, 771-7569.

St. Louis MO

Experimenters' Paradise. Electronic and mechanical components. Computer People, Audio People, Hams, Robot Builders, Experimenters. Open six days a week. **Gateway Electronics Corp.**, 8123-25 Page Blvd., St. Louis MO 63130, 427-6116.

White Plains NY

Processor Technology, North Star HORIZON, Apple II, Commodore PET and KIM, full line of books, components and peripherals; classes in our Seminar Room. **The Computer Corner**, 200 Hamilton Avenue, White Plains NY 10601, 949-3282.

Akron OH

We've got it all. Business systems. Personal systems. Software packages. Custom programming. Terminals. Printers. Service and books. Easy freeway access. 10 AM to 6 PM Monday-Saturday. **The Basic Computer Shop**, Fairlawn Plaza, 2671 West Market St., Akron OH 44313, 867-0808.

York PA

Personal and small-business systems. Components and peripherals. Books, magazines, information. Hobbyists welcome. 1/2 block from Business 83 at Iron Bridge. **G.Y.C. Co.**, 51 Hamilton Ave., York PA 17404, 854-0481.

Memphis TN

Featuring Apple, Bally Arcade, Digital Group, North Star, PolyMorphic 8813, Texas Instruments, Vector Graphic, KIM, AIM, Elf II, 21st Century Tek and many others. Programming and custom design. **Computerlab**, 627 S. Mendenhall, Memphis TN, 761-4743.

Houston TX

Experimenters' Paradise! Electronic and mechanical components for computer people, audio people, hams, robot builders, experimenters. Open six days a week. **Gateway Electronics, Inc.**, 8932 Clarkcrest, Houston TX 77063, 978-6575.

Houston TX

Bare boards, kits, small systems, multiuser systems, custom hardware design, software for business or hobby, nationwide consulting available. Please call. **Houston Computer Mart**, 8029 Gulf Freeway, Houston TX 77017, 649-4188.

Richland WA

Apple, North Star, Ohio Scientific. All products listed in Byte Shopper, classes, literature, electronic parts, repair service. Custom design/consulting in both hardware and software. **Ye Olde Computer Shoppe, Inc.**, 1301 George Washington Way, Richland WA 99352, 946-3330.

Madison WI

Specializing in complete tested systems for unique applications. Cromemco, TEI, CompuColor II, Godbout, North Star, Vector Graphic, Hazeltine, Perkin-Elmer, U.S. Robotics and much more. **Magic Lantern Computers**, 6414 Copps Ave., Madison WI 53716, 221-8643.

Dealers: Listings are \$15 per month in prepaid quarterly payments, or one yearly payment of \$150, also prepaid. Ads include 25 words describing your products and services plus your company name, address and phone. (No area codes or merchandise prices, please.) Call Marcia at 603-924-7138 or write Kilobaud MICROCOMPUTING, Ad Department, Peterborough NH 03458.

MOVING?

Let us know 8 weeks in advance so that you won't miss a single issue of *Kilobaud Microcomputing*. Attach old label where indicated and print new address in space provided. Also include your mailing label whenever you write concerning your subscription. It helps us serve you promptly.

- | | |
|---|---|
| <input type="checkbox"/> Address change only | <input type="checkbox"/> Payment enclosed (1 extra BONUS issue) |
| <input type="checkbox"/> Extend subscription | <input type="checkbox"/> Bill me later |
| <input type="checkbox"/> Enter new subscription | |
| <input type="checkbox"/> 1 year \$18.00 | |

If you have no label handy, print OLD address here.

AFFIX LABEL

Name _____ Call _____

Address _____

City _____ State _____ Zip _____

print NEW address here:

Name _____ Call _____

Address _____

City _____ State _____ Zip _____

Kilobaud Microcomputing P.O. Box 997 • Farmingdale NY 11737

kb microcomputing book nook

● **HOBBY COMPUTERS ARE HERE!**—BK7322—If you want to come up to speed on how computers work . . . hardware and software . . . this is an excellent book. It starts with the fundamentals and explains the circuits, the basics of programming, along with a couple of TVT construction projects, ASCII-Baudot, etc. This book has the highest recommendations as a teaching aid for newcomers. \$4.95.*


● **THE NEW HOBBY COMPUTERS**—BK7340—This book takes it from where *Hobby Computers Are Here!* leaves off, with chapters on Large Scale Integration, how to choose a microprocessor chip, an introduction to programming, low cost I/O for a computer, computer arithmetic, checking memory boards, a Baudot monitor/editor system, an audible logic probe for finding those tough problems, a ham's computer, a computer QSO machine . . . and much, much more! \$4.95*

● **INTRODUCTION TO MICROPROCESSORS**—BK1032—by Charles Rockwell of MICROLOG, is an ideal reference for the individual desiring to understand the hardware aspects of microprocessor systems. Describes the hardware details of computer devices in terms the beginner can understand, instead of treating the micro chip as a "black box." Specific systems are not described and programming is only briefly discussed. \$17.50 U.S. and Canada; \$20 elsewhere.*

● **BASIC NEW 2ND EDITION**—BK1081—by Bob Albrecht. Self-teaching guide to the computer language you will need to know for use with your microcomputer. This is one of the easiest ways to learn computer programming. \$4.95.*

● **SCIENTIFIC RESEARCH INSTRUMENT'S BASIC SOFTWARE LIBRARY** is a complete do-it-yourself kit, written in everybody's BASIC, immediately executable in ANY computer with 8K; no other peripherals needed. **Volume I** contains business and recreational programs and is 300 pages. **Volume II** is 260 pages and contains math, engineering, statistics and plotting programs. **Volume III** contains money managing, advanced business programs such as billing, A/R, inventory, payroll, etc. **Volume IV** contains general purpose programs such as loans, rates, retirement, plus games: Poker, Enterprise (take charge while Capt. Kirk is away), Football and more! **Volume V** is filled with experimenters' programs, including games, pictures and misc. problems such as "logic." **Volume I**—LB1002—& **Volume II**—LB1003—\$24.95* each, **Volume III**—LB1004—\$39.95*, **Volume IV**—LB1005—& **Volume V**—LB1006—\$9.95* each, **Volume VI**—LB1007—\$49.95*, **Volume VII**—LB1008—\$39.95.*

● **MICROPROCESSOR INTERFACING TECHNIQUES**—BK1037—by Austin Lesea & Rodney Zaks will teach you how to interconnect a complete system and interface it to all the usual peripherals. It covers hardware and software skills and techniques, including the use and design of model buses such as the IEEE 488 or S100. \$9.95.*



● **TTL COOKBOOK**—BK1063—by Donald Lancaster. Explains what TTL is, how it works, and how to use it. Discusses practical applications, such as a digital counter and display system, events counter, electronic stopwatch, digital voltmeter and a digital tachometer. \$8.95.

● **CMOS COOKBOOK**—BK1011—by Don Lancaster. Details the application of CMOS, the low power logic family suitable for most applications presently dominated by TTL. Required reading for every serious digital experimenter! \$9.95.*

● **TVT COOKBOOK**—BK1064—by Don Lancaster. Describes the use of a standard television receiver as a microprocessor CRT terminal. Explains and describes character generation, cursor control and interface information in typical, easy-to-understand Lancaster style. \$9.95.*

● **THE "COMPULATOR" BOOK—BUILDING SUPER CALCULATORS & MINICOMPUTER HARDWARE WITH CALCULATOR CHIPS**—BK1012—by R.P. Haviland, provides ideas, design info and/or printed circuit boards for calculator chip projects such as tape control of calculator electronic lock, dial-a-telephone, etc. \$7.95.*

● **BASIC COMPUTER GAMES**—BK1074—Okay, so once you get your computer and are running in BASIC, then what? Then you need some programs in BASIC, that's what. This book has 101 games for you from very simple to real buggers. You get the games, a description of the games, the listing to put in your computer and a sample run to show you how they work. Fun. Any one game will be worth more than the price of the book for the fun you and your family will have with it. \$7.50.*

● **WHAT TO DO AFTER YOU HIT RETURN**—BK1071—PCC's first book of computer games . . . 48 different computer games you can play in BASIC . . . programs, descriptions, many illustrations. Lunar Landing, Hammurabi, King, Civel 2, Qubic 5, Taxman, Star Trek, Crash, Market, etc. \$10.95.*

● **MICROCOMPUTING CODING SHEETS** *Microcomputing's* dozen or so programmers wouldn't try to work without these handy scratch pads, which help prevent the little errors that can cost hours and hours of programming time. Available for programming is **Assembly/Machine Language** (PD1001), which has columns for address, instruction (3 bytes), source code (label, op code, operand) and comments; and for **BASIC** (PD1002) which is 72 columns wide. 50 sheets to a pad. \$2.39.*

*Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to:
 Kilobaud Microcomputing Book Department • Peterborough NH 03458. Be sure to include check or detailed credit card information.
 All orders, add \$1.00 shipping & handling.

kb microcomputing book nook

● **PROGRAMMING IN PASCAL**—BK1140—by Peter Grogono. The computer programming language PASCAL was the first language to embody in a coherent way the concepts of structured programming, which has been defined by Edsger Dijkstra and C.A.R. Hoare. As such, it is a landmark in the development of programming languages. PASCAL was developed by Niklaus Wirth in Zurich; it is derived from the language ALGOL 60 but is more powerful and easier to use. PASCAL is now widely accepted as a useful language that can be efficiently implemented, and as an excellent teaching tool. It does not assume knowledge of any other programming language; it is therefore suitable for an introductory course. \$9.95.*

● **MICROPROCESSOR LEXICON—ACRONYMS AND DEFINITIONS**—BK1040—compiled by the staff of SYBEX, is a convenient reference in pocket-size format. Sections include acronyms and definitions, part numbers and their definitions, S-100 signals; RS232 signals, IEEE 499 signals, microcomputers and microprocessors, JETDS summary (military) and a code conversion table. \$2.95.*

● **INSTANT BASIC**—BK1127—by Jerald R. Brown. For the personal computer enthusiast or the user of DEC's BASIC PLUS language, here is a new book to teach you BASIC. It teaches BASIC to beginners using interesting programming ideas and applications that will be easily understood by the home computer programmer. BASIC PLUS users know that the two languages are very similar, so this book can be used by them as well. This is an "active participation" workbook, designed to be used with your home computer so you can learn by doing! Ideas are slowly introduced in a nonmathematical context so the beginner can quickly learn good programming techniques. \$6.00.*

● **MY COMPUTER LIKES ME . . . WHEN I SPEAK BASIC**—BK1039—An introduction to BASIC . . . simple enough for kids. If you want to teach BASIC to anyone quickly, this is the way to go. \$2.00.*

● **COMPUTER PROGRAMMING HANDBOOK**—BK1014—by Peter Stark. A complete guide to computer programming and data processing. Includes many worked-out examples and history of computers. \$9.95.*

● **MICROCOMPUTER DICTIONARY**—BK1034—This microcomputer dictionary fills the need to become quickly acquainted with the terminology and nomenclature of the revolution in computers. There is also a comprehensive electronics/computer abbreviations and acronyms section. \$15.95.*

● **YOUR HOME COMPUTER**—BK1172—by James White, is an introduction to the world of personal microcomputing. This book tells you everything you want to know about home computing and gives the computer novice a painless introduction to microcomputer technology and terminology, beginning with what computers are and how they work. This basic book requires no prior knowledge or experience in electronics or computing. It provides information about home computer kits; guidelines for selecting and building your own microcomputer, how to use your home computer and what you can do with it; lists of computer stores, clubs, periodicals; and answers to many more of your questions about microcomputers and the jargon surrounding the personal computing scene today. \$6.00.*

● **HOW TO BUILD A MICROCOMPUTER—AND REALLY UNDERSTAND IT**—BK7325—by Sam Creason. The electronics hobbyist who wants to build his own microcomputer system now has a practical "How-To" guidebook. This book is a combination technical manual and programming guide that takes the hobbyist step-by-step through the design, construction, testing and debugging of a complete microcomputer system. Must reading for anyone desiring a true understanding of small computer systems. \$9.95.*

THE BASIC HANDBOOK—BK1174—by David Lien. This book is unique. It is a virtual ENCYCLOPEDIA of BASIC. While not favoring one computer over another, it explains over 250 BASIC words, how to use them and alternate strategies. If a computer does not possess the capabilities of a needed or specified word, there are often ways to accomplish the same function by using another word or combination of words. That's where the HANDBOOK comes in. It helps you get the most from your computer, be it a "bottom-of-the-line" micro or an oversized monster. \$14.95.*

● **SCELBI'S FIRST BOOK OF COMPUTER GAMES**—BK1048—Need a game for your 8008 or 8080 microprocessor? This book has three popular games: "Space Capture," "Hexpaw" and "Hangman." Complete flowcharts, logic description, program listing and instructions are provided. A must for the game freak! \$14.95.*

● **MICROCOMPUTER PRIMER**—BK1035—by M. Waite and M. Pardee. Describes basic computer theory, explains numbering systems and introduces the reader to the world of programming. Describes the world of microcomputing in "real world" terminology. \$7.95.*

● **THE STORY OF COMPUTERS**—BK1056—by Donald D. Spencer, is to computer books what *Dick and Jane* is to novels . . . elementary, gives the non-computerist a fair idea of what the hobbyist is talking about when he speaks computer lingo. Attempts to explain what computers are and can do to a spouse, child or any non-electronics-minded friend. \$4.95.*



*Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to:
 Kilobaud Microcomputing Book Department • Peterborough NH 03458. Be sure to include check or detailed credit card information.
 All orders, add \$1.00 shipping & handling.



1978 kilobaud BINDERS

Keep your KILOBAUDs from being lost or damaged in these handsomely appointed binders with rich blue covers and gold lettering. Each binder holds 12 issues, making an EXCELLENT REFERENCE HANDBOOK. Several binders form a quality library you can be proud of.

Order yours today...

only \$6.50 each (BN1011)... 2 for \$12.00 (BN1012)

Use the order card in the back of this magazine or itemize your order on a separate piece of paper and mail to:

KILOBAUD BINDERS • PETERBOROUGH NH 03458

Be sure to include check or detailed credit card information.

is HARD COPY STORAGE a problem?

KILOBAUD MICROCOMPUTING, as thick as it is, is more like a floppy when it comes to standing on the bookshelf. Try the KILOBAUD MICROCOMPUTING Library Shelf Boxes... sturdy corrugated white dirt-resistant cardboard boxes which will keep them from flopping around. We have self-sticking labels for the boxes, too, not only for KILOBAUD MICROCOMPUTING, but also for 73 Magazine... and for CQ, QST, Ham Radio, Personal Com-



puting, Radio Electronics, Interface Age, and Byte. Ask for whatever stickers you want with your box order. They hold a full year of KILOBAUD MICROCOMPUTING... or 73 Magazine. Your magazine library is your prime reference; keep it handy and keep it neat with these strong library shelf boxes. One box (BX-1001) is \$2.00, 2-7 boxes (BX-1001) are \$1.50 each, and eight or more boxes (BX-1002) are \$1.25 each. Be sure to specify which labels we should send. Have your credit card handy and call our toll-free order number 800-258-5473, or use the order card in the back of the magazine and mail to:

kilobaud

MICROCOMPUTING

peterborough nh 03458

kilobaud
MICROCOMPUTING

INDEX TO ADVERTISERS

A90 Aardvark Technical Services... 145	C124 Cost Effective Computer Ser... 138	M73 Micromail... 136	R20 RNB Enterprises... 173
A82 Aaron Associates, Inc... 152	C123 Cuddly Software... 145	M95 Micro Management Systems... 144	R7 Rondure Company... 98
A88 AB Computers... 144	C132 Custom Electronics... 145	M54 Micro-Mega... 30	S55 3S Sales... 148
A75 ACS Service... 130	C129 Cybernetics, Inc... 134, 152	M14 Micro-Peripherals, Inc... 19	S91 Sawyer Software... 156
A85 Adco Electronics... 20	D43 Dr. Daley... 30	M61 Micro Products Unltd... 35	S1 Scelbi Publications... 141
A73 Addmaster Corp... 151	D51 Darrell's Appeware House... 154	M87 Microsette Co... 30	S84 Shannon-Rice Electronics... 145
A38 Advanced Computer Products... 149, 152, 167	D50 Data/Print... 131	M44 Micro Technology Unltd... 138	S76 Steven E. Shaw, P.E... 150
A78 Aladdin Computer Corp... C111	D32 Data Vector Corp... 139	M61 Micro World Computer Store... 145	S88 Michael Shryver Software... 43
A74 American Data Home Computer... 15	D28 Deltronics... 122, 138	M94 Mid East Micro... 122	S86 Simplicity Software Systems... 161
A66 American Square Computers... 30	D52 Device Oriented Games, Inc... 156	M70 Midwest Scientific... CIV	S74 68 Micro Journal... 35
A84 Apollo Software... 94	D37 Digital Dynamics, Inc... 42	M39 Mikos... 163	S69 Small Business Computers Magazine... 132
A22 A.P. Products, Inc... 18, 31	D54 Digital Learning Modules Co... 127	M6 Mini Micro Mart... 172	S95 Small Business Computers Ser... 17
A83 Apple TV & Computing... 144	D20 Digital Research Corporation... 174	M20 Motorola Semiconductor Prod... 16	S51 Small System Software... 146
A87 AQ Systems, Inc... 16	D53 Digital Service & Design... 66	M83 Multi Business Computer Systems... 144	S52 Southeastern Software... 150
A86 Aresco... 18	D34 D & N Micro Products... 138	M87 Mumford Micro Systems... 66	S87 Southern Systems of Birmingham... 53
A15 Atlanta HamFestival... 128	E34 Ecosoft... 150	N12 NEECO... 129	S61 Supersoft... 151
A89 August Automation... 150	E36 Electronic Specialists, Inc... 35	N20 Nestar Systems, Inc... 140	S6 SWTPC... C11
A79 Austin Electronics... 47	E42 Elektronikladen... 155	N15 Netronics R & D Ltd... 131	S42 Sybex, Inc... 104
A71 Automated Simulations... 154	F16 Findex, Inc... 17	N7 Newman Computer Exchange... 164	T59 Jim Tamburo Graphics... 35
B48 The Basic Business Software, Inc... 157	F15 FMG Corp... 126	N13 Nucleus, Inc... 42	T57 Taranto & Associates... 128
B41 Belden Corp... 19	F8 Forethought Products... 128	O1 Ohio Scientific... 8-11	T11 Tarbell Electronics... 149
B33 The Bottom Shelf, Inc... 79	G4 Godbout Electronics... 165	O5 OK Machine & Tool... 87	T26 Telecommunications Services... 150
B43 Buss... 134, 140	G24 GPA Electronics... 137	O7 Oliver Advanced Engineer... 7	T51 Telesis Laboratory, Peripherals Div... 18
C131 CAP Electronics... 140	H26 Graham-Dorian Enterprises... 31	O15 Olympic Electronics... 145	T28 Thinker Toys... 113
C121 Cascade Enterprises... 157	H41 Hartwell's Office World... 130	O2 On-Line... 35	T56 TNW Corp... 63
C128 Cecdat, Inc... 148	H35 The Hickok Electrical Instrument Co... 18	O10 Optimal Technology, Inc... 152	T58 Tora Systems Limited... 133
C116 CGRS Microtech... 126	H25 Hobby World... 161	O11 Orcomp Data Systems... 157	T41 Total Information Services, Inc... 42
C125 Chrislin Industries, Inc... 20	H29 HUH Electronics... 56, 57	O14 Organic Software... 138	T60 Trace Electronics, Inc... 19
C122 CompuCover... 127	I37 Industrial Modules, Inc... 19	O8 Orthon Computers... 94	T46 Transition Enterprises, Inc... 30
C130 CompuMax Associates, Inc... 154	I22 Inntronics... 156	O6 Osborne & Associates... 83, 160	V8 Vector Electronics, Co... 20
C109 Compusoft Publishing... 123	I24 Innovative Technology... 63	O9 Otio Electronics... 55	V10 Vector Graphics, Inc... 19
C126 Compusource Corp... 20	I30 Input/Output Unlimited... 153	P9 PAIA... 59	V20 Vista Computer Company... 139
C36 Computalker Consultants... 154	I32 Instant Software... 67, 106, 107	P38 Pan American Electronics... 130, 144	V22 VM Professional Application Software, Ltd... 144
C127 The Computer Bus... 16	I9 Integrated Circuits Unlimited... 168	P7 Percom Data Company, Inc... 105	V19 VR Data Corporation... 72, 127
C64 Computer Corner of NJ... 148	I21 Interdec Data Systems... 21	P52 The Peripheral People... 139, 144	* Wallen Electronics... 166
C133 The Computer Connection... 66	I33 ISDG... 139	* Personal Computing Festival... 142	W22 Wameco, Inc... 163
C77 Computer Data Publishing... 151	* Ithaca Audio... 91, 119	P39 Personal Software... 73	W13 Wasatch Semiconductor Prod... 136
C117 The Computer Factory... 23	J1 Jameco Electronics... 170, 171	* Plainsman Micro Systems... 42	W20 WEB Associates... 42, 94
C111 Computer Forum... 127	J12 JPC Products... 133	P46 Pragmatic Designs, Inc... 155	W25 Western Digital... 109
C104 Computer Information Exch... 151	K14 Key Electronics... 139	P53 PRF-TEL Computer Electronics... 144	W29 West Side Electronics... 151
C103 Computer Packages, Unltd... 63	* Kilobaud... 99, 134	P21 Priority One Electronics... 169	W16 World Wide Electronics... 35
C80 Computer Port... 146	L19 Level IV Products, Inc... 133	P48 Programma International, Inc... 95	X4 Xitex Corp... 90
C120 Computer Printers International... 3	L16 Lifeboat Associates... 59	P37 P.S. Software House... 42, 150	X2 X & Y Enterprises... 122
C135 The Computer Shack... 138	M77 Madhatter Software... 158	* Robert Elliott Purser... 30	Y2 Young's... 150
C134 The Computer Shop... 151	M88 The Mail Mart... 63	Q8 Quant Systems... 63	Z3 Zilog, Inc... 20
C100 The Computer Store, Inc... 103	M17 Marketline, Inc... 145	Q3 Quest Electronics... 162	From Kilobaud... Pages 99, 175-178
* Computer Systems Design 134, 136	M93 Metamatics, Inc... 139	R30 R2E of America... 16	
C94 The Computerist... 140	M74 Micro... 150	R24 Racet Computes... 53	
C81 Computers One... 151	M89 Micro Architect... 145	R12 Rainbow Computing, Inc... 145	
C86 Computrex... 63, 150	M30 Micro Computer Devices... 135, 143	R8 Ramsey Electronics... 159	
C114 Computronics, Inc... 149	M82 Microcomputer Technology, Inc 122	R32 REAL-LIFE Simulations... 144	
C107 Connecticut microComputer... 127		* The Recreational Programmer... 133	

*Reader Service inquiries not honored. Please contact advertiser directly.

READER SERVICE

To receive more information from any of the advertisers in this issue of Kilobaud Microcomputing, postage-paid return cards are provided here for your convenience. If you wish to hear from one or several advertisers, refer to the ad itself. You will find numbers near the logo of each advertiser. Each represents the advertiser's individual Reader Service number. Circle the corresponding numbers on one of the cards on this page, include your name, address & zip and drop in a mailbox. In four to six weeks you'll hear from the advertiser directly.

Return this card to receive full information on the many products advertised in this issue. Limit: 25 requests. ☐ Subscriber ☐ Newsstand. This card is valid until July 31, 1979.

A15	A83	B48	C107	C125	D20	D54	H26	I37	M39	M83	N20	O15	Q3	S42	S88	T58	W22
A22	A84	C36	C109	C126	D28	E34	H29	J1	M44	M87	O1	P7	Q8	S51	S91	T59	W25
A38	A85	C64	C111	C127	D32	E36	H35	J12	M54	M88	O2	P9	R7	S52	S95	T60	W29
A66	A86	C77	C114	C128	D34	E42	H41	K14	M61	M89	O5	P21	R8	S55	T11	V8	X2
A71	A87	C80	C116	C129	D37	F8	I9	L16	M67	M93	O6	P37	R12	S61	T26	V10	X4
A73	A88	C81	C117	C130	D40	F15	I21	L19	M70	M94	O7	P38	R20	S69	T28	V19	Y2
A74	A89	C86	C120	C131	D43	F16	I22	M6	M73	M95	O8	P39	R24	S74	T41	V20	Z3
A75	A90	C94	C121	C132	D50	G4	I24	M14	M74	N7	O9	P46	R30	S76	T46	V22	
A78	B33	C100	C122	C133	D51	G20	I30	M17	M77	N12	O10	P48	R32	S84	T51	W13	
A79	B41	C103	C123	C134	D52	G24	I32	M20	M81	N13	O11	P52	S1	S86	T56	W16	
A82	B43	C104	C124	C135	D53	H25	I33	M30	M82	N15	O14	P53	S6	S87	T57	W20	

Kilobaud
MICROCOMPUTING
73

This month's **ARTICLE WINNER** (title page number): _____

Name _____
(PLEASE TYPE OR PRINT CLEARLY)

Address _____

City _____ State _____ Zip _____

KB 6/79



**NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES**

BUSINESS REPLY CARD

FIRST CLASS PERMIT NO. 17 PETERBOROUGH NH 03458

POSTAGE WILL BE PAID BY ADDRESSEE

kilobaud

MICROCOMPUTING

peterborough nh 03458

Att: Mail Order

READER SERVICE REPLY CARD

Return this card to receive full information on the many products advertised in this issue. Limit: 25 requests. ☐ Subscriber ☐ Newsstand. This card is valid until July 31, 1979.

A15	A83	B48	C107	C125	D20	D54	H26	I37	M39	M83	N20	O15	Q3	S42	S88	T58	W22
A22	A84	C36	C109	C126	D28	E34	H29	J1	M44	M87	O1	P7	Q8	S51	S91	T59	W25
A38	A85	C64	C111	C127	D32	E36	H35	J12	M54	M88	O2	P9	R7	S52	S95	T60	W29
A66	A86	C77	C114	C128	D34	E42	H41	K14	M61	M89	O5	P21	R8	S55	T11	V8	X2
A71	A87	C80	C116	C129	D37	F8	I9	L16	M67	M93	O6	P37	R12	S61	T26	V10	X4
A73	A88	C81	C117	C130	D40	F15	I21	L19	M70	M94	O7	P38	R20	S69	T28	V19	Y2
A74	A89	C86	C120	C131	D43	F16	I22	M6	M73	M95	O8	P39	R24	S74	T41	V20	Z3
A75	A90	C94	C121	C132	D50	G4	I24	M14	M74	N7	O9	P46	R30	S76	T46	V22	
A78	B33	C100	C122	C133	D51	G20	I30	M17	M77	N12	O10	P48	R32	S84	T51	W13	
A79	B41	C103	C123	C134	D52	G24	I32	M20	M81	N13	O11	P52	S1	S86	T56	W16	
A82	B43	C104	C124	C135	D53	H25	I33	M30	M82	N15	O14	P53	S6	S87	T57	W20	

Kilobaud
MICROCOMPUTING
73

This month's **ARTICLE WINNER** (title page number): _____

Name _____
(PLEASE TYPE OR PRINT CLEARLY)

Address _____

City _____ State _____ Zip _____

KB 6/79

kilobaud
MICROCOMPUTING

BUSINESS REPLY CARD

FIRST CLASS PERMIT NO. 17 PETERBOROUGH NH 03458

POSTAGE WILL BE PAID BY ADDRESSEE

kilobaud

MICROCOMPUTING

peterborough nh 03458

ATTN: READER SERVICE

NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BOOK NOOK ORDER FORM

Please send me the following KB/MC products: (please print or type!)

Qty.	Catalog #	Description	Unit Price	Total
Add \$1.00 shipping & handling:				
Total:				

Enclosed \$ _____ ☐ Check ☐ Money order

Bill: ☐ American Express ☐ BankAmericard/Visa ☐ MasterCharge

Credit Card # _____

Expiration date _____ Signature _____

Name _____

Address _____

City _____ State _____ Zip _____

KB 6/79

BUSINESS REPLY CARD

FIRST CLASS PERMIT NO. 17 PETERBOROUGH NH 03458

POSTAGE WILL BE PAID BY ADDRESSEE

kilobaud

MICROCOMPUTING

peterborough nh 03458

ATTN: READER SERVICE

NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

kilobaud
MICROCOMPUTING
books, etc.

BK1074 BASIC Computer Game
—\$7.50

BK1081 BASIC New 2nd Edition
—\$4.95

BK1174 The BASIC Handbook—
\$14.95

BN1011 Binder—KB—1—\$6.50

BN1012 Binder—KB—2 & up—
\$6.00 each

BK1011 CMOS Cookbook—\$9.95

BK1012 The "Compulator" Book
—Building Super Calculator
& Minicomputer Hardware
With Calculator Chips—\$7.95

BK1014 Computer Programming
Handbook—\$9.95

BK7322 Hobby Computers Are
Here!—\$4.95

BK1131 Instant BASIC—\$6.00

BK1032 Introduction to Micro
processors—\$17.50 USA; \$20.00
Elsewhere

Kilobaud Coding Sheets PD1002
—Assembly/Machine Language—
\$2.39; PD1002—BASIC—\$2.39

BK1034 Microcomputer Dictionary—
\$15.95

BK1035 Microcomputer Primer—
\$7.95

BK1037 Microprocessor Interfacing
Techniques—\$9.95

BK1137 Microprocessor Lexicon
—Acronyms and Definitions—
\$2.95

BK1039 My Computer Likes Me
... When I Speak BASIC—
\$2.00

BK7340 The New Hobby Computers—
\$4.95

BK1140 Programming in PASCAL—
\$9.95

BK1048 Scelbi's First Book of
Computer Games—\$14.95

Scientific Research Instrumentation
BASIC Software Library

LB1002 Vol. I—\$24.95, LB1003
Vol. II—\$24.95, LB1004 Vol. III—
\$39.95, LB1005 Vol. IV—\$39.95,
LB1006 Vol. V—\$39.95, LB1007
Vol. VI—\$49.95, LB1008 Vol. VII—
\$39.95

BX1000 Shelf Box—1—\$2.00

BX1001 Shelf Box—2—\$1.00
each

BX1002 Shelf Box—8 up—\$1.00
each

BK1056 The Story of Computing—
\$4.95

BK1063 TTL Cookbook—\$8.95

BK1064 TVT Cookbook—\$9.95

BK1071 What To Do After You Buy
Return—\$10.95

BK1172 Your Home Computer—
\$6.00

Now You Can Make Your Own Magic

Unleash the Full Power
of Your
Personal Computer
With the
All-New Aladdin
Personal
Programs™



Aladdin Automation now offers
the magic of a full range of
Personal Program™ series
specially designed to support
most popular personal
computers available today.
Some Personal Programs™ will
take you to faraway places of
adventure, action-packed
adventures. Others will bring
filled learning experiences
to you and your child. Still
others are designed for your own

use in the home or office.

All Aladdin Personal
Programs™ are moderately priced.

Visit your personal computer
dealer today to see and
experience the magic waiting for
you in every one of the Aladdin
Personal Programs™. (And if
your dealer hasn't ordered his
supply yet, then ask him to write
Aladdin Automation for complete
information on all the Personal
Programs™ available now.)

**Welcome To The All-New
World Of Aladdin. And Get Ready
To Make Your Own Magic**



ALADDIN AUTOMATION, INC.
ALADDIN COMPUTER CORP.

3420 Kenyon St. San Diego, Ca. 92110



Small Computers For Big Jobs

Personal Computer Place
Mesa, AZ

Phoenix Micro Systems
Mesa, AZ

A-Vidd Electronics
Long Beach, CA

Software Dynamics
Anaheim, CA

Datek
Newington, CT

Fuel Computer Corp.
New Haven, CT

Harper Buffing
E. Hartford, CT

Microcomputer Systems
Tampa, FL

American Microprocessors
Half Day, IL

Computerland
Arlington Heights, IL

Data Mart
Arlington Heights, IL

Great Lakes Industries
Elgin, IL

Lillipute Computer Mart
Skokie, IL

Midland Standard
Elgin, IL

Electronic Enterprises
Logansport, IN

Johnson Controls
Goshen, IN

Electronic Data
Des Moines, IA

Barney & Assoc.
Pittsburg, KS

CMPTR-C
Topeka, KS

Micro Dynamics
Olathe, KS

Freeman Micro Tech.
W. Monroe, LA

Crockergraphics
Needham Heights, MA

Pacer Systems
Burlington, MA

O-M Sales
Ann Arbor, MI

Gallion Data System
Rockaway Beach, MO

H & K Computer Corp.
Kansas City, MO

Compact Computers
Butte, MT

Acutronics
Summit, NJ

Beacon Computer
Metuchen, NJ

High Technology
Oklahoma City, OK

The Electronics Place
Pittsburgh, PA

Gallion Data System
Camp Hill, PA

G.Y.C. Company
York, PA

International Data
Solebury, PA

The Computer Shop
San Antonio, TX

Barbara Rush
Mesquite, TX

Small Computer Products
Austin, TX

Southwest Electronics
Melbourn, Australia

Sontron Instruments
Victoria, Australia

Arelco
Belgium

The Computer Circuit
Ontario, Canada

Strumech Engineering
Staffordshire, England

MRL Building
Delft, Holland

Hauker HF
Reykjavik, Iceland

Electricity Supply Board
Ireland

Digito Systemas S.A.
Monterrey, Mexico

ECONZ
New Zealand

Radiokom
Transvaal, South Africa

Testas Turkish Electronics
Ankara, Turkey

Sistema 6.600
Caracas, Venezuela

C.O.I. - Systeme Munchen
West Germany



Midwest Scientific Instruments

220 W. Cedar • Olathe, KS 66061 • (913) 764-3273 • TWX 910 749 6403 (MSI OLAT) • TELEX 42525 (MSI OLAT)